

AG-26A中英文说明书

385mm

183mm

充电款木质音箱AG-26A

非常感谢您购买 AROMA 品牌音箱 AG-26A。请在使用本产品前，仔细阅读使用说明书。

AROMA

咨询电话: 0755-29770450
广东省深圳市宝安区西乡街道三围社区工业路56号特楼
© 2018 深圳市阿诺玛乐器有限公司 aromausic.cn

注意事项

避免放置的地方

在以下地方放置音箱可能会导致故障发生。

- 潮湿或过度潮湿的地方。
- 灰尘过多的地方。
- 剧烈震动的地方。
- 与磁体接近的地方。

电源

本产品内带锂电池。当不使用音箱时，请及时关闭电源开关。

应远离易燃易爆物品

本产品手机闪光灯照射设备大型可导电导致使用干扰。在使用音箱时应与这类设备保持适当的距离。

小心操作

为了避免损坏器材，请不要大力按放按钮或其他操作件。

清洁

如果产品表面脏了，请用干净的布擦拭。不要使用液体清洁剂，譬如：苯、酒精，或者其他含有腐蚀性化学成分的清洁剂。

防止异物进入产品内

不要将含有液体的物品放置在产品旁边。如果液体泼入本产品，可能会引起短路、火灾或触电。非常小心不要让金属物品进入产品内。

保留说明书

请妥善保管好此书，以备再次查阅。

规格功能

1. 低音.....控制低音频率

2. 高音.....控制高音频率

3. 高低.....控制中音频率

4. 混响.....控制混响效果

5. 音量.....控制音量大小

6. 延迟.....控制延迟时间

7. 总音量.....控制总音量

8. LED.....充电指示灯

9, BT.....蓝牙连接按钮

10. 电源.....电源开关

11. LED.....充电指示灯

12. DC 输入.....充电接口 (15V/1.5A)

13. MIC 输入.....麦克风输入接口

14. 吉他输入.....吉他输入接口

15. LINE-OUT.....信号输出

产品特点

- 便携式内置锂电池设计，无源外接电源可享受本产品带给您的音乐乐趣；
- 本产品专业的喇叭喇叭阵列，完美还原乐器音色；
- 本产品采用专业级喇叭喇叭阵列设计，音质表现完美，更好的突出了吉他的声音和人声演唱的表现；
- 本产品低音部分有数字混响功能，进一步丰富了音色；
- 本产品配备了蓝牙、无线充电功能，可以无线充电手机、蓝牙耳机一体化的组合设备。

增加使用功能

- 打开电源开关，蓝色 LED 会闪烁电源显示相等的状态 (见上表蓝色 LED 指示)；
- 将吉他插进音箱与总音量按钮连接；
- 调节合适的吉他音量旋钮位置、音色按钮和混响按钮位置。
- 调节合适的蓝牙音量旋钮位置。

增加蓝牙无线功能

- 将蓝牙设备与音箱的 MAC 地址，选择新款手机的蓝牙或 NFC 扫描；
- 调节合适的蓝牙音量旋钮位置；
- 调节合适的蓝牙音量旋钮位置。

增加使用 LINE-OUT 功能

- LINE-OUT 接口为 3.5mm 的莲花接口；
- 当连接 LINE-OUT 音频线时，本产品喇叭会继续发声。

技术参数

通道 1 (吉他通道)

输入阻抗: 6.35mm x 1;

输入阻抗: 10Kohm

EQ 调节: 低频、中频音色调节

混响控制: 有

输出功率: $20W$ (标准)

喇叭单元: 6.5寸同轴喇叭, 30W x 1

蓝牙版本: 4.2 版

充电接口: 15V/1.5A (9-4) 一键

电池规格: 11.1V/2200mAh (锂电池)

接口规格: >math>64</math>(80%音质)

充电时间: 3H

通道 2 (蓝牙通道)

输入阻抗: 6.35mm x 1;

输入阻抗: 10Kohm

混响控制: 有

蓝牙版本: 4.2 版

产品状态

产品状态	蓝色 LED 指示	红色 LED 指示
打开电源	30%电量时 3Hz 闪烁	充电指示灯亮
蓝牙播放	5%电量时 6Hz 闪烁	充电指示灯亮
充电时	充电指示灯亮	充电指示灯亮

如何开启 Line-OUT 功能

- Turn power ON, the indicator light is lit a color, which differs to different power level.
- Link your acoustic guitar by a cable to GUITAR INPUT socket.
- Adjust Guitar Volume, Bass and Treble knobs and Master knob to get a suitable volume and tone output.
- Adjust guitar reverb effect to get a ideal effect.

如何开启 Mic Function

- Link your moving coil microphone cable to MIC INPUT XLR or 6.35mm mono socket.
- Adjust Mic Volume knob and MASTER knob to get a comfortable volume.
- Adjust ECHO knob to get a satisfied echo effect.

如何开启 LINE-OUT Function

- Link out stereo sound with a 3.5mm gauge jack.
- The amp still works when Line out connected.

Product Parameter

Channel 1 (Guitar) Input socket: 6.35mm gauge jack x 1

Channel 2 (mic.) Input socket: 6.35mm gauge jack x 1

Input impedance: 10Kohm

EQ: bass, treble

Reverb control

Bluetooth version: 4.2

Peak power: 20W

Battery life: 3 H (80% volume level)

Speaker: 6.5 inch, 6.8 range, 30W x 1

Recharge socket: 15V/1.5A (9-4)

Specifications

Net weight: 3.6kg Gross weight: 4.0kg

Dimension: 280 x 190 x 200mm Package size: 330 x 240 x 250mm

Product Contents: AG-26A amp, handle x 1, power adapter x 1, operation manual.

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off, the user is encouraged to take the following corrective measures:

- Reorient or relocate the receiving antenna.
- Increase the distance between the equipment and the receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not specifically approved by the manufacturer could void your authority to operate the equipment.

The FCC cautions that for the FCC Rules, Compliance with the following conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause the device to operate in an unintended manner.

The device has been validated to meet general IP exposure requirements. The device will be used in outdoor applications without restriction.

ACCUSTIC GUITAR AMP AG-26A OWNERS' MANUAL

Thank you for purchasing AROMA AC-26A, please read this manual carefully before your operation.

AROMA

©2018 Aroma Music Co., Ltd. aromausic.cn

Precautions

Location

Using the unit in the following locations can result in a malfunction.

- Locations of extreme temperature or humidity
- Excessively dusty or dirty locations
- Locations of excessive vibration
- Cases to magnetic fields

Power supply

Be sure to turn the power OFF when the unit is not in use.

Interference with other electrical devices

Radios and televisions placed nearby may experience reception interference. Operate this unit at a suitable distance from radios and televisions.

Handling

To avoid leakage, do not apply excessive force to the switches or controls.

Care

If the exterior becomes dirty, wipe it with a clean, dry cloth. Do not use liquid cleaners such as benzene or thinner or cleaning compounds of flammable liquids.

Keeping foreign matter out of your equipment

Never set any container with liquid in it near this equipment. If liquid gets into the equipment, it could cause a breakdown, fire, or electrical shock. Be careful not to let metal objects get into the equipment.

Keep this manual

After reading this manual, please keep it for later reference.

Panel Controls

规格功能

1. VOLUME.....控制 guitar volume

2. BASS.....控制 guitar low frequency tone

3. TREBLE.....控制 guitar high frequency tone

4. REVERB.....控制 guitar reverb effect

5. VOLUME.....控制 microphone volume

6. ECHO.....控制 microphone reverb echo effect

7. MASTER.....控制 master volume of guitar and mic

8. LED.....amp work condition light (blue color, details at Table)

9. BT.....蓝牙连接按钮

10. POWER.....switch power ON/OFF

11. LED.....power recharging condition light

12. DC INPUT.....power recharging jack (15V/1.5A)

13. MIC INPUT.....2 in 1 jack (XLR and 6.35mm gauge) Mic

14. GUITAR INPUT.....guitar cable input jack

15. LINE-OUT.....signal output

Table

Work condition	Blue LED indicator	Red LED indicator
Power On	Power less than 30% Light flashes fast	/
Bluetooth On	Power less than 5% Playing	Light flashes slowly and Power (100%)
Recharging condition	Recharging duration Recharging full	Light ON Light OFF

Amp Features

- Rechargeable battery inside, to enjoy music and playing anywhere any time.
- High performance of original guitar sound.
- Specific speaker and cabinet design for acoustic guitars and human voice.
- Digital reverb effect inside guitar channel.
- With functions of Bluetooth and microphone input to enjoy the fun of playing guitar, singing with background music in the same time.

● 产品料号 1.5.03.0163000

● 物料名称 AG-26A中英文说明书

● 材质/工艺 70g书写纸/正反面单色印刷

● 设计师 潘绍者

● 日期 20190110