Bluetooth Earphone
A2S
User Manual

Shenzhen Mees Hi-Tech Co., Ltd

Accessories

Charge box

Ear tips

Headset

Charge cable

User manual

1.A2 overview:



No.	Function
1	LED indicator
2	Microphone
3	Touch
4	Charging case LED indicator

2.ZINOFF:

When you take the headset out of the charging box, the headset will automatically turn on and enter pairing mode. When you put the headset back, the headset will automatically shut down. When the headset is not connected, press and hold the touch area for 5 seconds to shut down. When the earphone is not connected and automatically shut down after 5 minutes.

3.Mobile phone pairing guide:

1)Take out the two earphones from the charging box, the two headset are auto-matically turned on and interconnecting.

Note: 1) You have about 3 minutes to connect the headset to your mobile phone, otherwise the headset will exit the pairing mode. Put the headset back in the charging box and pick it up again to reenter the pairing mode.

2) Open the Bluetooth function menu on the mobile phone, select A2, and click to connect. When the connection is correct and connected, the left or right ear will hear "connected".

Note: Only the right earphone will connect to your phone. The left earphone will connect to the right earphone.

4、Pairing guide for left and right headset:

1) Put the two headset back into the charging box, and the case then out at the same time, Ensure that the headset is not connected to the mobile phone or other devices, and the LED light flashes red and blue alternately, indicating pairing.

2) Take the headset out of the charging box, and both headset will automatically turn on, accompanied by the prompt sound "power on".

3) The left and right headset are automatically paired without any operations.

4) If you do not hear the "TWS connected" tones, please repeat the above steps.

5) When you need to disconnect the pairing, you can put the left and right headset back into the charging box and take them out, After the two headset are connected, they will automatically connect back to the phone.

5、Use the left headset alone:

Take out the left headset from the charging box and automatically enter the pairing mode. Search for the Bluetooth name "A2" on the phone and click to pair. The phone is search for the device, select "A2" and click the pairing connection, a Bluetooth connection tone "connected" prompt, the connection is successful.

6、Use the right headset alone:

Take out the left headset from the charging box and automatically enter the pairing mode. Search for the Bluetooth name "A2" on the phone and click to pair. The phone is search for the device, select "A2" and click the pairing connection, a Bluetooth connection tone "connected" prompt, the connection is successful.

7、The earphone cannot be automatically connected back and there is no sound in one headset:

1) Put the two headset back into the charging box, first and click "A2" in the Bluetooth list of the mobile phone. 2) Refer to "Left and Right Ear Pairing Guide" to pair the left and right headset again. 3) Refer to the "Mobile phone pairing guide" to reach and connect the phone and headset.

8、The correct way of wearing:

Wrong way of wearing



9.Music:

Start your music player to play music, you can use any headset to control.

Music touch control area
(Pause/Play/Previous/Next song)

※ Make sure the wireless connection between the headset and the phone is successful.
※ Touch once to pause the music, Touch again to resume playback.
※ Touch the left headset twice to play the previous song.
※ Touch the right headset twice to play the next song.
※ Long touch the right headset to increase the volume.
※ Long touch the left headset to reduce the volume.

10.Phone call

When making and receiving calls, the left and right headset operations are effective.

Phone call touch control area
(Answer/reject,etc.)

Incoming call reminder: Touch once on the call function touch control area.
Reject a call: Long touch the call function touch control area for 3 seconds.
Hang up a call: Touch the call function touch control area.
Switch between the left and right headset: Double touch control area, effective connection to the end user headset.

11.Charge the headset:

Put the headset into the charging area, When charging, the white light of the headset breathes and flash, and the headset start to charging, The light turns off when the headset is fully charged.

12.Charge the charging case:

Plug the charging cable into the charge port to charge the charging box and headset,When charging, the charging box indicator will flash red.

Attention: Any attempt to remove or replace the battery will damage the product and void the product warranty.

13.LED indicator of the charging box:

The LED signal colours in indicator shows the exact numbers of the battery capacity left. Each colour shows which helps the recharge of your product. Make sure to fully charge before use.

14.Low battery warning

The headset can let you know that the battery level is low, When the battery is low, the headset will give a reminder, please charge the battery in time.

15.Headset status indicator

Status	Indicator
Power on	Red light flashes 3 times
Pairing	Red and blue lights flash alternately
Connected	Red flashes once every 5 seconds

16.Charging box status indicator

Status	Indicator
Charging	Red light flashes
Fully charged	Red light is always on

Attention: Any attempt to remove or replace the battery will damage the product and void the product warranty.

17.Basic parameters of the headset:

Model: A2
Bluetooth version: Bluetooth 5.0
Weight: Headset: 3g(*2pcs)
Headset battery capacity: 45mAh
Headset charging time: about 2 hours
Working voltage: 3.7V-4.2V
Standby time: about 48 hours
Headset playing time: 4 hours of playback(Tests from factory default volume to mid-low charge case)
Talk time: about 3 hours
Support Profile：HSP、HFP、A2DP、AVRCP
Bluetooth frequency: 2.4G
Audio sampling rate(fixed): 16bit
Audio sampling rate: 44x1 48kHz
Charging box battery capacity: 1800C - 2BC
Operating temperature: -4°C ~ +45°C
Working humidity: 45%-85% (Humidity)

18.Basic parameters of headset drivers:

Driver size：13mm Impedance：32Ω±3Ω
Sensitivity: 105dB±3dB Frequency response: 20-20kHz
Rated power consumption: 5mW, maximum 6mW

19. Basic parameters of headset microphones:

Microphone: 2 pcs
SNR: ≥65dB
Sensitivity: -42±3dB

20、Basic parameters of the charging box:

Input: 5V/1A
Charging time: about 2 hours
The charging box can provide charging times for the headset: 2 times.
Charging time of the charging box: about 2.4 hours

21、Use safety instructions:

Please keep the product away from the source of heat and moisture, avoid exposing it to high temperature, damp and dusty environments as this may cause permanent damage to the earphone or shortening. Please do not use AC when driving, riding bicycle, crossing the road, etc, where your concentration is required, Also, if you use headset while watching a video, the audio and video may be out of sync.

After charging is complete, please unplug the charging cable from the body to avoid leaving the product in a charging state for a long time.
Please do not disassemble the product yourself, as this will void the warranty of the headset and may damage the product. If the product is dirty, please wipe and comfirm of the charger interface for specific maintenance, and if it causes serious damage to the product and the product worsens, it will be recycled at the same time.

FCC ID:2AKD2-A2

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.
-Increase the separation between the equipment and receiver.
-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.