

Test Model: SPK400-Q

# SPK400-Q

## Motorcycle Bluetooth Speaker



## USER MANUAL

### 1. Contents

- 4 x Speakers
- 1 x Wired Control
- 4 x Mounting Clamps
- 16 x Screws
- 2 x Hex Screw Driver
- 1 x Power Cord
- 2 x Fuse
- 1 x User's Manual

### 2. Features

- 4.5" High-Performance Waterproof Speakers
- 3" Full Range Sound Core
- Built-In Bluetooth 5.0 for Audio Streaming
- 3.5mm AUX Input Jack
- Built-In 1200W D-Class Amplifier
- All-Function Wired Remote
- SAE Quick Disconnect Power Cable
- Advanced Plating Process - Fade and Scratches Resistant

### 3. Read Before Installation

- 1) The components and wiring should not be installed on or around any moving parts, keep away from ignition parts, fuel lines, engine or any hot exhaust.
- 2) Speakers should not be installed where they might inhibit safety features on the vehicle such as lights, horns, brake levers, etc..
- 3) Always test the speakers/amplifier prior to installation. Connect to the battery and play the music at least 3-minute to ensure the product is fully functional.
- 4) Cutting rubber insert may be required for certain bar sizes.
- 5) For certain model, an external amplifier with no waterproof feature is required to install in a shaded area to avoid rains and direct sunlight.
- 6) To avoid battery draining, disconnect the speaker from the battery if the motorcycle/ATV is planned non-operation for more than 15 days.
- 7) Please note the music volume is tuned and limited to ensure driving safety.

- 8) The product is designed for in-town cruising.
- 9) The product is not recommended to use for high-speed highway driving.
- 10) Please connect to a correct power supply (DC 10 - 16 V)
- 11) Do not drop the unit into water.
- 12) Please confirm the wiring before turning on the unit.
- 13) Please make sure the speakers are tightly clamped on the handlebar.

### 4. Installation

#### Wiring:

- 1) Connect the master and slave speakers via RCA cable.
- 2) Connect the master speaker with included SAE power cord.
- 3) Connect the power cord to a 12V battery.  
(Positive: RED, Negative: Black)
- 4) Connect the wired control to the 3.5mm female socket for remote.

#### Mounting the speakers:

- 1) Screw the mounting bracket to the bottom of the speaker.
- 2) Locate a safety mounting location on the mounting bar.
- 3) Install the speaker with mounting clamp.  
(For larger bar size, remove the included black rubber insert)



## 5. Operation Instruction



1. Power On/off - Long Press  
Mode Change - Single Click
2. Volume Down - Single Click
3. Volume Up - Single Click
4. Last Song - Single Click
5. Next Song - Single Click
6. Play/Pause - Single Click

## 6. Bluetooth Connection

1. Power on the stereo system.
2. Press mode(on/off) to switch the unit in Bluetooth mode.
3. Enable Bluetooth function on your smartphone.
4. Search for Bluetooth device named "GOHAWK".
5. Pair the device with the stereo system (Enter 0000 if it asks for a PIN)
6. "Connected" will be indicated if successfully connected.
7. Start streaming your music and radio channels wirelessly.

## 7. Troubleshooting

### **The unit is not turning on:**

1. Double check if the wiring is correct.
2. Inspect the fuse, replace it if blown.
3. Check if the battery is in good condition, unit required at least 12V to operate.
4. Wired control is defective if no light indication, contact our customer support.

### **Volume is not loud enough:**

1. Check if all speakers are in working condition, contact us if one of them is blown.
2. Adjust the speaker direction toward driver's position.
3. Turn on the volume all the way up on BOTH stereo unit AND music device (such as smartphone and mp3 player)
4. Check if your battery has at least 12V after motorcycle /ATV startup.
5. Contact our customer support if above steps do not fix the issue.

### **Mounting clamp is not compatible with my bar:**

1. Mounting clamp is designed for bar size within 1" to 1.5" (38mm)
2. Custom mounting may be required if your bar size is not within the recommended size.
3. Please check the product specification online for accurate dimension.
4. Contact our customer support if you have trouble installing the item.

## 8. Specifications

### **Built-In Amplifier:**

Working Voltage: DC 10-16 V  
Rated Power: 4\*30W @ 4Ω  
Peak Power: 1200W  
Channel: 4.0  
S/N: >80dB

### **Speaker:**

Outline Size: 4.5" x 5.5"  
Sound Core: 3" Full Range  
Rated Power: 20W  
Impedance: 4Ω  
Sensitivity: 84dB

## 9. Warranty

### **REGISTER YOUR PRODUCT:**

<http://goldenhawkusa.com/warranty>

### **1-Year Limited Parts Warranty:**

All Golden Hawk USA products purchased in the United States are warranted for a period of one year from the purchase date against defects in materials and workmanship. We will provide you with free parts for one year after your purchase. The warranty is for replacement at the sole discretion of the selling dealer. If we choose to replace your product, we may replace it with a new or reconditioned unit of the same or similar design. The customer is responsible for freight charges incurred to return the product.

For all other countries, contact our technical support where you must send a copy of the original invoice with the date of purchase. Please enclose a letter stating the problem you are having with the product, your daytime phone number, and your return shipping address (no P.O. Box). Contact us to receive an RA# before sending your defective item. This warranty does not cover any unit subject to abuse, neglect, incorrect wiring, water and/or physical damage, or any repair or modification performed by someone other than a Golden Hawk USA repair technician.

Any damages resulting from legal action for breach of expressed or implied warranties shall be limited to the cost of the original purchase price of the unit. As a condition of this warranty, it is agreed that the remedy provided in this document is the sole remedy under this warranty. All liability for incidental damages is excluded. The purchaser agrees to retain the original proof-of-purchase for establishing the effective date of this warranty. Should Golden Hawk USA or an authorized dealer replace your product under warranty, this replacement shall be considered a transaction under the original warranty and does not extend the original warranty period.

## 10. Product Support

Please visit: <http://goldenhawkusa.com/contact-us>  
email to [info@goldenhawkusa.com](mailto:info@goldenhawkusa.com)

#### FCC Warning Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- - Reorient or relocate the receiving antenna.
- - Increase the separation between the equipment and receiver.
- - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- - Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.