


STEP 3

CONTROL YOUR MEDIA AND CALLS.

Music and other audio will play automatically from your paired smart device. You can either control the media directly from your device, or use the onboard buttons for the following functions:

FUNCTION	OPERATION	
Play or pause the music.	Press the 🖌 button while music is playing to pause; press 🕅 again to resume.	
Increase the volume.	Press and hold the + button until the volume reaches a desired level.	
Decrease the volume.	Press and hold the - button until the volume reaches a desired level.	
Skip ahead to the next song.	Press the + button once while playing media.	
Skip back to a previous song.	Press the - button once while playing media.	
While in AUX mode, the playing/pausing, track selection and volume functions can be controlled directly from your device.		
Accept an incoming call.	Press the MI button while receiving an incoming call.	
End/hang up an ongoing ca	Press the H button during an ongoing call to end it.	
Reject an incoming call.	Press and hold the M button for 2 seconds while receiving an incoming call.	
Redial the last number.	Press the M button twice (while playing music or in Standby mode).	
Hands-free calling functions are only available while in Bluetooth mode (not when using an AUX/wired connection).		

PRODUCT OVERVIEW



- Works with AUX-Compatible (3,5mm) and
- Bluetooth-Compatible Devices
- Up to 5 Hours of Playback & Talking Time
- ${\scriptstyle \bullet}$ Convenient Onboard Button Controls
- Compact Lightweight Design for Easy Travel & Storage

USING WITH A WIRED (AUX) CONNECTION

When using with an AUX (3.5mm) connection, simply plug the cable into the audio source (smartphone, tablet, etc.) and connect the other end of the cable to the headphones. Media will play immediately, even while the headphones are turned off. All media and volume settings can be controlled directly from the device (onboard buttons will have no effect).

CHARGING YOUR HEADPHONES

- To charge the headphones, insert the included Micro-USB charging cable into the Micro-USB input charging port located next to the 3.5mm audio jack (see diagram for reference).
- 2. Connect to a reliable power source (AC wall adapter, computer, etc.) and the unit will begin to charge.
 - The LED Indicator will illuminate red while the unit is charging.
 - When the unit is fully charged, the LED indicator will turn off.
 - Fully charging the unit from a depleted battery takes approximately 2 to 3 hours.

IMPORTANT SAFEGUARDS

- Try to avoid continuous use of your headphones at high volumes. Using at high volumes for prolonged periods of time can cause hearing damage to the user. Limit to 1-hour intervals if possible.
- Operate responsibly and at safe volumes. To prevent safety risks, avoid using headphones while operating a vehicle such as a car or bicycle.
- Avoid prolonged exposure to sunlight, high temperatures, dusty and humid environments. Such conditions can cause irreversible damage to
- the wiring which may affect or prohibit normal use.

 If your tzumi headphones malfunction, do not attempt to repair the
 - If your scinning appropriate manufacture is a science of the input of epole interprise of the science of the scie

USING YOUR HEADPHONES

STEP 1

TURN ON THE HEADPHONES AND ENTER PAIRING MODE. • Turn the headphones on by pressing and holding the Play/Pause/Power button for 3 seconds. You will hear "Power On" and the LED Indicator will begin to flash red and blue alternately.

• The unit will then automatically enter Bluetooth pairing mode. The LED Indicator will continue to flash red and blue while in pairing mode.

STEP 2:

PAIR YOUR SMART DEVICE.

 Once in pairing mode, open the Settings menu on your smart device (smartphone, tablet, etc.). Enable Bluetooth pairing and wait for your device to locate the headphones. Keep the device and headphones within 3 feet of each other.

• When this happens, "Tzumi Headphones" will appear on the device list; select this option. Follow the prompt to pair the headphones.

• You will hear "Bluetooth Connected" to indicate that a successful connection has been made.

 These steps will only be necessary when pairing your headphones to a Bluetooth device for the first time. Once you have completed a successful device pairing for the first use, your device will automatically recognize and pair to the headphones going forward.

SPECIFICATIONS

	Approx. 33 ft 200 mAh 5 V 3.7 V ABS with Metallic Printing Approx. 5 hours at 50% Volume;
Calling/Talking Time Charging Time Standby Time Frequency Response Watts per Channel Speaker Size Max. Input Nominal Impedance Speaker Sensitivity	Approx. 2 Hours Up to 120 Hours 20 Hz - 20,000 Hz 10 mW 40mm 5 V / 200 mA 32 Ω 103 dB ± 3 dB
Charging Port/Interface Cable Length Dimensions Weight	50 cm (Approx. 20 in.) 183 x 1775 x 78 mm (7.2 x 7.0 x 3.1 in)

tzumi® Eros Stereo Headphones Distributed by tzumi® INC. NY, NY 10016 ©Copyright 2019 tzumi® All Rights Reserved. Made In China.

The Bluetooth trademarks are owned by Bluetooth SIG, Inc. Other trademarks and trade names in this document are those of their respective owners. © 2019 Bluetooth SIG, Inc. Subject to change without prior notice. FCC#:XXXXXXXXX

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.