

Shenzhen Yongman digital Technology Co., LTD

2nd Floor, Building A, Tiantong Industrial Zone, Longhua District, Shenzhen

No.	50638	Name	Wireless charge transmitting coil			
Size	$\Phi 43.5 * \Phi 5 * H1.8$	paste method	Hot-air self-adhesive			
			A	$20.5 \pm 0.5$		
			B	$39.0 \pm 1.0$		
			C	$43.5 \pm 0.5$		
			D	$35 \pm 2$		
			E	4M AX		
			F	$1.17 \pm 0.1$		
			G	$0.6 \pm 0.1$		
			H	$1.8 \pm 0.1$		
						Unit: MM
wire rod	0.08*48	winding	Single wire folded			
no. of turns	11 Ts					
Chip size	$\Phi 43.5 * \Phi 5 * 0.6$	L	$7.8 \pm 10\%$			
Coil size	$\Phi 39.0 * 20.5$					
			Note	counterclockwise		