SP9X

Operating Instructions

Product Introduction



Headset

Battery compartment (The appearance is for reference only, subject to the actual object)

Instructions

Charging line

(1) Do not attempt to disassemble or replace any part of the product except for the operation mode specified in the manual What parts.
(2) Do not put the product into water or any other liquid. This product is not waterproof.
(3) If any liquid accidentally enters the product, please disconnect it immediately and remove the product.
(4) To avoid electric shock, make sure your hands are free from water when installing or uninstalling the product.
(5) Do not place this product near heat sources or directly expose it to fire sources.
(6) Do not place this product in an environment with strong electromagnetic force, otherwise it may cause product failure.

Basic parameters

Product name	Bluetooth headset
Charging interface	Type-C
Speaker Impedance	32Ω
Headphone input parameters	5V⎓30mA MAX (single ear)
Rated capacity of single earphone battery	25mAh
Rated capacity of charging box battery	180mAh
Input parameters of charging box	Wired input: 5V⎓300mA MAX
Wireless connection	V5.4 +BR+EDR
Bluetooth protocol	a2dp\avctp\avdtp\avrcp\hfp\spp\smp\att\gap\ gatt\rfcomm\sdp\l2cap
Working distance	10M (barrier free and open environment)
working temperature	5°C~40°C
Charging time of headphone box	About 1.5 hours (using wired charging)
Headphone charging time	30minute
Headphone range	About 4 hours
Overall endurance with the charging box	About 12 hours

*All technical information shall be subject to actual performance

Charge the charging box
Connect the charging box to the 5V power adapter with Type-C charging cable.



(The appearance is for reference only, subject to the actual object)

Rated input: 5V⎓30mA (headset) 5V⎓300mA (charging box)

Use function operation

charge
Charge the earphone: Place the headphones into the charging compartment, close the compartment cover, and the headphones will automatically enter the charging state.
Charge the charging box: Use the TYPE-C charging cable included in the package to charge the charging box. When charging, the digital display digital jumping. When charging is complete, 100% is displayed.
Tip: Please select a power adapter that complies with CCC certification for charging.

View power
Check the headset power: After the headset is connected to the phone, you can check the headset power in the phone status bar.
Note: The status bar of the phone only shows the low battery level of the two headphones. Some mobile phones don't work Check the battery with the headset.
Check the charge of the charging box:Charging box display shows battery level.

Power on: Open the charging compartment and the headphones will automatically turn on.
Sleep: Put the headset back into the charging box, close the box cover, and the headset will automatically disconnect and enter the sleep state.
Tip: After use, please put the headset back into the charging box in time to prolong the service life and prevent loss.

Connect
Connect new device
1. Open the charging compartment cover, remove the headphones, and wait for them to pair automatically. When one of the headphone lights turns off and the other one flashes red and blue alternately, it means that the headphones have been paired successfully.
2. Turn on Bluetooth, search for and connect "SP9X", enter "0000" for the connection password.

Connection interrupted
When Bluetooth is turned off or the headset connection range is exceeded, the headset will automatically enter the waiting connection state;
If the headset is not connected to any device within 10 minutes, it will enter the sleep state, and then it will wake up after being put into the charging box again, and it will enter the waiting connection state.

Automatic reconnection
The headset is in the charging box. Open the charging box, and the headset will automatically connect to the recently connected Bluetooth device; If no connection record is detected or any Bluetooth device cannot be successfully connected back, the headset will automatically enter the waiting connection state.
Tip: If the headset cannot be automatically connected back to the device, you need to manually connect it on the Bluetooth interface of the device.
Tip: Due to the connection characteristics of the Bluetooth signal, there may be intermittent disconnection or silence in places where 2.4GHz electromagnetic signal interference is intensive.

Function introduction

Conversation
Tap the headset on either side: answer the call
Long press on either side of the headset: reject/end
Music
Tap either side of the headset to play/pause
Click the right earphone twice: the next one; click the left earphone twice: the previous one
Tap the right earphone three times to increase the volume, and tap the left earphone three times to decrease the volume.
To prevent possible hearing loss, do not use this product at high volume for a long time.

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
—Reorient or relocate the receiving antenna.
—Increase the separation between the equipment and receiver.
—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
—Consult the dealer or an experienced radio/TV technician for help.

Note: The Grantee is not responsible for any changes or modifications not expressly approved by the party responsible for compliance. such modifications could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement.
This equipment complies with FCC's RF radiation exposure limits set forth for an uncontrolled environment. This device and its antenna(s) must not be co-located or conjunction with any other antenna or transmitter.

SP9X

操作说明书

物品清单

电池仓 (外观仅参考，以实物为准)

说明书

充电线

产品使用简介

(1)除说明书有特殊标示的操作方式以外，请勿尝试拆卸或更换产品内的任何零件。
(2)请勿将产品放入水或其他任何液体中，此产品非防水设计。
(3)如果有任何液体不小心进入产品内时，请立即断开连接并移开此产品。
(4)为避免触电，请在安装或卸载产品时，确保手上没有沾水。
(5)请勿将此产品放置于热源附近或直接暴露在火源附近。
(6)请勿将本产品放置在有强大电磁力的环境中，否则会导致产品故障。

基本参数

产品名称	蓝牙耳机
充电接口	Type-C
喇叭阻抗	32Ω
耳机输入参数	5V⎓30mA MAX(单耳)
单耳机电池额定容量	25mAh
充电盒电池额定容量	180mAh
充电盒输入参数	有线输入：5V⎓300mA MAX
无线连接	V5.4 +BR+EDR
蓝牙协议	a2dp\avctp\avdtp\avrcp\hfp\spp\smp\att\gap\ gatt\rfcomm\sdp\l2cap
工作距离	10M(无障碍空旷环境)
工作温度	5°C~40°C
耳机盒充电时间	约1小时 (使用有线充电)
耳机充电时间	30分钟
耳机续航	约4小时
配合充电盒整体续航	约12小时

*所有技术信息以实际性能为准

给充电盒充电
用Type-C充电线连接充电盒到5V电源适配器。



(外观仅参考，以实物为准)

额定输入:5V⎓30mA(耳机) 5V⎓300mA(充电盒)

使用功能操作

充电
· 为耳机充电: 将耳机放入充电仓，关闭仓盖，耳机自动进入充电状态。
· 为充电盒充电：使用包装内含的TYPE-C充电线为充电盒充电，充电时，数码显示数字跳动。充电完成时，显示100%。
提示： 请选用符合CCC认证的电源适配器充电。
指示： 说明书中的产品、配件、用户界面等插图均为示意图，仅供参考。
由于产品的更新与升级，产品实物与示意图可能略有差异，请以实物为准。

查看电量
, 查看耳机电量:耳机连接手机后，可在手机状态栏查看耳机电量。
注意： 手机状态栏仅显示两只耳机中电量较低的耳机电量。部分手机不支持耳机电量查看。
, 查看充电盒电量: 充电盒显示屏显示电量。

开机: 打开充电仓，耳机自动开机。
休眠: 休眠：耳机放回充电仓，关闭仓盖，耳机自动断连，并进入充电状态，充满后自动进入休眠状态。
提示: 使用完，请及时将耳机放回充电盒，以延长使用寿命及防止丢失。

连接
连接新设备
1. 打开充电仓盖，取出耳机，等待耳机自动配对,一只指示灯闪烁，一只耳机灯熄灭，代表配对成功，连接手机后就两只耳机灯都灭掉。
2. 开启设备蓝牙,搜索并连接" SP9X" 如需连接密码,输入"0000"

连接中断
当设备关闭蓝牙或超出耳机连接范围时，耳机自动进入等待连接状态;
若10分钟内未连接到任何设备，耳机进入休眠状态，重新放入充电盒并关闭充电仓，再重新取出即可重新唤醒，进入等待链接状态。

自动回连
耳机在充电盒中，打开充电仓盖，耳机将自动回连最近连接过的蓝牙设备;
若没有检测到连接记录或无法成功回连任何蓝牙设备，耳机自动进入等待连接状态。
提示：若耳机不能与设备自动回连，需在设备的蓝牙界面进行手动连接。
提示：由于蓝牙信号的连接特性，在2.4GHz的电磁信号干扰密集的地方，可能偶有间歇性断连或无声的情况。

功能介绍

通话
轻击一下任意一侧耳机：接听电话
长按任意一侧耳机：拒接/挂断
音乐
轻击一下任意一侧耳机：播放/暂停
轻击二下右一侧耳机：下一首、轻击二下左一侧耳机：上一首
轻击三下右一侧耳机：音量加大、轻击三下左一侧耳机：音量减小。
为了防止可能出现的听力损伤，请勿长时间用高音量使用本产品。