














 <p>FCC ID: 2AXSO-JH-01</p>	<p>Product Parameter</p> <p>Model: JH-01 zigbee In/Out:125V AC/50/60Hz Max.Current: 10A RF Standard:Zigbee IEEE 802.15.4 Powered by:Live and Neutral Material: pc,ABS VO Weight:60g Size:48X48X52mm</p> <p>Distinguishing Feature</p> <ul style="list-style-type: none"> Without other Zigbee hub, directly support Amazon Echo Smart Speaker to config the controller. After paired, you can use the Alexa APP or Voice to control the device. Support access to Samsung SmartThings hub, Amazon Echo Plus, Amazon Echo Show(2nd), eWeLink hub or other HA and 3.0 hub. Zigbee plug can be controlled by the button on itself. 	<p>Configuration Steps</p> <p>amazon alexa WORKS WITH SmartThings</p> <p>Works with Amazon Alexa</p>  <ol style="list-style-type: none"> Confirm that the Blue LED of Zigbee Plug is flashing. If the indicator is always on, press and hold the button until it is flashing or powered off the Zigbee Plug and then power on for 3-8s. Repeat five times, then the Plug enter config mode, the Green LED will flash. Ask, "Alexa, discover my devices." Wait for the Zigbee Plug Blue LED indicator to be always on, and the Plug is connected to echo plus or echo show(2nd). Ask, "Alexa, turn on first plug." This will turn the Plug on. 	<ol style="list-style-type: none"> You can use Amazon Alexa App to and group, routines of modify device names such as bedroom plug. At this point you can use Alexa App or Voice to control the devices. <p>amazon alexa WORKS WITH SmartThings</p> <p>Work with Samsung SmartThings hub & Amazon Alexa</p>  <ol style="list-style-type: none"> Confirm that the Blue LED of Zigbee plug is flashing. If the indicator is always on, press and hold the button until it is flashing or powered off the Zigbee plug and then power on for 3-8s. Repeat five times, then the plug enter config mode, the green LED will flash.
			

<ol style="list-style-type: none"> Open the SmartThings App and add the Zigbee plug. When the green LED indicator is always on, the plug has been added to the smartThings hub. If the App does not recognize the device type, please refer to the SmartThings Config, pdf document. Enable SmartThings Skill in the Amazon Alexa APP or alexa.amazon.com Ask, "discover my devices." can add zigbee Plug to amazon smart home. 	 <p>1: In the Alexa App interface click "+" icon, You can add devices and groups. In the device list interface you can control or modify the device type and name, as shown in the following picture.</p> <p>2: In the Alexa App Smart Home interface you can operate the devices conveniently</p> 	<p>SmartThings App</p>  <ol style="list-style-type: none"> Click "+" to add or reset the device at the upper right corner on the all device list screen in the smartThings APP. Select "Add Device" in the pop-out window 	<ol style="list-style-type: none"> Choose the room you want after entering this interface, or click "add new room" then click "next" Do what app tells you and wait patiently.   
<ol style="list-style-type: none"> You can use SmartThings App or Amazon Alexa APP to add group, routines or modify device names such as bedroom plug. At this point you can use Alexa App or Voice to control the devices. <p>SmartThings App and Alexa App operation (Add device, group, routines)</p> <ul style="list-style-type: none"> Alexa APP 	<p>3: In the Alexa App routines interface you can set up some devices and events (Ask, "Alexa, good morning." It will turn on the bedroom lights, open the curtains, and forecast the weather, traffic conditions, to-do items, etc.)</p> 	<ol style="list-style-type: none"> Click "Next" on the default hub connection interface Select "eWeLink" icon to add device on the add device screen  	<ol style="list-style-type: none"> After the device is successfully connected, name the device and click "Done" Return to the main interface, device has been added, and you will see the device and you can begin to set.  

<p>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p> <p>FCC warning: Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p>	<p>with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p> <ul style="list-style-type: none"> -Reorient or relocate the receiving antenna. -Increase the separation between the equipment and receiver.
<p>Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance</p>	<ul style="list-style-type: none"> -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -Consult the dealer or an experienced radio/TV technician for help. <p>This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.</p>