

Page 1 of 17 FCC ID: 2AYFP-TRK4-OX Report No.: LCSA111122131E

FCC Part 15, Subpart B, Class B ARTIKA FOR LIVING INC OXION 4 TRACK LIGHT

Test Model: TRK4-OX-HD1BG

Additional Model No.: TRK4-OX-XXXXXX("XXXXXX" can be A to Z and/or 0 to

9 and/or blank (commercial code))

Prepared for : ARTIKA FOR LIVING INC

Address : 1756 50th avenue, Lachine, Qc, CanadaH8T 2V5

Lachine Canada

Prepared by : Shenzhen LCS Compliance Testing Laboratory Ltd. Address : 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park

Yabianxueziwei, Shajing Street, Baoan District,

Shenzhen, 518000, China

Tel : (+86)755-82591330 Fax : (+86)755-82591332 Web : www.LCS-cert.com

Mail : webmaster@LCS-cert.com

Date of receipt of test sample : November 23, 2022

Number of tested samples : 2

Sample No. : A111122131 Serial number : Prototype

Date of Test : November 23, 2022 ~ November 25, 2022

Date of Report : November 26, 2022



Page 2 of 17 FCC ID: 2AYFP-TRK4-OX

Report No.: LCSA111122131E

FCC Part 15, Subpart B, Class B FCC 47 CFR Part 15 Subpart B, Class B, ANSI C63.4 -2014

Report Reference No.: : LCSA111122131E

Date Of Issue: : November 26, 2022

Testing Laboratory Name: Shenzhen LCS Compliance Testing Laboratory Ltd.

Address:: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park

Yabianxueziwei, Shajing Street, Baoan District, Shenzhen,

518000, China

Testing Location/ Procedure...: Full application of Harmonised standards

Partial application of Harmonised standards

Other standard testing method

Applicant's Name.....: : ARTIKA FOR LIVING INC

Canada

Test Specification

Standard.....: FCC 47 CFR Part 15 Subpart B, Class B, ANSI C63.4

-2014

Test Report Form No.....: LCSEMC-1.0

TRF Originator.....: Shenzhen LCS Compliance Testing Laboratory Ltd.

Master TRF.....: Dated 2011-03

SHENZHEN LCS COMPLIANCE TESTING LABORATORY LTD. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the SHENZHEN LCS COMPLIANCE TESTING LABORATORY LTD. is acknowledged as copyright owner and source of the material. SHENZHEN LCS COMPLIANCE TESTING LABORATORY LTD. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test Item Description.....: OXION 4 TRACK LIGHT

Test Model: TRK4-OX-HD1BG

Trade Mark: Artika

Ratings: Input: AC 120V, 60Hz, 23W

Result: : Positive

Compiled by: Supervised by:

(am Jus

Vera Deng/ Administrator Cary Luo/ Technique principal

Gavin Liang/ Manager

Approved by:

FCC -- TEST REPORT

November 26, 2022 **Test Report No.:** LCSA111122131E Date of issue

Test Model: TRK4-OX-HD1BG EUT.....: : OXION 4 TRACK LIGHT Applicant.....: : ARTIKA FOR LIVING INC 1756 50th avenue, Lachine, Qc, CanadaH8T 2V5 Address..... Lachine Canada Telephone.....:: : / Fax.....: : / Manufacturer.....: ZHONGSHAN C5 LIGHTING CO. LTD 1# Henglong Road, Tongyi Industrial Area, Cao San, Address..... Guzhen, Zhongshan, Guangdong, China. Telephone..... Fax.....: : / Factory.....:: ZHONGSHAN C5 LIGHTING CO. LTD 1# Henglong Road, Tongyi Industrial Area, Cao San, Address..... Guzhen, Zhongshan, Guangdong, China. Telephone.....: : / Fax.....:: : /

Test Result according to the standards on page 6: Positive

The test report merely corresponds to the test sample.

It is not permitted to copy extracts of these test result without the written permission of the test laboratory.





FCC ID: 2AYFP-TRK4-OX

Report No.: LCSA111122131E

Revision History

Report Version Issue Date		Revision Content	Revised By
000	November 26, 2022	Initial Issue	






















TABLE OF CONTENTS

Test Report Description	Page
1. SUMMARY OF STANDARDS AND RESULTS	6
1.1. Description of Standards and Results	6
2. GENERAL INFORMATION	7
2.1. Description of Device (EUT)	7
2.2. Support Equipment List	7
2.3 External I/O Cable	7
2.4. Description of Test Facility	8
2.5. Statement of the Measurement Uncertainty	8
2.6. Measurement Uncertainty	8
3. TEST RESULTS	
3.1. POWER LINE CONDUCTED EMISSION MEASUREMENT	
3.2. Radiated emission Measurement	13
4. TEST SETUP PHOTOGRAPHS OF EUT	17
5. EXTERIOR PHOTOGRAPHS OF THE EUT	17
6. INTERIOR PHOTOGRAPHS OF THE EUT	17













1. SUMMARY OF STANDARDS AND RESULTS

1.1. Description of Standards and Results

The EUT have been tested according to the applicable standards as referenced below.

EMISSION							
Description of Test Item	Standard	Limits	Results				
Conducted disturbance at mains terminals	FCC 47 CFR Part 15 Subpart B, Class B, ANSI C63.4 -2014	Class B	PASS				
Radiated disturbance	FCC 47 CFR Part 15 Subpart B, Class B, ANSI C63.4 -2014	Class B	PASS				

Test mode:		
Mode 1	Lighting	Record







2.1. Description of Device (EUT)

EUT : OXION 4 TRACK LIGHT

Trade Mark : Artika

Test Model : TRK4-OX-HD1BG

Additional Model No.: TRK4-OX-XXXXXX("XXXXXX" can be A to Z and/or 0 to

9 and/or blank (commercial code))

Model Declaration : PCB board, structure and internal of these model(s) are

the same, So no additional models were tested

Report No.: LCSA111122131E

Power Supply : Input: AC 120V, 60Hz, 23W

Highest internal

: Fx ≤ 108 MHz

frequency (Fx)

Highest internal frequency (Fx)	Highest measured frequency			
Fx ≤ 108 MHz	1 GHz			
108 MHz < Fx ≤ 500 MHz	2 GHz			
500 MHz < Fx ≤ 1 GHz	5 GHz			
Fx > 1 GHz	5 x Fx up to a maximum of 6 GHz			

NOTE 1 For FM and TV broadcast receivers, Fx is determined from the highest frequency generated or used excluding the local oscillator and tuned frequencies.

Where Fx is unknown, the radiated emission measurements shall be performed up to 6 GHz.

2.2. Support Equipment List

Manufacturer	Description Model		Serial Number	Certificate

2.3 External I/O Cable

I/O Port Description Quantity		Cable	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg Å & 301 Bldg Č, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China







2.4. Description of Test Facility

Site Description

EMC Lab. : NVLAP Accreditation Code is 600167-0.

FCC Designation Number is CN5024.

CAB identifier is CN0071.

CNAS Registration Number is L4595.

FCC Test Firm Registration Number: 254912.

2.5. Statement of the Measurement Uncertainty

The data and results referenced in this document are true and accurate. The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities. The measurement uncertainty was calculated for all measurements listed in this test report acc. To CISPR 16 – 4 "Specification for radio disturbance and immunity measuring apparatus and methods – Part 4: Uncertainty in EMC Measurements" and is documented in the LCS quality system acc. To DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

2.6. Measurement Uncertainty

Test	Test Parameters		Expanded Uncertainty (Ucispr)
Conducted Emission	Level accuracy (9kHz to 150kHz) (150kHz to 30MHz)	± 2.63 dB ± 2.35 dB	± 3.8 dB ± 3.4 dB
Radiated Emission	Level accuracy (30MHz to 1000MHz)	± 3.48 dB	± 5.3 dB
Radiated Emission	Level accuracy (above 1000MHz)	± 3.90 dB	± 5.2 dB

- (1) Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the apparatus.
- (2) The reported expanded uncertainty of measurement is stated as the standard uncertainty of measurement multiplied by the coverage factor of k=2, which for a normal distribution corresponds to a coverage probability of approximately 95%.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China



3. TEST RESULTS


3.1. POWER LINE CONDUCTED EMISSION MEASUREMENT

3.1.1. Test Equipment

The following test equipments are used during the power line conducted measurement:

Item	Equipment	Manufacturer	Model No.	Serial No.	Cal Date	Due Date
1	EMI Test Software	Farad	EZ	/	N/A	N/A
2	EMI Test Receiver	R&S	ESR3	102312	2022-02-18	2023-02-17
3	Artificial Mains	R&S	ENV216	101288	2022-06-16	2023-06-15
4	Pulse Limiter	R&S	ESH3-Z2	102750-NB	2022-08-17	2023-08-16
5	Impedance Stabilization Network	TESEQ	ISN T800	45130	2022-10-29	2023-10-28

3.1.2.Block Diagram of Test Setup



3.1.3.Test Standard

Power Line Conducted Emission Limits (Class B)

Frequency			Limit (dBμV)		
(MHz)			Quasi-peak Level Average Level		
0.15	~	0.50	66.0 ~ 56.0 *	56.0 ~ 46.0 *	
0.50	~	5.00	56.0	46.0	
5.00	~	30.00	60.0	50.0	

NOTE1-The lower limit shall apply at the transition frequencies.

NOTE2-The limit decreases linearly with the logarithm of the frequency in the range 0.15MHz to 0.50MHz.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

3.1.4.EUT Configuration on Test

The following equipments are installed on Power Line Conducted Emission Measurement to meet the commission requirement and operating regulations in a manner, which tends to maximize its emission characteristics in a normal application.

Report No.: LCSA111122131E

3.1.5. Operating Condition of EUT

- 3.1.5.1. Setup the EUT as shown on Section 3.1.2
- 3.1.5.2. Turn on the power of all equipments.
- 3.1.5.3.Let the EUT work in measuring Lighting and measure it.

3.1.6.Test Procedure

The EUT system is connected to the power mains through a line impedance stabilization network (L.I.S.N.). This provides 50ohm coupling impedance for the EUT system. Please refer the block diagram of the test setup and photographs. Both sides of AC line are checked to find out the maximum conducted emission. In order to find the maximum emission levels, the relative positions of equipment and all of the interface cables shall be changed according to FCC/ANSI C63.4-2014 on Conducted Emission Measurement.

The bandwidth of the test receiver is set at 9kHz.

The frequency range from 150kHz to 30MHz is investigated

3.1.7.Test Results

PASS.

The test result please refer to the next page.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Test Model	TRK4-OX-I	HD1BG Te	est Mode	Lighting
Environmental Condi	itions 23.5℃, 53.	3% RH T e	est Engineer	Nick Peng
Pol	Line	Te	est Voltage	AC 120V/60Hz
90.0 dBuV				
80				
70				
60 1			FCC PART 15B Cond	duction(QP)
50	5	3	FCC PART 158 Cond	luction(AV6)
40		/^/ [*] /^/^/\/\/\/\/		MAN 12
30		Markethanana		
20	V V V V V	V	Andrew Comments	AVG
10				
0				
-10				
-20				
-30 0.150	0.500 0.800	(MHz)		30.000
	Reading Correct	Measure-	5.000	30.000
No. Mk. Fred	•		it Margin	
MHz		dBuV dBu\		or Comment
1 0.13		59.31 65.5		THE Testi
2 0.16		36.34 55.4		rcs .
3 0.27		53.74 61.0		
4 0.29 5 0.96		35.68 50.2 48.05 56.0		
6 1.03		33.49 46.0		<u> </u>
7 1.98 8 2.07		46.05 56.0 31.76 46.0		<u> </u>
				1
9 6.50		48.45 60.0 32.78 50.0		6份
11 23.11		46.84 60.0		gLab
12 23.32		33.59 50.0		<u></u>
12 20.02	.01 10.00 20.00	30.00 30.0	- 10. 1 1 AVO	<u> </u>



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com



Test Mo	del		TRK4-OX	-HD1BG	Test Mode)	Lighting
Environ	mental	Conditions	23.5℃, 53	3.3% RH	Test Engi	neer	Nick Peng
Pol			Neutral	,	Test Volta	ige	AC 120V/60Hz
90	.0 dBuV						
80							
70							
60	1				FCC PART	15B Conduc	ction(QP)
50	, Maria	-alp	3	5	FCC PART	15B Conduc	tion(AVG)
40		1. Carlow		<u> </u>	The first	Water Street	
30	* A	A. Alaka		6 Company	_\ 8	10	peak
20			ON WHILL CAN	Mark Marker of Land	- Thursday	" Maryan and Mardage Sign	many 1
10							AVG
0							
-10	. 📙						
-20	. 📙						
-30							
_	0.150	0.500 Par	0.800 ading Correct	(MHz) Measure-	5.000		30.000
	No. Mk.	_	evel Factor		imit Margin		
- 170		MHz di	BuV dB	dBuV	dBuV dB	Detector	Comment
世语检测图	1 *	0.1726 38	3.81 19.63	58.44 6	4.83 -6.39	QP	女闲检 ^测
LCSTesti	2	0.1740 11	1.62 19.63	31.25 5	4.77 -23.52	AVG	LCSTes
	3	0.9691 25	5.69 19.65	45.34 5	6.00 -10.66	QP	
	4		1.83 19.65	31.48 4	6.00 -14.52	AVG	
_	5		1.99 19.71		6.00 -11.30	QP	
_	6		1.96 19.71	31.67 4	6.00 -14.33	AVG	
_	7		7.65 19.82		0.00 -12.53	QP	
	8		2.86 19.82		0.00 -17.32	AVG	
	9		3.59 19.84		0.00 -16.57	QP	_ 115
	10		.61 19.84		0.00 -21.55	AVG	E 177
VISA	11		5.28 20.07		0.00 -13.65	QP	19
114	12	23.0955 13	3.68 20.07	33.75 5	0.00 -16.25	AVG	

^{***}Note: 1) Pre-scan all modes and recorded the worst case results in this report.



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

²⁾ Margin= Reading level + Correct factor - Limit Correct Factor= Lisn Factor+Cable Factor




3.2. Radiated emission Measurement

3.2.1. Test Equipment


The following test equipments are used during the radiated emission

Item	Test equipment	Manufacturer	Model No.	Serial No.	Cal Date	Due Date	
1	EMI Test Software	AUDIX	E3	/	N/A	N/A	
2	By-log Antenna	SCHWARZBECK	VULB9163	9163-470	2021-09-12	2024-09-11	
3	Horn Antenna	SCHWARZBECK	BBHA 9120D	9120D-1925	2021-09-05	2024-09-04	
4	EMI Test Receiver	R&S	ESR3	102311	2022-08-17	2023-08-16	
5	Broadband Preamplifier	/ 1	BP-01M18G	P190501	2022-06-16	2023-06-15	
6	EMI Test Software	Farad	EZ	1	N/A	N/A	
7	MXA Signal Analyzer	Agilent	N9020A	MY50510140	2022-10-29	2023-10-28	
8	EMI Test Receiver	R&S	ESPI	101940	2022-08-17	2023-08-16	

3.2.2. Block Diagram of Test Setup



Below 1GHz



Above 1GHz



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com Scan code to check authenticity



3.2.3. Radiated Emission Limit (Class B)

Limits for Radiated Disturbance Below 1GHz

Report No.: LCSA111122131E

FREQUENCY	DISTANCE	FIELD STRENGTHS LIMIT				
MHz	Meters	μV/m	dB(μV)/m			
30 ~ 88	3	100	40			
88 ~ 216	3	150	43.5			
216 ~ 960	3	200	46			
960 ~ 1000	3	500	54			

Remark: (1) Emission level (dB) μ V = 20 log Emission level μ V/m

- (2) The smaller limit shall apply at the cross point between two frequency bands.
- (3) Distance is the distance in meters between the measuring instrument, antenna and the closest point of any part of the device or system.

	Limits for Radiated Emission Above 1GHz									
ĺ	Frequency Distance Peak Limit Average L									
	(MHz)	(Meters)	(dBµV/m)	(dBµV/m)						
ĺ	Above 1000	3	54							
	***Note: The lower limit applies at the transition frequency.									

3.2.4. EUT Configuration on Measurement

The following equipment are installed on Radiated Emission Measurement to meet the commission requirements and operating regulations in a manner which tends to maximize its emission characteristics in normal application.

3.2.5. Operating Condition of EUT

- 3.2.5.1. Setup the EUT as shown in Section 3.2.2.
- 3.2.5.2.Let the EUT work in test Lighting and measure it.

3.2.6. Test Procedure

EUT and its simulators are placed on a turntable, which is 0.8 meter high above ground. The turntable can rotate 360 degrees to determine the position of the maximum emission level. EUT is set 3.0 meters away from the receiving antenna, which is mounted on a antenna tower. The antenna can be moved up and down between 1.0 meter and 4 meters to find out the maximum emission level. Broadband antenna (calibrated by-log antenna) is used as receiving antenna. Both horizontal and vertical polarization of the antenna is set on measurement. In order to find the maximum emission levels, all of the interface cables must be manipulated according to ANSI C63.4-2014 on radiated emission measurement.

The bandwidth of the EMI test receiver is set at 120kHz, 300kHz. The frequency range from 30MHz to 1000MHz is checked.

3.2.7. Radiated Emission Noise Measurement Result

PASS.

The scanning waveforms please refer to the next page.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com Scan code to check authenticity



FCC ID: 2AYFP-TRK4-OX

Report No.: LCSA111122131E




Test	Model					TF	RK4-	OX-HD1B0	}	T	es	t N	lode			Lig	gh	ting	- H	检测
Environmental Conditions			;	23.8℃, 52.1% RH		Detector Function					Quasi-peak			Testin						
Pol				Vertical		Distance				3m										
Test Engineer				Nick Peng			Test Voltage					AC 120V/60Hz			Hz					
70	70.0 dBuV/m		Τ																	
60		_					\square		FC	C Part15 RE-Cla	ss R	30-	10001	IH2	\square	\dashv				
50		+										_Ма	rgin -6 dE		_00	10001			∄	
40		+			Ļ									+					4	
30	*			2	F		3					, X		+				\square	\dashv	
20		hah	~~~	\wedge	<u> </u>		\wedge	المعربين الم	1 /	N	A COLOR	W 194	TANK MANAGE	An _{an} r	ydy)larsed	الهيما	Mayor	A LONG PARTY	pea	k
10					Two to	سكلها		Janes Jakoba	٧					_					\dashv	
0										\Box				+					\dashv	
-10	·													+					\dashv	
-20	o			-	_					H		+		+					\dashv	
-30	30.000		60.00					(MHz)				300	0.00						1000.00	a
立语 LCST	No.	Frequ (M		,			ing V)	Factor (dB/m)		Le Bu		el .	Limit (dBuV/n			argii dB)	n	Dete	ector	检测 Testin
	1	30.7	7454		49	9.6	67	-18.35		31.	32	2	40.00		-8	3.68		C	P	
	2	71.0	0803		4	6.7	'5	-19.51		27.	2	4	40.00		-12	2.76	3	C	(P	
	3	110.	9570		4	3.6	64	-19.15		24.	49	9	43.50		-19	9.01	1	C	P	
	4	199.	2855		3	7.7	2	-17.45		20.	2	7	43.50		-2	3.23	3	C	P	
	5	294.	1137		4	2.4	7	-15.56		26.	9	1	46.00		-19	9.09	9	C	P	
	6	465.	5994		3	4.4	2	-14.46		19.	9	6	46.00		-20	6.04	1	C	P	



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China



Test Model	TRK4-OX-HD1BG	Test Mode	Lighting		
Environmental Conditions	23.8℃, 52.1% RH	Detector Function	Quasi-peak		
Pol	Horizontal	Distance	3m		
Test Engineer	Nick Peng	Test Voltage	AC 120V/60Hz		
70.0 dBuV/m					



 	00.00		, ,	500.			
No.	Frequency (MHz)	Reading (dBuV)	~ 1 1			Margin (dB)	Detector
1	32.2925	44.56	-18.15	26.41	40.00	-13.59	QP
2	71.5805	43.88	-19.53	24.35	40.00	-15.65	QP
3	118.6013	41.08	-19.81	21.27	43.50	-22.23	QP
4	209.3129	43.00	-17.15	25.85	43.50	-17.65	QP
5	296.1836	42.24	-15.57	26.67	46.00	-19.33	QP
6	689.5644	31.87	-10.98	20.89	46.00	-25.11	QP

Note:1). Pre-Scan all mode, Thus record worse case mode result in this report.

2) Margin= Reading level + Correct factor - Limit

Correct Factor=Antenna Factor+Cable Factor- Pre-amplifier Factor



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

4. TEST SETUP PHOTOGRAPHS OF EUT

Please refer to separated files for Test Setup Photos of the EUT.

5. EXTERIOR PHOTOGRAPHS OF THE EUT

Please refer to separated files for External Photos of the EUT.

6. INTERIOR PHOTOGRAPHS OF THE EUT

Please refer to separated files for Internal Photos of the EUT.

-----THE END OF TEST REPORT-----

