

Q1:What should I pay attention to before WiFi connection? A1:APP permission: Pls turn on GPS and all permissionsselect"allow"; iOS iphone:pls enable location action by setting>privacy>location ser vices>cam720 APP>enablepreciselocation,select"always" WiFi requirement: Pls ensure the Name and password of the router are not more than 16 characters Note: pls take the camera near the router for first connection,cellphone connected the same wifi Q2:What should I pay attention to before Wiredconnection?

A2:Ethernet cable:pls check the cable is working and check the indica NOTE: pls confirm the cellphone connected the same wifi of the router that camera connected. Q3:How to do if the camera is often offline?

A3:Adapter: pls check the adapter and outlet for the camera,or check

the camera's record, if there are some broken records, the problem is Network: pls check the network,is it normal APP permission: pls check mobile network permission on the APP is enable, otherwise, the APP can't work under mobile network. Reconfigure the camera: delete the camera from the APP> add the camera after reset the camera as the first connection

# Sign up & Login

**Register an account:** Click "Regis ter" > enter your email address, set your APP passcode, check the veri fication code, and wait for Power and Reset the camera: Pls plug the adapter for the camera, the verification to be completed and then jump directly to the APP list. you hearing "Di-",camera will do self-inspection after "Di-"2 times Requirement Before WiFi connection: pls read Q1 above: Don't ban permissions of the APP

Note: if you don't want register an account, it can't remote, but you canuse stand alone mode to view the camera. This mode only support Local view.



(2.4Ghz signal transfer distanceis longer, 5Ghz is shorter but faster in speed).

WiFi connection



NOTE: some models only support 2.4Ghz WiFi, cellphone connected 2.4G WiFi for first connection; if camera support 2.4G/5G dual-band WiFi, pls choose the right WiFi accordingto the place you want to install

1.In the APP: click"+"> select"WiFi connection" 2.Check "configure the network when you hear the device tone" > Tap"next step"

for example, if it's a wooden wall, expansion screws are not



pls back to cam720 APP

3.Follow the Tips Shown in the APP(pls connect WiFi to JA-


\*\*\* or JAA-\*\*\*, and then back to Cam720 APP)to find the

Camera's WiFi(namedJA-\*\* / JAA-\*\*\*),after connected it

honor\_foreign (3.40.90)
Connected (top to share) ChinaNetrqSn7

4. Enter the right password of the WiFi that your phone conne cted to, Tap"Next Step)

5. When the device is connected, pls wait patiently until camera is online",then click the video to view




Plug the power supply and Ethernet cable to the router: Pls plug the adapter for the camera, and connect the camera with the Ethenet cable to the router hearing Prompted, select wired connection to connect it.




Wired Connection

Connect to the router LAN port through a network cable






















1. Back to the device list



Share your camera with your friends and families

1. Your friend should have an account of cam720 APP.


2.in main account, enter the Email of the friend APP account

Share



# Playback

1.Turn on the playback function and two Record method ava ilable: SDcard record(8-128G) and Cloud Record. 2.New users can get a trial cloud storage for free,pls don't 3.SD card record supports 3 record modes: 24/7 continuous,






#### Installation Indoor Camera-stent assembly

1. This camera can be placed on the desktop, or do ceil or Wall mounted.
2. Attach the bracket to the wall and make a mark on the hole to ponch holes, and use a 6mm drill bit to get the holes, then Stuff the rubber stopper into the hole.
3. Align the bracket with the hole position and tighten the screws. Fix the





Outdoor camera

# Important Use Notice

1.Attach the bracket to the wall and make a mark on the hole to ponch holes, and use a 6mm drill bit to get the holes, then Stuff the rubber 1. The use of unapproved or incompatible power adaptersmay cause stopper into the hole.

2. Select a suitable location and install expansion screws on the wall. fire, explosion or other dangers.

2.This product and accessories contain some small parts to avoid hildren contact and cause swallowing small parts, causing suffocation or other hazards, in addition, this product is not a toy, children should be used under adult supervision.

3. Please use this product within the appropriate temperature range. When the ambient temperature is too high or too low,it may cause errors, avoid rain or moisture on the product and its accessories, so as not to affect the use of the product.

4. Suitable for equipment, suitable for areas with an altitude of 2000

meters and below. 5.WiFi device should be under a good wifi signal area,pls avoid choosing a closed environment installation which may cause bad signal.

### Important Use Notice

1. Failed in connection at first connection? Pls view the operation video at last page(Scan the QR code toview), and pls view wifi connection steps from Page5, if still failed, pls message

seller to get support, we also offer online support if you need. 2.Change a router.camera is offline? pls delete the camera from the APP, and take the camera to near the new router,power and reset it, search and add it.

1,Check the status of the SD card in the APP 2,Check the record setup 3,format SD card 4,change a SD card to test 5,message Seller to get

4.Camera is offline? Read the Q3 at page3 and follow it to check, if there is further question, pls message seller to get support

5.The instructions are not detailed enough? It's general quick user guide,so less many details,pls contact seller to get the E-user manual and operation video accordingto your order.

## After-sale Service & Tech Support

We offer a one-year warranty and lifetime technical support! As long as there is any problem, please feel free to contact thepurchase store, we will quickly provide an effective solution.

By scanning the QR code below to access Youtube, Selectthe right operation video for your camera according to APPand Model of the camera Or message seller to get the operation video directly.



(Scan the QR code to view)

#### **FCC Warning**

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interferenceto radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

#### **Radiation Exposure Statement**

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.