

Sign up an account by email and login, please read the instructions carefully before use.

Download CAM720 APP from APP store or Google play, or by Scanning the QR code above.

Q1:What should I pay attention to before WiFi connection?

A1:APP permission: Pls turn on GPS and all permissionsselect"allow"; iOS iphone:pls enable location action by setting>privacy>location ser vices>cam720 APP>enablepreciselocation,select"always" WiFi requirement: Pls ensure the Name and password of the router are

not more than 16 characters Note: pls take the camera near the router for first connection, cellphone

connected the same wifi Q2:What should I pay attention to before Wiredconnection? A2:Ethernet cable:pls check the cable is working and check the indica tor of the network port is always on

NOTE: pls confirm the cellphone connected the same wifi of the router that camera connected.

O3:How to do if the camera is often offline? A3:Adapter: pls check the adapter and outlet for the camera, or check the camera's record, if there are some broken records, the problem is

camera after reset the camera as the first connection

in power;camera can record without wifi

Network: pls check the network, is it normal APP permission: pls check mobile network permission on the APP is enable, otherwise, the APP can't work under mobile network. Reconfigure the camera: delete the camera from the APP> add the

1.Register an account: Click"sign up"> enter Email, set your APP pass word, check the verified code

Sign up & Login



Note: if you don't want register an account, it can't remote, but you canuse stand alone mode to view the camera. This mode only support Local view



WiFi connection


Power and Reset the camera: Pis plug the adapter for the camera, Reset the camera by long press the reset button for 5 seconds until you hearing "Di-",camera will do self-inspection after "Di-"2 times Requirement Before WiFi connection: pls read Q1 above: Don't ban permissions of the APP

NOTE: some models only support 2.4Ghz WiFi, cellphone connected 2.4G WiFi for first connection; if camera support 2.4G/5G dual-band WiFi, pls choose the right WiFi according to the place you want to install (2.4Ghz signal transfer distanceis longer, 5Ghz is shorter but faster in

The device connects to the router via WiFi

1.In the APP: click"+"> select"WiFi connection" 2. Check "configure the network when you hear the device

tone" > Tap"next step"



3. Follow the Tips Shown in the APP(pls connect WiFi to JA-*** or JAA-***, and then back to Cam720 APP)to find the Camera's WiFi(namedJA-**/JAA-***), after connected it



pls back to cam720 APP

4. Enter the right password of the WiFi that your phone conne cted to, Tap"Next Step)

5. When the device is connected, pls wait patiently until camera is online", then click the video to view



Connect to the router LAN port through a network cable

Plug the power supply and Ethernet cable to the router: Pls plug the adapter for the camera, and connect the camera with the Ethenet

Reset the camera: Long-press the reset button about 5-8s until you hearing Prompted, select wired connection to connect it.

NOTE: pls read Q2 above if there is a problem in wired connection if the camera has a Network port, it supports wired/WiFi connection, otherwise, pls select wifi connection to connect.

2. Search and select the IP of the camera, click to add 3. Click the video to view until hearing "camera is online"

1. In the APP, click"+"> select "network cable connection"



.

5. Turn on the microphone 6. Screenshot to save the image 7. Swich into Full-screen image 8.Playback (SD card Playback | Cloud Playback) 9. Setting of cruise 10. Preset point settings 11. TZP rotation control 12. Turn on voice intercom

1. Return to the device list

3. More function settings

4. Switch image effects

2. Share the device

13. Turn on screen record function 1. Start Live video 2. Subscribe Cloud storage 3. More functions setup

4. User information 5. Modify the device name

Add more cameras



2. Modify the device name 3. Share equipment SD card setup 5. Detection alarm settings 6. Buy cloud storage 7. Image Flip: upside down 8. Choose a call mode 9. Enable/Disable Auto tracking 10, Indicator light switch 11. Choose night vision mode 12. Set the time zone 13. Switch WIFI network

1. Back to the device list

14. Camera information 15. Camera version number 16. Delete the camera 17. Transfer the camera to

another account

Share your camera with your friends and families 1. Your friend should have an account of cam720 APP.


2.in main account, enter the Email of the friend APP account or scanthe QR code of the account to share it. 3. Freely set the permission on this shared account.





1. Turn on the playback function and two Record method ava ilable: SDcard record(8-128G) and Cloud Record. 2. New users can get a trial cloud storage for free, pls don't

3.SD card record supports 3 record modes: 24/7 continuous, motion-triggered, scheduled record.





Installation

Indoor Camera-stent assembly 1. This camera can be placed on the desktop, or do ceil or Wall mounted.

2.Attach the bracket to the wall and make a mark on the hole to ponch holes, and use a 6mm drill bit to get the holes, then Stuff the rubber stopper into the hole. Subper into the role.

3. Align the bracket with the hole position and tighten the screws. Fix the body, hold the body and turnit tightly.





Important Use Notice

1. The use of unapproved or incompatible power adaptersmay cause

2. This product and accessories contain some small parts to avoid hildren contact and cause swallowing small parts, causing suffocation or other hazards, in addition, this product is not a toy, children should be used under adult supervision.

3. Please use this product within the appropriate temperature range. When the ambient temperature is too high or too low,it may cause errors, avoid rain or moisture on the product and its accessories, so as not to affect the use of the product.

4. Suitable for equipment, suitable for areas with an altitude of 2000 meters and below.

a closed environment installation which may cause bad signal.

Important Use Notice

1.Failed in connection at first connection? Pls view the operation video at last page(Scanthe QR code toview),

and pls view wifi connection steps from Page5, if still failed, pls message seller to get support, we also offer online support if you need. 2. Change a router, camera is offline? pls delete the camera from the APP, and take the camera to near the new router, power and reset it, search and add it.

3.Stop record? 1,Check the status of the SD card in the APP 2,Check the record setup 3,format SD card 4,change a SD card to test 5,message Seller to get support

4. Camera is offline? Read the Q3 at page 3 and follow it to check, if there is further question, pls message seller to get support $\,$

5. The instructions are not detailed enough? It's general quick user guide, so less many details, pls contact seller to get the E-user manual and operation video accordingto your order.

After-sale Service & Tech Support

We offer a one-year warranty and lifetime technical support! As long as there is any problem, please feel free to contact thepurchase store, we will quickly provide an effective solution.

E-mail: technicalreply@qacctv.com market@qacctv.com Tel: +1-202-945-9595 Website: http://www.qacctv.com

This manual is a quick guide for use. The pictures and illustrations provided in the manual are for illustration and illustraction purposesonly and may differ from the specific product. Please refer to the actual product, due to product version upgrades or other needs, tis manual may be updated. If you need the latest manual or trouble shooting oruser manual with more details, pls visit the offical website, or contacthe seller to get. By scanning the QR code below to access Youtube, Selectthe right operation video for your camera according to APP and Model of the camera Or message seller to get the operation video directly.



This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause

harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Wired Connection

cable to the router

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna. -Increase the separation between the equipment and receiver. -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.