



单张纸(凤琴式折叠)

版本	修改内容	修改日期
R01/00		

PISEN P2真无线蓝牙耳机(国际版)(BHD-TW13)_说明书

材质: 太阳60g双胶纸, 双面印刷, 1C
展开尺寸: 208×70mm, 成品尺寸: 52×70mm

封面

PISEN®

P2
(BHD-TW13)

User Manual

Q.C. PASSED, RoHS, CE, FCC, etc.

For FAQs and more help information, please visit: <https://en.pisengroup.com>
Contact: support@pisengroup.com

Specification parameters

Product model	BHD-TW13
FCC ID	2BCVO-BHD-TW13
Dimensions	50.5*45.5*21.8mm (1.99*1.79*0.86in)
Weight	Approx. 38.1g (1.34oz)
Battery type	Rechargeable polymer lithium battery
Charging input	DC 5V=1A
Battery capacity of earbuds	35mAh*2
Battery capacity of charging case	400mAh
Rated voltage	3.7V
Frequency response range	20Hz-20KHz
Charging time	Approx. 1.5h
Endurance	Approx. 22h
Endurance of single earbud	Approx. 5.5h (50% volume)
Operation range	≤10 meters
Supported protocols	Headset / Handsfree / A2DP / AVRCP
Accessories	Earbud*2, earbuds charging case*1, Type-C charging cable*1, User Manual*1, Large/Medium/Small ear caps each *2

The above data is sourced from the PISEN Laboratory, while actual parameters may vary with product or other factors.

Kind reminders

Thank you for buying the P2. Please read this manual carefully to ensure safe and satisfactory operation, and properly keep it for future reference.

- The specifications and external appearance of this product are subject to change and improvement at any time.
- The design and specifications are subject to change without prior notice.
- Please clean the earbuds with a dry cloth frequently.

Product diagram

Use instructions for earbuds

- Power-on**
Open the lid of charging case, and the earbuds will be automatically powered on.
- Power-off**
a. Put the earphones into the charging case and close the lid, the earphones will turn off and charge.
b. Long press any earphone touch function button for 8 seconds to turn off the earphones.
- Earbuds pairing**
Open the charging case when the battery is under normal condition, and the left and right earbuds will be automatically powered on and paired with the device.
- Connecting to a mobile phone**
 - Dual earphone connection to phone**
Open the charging case, the earphones enter pairing mode. Search for the pairing name "Pisen P2" on the phone, Click to connect, and after successful connection, a prompt sound will be played. (Supports single earphone connection)
 - Automatically connect to phone**
When there is a pairing record, open the charging case cover and the earphones will automatically reconnect to the most recently connected phone.

Instructions for earbuds touch controls

Music play mode

- Pause/Play: Double click on the function key of any earphone
- Next track: Triple click on the function key on the right earphone(R)
- Previous track: Three clicks on the right earphone(R)

Phone-call mode

- Answer: Double click on the function key of any earphone
- Hang up: Double click on the function key of any earphone
- Reject: Press and hold the function button of any earphone for 2 seconds

Game mode

Touch the function key of any earphone 4 times to open game mode, repeat the operation to close it.

Voice assistant

When the earphones are connected to the phone, long press the function button on the left earphone for 3 seconds to activate the voice control function. Repeat the operation to exit.

Factory reset

Open the cover of the charging case press and hold the reset button of the charging box for 10 seconds until the white indicator light flashes quickly for 3 seconds before turning off. At this time, the earphones are turned off and the factory settings have been successfully restored.

Mode Switching

After the earphones are turned on, they default to active ANC noise reduction mode. Long press for 3 seconds to enter normal mode, and then long press for 3 seconds to enter transparent mode, and cycle through switching in sequence.
Note: The mode switch only needs to be long pressed on the right ear for 3 seconds, and do not need to wait until 3 seconds to release the finger.

LED indicator state

Charging indicator

- Charge the earbuds in the charging case:
Place the earphones into the charging case and close the cover. The white indicator light on the charging case will remain on for 4 seconds, two (left and right) earphones are charging normally.
- Low battery warning for charging case:
After opening the charging box cover:
Low battery: The white indicator light flashes for 4 seconds before turning off.
- Charging the charging case:
Charging: White indicator light flashing.
Fully charged: The white indicator light remains on.

Warning:

- Please store and use the product at normal temperature;
- Do not expose the product to the rain or humid environment;
- Do not throw or toss the product, so as to avoid damage;
- Do not disassemble, repair, or modify the product by yourself;
- The product contains a non-replaceable lithium battery, so be sure not to dispose of it randomly, put it in fire, or expose it to direct sunlight, so as to avoid hazards;
- Please dispose of the battery according to local regulations and recycle it whenever possible, and be sure not to dispose of it as the domestic waste, so as to avoid environmental pollution.

Kind reminders:

- To avoid the hearing damage, please keep the volume at a moderate level and avoid listening to music at a high volume for a long time, as it may result in permanent hearing damage or deafness.
- Please refrain from making phone calls or using earbuds while driving, cycling, crossing roads, or engaging in situations that require focused attention.
- When watching videos with earbuds, the audio and video may get out of sync slightly.
- If the earbuds are not used for a long time, please fully charge them at least once a month to extend the battery life.
- If the earbuds are still connected or not charged after being put into the charging case, please wipe the stain on the charging contacts of earbuds to ensure good charging contact.
- The output voltage and current of charger shall not exceed 5V/1A. If their specified values are exceeded, the product will be seriously damaged and the warranty will be voided.

FCC Warning:

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no

guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Name and company of U.S. agent: FCC US Agent, LLC
Physical U.S. address of agent: 3722 Illinois Avenue, Saint Charles, IL 60174, USA
FRN of U.S. agent: 0033402884
Email address of U.S. agent: Support@FCCUSAgent.com

PATECH_ISC
Address: B26*27, Quarter B, Hoang Cau Str, O Cho Dua Ward, Dong Da Dist, Ha Noi, Viet Nam
Tel: 0084 -24 66616999

Yarn En Tees (PH)
Address: 7th Floor Unit 3,1464 Antonio Rivera St. Tondo Manila
Tel: 09816089999

Import by: AOCE INFORMATION TECHNOLOGY
Add: G1 rue de Lyon 75012 Paris
Contact(Name,email,tel): Johnson.wang , aoce-service@outlook.com
Tel:+9-163 1014 128

Design By Pisen Made in China
Manufacturer: GUANGDONG PISEN ELECTRONICS CO., LTD.
Address: No.9, Cinfu 1st street, Jintang Industrial Park, Henggang Town, Longgang Distrit, Shenzhen, P.R.China

PISEN The brand belongs to GUANGDONG PISEN ELECTRONICS CO., LTD.

设计	黄运安	日期	2024-01-15	材料	成品规格	52×70mm	物料编码	物料名称: PISEN P2真无线蓝牙耳机(国际版)(BHD-TW13)_说明书
审核	杜志鸿	日期	2024-01-15	工艺	单位	mm	品胜股份 PISEN SHARES	产品中心
批准	卢松	日期	2024-01-15	比例	1:1	公差		