Bt36 helmet Bluetooth headset



AN INSTRUCTION MANUAL

FCC STATEMENT

- This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received, including interference that may cause undesired operation.
- 2. Changes or modifications not expressly approved by the party. responsible for compliance could void the user's authority to operate the equipment.
- NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules, These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio
- communications, However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the
- Reorient or relocate the receiving antenna. Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the
- Consult the dealer or an experienced radio/TV technician for help. RF warning statement
- The device has been evaluated to meet general RF exposure requirement, The device can be used in portable exposure condition without restriction.

Welcome to use this helmet Bluetooth headset. I hope you can read this manual carefully and operate it more easily and install it more quickly

This product uses the latest 5.3 Bluetooth chip, uses the latest Bluetooth technology, stereo and strong. Ultra-strong signal transmission, ultra-low power consumption, and support for all Bluetooth devices to automatically answer calls, and no longer need to answer calls manually when calling, safe and fast. Use 40MM strong magnetic high-quality speaker

Press the telephone symbol key " 🔥 " Two to three seconds and the machine can be started. At this time, the indicator light will flash alternately red and blue, and the machine is in the starting state. Press the phone symbol key to turn off " 💍" Two to three seconds and it can be turned off, there will be a prompt tone, and the light will not light up after turning off

After power-on, the indicator light flashes red and blue alternately. At this time, do not connect with the mobile phone, and press it quickly and continuously for 2 times " 🔥 " Start key, and switch between Chinese and English voice.

After the Bluetooth headset is turned on, connect with the mobile phone A first, then turn off the Bluetooth of the mobile phone A, and then turn on the Bluetooth of the mobile phone A, and then connect two mobile phones at the same time.

After power-on, the indicator light flashes red and blue alternately. At this time, turn on the Bluetooth device on the mobile phone, search for the Bluetooth device on the mobile phone, and find the "BT36" point to connect for a few seconds. Once connected, the next time you use it, the phone Bluetooth and Bluetooth headset will be automatically connected when both are turned on.

Multi-function knob, turn it forward for the previous song, turn it backward for the next song, turn it forward for the volume decrease, and turn it back for the volume increase. Press the middle phone symbol " 🔊 " to pause the playback.

When you call, there will be a mobile phone number broadcast, and then you can answer the call automatically, or you can press the telephone symbol "🔊" key to answer the

The low power of the product will give a voice prompt for charging. It can be fully charged for 3-4 hours. The red light will be on when charging, and the red light will be off when

three

Press the " ." key once to activate the Siri function of the

Press "A" once to switch between automatic answering and non-automatic answering


Press the FM button once to switch to the FM radio model. Press and hold the telephone symbol button for two seconds to search for a radio station. After searching for a radio station, one of the radio stations will be played. Turn the multi-function knob forward or backward to switch to different radio buttons. The radio volume will slowly decrease, and the radio volume will slowly increase.

- 1. Bluetooth version: V5.3+EDR
- 2. Frequency range: 2.4026GHZ-2.480GHZ Transmission distance: above 10M
- 4. MIC distance:<1m
- 5. Battery: 3.7V/600 mAh
- 6. Charging time: 2-3 hours
- . Standby time: about 120 hours 8. Continuous working time: about 15 hours
- . Bluetooth name: BT36



Click to start Siri function


Red and blue indicator



Push back to pull out the base clip

Click to turn on the radio

Click to switch between automatic



four

9





installation diagram



one







Installation of back clamp base



installation diagram











ee the left figure for nstallation. The horn is lose to the ear, and the microphone rod is installed t a suitable position

nine



nstallation of right horn:

pare wool round velcro ape, tear off white release



















- 1. A helmet Bluetooth headset.
- 2. One charging cable.
- 3. One manual 4. Two spare surgical stickers.
- 5. One spare cotton.