

# **Antenna Datasheet**

Product OC: Y0YRX00A1FA

Version: 1.0

Date: 2024-06-29 Status: Preliminary

Product Name: Wifi/BT

**Key Features:** 

Frequency Band: 2400-2500

Dimensions: 20\*14mm Efficiency: Up to 42.7%

RoHS and REACH Compliant

## Overview

Quectel Wi-Fi 2.4G antenna covers 2.4 ~2.5GHz bands, fully satisfying customers' requirements for Wi-Fi/Zigbee/BT antennas. There are various antenna types, including built-in FPC/PCB antenna, ceramic patch antenna, and other external antennas of different shapes or sizes. The antenna performance meets the customers' demands for efficiency, gain, and radiation and ensures the superior experience of the customers' products in use.



# **Contents**

O١	/erview		2
Сс	ontents		3
1	Specification	on	4
	1.1. Elec	trical	4
	1.2. Mec	chanical, Environmental	5
2	Drawing		6
3	Detailed F	Performance	7
	3.1. S-Pa	arameter Test	7
	3.1.1.	VSWR	7
	3.1.2.	Return Loss	8
	3.2. Radi	iation Performance Test	9
	3.2.1.	Efficiency	9
	3.2.2.	Average Gain	10
	3.2.3.	Peak Gain	11
	3.2.4.	3D & 2D Radiation Pattern	12
4	Packaging.		15
Сс	ntact US		16
Le	gal Notices		17
Re	vision Histor	7	19



# 1 Specification

Test Condition: Assembled in test device

#### 1.1. Electrical

Electrical						
Frequency Range	2400-2500MHz					
Impedance	50 Ω					
Polarization	Linear					
Radiation Pattern	Omni-directional					

Electrical - Detail													
Band	Band	B71	B12 /B13 /B28	B5 /B8 /B26	N74 /N75 /N76	B1 /B2 /B3	B40	Wi-Fi/B T 2G	B38 /B41	B42 /B48 /N77	N79	Wi-Fi 5G	
SPEC	Freq.	600-	700-	820-	1420-1	1700-2	2300-2	2400-2	2500-2	3300-4	4400-5	5150-5	
	(MHz)	700	810	960	520	170	400	500	690	200	000	850	
Max. VS	WR	-	-	-	_	-	-	2.4	-	_	_	_	
Max. Return Loss (dB)		-	-	-	-	-	-	-7.9	-	-	-	-	
AVG Eff.	(%)	-	-	-	_	_	-	40.3	_	_	_	-	
AVG AV	G Gain (dB)	-	-	-	_	_	-	-4.0	_	_	-	-	
Max. Peak Gain (dBi)		-	-	-	_	-	-	2.2	-	-	-	-	
VSWR						≤ 2	≤ 2.4						
Return L	.oss					≤ -	≤ -7.9 dB						
Peak Ga	in					≤ 2	≤ 2.2 dBi						

Antenna\_Datasheet 4 / 19




## 1.2. Mechanical, Environmental


Mechanical							
Antenna Dimensions	20* 14 *0.1mm						
Material & Color	FPC & Black						
Cable Type & Color & Length	Ф0.81 & Black & 60mm						
Connector Type	IPEX MHF 1						
Mounting Type	Adhesive						
Weight	Typ.0.3g						
Environmental							
Operation Temperature	-40 °C to +85 °C						
Storage Temperature	-40 °C to +85 °C						
RoHS & REACH Compliant	Yes						

Antenna\_Datasheet 5 / 19



# 2 Drawing






Antenna\_Datasheet 6 / 19



# 3 Detailed Performance

#### 3.1. S-Parameter Test

#### 3.1.1. VSWR




#### **VSWR**

Frequency (MHz)	2400	2450	2500	-	_	_	_	_	_	-
VSWR	2.4	2.0	1.7	_	_	_	_	_	_	_

Antenna\_Datasheet 7 / 19



#### 3.1.2. Return Loss



#### Return Loss (dB)

Frequency (MHz)	2400	2450	2500	-	_	_	_	-	_	-
Return Loss (dB)	-7.9	-9.7	-12.2	_	_	_	_	_	_	-

Antenna\_Datasheet 8 / 19



#### 3.2. Radiation Performance Test

#### 3.2.1. Efficiency




#### Efficiency (%)

Frequency (MHz)	2400	2450	2500	_	_	_	_	_	_	-
Efficiency (%)	36.2	41.1	42.7	_	_	_	_	_	_	_

Antenna\_Datasheet 9 / 19



#### 3.2.2. Average Gain




#### Average Gain (dB)

Frequency (MHz)	2400	2450	2500	-	-	-	-	-	_	-
Average Gain (dB)	-4.4	-3.9	-3.7	-	-	_	_	_	_	-

Antenna\_Datasheet 10 / 19



#### 3.2.3. Peak Gain



#### Peak Gain (dBi)

Frequency (MHz)	2400	2450	2500	-	-	-	-	-	-	-
Peak Gain (dBi)	2.1	1.9	0.7	_	_	_	_	_	_	_


Antenna\_Datasheet 11 / 19



#### 3.2.4. 3D & 2D Radiation Pattern


• Test Condition: Assembled in test device

• Test Chamber: HF-G-1



Antenna\_Datasheet 12 / 19





Antenna\_Datasheet 13 / 19



# 4 Packaging

Antenna\_Datasheet 14 / 19



### **Contact US**

At Quectel, our aim is to provide timely and comprehensive services to our customers. If you require any assistance, please contact our headquarters:

Quectel Wireless Solutions Co., Ltd.

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai 200233, China

Tel: +86 21 5108 6236 Email: <u>info@quectel.com</u>

Or our local offices. For more information, please visit:

http://www.quectel.com/support/sales.htm.

For technical support, or to report documentation errors, please visit:

http://www.quectel.com/support/technical.htm.

Or email us at: <a href="mailto:support@quectel.com">support@quectel.com</a>.

Antenna\_Datasheet 15 / 19



# **Legal Notices**

We offer information as a service to you. The provided information is based on your requirements and we make every effort to ensure its quality. You agree that you are responsible for using independent analysis and evaluation in designing intended products, and we provide reference designs for illustrative purposes only. Before using any hardware, software or service guided by this document, please read this notice carefully. Even though we employ commercially reasonable efforts to provide the best possible experience, you hereby acknowledge and agree that this document and related services hereunder are provided to you on an "as available" basis. We may revise or restate this document from time to time at our sole discretion without any prior notice to you.

#### Use and Disclosure Restrictions

#### **License Agreements**

Documents and information provided by us shall be kept confidential, unless specific permission is granted. They shall not be accessed or used for any purpose except as expressly provided herein.

#### Copyright

Our and third-party products hereunder may contain copyrighted material. Such copyrighted material shall not be copied, reproduced, distributed, merged, published, translated, or modified without prior written consent. We and the third party have exclusive rights over copyrighted material. No license shall be granted or conveyed under any patents, copyrights, trademarks, or service mark rights. To avoid ambiguities, purchasing in any form cannot be deemed as granting a license other than the normal non-exclusive, royalty-free license to use the material. We reserve the right to take legal action for noncompliance with abovementioned requirements, unauthorized use, or other illegal or malicious use of the material.

#### **Trademarks**

Except as otherwise set forth herein, nothing in this document shall be construed as conferring any rights to use any trademark, trade name or name, abbreviation, or counterfeit product thereof owned by Quectel or any third party in advertising, publicity, or other aspects.

#### Third-Party Rights

This document may refer to hardware, software and/or documentation owned by one or more third parties ("third-party materials"). Use of such third-party materials shall be governed by all restrictions and obligations applicable thereto.

Antenna\_Datasheet 16 / 19



We make no warranty or representation, either express or implied, regarding the third-party materials, including but not limited to any implied or statutory, warranties of merchantability or fitness for a particular purpose, quiet enjoyment, system integration, information accuracy, and non-infringement of any third-party intellectual property rights with regard to the licensed technology or use thereof. Nothing herein constitutes a representation or warranty by us to either develop, enhance, modify, distribute, market, sell, offer for sale, or otherwise maintain production of any our products or any other hardware, software, device, tool, information, or product. We moreover disclaim any and all warranties arising from the course of dealing or usage of trade.

### **Privacy Policy**

To implement module functionality, certain device data are uploaded to Quectel's or third-party's servers, including carriers, chipset suppliers or customer-designated servers. Quectel, strictly abiding by the relevant laws and regulations, shall retain, use, disclose or otherwise process relevant data for the purpose of performing the service only or as permitted by applicable laws. Before data interaction with third parties, please be informed of their privacy and data security policy.

#### Disclaimer

- a) We acknowledge no liability for any injury or damage arising from the reliance upon the information.
- b) We shall bear no liability resulting from any inaccuracies or omissions, or from the use of the information contained herein.
- c) While we have made every effort to ensure that the functions and features under
- d) development are free from errors, it is possible that they could contain errors, inaccuracies, and omissions. Unless otherwise provided by valid agreement, we make no warranties of any kind, either implied or express, and exclude all liability for any loss or damage suffered in connection with the use of features and functions under development, to the maximum extent permitted by law, regardless of whether such loss or damage may have been foreseeable.
- e) We are not responsible for the accessibility, safety, accuracy, availability, legality, or completeness of information, advertising, commercial offers, products, services, and materials on third-party websites and third-party resources.

Copyright © Quectel Wireless Solutions Co., Ltd. 2022. All rights reserved.

Antenna\_Datasheet 17 / 19



# **Revision History**

Version	Date	Author	Note
-	2023-11-02	Raoul Rao Vinnie Liu	Creation of the document
1.0	2023-11-02	Raoul Rao Vinnie Liu	First official release



Antenna\_Datasheet 19 / 19