

ES3DV3- SN:3335

July 26, 2018

|           |   |   |        |        |       |      |       |         |
|-----------|---|---|--------|--------|-------|------|-------|---------|
| 10081-CAB | CDMA2000 (1xRTT, RC3)                               | X | 0.87   | 65.42  | 12.69 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.92   | 67.28  | 13.42 |      | 150.0 |         |
|           |   | Z | 0.72   | 64.00  | 11.01 |      | 150.0 |         |
| 10082-CAB | IS-54 / IS-136 FDD (TDMA/FDM, PI/4-DQPSK, Fullrate) | X | 2.45   | 64.58  | 9.62  | 4.77 | 80.0  | ± 9.6 % |
|           |   | Y | 1.95   | 63.35  | 8.27  |      | 80.0  |         |
|           |   | Z | 1.78   | 62.53  | 7.60  |      | 80.0  |         |
| 10090-DAC | GPRS-FDD (TDMA, GMSK, TN 0-4)                       | X | 34.04  | 103.41 | 27.54 | 6.56 | 60.0  | ± 9.6 % |
|           |   | Y | 100.00 | 117.70 | 30.00 |      | 60.0  |         |
|           |   | Z | 100.00 | 116.43 | 29.25 |      | 60.0  |         |
| 10097-CAB | UMTS-FDD (HSDPA)                                    | X | 1.78   | 66.78  | 15.22 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 1.86   | 68.12  | 15.94 |      | 150.0 |         |
|           |   | Z | 1.71   | 66.61  | 14.83 |      | 150.0 |         |
| 10098-CAB | UMTS-FDD (HSUPA, Subtest 2)                         | X | 1.74   | 66.72  | 15.17 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 1.82   | 68.10  | 15.91 |      | 150.0 |         |
|           |   | Z | 1.67   | 66.56  | 14.79 |      | 150.0 |         |
| 10099-DAC | EDGE-FDD (TDMA, 8PSK, TN 0-4)                       | X | 14.93  | 94.01  | 31.86 | 9.56 | 60.0  | ± 9.6 % |
|           |   | Y | 24.04  | 109.03 | 37.58 |      | 60.0  |         |
|           |   | Z | 19.46  | 103.72 | 35.62 |      | 60.0  |         |
| 10100-CAE | LTE-FDD (SC-FDMA, 100% RB, 20 MHz, QPSK)            | X | 3.18   | 70.09  | 16.29 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 3.26   | 71.07  | 16.92 |      | 150.0 |         |
|           |   | Z | 2.98   | 69.50  | 16.02 |      | 150.0 |         |
| 10101-CAE | LTE-FDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM)          | X | 3.33   | 67.56  | 15.77 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 3.32   | 67.99  | 16.09 |      | 150.0 |         |
|           |   | Z | 3.18   | 67.22  | 15.56 |      | 150.0 |         |
| 10102-CAE | LTE-FDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM)          | X | 3.44   | 67.51  | 15.87 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 3.41   | 67.91  | 16.16 |      | 150.0 |         |
|           |   | Z | 3.29   | 67.20  | 15.67 |      | 150.0 |         |
| 10103-CAF | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, QPSK)            | X | 8.45   | 77.00  | 20.66 | 3.98 | 65.0  | ± 9.6 % |
|           |   | Y | 8.95   | 79.30  | 21.65 |      | 65.0  |         |
|           |   | Z | 8.61   | 78.70  | 21.35 |      | 65.0  |         |
| 10104-CAF | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM)          | X | 8.54   | 76.02  | 21.10 | 3.98 | 65.0  | ± 9.6 % |
|           |   | Y | 8.57   | 77.37  | 21.76 |      | 65.0  |         |
|           |   | Z | 8.26   | 76.73  | 21.40 |      | 65.0  |         |
| 10105-CAF | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM)          | X | 7.72   | 74.02  | 20.51 | 3.98 | 65.0  | ± 9.6 % |
|           |   | Y | 7.88   | 75.69  | 21.33 |      | 65.0  |         |
|           |   | Z | 7.54   | 74.95  | 20.94 |      | 65.0  |         |
| 10108-CAF | LTE-FDD (SC-FDMA, 100% RB, 10 MHz, QPSK)            | X | 2.82   | 69.31  | 16.12 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.86   | 70.28  | 16.75 |      | 150.0 |         |
|           |   | Z | 2.61   | 68.76  | 15.84 |      | 150.0 |         |
| 10109-CAF | LTE-FDD (SC-FDMA, 100% RB, 10 MHz, 16-QAM)          | X | 3.00   | 67.31  | 15.68 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.98   | 67.82  | 16.01 |      | 150.0 |         |
|           |   | Z | 2.83   | 66.99  | 15.42 |      | 150.0 |         |
| 10110-CAF | LTE-FDD (SC-FDMA, 100% RB, 5 MHz, QPSK)             | X | 2.31   | 68.29  | 15.75 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.33   | 69.40  | 16.43 |      | 150.0 |         |
|           |   | Z | 2.11   | 67.80  | 15.39 |      | 150.0 |         |
| 10111-CAF | LTE-FDD (SC-FDMA, 100% RB, 5 MHz, 16-QAM)           | X | 2.69   | 67.70  | 15.91 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.68   | 68.49  | 16.29 |      | 150.0 |         |
|           |   | Z | 2.52   | 67.50  | 15.55 |      | 150.0 |         |

ES3DV3- SN:3335

July 26, 2018

|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10112-CAF | LTE-FDD (SC-FDMA, 100% RB, 10 MHz, 64-QAM)     | X | 3.13 | 67.27 | 15.74 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.10 | 67.76 | 16.04 |      | 150.0 |         |
|           |  | Z | 2.96 | 67.00 | 15.50 |      | 150.0 |         |
| 10113-CAF | LTE-FDD (SC-FDMA, 100% RB, 5 MHz, 64-QAM)      | X | 2.85 | 67.81 | 16.04 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.83 | 68.57 | 16.39 |      | 150.0 |         |
|           |  | Z | 2.67 | 67.67 | 15.71 |      | 150.0 |         |
| 10114-CAC | IEEE 802.11n (HT Greenfield, 13.5 Mbps, BPSK)  | X | 5.23 | 67.18 | 16.32 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.17 | 67.42 | 16.48 |      | 150.0 |         |
|           |  | Z | 5.12 | 67.20 | 16.31 |      | 150.0 |         |
| 10115-CAC | IEEE 802.11n (HT Greenfield, 81 Mbps, 16-QAM)  | X | 5.62 | 67.53 | 16.50 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.53 | 67.73 | 16.64 |      | 150.0 |         |
|           |  | Z | 5.44 | 67.42 | 16.43 |      | 150.0 |         |
| 10116-CAC | IEEE 802.11n (HT Greenfield, 135 Mbps, 64-QAM) | X | 5.36 | 67.45 | 16.37 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.30 | 67.68 | 16.53 |      | 150.0 |         |
|           |  | Z | 5.23 | 67.43 | 16.35 |      | 150.0 |         |
| 10117-CAC | IEEE 802.11n (HT Mixed, 13.5 Mbps, BPSK)       | X | 5.24 | 67.21 | 16.36 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.16 | 67.37 | 16.47 |      | 150.0 |         |
|           |  | Z | 5.09 | 67.08 | 16.26 |      | 150.0 |         |
| 10118-CAC | IEEE 802.11n (HT Mixed, 81 Mbps, 16-QAM)       | X | 5.66 | 67.60 | 16.55 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.61 | 67.91 | 16.74 |      | 150.0 |         |
|           |  | Z | 5.53 | 67.66 | 16.56 |      | 150.0 |         |
| 10119-CAC | IEEE 802.11n (HT Mixed, 135 Mbps, 64-QAM)      | X | 5.33 | 67.41 | 16.37 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.27 | 67.61 | 16.51 |      | 150.0 |         |
|           |  | Z | 5.20 | 67.37 | 16.33 |      | 150.0 |         |
| 10140-CAE | LTE-FDD (SC-FDMA, 100% RB, 15 MHz, 16-QAM)     | X | 3.49 | 67.52 | 15.80 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.46 | 67.91 | 16.08 |      | 150.0 |         |
|           |  | Z | 3.32 | 67.21 | 15.60 |      | 150.0 |         |
| 10141-CAE | LTE-FDD (SC-FDMA, 100% RB, 15 MHz, 64-QAM)     | X | 3.61 | 67.57 | 15.96 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.58 | 67.96 | 16.23 |      | 150.0 |         |
|           |  | Z | 3.45 | 67.32 | 15.78 |      | 150.0 |         |
| 10142-CAE | LTE-FDD (SC-FDMA, 100% RB, 3 MHz, QPSK)        | X | 2.08 | 68.08 | 15.51 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.11 | 69.40 | 16.18 |      | 150.0 |         |
|           |  | Z | 1.87 | 67.56 | 14.95 |      | 150.0 |         |
| 10143-CAE | LTE-FDD (SC-FDMA, 100% RB, 3 MHz, 16-QAM)      | X | 2.54 | 68.19 | 15.75 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.55 | 69.24 | 16.11 |      | 150.0 |         |
|           |  | Z | 2.34 | 67.89 | 15.11 |      | 150.0 |         |
| 10144-CAE | LTE-FDD (SC-FDMA, 100% RB, 3 MHz, 64-QAM)      | X | 2.39 | 66.48 | 14.47 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.36 | 67.19 | 14.65 |      | 150.0 |         |
|           |  | Z | 2.17 | 66.00 | 13.70 |      | 150.0 |         |
| 10145-CAF | LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, QPSK)      | X | 1.45 | 66.26 | 13.30 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.39 | 66.72 | 13.04 |      | 150.0 |         |
|           |  | Z | 1.13 | 64.09 | 11.04 |      | 150.0 |         |
| 10146-CAF | LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, 16-QAM)    | X | 3.03 | 71.19 | 15.45 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.28 | 72.65 | 15.20 |      | 150.0 |         |
|           |  | Z | 2.22 | 67.64 | 12.46 |      | 150.0 |         |
| 10147-CAF | LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, 64-QAM)    | X | 3.70 | 74.14 | 16.90 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.47 | 76.81 | 17.01 |      | 150.0 |         |
|           |  | Z | 2.67 | 69.97 | 13.67 |      | 150.0 |         |

ES3DV3-SN:3335

July 26, 2018

|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10149-CAE | LTE-FDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM)  | X | 3.01 | 67.37 | 15.72 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.98 | 67.88 | 16.05 |      | 150.0 |         |
|           |  | Z | 2.84 | 67.04 | 15.46 |      | 150.0 |         |
| 10150-CAE | LTE-FDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM)  | X | 3.13 | 67.31 | 15.78 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.10 | 67.80 | 16.08 |      | 150.0 |         |
|           |  | Z | 2.97 | 67.05 | 15.54 |      | 150.0 |         |
| 10151-CAF | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, QPSK)    | X | 8.72 | 78.65 | 21.42 | 3.98 | 65.0  | ± 9.6 % |
|           |  | Y | 9.51 | 81.62 | 22.63 |      | 65.0  |         |
|           |  | Z | 9.09 | 80.92 | 22.26 |      | 65.0  |         |
| 10152-CAF | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM)  | X | 8.14 | 76.09 | 20.94 | 3.98 | 65.0  | ± 9.6 % |
|           |  | Y | 8.23 | 77.66 | 21.63 |      | 65.0  |         |
|           |  | Z | 7.86 | 76.88 | 21.18 |      | 65.0  |         |
| 10153-CAF | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM)  | X | 8.49 | 76.79 | 21.56 | 3.98 | 65.0  | ± 9.6 % |
|           |  | Y | 8.61 | 78.43 | 22.29 |      | 65.0  |         |
|           |  | Z | 8.30 | 77.82 | 21.92 |      | 65.0  |         |
| 10154-CAF | LTE-FDD (SC-FDMA, 50% RB, 10 MHz, QPSK)    | X | 2.37 | 68.75 | 16.05 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.38 | 69.82 | 16.69 |      | 150.0 |         |
|           |  | Z | 2.16 | 68.16 | 15.63 |      | 150.0 |         |
| 10155-CAF | LTE-FDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM)  | X | 2.69 | 67.70 | 15.91 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.68 | 68.50 | 16.30 |      | 150.0 |         |
|           |  | Z | 2.52 | 67.51 | 15.56 |      | 150.0 |         |
| 10156-CAF | LTE-FDD (SC-FDMA, 50% RB, 5 MHz, QPSK)     | X | 1.94 | 68.21 | 15.44 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.97 | 69.62 | 16.09 |      | 150.0 |         |
|           |  | Z | 1.71 | 67.46 | 14.64 |      | 150.0 |         |
| 10157-CAF | LTE-FDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM)   | X | 2.22 | 66.95 | 14.55 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.20 | 67.85 | 14.77 |      | 150.0 |         |
|           |  | Z | 1.98 | 66.32 | 13.60 |      | 150.0 |         |
| 10158-CAF | LTE-FDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM)  | X | 2.85 | 67.85 | 16.07 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.84 | 68.62 | 16.43 |      | 150.0 |         |
|           |  | Z | 2.68 | 67.73 | 15.75 |      | 150.0 |         |
| 10159-CAF | LTE-FDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM)   | X | 2.33 | 67.38 | 14.85 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.31 | 68.28 | 15.05 |      | 150.0 |         |
|           |  | Z | 2.08 | 66.72 | 13.87 |      | 150.0 |         |
| 10160-CAE | LTE-FDD (SC-FDMA, 50% RB, 15 MHz, QPSK)    | X | 2.81 | 68.32 | 15.96 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.83 | 69.17 | 16.49 |      | 150.0 |         |
|           |  | Z | 2.66 | 68.09 | 15.77 |      | 150.0 |         |
| 10161-CAE | LTE-FDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM)  | X | 3.03 | 67.18 | 15.72 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.00 | 67.72 | 16.02 |      | 150.0 |         |
|           |  | Z | 2.86 | 66.96 | 15.45 |      | 150.0 |         |
| 10162-CAE | LTE-FDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM)  | X | 3.13 | 67.23 | 15.79 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.10 | 67.82 | 16.11 |      | 150.0 |         |
|           |  | Z | 2.97 | 67.10 | 15.57 |      | 150.0 |         |
| 10166-CAF | LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK)   | X | 3.95 | 69.79 | 19.16 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.96 | 71.22 | 19.96 |      | 150.0 |         |
|           |  | Z | 3.74 | 70.24 | 19.36 |      | 150.0 |         |
| 10167-CAF | LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM) | X | 5.00 | 72.57 | 19.59 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 5.28 | 75.30 | 20.83 |      | 150.0 |         |
|           |  | Z | 4.78 | 73.62 | 19.97 |      | 150.0 |         |

ES3DV3- SN:3335

July 26, 2018

|           |  |   |       |        |       |      |       |         |
|-----------|--|---|-------|--------|-------|------|-------|---------|
| 10168-CAF | LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM) | X | 5.44  | 74.41  | 20.71 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 5.90  | 77.67  | 22.14 |      | 150.0 |         |
|           |  | Z | 5.35  | 76.06  | 21.36 |      | 150.0 |         |
| 10169-CAE | LTE-FDD (SC-FDMA, 1 RB, 20 MHz, QPSK)      | X | 3.65  | 71.15  | 19.66 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.61  | 72.65  | 20.61 |      | 150.0 |         |
|           |  | Z | 3.24  | 70.52  | 19.48 |      | 150.0 |         |
| 10170-CAE | LTE-FDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)    | X | 5.24  | 76.96  | 21.77 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 6.01  | 81.72  | 23.86 |      | 150.0 |         |
|           |  | Z | 4.86  | 77.77  | 22.21 |      | 150.0 |         |
| 10171-AAE | LTE-FDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM)    | X | 4.29  | 72.74  | 19.11 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 4.63  | 76.11  | 20.69 |      | 150.0 |         |
|           |  | Z | 3.85  | 72.83  | 19.17 |      | 150.0 |         |
| 10172-CAF | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, QPSK)      | X | 17.76 | 97.33  | 29.58 | 6.02 | 65.0  | ± 9.6 % |
|           |  | Y | 73.92 | 128.98 | 38.93 |      | 65.0  |         |
|           |  | Z | 35.06 | 114.40 | 34.96 |      | 65.0  |         |
| 10173-CAF | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)    | X | 18.67 | 94.64  | 27.36 | 6.02 | 65.0  | ± 9.6 % |
|           |  | Y | 83.79 | 124.05 | 35.58 |      | 65.0  |         |
|           |  | Z | 47.03 | 114.00 | 32.91 |      | 65.0  |         |
| 10174-CAF | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM)    | X | 15.92 | 90.86  | 25.73 | 6.02 | 65.0  | ± 9.6 % |
|           |  | Y | 54.27 | 114.54 | 32.57 |      | 65.0  |         |
|           |  | Z | 34.11 | 106.79 | 30.40 |      | 65.0  |         |
| 10175-CAF | LTE-FDD (SC-FDMA, 1 RB, 10 MHz, QPSK)      | X | 3.59  | 70.78  | 19.39 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.56  | 72.27  | 20.34 |      | 150.0 |         |
|           |  | Z | 3.20  | 70.17  | 19.22 |      | 150.0 |         |
| 10176-CAF | LTE-FDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM)    | X | 5.24  | 76.99  | 21.78 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 6.02  | 81.75  | 23.87 |      | 150.0 |         |
|           |  | Z | 4.87  | 77.79  | 22.22 |      | 150.0 |         |
| 10177-CAH | LTE-FDD (SC-FDMA, 1 RB, 5 MHz, QPSK)       | X | 3.63  | 70.97  | 19.51 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.69  | 72.45  | 20.44 |      | 150.0 |         |
|           |  | Z | 3.23  | 70.34  | 19.32 |      | 150.0 |         |
| 10178-CAF | LTE-FDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM)     | X | 5.16  | 76.67  | 21.62 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 5.93  | 81.41  | 23.72 |      | 150.0 |         |
|           |  | Z | 4.80  | 77.51  | 22.08 |      | 150.0 |         |
| 10179-CAF | LTE-FDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM)    | X | 4.70  | 74.64  | 20.27 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 5.25  | 78.72  | 22.12 |      | 150.0 |         |
|           |  | Z | 4.30  | 75.11  | 20.53 |      | 150.0 |         |
| 10180-CAF | LTE-FDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM)     | X | 4.27  | 72.64  | 19.05 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 4.61  | 76.01  | 20.63 |      | 150.0 |         |
|           |  | Z | 3.83  | 72.74  | 19.12 |      | 150.0 |         |
| 10181-CAE | LTE-FDD (SC-FDMA, 1 RB, 15 MHz, QPSK)      | X | 3.62  | 70.95  | 19.50 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.59  | 72.43  | 20.44 |      | 150.0 |         |
|           |  | Z | 3.22  | 70.32  | 19.31 |      | 150.0 |         |
| 10182-CAE | LTE-FDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM)    | X | 5.15  | 76.64  | 21.61 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 5.91  | 81.38  | 23.70 |      | 150.0 |         |
|           |  | Z | 4.79  | 77.48  | 22.07 |      | 150.0 |         |
| 10183-AAD | LTE-FDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM)    | X | 4.27  | 72.61  | 19.04 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 4.60  | 75.98  | 20.62 |      | 150.0 |         |
|           |  | Z | 3.83  | 72.72  | 19.10 |      | 150.0 |         |

ES3DV3- SN:3335

July 26, 2018

|           |   |   |      |       |       |      |       |         |
|-----------|---|---|------|-------|-------|------|-------|---------|
| 10184-CAE | LTE-FDD (SC-FDMA, 1 RB, 3 MHz, QPSK)          | X | 3.64 | 71.00 | 19.53 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 3.60 | 72.48 | 20.46 |      | 150.0 |         |
|           |   | Z | 3.23 | 70.36 | 19.33 |      | 150.0 |         |
| 10185-CAE | LTE-FDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM)        | X | 5.18 | 76.71 | 21.65 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 5.95 | 81.47 | 23.74 |      | 150.0 |         |
|           |   | Z | 4.82 | 77.57 | 22.11 |      | 150.0 |         |
| 10186-AAE | LTE-FDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM)        | X | 4.29 | 72.68 | 19.07 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 4.62 | 76.06 | 20.65 |      | 150.0 |         |
|           |   | Z | 3.85 | 72.79 | 19.14 |      | 150.0 |         |
| 10187-CAF | LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK)        | X | 3.64 | 71.03 | 19.57 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 3.61 | 72.54 | 20.52 |      | 150.0 |         |
|           |   | Z | 3.24 | 70.42 | 19.40 |      | 150.0 |         |
| 10188-CAF | LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM)      | X | 5.37 | 77.47 | 22.05 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 6.22 | 82.41 | 24.20 |      | 150.0 |         |
|           |   | Z | 5.01 | 78.38 | 22.53 |      | 150.0 |         |
| 10189-AAF | LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM)      | X | 4.39 | 73.14 | 19.35 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 4.76 | 76.64 | 20.98 |      | 150.0 |         |
|           |   | Z | 3.95 | 73.29 | 19.44 |      | 150.0 |         |
| 10193-CAC | IEEE 802.11n (HT Greenfield, 6.5 Mbps, BPSK)  | X | 4.66 | 66.56 | 16.09 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.59 | 66.83 | 16.23 |      | 150.0 |         |
|           |   | Z | 4.51 | 66.55 | 15.98 |      | 150.0 |         |
| 10194-CAC | IEEE 802.11n (HT Greenfield, 39 Mbps, 16-QAM) | X | 4.86 | 66.94 | 16.20 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.77 | 67.18 | 16.34 |      | 150.0 |         |
|           |   | Z | 4.68 | 66.88 | 16.11 |      | 150.0 |         |
| 10195-CAC | IEEE 802.11n (HT Greenfield, 65 Mbps, 64-QAM) | X | 4.90 | 66.95 | 16.21 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.81 | 67.20 | 16.36 |      | 150.0 |         |
|           |   | Z | 4.72 | 66.91 | 16.13 |      | 150.0 |         |
| 10196-CAC | IEEE 802.11n (HT Mixed, 6.5 Mbps, BPSK)       | X | 4.68 | 66.67 | 16.13 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.60 | 66.92 | 16.26 |      | 150.0 |         |
|           |   | Z | 4.51 | 66.62 | 16.01 |      | 150.0 |         |
| 10197-CAC | IEEE 802.11n (HT Mixed, 39 Mbps, 16-QAM)      | X | 4.88 | 66.96 | 16.21 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.79 | 67.20 | 16.36 |      | 150.0 |         |
|           |   | Z | 4.70 | 66.90 | 16.12 |      | 150.0 |         |
| 10198-CAC | IEEE 802.11n (HT Mixed, 65 Mbps, 64-QAM)      | X | 4.90 | 66.96 | 16.22 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.82 | 67.22 | 16.37 |      | 150.0 |         |
|           |   | Z | 4.73 | 66.93 | 16.14 |      | 150.0 |         |
| 10219-CAC | IEEE 802.11n (HT Mixed, 7.2 Mbps, BPSK)       | X | 4.63 | 66.68 | 16.09 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.55 | 66.93 | 16.22 |      | 150.0 |         |
|           |   | Z | 4.46 | 66.63 | 15.96 |      | 150.0 |         |
| 10220-CAC | IEEE 802.11n (HT Mixed, 43.3 Mbps, 16-QAM)    | X | 4.88 | 66.96 | 16.22 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.78 | 67.18 | 16.35 |      | 150.0 |         |
|           |   | Z | 4.89 | 66.88 | 16.12 |      | 150.0 |         |
| 10221-CAC | IEEE 802.11n (HT Mixed, 72.2 Mbps, 64-QAM)    | X | 4.91 | 66.91 | 16.21 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.82 | 67.15 | 16.36 |      | 150.0 |         |
|           |   | Z | 4.74 | 66.86 | 16.13 |      | 150.0 |         |
| 10222-CAC | IEEE 802.11n (HT Mixed, 15 Mbps, BPSK)        | X | 5.22 | 67.24 | 16.36 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.14 | 67.38 | 16.47 |      | 150.0 |         |
|           |   | Z | 5.06 | 67.08 | 16.26 |      | 150.0 |         |

ES3DV3~ SN:3335

July 26, 2018

|           |   |   |       |        |       |      |       |         |  |
|-----------|---|---|-------|--------|-------|------|-------|---------|--|
| 10223-CAC | IEEE 802.11n (HT Mixed, 90 Mbps, 16-QAM)  | X | 5.61  | 67.61  | 16.57 | 0.00 | 150.0 | ± 9.6 % |  |
|           |   | Y | 5.46  | 67.60  | 16.60 |      |       | 150.0   |  |
|           |   | Z | 5.38  | 67.32  | 16.40 |      |       | 150.0   |  |
| 10224-CAC | IEEE 802.11n (HT Mixed, 150 Mbps, 64-QAM) | X | 5.27  | 67.35  | 16.33 | 0.00 | 150.0 | ± 9.6 % |  |
|           |   | Y | 5.18  | 67.48  | 16.44 |      |       | 150.0   |  |
|           |   | Z | 5.11  | 67.19  | 16.24 |      |       | 150.0   |  |
| 10225-CAB | UMTS-FDD (HSPA+)                          | X | 2.90  | 65.91  | 15.33 | 0.00 | 150.0 | ± 9.6 % |  |
|           |   | Y | 2.86  | 66.41  | 15.52 |      |       | 150.0   |  |
|           |   | Z | 2.75  | 65.82  | 14.99 |      |       | 150.0   |  |
| 10226-CAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM)  | X | 19.40 | 95.42  | 27.69 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 93.42 | 126.21 | 36.20 |      |       | 65.0    |  |
|           |   | Z | 52.06 | 116.00 | 33.53 |      |       | 65.0    |  |
| 10227-CAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM)  | X | 16.99 | 92.09  | 26.22 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 59.97 | 116.43 | 33.15 |      |       | 65.0    |  |
|           |   | Z | 39.75 | 109.54 | 31.23 |      |       | 65.0    |  |
| 10228-CAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK)    | X | 19.43 | 99.56  | 30.39 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 69.01 | 128.17 | 38.85 |      |       | 65.0    |  |
|           |   | Z | 36.88 | 115.87 | 35.47 |      |       | 65.0    |  |
| 10229-CAC | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM)    | X | 18.72 | 94.67  | 27.38 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 83.68 | 124.02 | 35.58 |      |       | 65.0    |  |
|           |   | Z | 47.16 | 114.04 | 32.93 |      |       | 65.0    |  |
| 10230-CAC | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM)    | X | 16.46 | 91.46  | 25.95 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 55.27 | 114.87 | 32.67 |      |       | 65.0    |  |
|           |   | Z | 36.63 | 108.00 | 30.74 |      |       | 65.0    |  |
| 10231-CAC | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, QPSK)      | X | 18.71 | 98.74  | 30.07 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 63.10 | 126.23 | 38.28 |      |       | 65.0    |  |
|           |   | Z | 34.03 | 114.14 | 34.92 |      |       | 65.0    |  |
| 10232-CAE | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM)    | X | 18.70 | 94.66  | 27.38 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 83.81 | 124.05 | 35.58 |      |       | 65.0    |  |
|           |   | Z | 47.17 | 114.05 | 32.94 |      |       | 65.0    |  |
| 10233-CAE | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM)    | X | 16.45 | 91.47  | 25.95 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 55.37 | 114.91 | 32.68 |      |       | 65.0    |  |
|           |   | Z | 36.63 | 108.01 | 30.74 |      |       | 65.0    |  |
| 10234-CAE | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, QPSK)      | X | 18.00 | 97.85  | 29.70 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 57.60 | 124.16 | 37.63 |      |       | 65.0    |  |
|           |   | Z | 31.55 | 112.43 | 34.33 |      |       | 65.0    |  |
| 10235-CAE | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM)   | X | 18.72 | 94.69  | 27.39 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 84.43 | 124.20 | 35.62 |      |       | 65.0    |  |
|           |   | Z | 47.40 | 114.15 | 32.96 |      |       | 65.0    |  |
| 10236-CAE | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM)   | X | 16.54 | 91.54  | 25.97 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 56.11 | 115.11 | 32.73 |      |       | 65.0    |  |
|           |   | Z | 37.05 | 108.18 | 30.78 |      |       | 65.0    |  |
| 10237-CAE | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, QPSK)     | X | 18.80 | 98.85  | 30.10 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 64.22 | 126.60 | 38.37 |      |       | 65.0    |  |
|           |   | Z | 34.38 | 114.37 | 34.98 |      |       | 65.0    |  |
| 10238-CAE | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM)   | X | 18.69 | 94.66  | 27.38 | 6.02 | 65.0  | ± 9.6 % |  |
|           |   | Y | 84.00 | 124.10 | 35.59 |      |       | 65.0    |  |
|           |   | Z | 47.18 | 114.07 | 32.94 |      |       | 65.0    |  |

ES3DV3-SN:3335

July 26, 2018

|           |  |   |       |        |       |      |      |         |
|-----------|--|---|-------|--------|-------|------|------|---------|
| 10239-CAE | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM)    | X | 16.44 | 91.47  | 25.95 | 6.02 | 65.0 | ± 9.6 % |
|           |  | Y | 55.45 | 114.96 | 32.69 |      | 65.0 |         |
|           |  | Z | 36.62 | 108.02 | 30.75 |      | 65.0 |         |
| 10240-CAE | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, QPSK)      | X | 18.75 | 98.81  | 30.09 | 6.02 | 65.0 | ± 9.6 % |
|           |  | Y | 63.94 | 126.53 | 38.35 |      | 65.0 |         |
|           |  | Z | 34.25 | 114.30 | 34.96 |      | 65.0 |         |
| 10241-CAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM) | X | 11.77 | 84.08  | 26.31 | 6.98 | 65.0 | ± 9.6 % |
|           |  | Y | 13.70 | 89.83  | 28.65 |      | 65.0 |         |
|           |  | Z | 12.37 | 87.76  | 27.72 |      | 65.0 |         |
| 10242-CAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM) | X | 11.05 | 82.65  | 25.66 | 6.98 | 65.0 | ± 9.6 % |
|           |  | Y | 13.36 | 89.28  | 28.38 |      | 65.0 |         |
|           |  | Z | 11.96 | 87.03  | 27.37 |      | 65.0 |         |
| 10243-CAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK)   | X | 9.32  | 80.83  | 25.74 | 6.98 | 65.0 | ± 9.6 % |
|           |  | Y | 10.49 | 86.01  | 28.14 |      | 65.0 |         |
|           |  | Z | 9.51  | 83.87  | 27.09 |      | 65.0 |         |
| 10244-CAC | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 16-QAM)   | X | 9.25  | 79.48  | 21.02 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 10.18 | 82.00  | 21.40 |      | 65.0 |         |
|           |  | Z | 9.15  | 80.16  | 20.37 |      | 65.0 |         |
| 10245-CAC | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 64-QAM)   | X | 9.18  | 79.14  | 20.85 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 9.92  | 81.33  | 21.10 |      | 65.0 |         |
|           |  | Z | 8.90  | 79.48  | 20.06 |      | 65.0 |         |
| 10246-CAC | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, QPSK)     | X | 8.47  | 80.70  | 21.30 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 9.88  | 84.33  | 22.22 |      | 65.0 |         |
|           |  | Z | 8.66  | 82.03  | 21.03 |      | 65.0 |         |
| 10247-CAE | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM)   | X | 7.61  | 76.79  | 20.31 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 7.74  | 78.26  | 20.56 |      | 65.0 |         |
|           |  | Z | 7.22  | 77.06  | 19.78 |      | 65.0 |         |
| 10248-CAE | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM)   | X | 7.64  | 76.41  | 20.14 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 7.68  | 77.69  | 20.33 |      | 65.0 |         |
|           |  | Z | 7.15  | 76.47  | 19.53 |      | 65.0 |         |
| 10249-CAE | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, QPSK)     | X | 9.04  | 81.75  | 22.18 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 11.12 | 86.63  | 23.73 |      | 65.0 |         |
|           |  | Z | 10.12 | 84.95  | 22.86 |      | 65.0 |         |
| 10250-CAE | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM)  | X | 8.32  | 78.16  | 21.88 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 8.67  | 80.34  | 22.70 |      | 65.0 |         |
|           |  | Z | 8.30  | 79.62  | 22.24 |      | 65.0 |         |
| 10251-CAE | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM)  | X | 7.98  | 76.33  | 20.88 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 8.14  | 78.10  | 21.53 |      | 65.0 |         |
|           |  | Z | 7.75  | 77.28  | 21.00 |      | 65.0 |         |
| 10252-CAE | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, QPSK)    | X | 9.04  | 80.95  | 22.38 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 10.62 | 85.37  | 24.01 |      | 65.0 |         |
|           |  | Z | 10.00 | 84.36  | 23.49 |      | 65.0 |         |
| 10253-CAE | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM)  | X | 7.96  | 75.57  | 20.78 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 8.01  | 77.05  | 21.41 |      | 65.0 |         |
|           |  | Z | 7.68  | 76.33  | 20.96 |      | 65.0 |         |
| 10254-CAE | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM)  | X | 8.31  | 76.27  | 21.36 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 8.39  | 77.82  | 22.01 |      | 65.0 |         |
|           |  | Z | 8.09  | 77.22  | 21.63 |      | 65.0 |         |