

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
TRANSISTOR				
1	01-2400120-A00	DIODE IN4001	1	D18
2	02-2235E70-A00	SMT DIODE DAN235E	1	D11
3	02-2356010-A00	SMT DIODE 1SS356 (ISS241&ISS314)	2	D1,D3
4	02-25350P0-A00	SMT VARICAP DIODE BB535 (1SV214)	4	D7,D8,D9,D10
5	02-2BAW560-A00	SMT DIODE BAW56 (EDS2836&1SS181)	1	D19
6	02-2J73262-A00	SMT DIODE MA2J732 SC-90A	1	D2
7	02-33904T0-A00	SMT TRANSISTOR MMBT3904	8	Q6,Q7,Q8,Q9,Q10 Q11,Q15,Q17
8	02-3490130-A00	SMT TRANSISTOR 2SC4901YK	5	Q1,Q2,Q3,Q4,Q21
9	02-38550SD-A00	SMT TRANSISTOR MPS8550S-D (SSA1197Y&2SA1298)	3	Q12,Q13,Q14
10	02-3390600-A00	SMT TRANSISTOR MMBT3906	5	Q16,Q18,Q19,Q26,Q27
11	02-4021020-A00	SMT FET 2SK210Y	1	Q22
12	02-4030220-A00	SMT FET 2SK302G RF AMP	1	Q20
13	02-4032030-A00	SMT FET 3SK320	1	Q23
14	02-4347620-A00	SMT POWER MOS FET 2SK3476	1	Q24
15	02-4307820-A00	SMT POWER MOS FET 2SK3078	1	Q25
16	02-5U30740-A00	SMT VARICAP HVU307	3	D4,D5,D6
17	02-6171V47-A00	SMT LED LAMP YELLOW L-171VYC 2125	2	D12,D13
18	02-6190V46-A00	SMT LED LAMP YELLOW L-190VYW 1608	4	D14,D15,D16,D17
IC				
1	03-0207001-A00	SMT IC NJM2070	1	IC3
2	03-0032411-A00	SMT IC LM324M&DBL324V	1	IC8
3	03-8825B01-A00	SMT IC PLL SIT8825B01-R0B0 16-TSSOP-0044	1	IC5
4	03-4116FV1-A00	SMT IC BA4116FV	1	IC4
5	03-614012M-A00	SMT IC XC61FC4012MR	1	IC9
6	03-6204502-A00	SMT IC XC6204B502MR	1	IC7
7	03-75S01F1-A00	SMT IC TA75S01F	1	IC1
8	03-78F94E9-A00	SMT IC FLASH MEMORY UPD78F9418	1	IC6
9	03-24C16N1-A00	SMT IC EEPROM AT24C16N-10SI2.7	1	IC2
CRYSTAL				
1	04-221435W-A00	CRYSTAL FILTER 21.4MHz +/-7.5KHz	2	F1,F2
2	04-32952C8-A00	CRYSTAL 20.95MHz UM-1 +/-5PPM	1	X1
3	04-341923C-S55	CRYSTAL 4.1943MHz (+/-30PMM) NC-3	1	X2
4	04-545015A-A00	CERAMIC FILTER 450KHz (LTM450EW) +/-7.5KHz	1	F3
IFT				
1	05-200022B-A00	IFT A002	1	T1
2	05-330203B-A00	SMT FM COIL 3.0T*D2.0*0.5mm (-) CW	1	L6

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
3	05-340203B-A00	SMT FM COIL 4.0T*D2.0*0.5mm (-) CW	4	L1,L2,L7,L8
4	05-350303B-A00	SMT FM COIL 5.0T*D3.0*0.5mm (-) CW	1	L23
5	05-360303B-A00	SMT FM COIL 6.0T*D3.0*0.5mm (-) CW	1	L22
6	05-8105030-A00	SMT CHOKE 3225 1UH (1ROM/K)	1	L9
7	05-8151044-A00	SMT INDUCTOR 2012 15nH +/-2% (C2012C-15NG)	1	L4
8	05-8181043-A00	SMT INDUCTOR 2520 18nH +/-2% (C2520C-18NG)	1	L5
9	05-8221043-A00	SMT INDUCTOR 2520 22nH +/-2% (C2520C-22NG)	1	L11
10	05-8225035-A00	SMT CHOKE 2520 2.2UH +/-10% (ELJFC2R2KF)	2	L17,L26
11	05-8271043-A00	SMT INDUCTOR 2520 27nH +/-2% (C2520C-27NG)	1	L24
12	05-8391043-A00	SMT INDUCTOR 2520 39nH +/-2% (C2520C-39NG)	2	L15,L16
13	05-8474013-A00	SMT INDUCTOR 2520 470nH +/-5% (C2520C-R47J)	1	L27
14	05-8561043-A00	SMT INDUCTOR 2520 56nH +/-2% (C2520C-56NG)	1	L3
15	05-8681043-A00	SMT INDUCTOR 2520 68nH +/-2% (C2520C-68NG)	2	L28,L29
16	05-A105026-A00	CHIP FERRITE INDUCTOR 1608 1UH +/-10% (SDFL1608Q1R0)	1	L10
17	05-A225026-A00	CHIP FERRITE INDUCTOR 1608 2.2UH +/-10% (SDFL1608Q2R2)	2	L18,L19
18	05-B104016-A00	CHIP CERAMIC INDUCTOR 1608 100nH +/-5%	2	L20,L25
19	05-B471016-A00	CHIP CERAMIC INDUCTOR 1608 47nH +/-5%	3	L12,L13,L14

CHIP RESISTOR PARTS

1	06-5102731-A00	CHIP RES 1608 1K OHM 1/10W +/-5%	6	R29,R30,R31,R54,R63 R108
2	06-5222731-A00	CHIP RES 1608 2.2K OHM 1/10W +/-5%	6	R32,R40,R53,R94,R95 R109
3	06-5332731-A00	CHIP RES 1608 3.3K OHM 1/10W +/-5%	5	R12,R14,R41,R67,R112
4	06-5472731-A00	CHIP RES 1608 4.7K OHM 1/10W +/-5%	11	R28,R36,R37,R38,R44 R99,R106,R130,R131,R132 R133
5	06-5562731-A00	CHIP RES 1608 5.6K OHM 1/10W +/-5%	3	R48,R90,R97
6	06-5103731-A00	CHIP RES 1608 10K OHM 1/10W +/-5%	15	R39,R42,R46,R49,R50 R51,R52,R64,R86,R91 R105,R134,R135,R136,R137
7	06-5123731-A00	CHIP RES 1608 12K OHM 1/10W +/-5%.	1	R96
8	06-5153731-A00	CHIP RES 1608 15K OHM 1/10W +/-5%	2	R45,R89
9	06-5203731-A00	CHIP RES 1608 20K OHM 1/10W +/-5%	2	R93,R123
10	06-5223731-A00	CHIP RES 1608 22K OHM 1/10W +/-5%	4	R84,R88,R92,R98
11	06-5273731-A00	CHIP RES 1608 27K OHM 1/10W +/-5%	1	R13
12	06-5303731-A00	CHIP RES 1608 30K OHM 1/10W +/-5%	2	R116,R117
13	06-5333731-A00	CHIP RES 1608 33K OHM 1/10W +/-5%	1	R11
14	06-5363731-A00	CHIP RES 1608 36K OHM 1/10W +/-5%	2	R107,R120
15	06-5393731-A00	CHIP RES 1608 39K OHM 1/10W +/-5%	1	R33
16	06-5473731-A00	CHIP RES 1608 47K OHM 1/10W +/-5%.	13	R18,R19,R20,R21,R22 R23,R43,R68,R74,R75 R77,R101,R114
17	06-5563731-A00	CHIP RES 1608 56K OHM 1/10W +/-5%	1	R126
18	06-5683731-A00	CHIP RES 1608 68K OHM 1/10W +/-5%	1	R80

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
19	06-5104731-A00	CHIP RES 1608 100K OHM 1/10W +/-5%	10	R65,R69,R70,R71,R72 R73,R81,R82,R83,R100
20	06-5124731-A00	CHIP RES 1608 120K OHM 1/10W +/-5%	1	R66
21	06-5154731-A00	CHIP RES 1608 150K OHM 1/10W +/-5%	2	R9,R10
22	06-5184731-A00	CHIP RES 1608 180K OHM 1/10W +/-5%	2	R35,R118
23	06-5224731-A00	CHIP RES 1608 220K OHM 1/10W +/-5%	1	R119
24	06-5304731-A00	CHIP RES 1608 300K OHM 1/10W +/-5%	2	R76,R103
25	06-5106731-A00	CHIP RES 1608 10M OHM 1/10W +/-10%	1	R102
26	06-5033731-A00	CHIP RES 1608 3.3 OHM 1/10W +/-5%	2	R25,R127
27	06-5047731-A00	CHIP RES 1608 4.7 OHM 1/10W +/-5%	1	R24
28	06-5100731-A00	CHIP RES 1608 10 OHM 1/10W +/-5%	1	R87
29	06-5220731-A00	CHIP RES 1608 22 OHM 1/10W +/-5%	2	R58,R111
30	06-5470731-A00	CHIP RES 1608 47 OHM 1/10W +/-5%	3	R15,R16,R17
31	06-5560731-A00	CHIP RES 1608 56 OHM 1/10W +/-5%	2	R62,R85
32	06-5101731-A00	CHIP RES 1608 100 OHM 1/10W +/-5%	7	R47,R55,R56,R57,R59 R60,R61
33	06-5221731-A00	CHIP RES 1608 220 OHM 1/10W +/-5%	8	R1,R2,R3,R4,R5 R6,R7,R8
34	06-5471731-A00	CHIP RES 1608 470 OHM 1/10W +/-5%	3	R26,R27,R34
35	06-7103253-A00	ROTARY POTENTIOMETER W/SW A10K RD810S-AA1-A103 8mm	1	VR4
36	06-8103153-A00	ROTARY POTENTIOMETER B10K RD810N-AA1-B103 8mm	1	VR2
37	06-A103117-A00	SMT SEMT-FIXED 10K EVM3YSX50B14	4	VR1,VR3,VR5,VR6
38	06-C101082-A00	CHIP NTC THERMISTOR 100 OHM +/-3% (1608101H3250)	1	RT1
39	06-D103432-A00	CHIP RESISTOR ARRAY 10K OHM 1/16W +/-5%	1	R125
40	06-D203432-A00	CHIP RESISTOR ARRAY 20K OHM 1/16W +/-5%	2	R78,R124
CAPACITOR PARTS				
1	07-410644C-A00	ELECT CAP 10UF 25V (D4*5mm)	3	C135,C136,C148
2	07-422634C-A00	ELECT CAP 22UF 16V +/-20% (D4*5mm)	2	C113,C138
3	07-4107244-A00	ELECT CAP 100UF 16V +/-20% (D5*8mm)	2	C134,C137
4	07-410734E-A00	ELECT CAP 100UF 16V (D6*5mm)	2	C132,C133
5	07-5005601-A00	CHIP CAP 1608 0.5PF 50V +/-0.25PF NPO	2	C70,C169
6	07-5010601-A00	CHIP CAP 1608 1PF 50V +/-0.25PF NPO	4	C21,C82,C130,C131
7	07-5030601-A00	CHIP CAP 1608 3PF 50V +/-0.25PF NPO	3	C53,C68,C127
8	07-5040601-A00	CHIP CAP 1608 4PF 50V +/-0.25PF NPO	3	C64,C72,C170
9	07-5050601-A00	CHIP CAP 1608 5PF 50V +/-0.25PF NPO	2	C125,C126
10	07-5060601-A00	CHIP CAP 1608 6PF 50V +/-0.25PF NPO	1	C81
11	07-5070601-A00	CHIP CAP 1608 7PF 50V +/-0.25PF NPO	2	C88,C150
12	07-5080601-A00	CHIP CAP 1608 8PF 50V +/-0.25PF NPO	4	C59,C76,C77,C78
13	07-5100601-A00	CHIP CAP 1608 10PF 50V +/-0.25PF NPO	7	C60,C61,C62,C63,C74 C110,C162
14	07-5120631-A00	CHIP CAP 1608 12PF 50V +/-5% NPO	3	C5,C6,C7
15	07-5150631-A00	CHIP CAP 1608 15PF 50V +/-5% NPO	5	C10,C56,C57,C58,C71
16	07-5180631-A00	CHIP CAP 1608 18PF 50V +/-5% NPO	3	C1,C2,C3
17	07-5200631-A00	CHIP CPA 1608 20PF 50V +/-5% NPO	1	C67

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
18	07-5220631-A00	CHIP CAP 1608 22PF 50V +/-5% NPO	4	C52,C73,C75,C107
19	07-5300631-A00	CHIP CAP 1608 30PF 50V +/-5% NPO	3	C65,C66,C151
20	07-5330631-A00	CHIP CAP 1608 33PF 50V +/-5% NPO	2	C8,C124
21	07-5470631-A00	CHIP CAP 1608 47PF 50V +/-5% NPO	3	C9,C11,C16
22	07-5101631-A00	CHIP CAP 1608 100PF 50V +/-5% NPO	7	C13,C55,C69,C80,C83 C84,C168
23	07-5221661-A00	CHIP CAP 1608 220PF 50V +/-10% X7R	4	C142,C143,C145,C161
24	07-5331661-A00	CHIP CAP 1608 330PF 50V +/-10% X7R	1	C4
25	07-5471661-A00	CHIP CAP 1608 470PF 50V +/-10% X7R	5	C153,C154,C155,C156,C157
26	07-5821661-A00	CHIP CAP 1608 820PF 50V +/-10% X7R	2	C146,C163
27	07-5102661-A00	CHIP CAP 1608 0.001UF 50V +/-10% X7R	43	C12,C14,C15,C17,C18 C19,C22,C23,C24,C25 C26,C27,C28,C29,C30 C31,C32,C33,C34,C35 C36,C37,C38,C39,C42 C43,C44,C45,C46,C49 C51,C54,C86,C98,C104 C108,C109,C129,C164,C166 C167,C171,C172
28	07-5103671-A00	CHIP CAP 1608 0.01UF 50V +80-20% Y5V	15	C41,C50,C85,C89,C90 C91,C92,C93,C94,C95 C96,C99,C102,C106,C141
29	07-5104681-A00	CHIP CAP 1608 0.1UF 50V +80-20% Y5V	15	C47,C103,C105,C112,C114 C115,C116,C117,C118,C119 C120,C121,C128,C140,C144
30	07-5223451-A00	CHIP CAP 1608 0.022UF 25V +/-10% X7R	1	C159
31	07-5332651-A00	CHIP CAP 1608 0.0033UF 50V +/-10% X7R	1	C79
32	07-5333661-A00	CHIP CAP 1608 0.033UF 50V +/-10% X7R	1	C139
33	07-5472651-A00	CHIP CAP 1608 0.0047UF 50V +/-10% X7R	3	C20,C48,C123
34	07-5473361-A00	CHIP CAP 1608 0.047UF 16V +/-10% X7R	2	C160,C165
35	07-5474671-A00	CHIP CAP 1608 0.47UF 16V +80-20% Y5V	1	C40
36	07-5105281-A00	CHIP CAP 1608 1UF 10V +80-20% Y5V	6	C97,C100,C101,C111,C122 C147
37	07-6225343-A00	SMT TAN CAP 3216 2.2UF 16V +/-20%	2	C87,C158
38	07-9100956-A00	SMT TRIMMER ELE CAP 10PF (CTC03E100)	1	VC1
39	07-C2206E1-A00	SMT CERAMIC CAP(UJ) 1608 22PF 50V +/-5%	1	C149
40	07-C5606E1-A00	SMT CERAMIC CAP(UJ) 1608 56PF 50V +/-5%	1	C152

CONNECTOR PARTS

1	08-0M340A0-A00	ANTENNA CONNECTOR HEAD (TNC)	1	
2	08-3864266-A00	SMD 2*4PIN FEMALE HEADER 1.27MM	1	J1
3	08-5060304-A00	PVC WIRE 28# BLACK 60mm (3+3)	1	
4	08-5060324-A00	PVC WIRE 28# RED 60mm (3+3)	1	
5	08-A254812-A00	SILICONE INTERCONNECTOR "SP" Pitch:0.18mm L25.0*W4.8*H1.5mm	1	

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
METAL PARTS				
1	30-1200535-A00	SCREW M2.0*5.0mm PM S/S	6	
2	30-1200665-A00	SCREW M2.0*6.0mm PB (T3P) S/S	2	
3	30-102806J-A00	SCREW M2.0*8.0mm PB (Black) IRON+NI	3	
4	30-1201235-A00	SCREW M2.0*12.0mm PM S/S	1	
5	30-1202565-A00	SCREW M2.0*25.0mm PB S/S	1	
6	30-1300935-A00	SCREW M3.0*9.0mm PM S/S	1	
7	32-5901813-A00	ANTENNA NUT M9.0*1.8mm (Cu)	1	
8	32-5902603-A00	SWITCH NUT	2	
9	35-0M34L05-A00	BATTERY LOCK PLATE	1	
10	35-0M34N12-A00	BATTERY LOCK NUT	1	
11	35-5MR3407-A00	HEAT SINK (AL)	1	
12	35-1M34L15-A00	LCD MOUNTING PLATE	1	
13	35-7M34015-A00	VCO SHIELD CASE (STEEL)	1	
14	35-9340A12-A00	ANTENNA HEAD	1	
15	36-AD51815-A00	METAL DOME D5-RNW-180	2	For PTT/Lamp
PLASTIC ASSESSRIOES				
1	40-1M34F19-A00	FRONT HOUSING (PC) (Q716-1-1 Black)	1	
2	40-1M34B19-A00	BACK HOUSING (PC) (Q716-1-1 Black)	1	
3	40-6M40L06-A00	LCD PROTECT LENS (PMMA) (8422C)	1	
4	44-6M34L06-A00	LCD BACK LIGHT PLATE (PMMA)	1	
5	40-7M34A17-A00	RUBBER DUCK ANTENNA SLEEVE (PU) (Q716-1-2 Grey)	1	
6	40-0M34P19-A00	PTT MOUNT PLATE (PC) (Q716-1-1 Black)	1	
7	40-3M34A19-A00	ANTENNA CAP (PC) (Q716-1-2 Grey)	1	
8	40-8M34B19-A00	BELT CLIP (PC) (Q716-1-1 Black)	1	
9	40-0M34B09-A00	BELT MOUNT BASE (PC) (Q716-1-1 Black)	1	
10	40-0M34C09-A00	CONTACT PLATE MOUNT BASE (PC) (Q716-1-1 Black)	1	
11	40-AM34P12-A00	PTT KEY (Silicone) (Q716-1-1 Black)	1	
12	40-AM34C12-A00	CHANNEL KEY (Silicone) (433 Grey)	1	
13	40-AM34S12-A00	SCAN/MEM KEY (Silicone) (433 Grey)	1	
14	40-AM34W12-A00	WX KEY (Silicone) (433 Grey/201 Red)	1	
15	40-4M34V11-A00	SQL/VOL KNOB (ABS) (Q716-1-2 Grey)	2	
16	40-5M34U02-A00	RUBBER RING FOR UNIT (Silicone) (Q716-1-1 Black)	1	
17	40-5M34P02-A00	RUBBER WASH FOR PTT (Silicone) (Q716-1-1 Black)	1	
18	43-5006021-A00	SINGLE COATED SPONGE L6*W5*H2MM	3	
19	44-1375000-A00	FELT D=37.5mm	1	FOR SPEAKER
20	44-D095402-A00	WATERPROOF FILM D9.5mm	1	FOR MIC
PACKING ACCESSORIES				
1	60-1MRH400-A00	CARTON	0.1	
2	60-2MRH400-A00	GIFT BOX	1	
3	60-8MRH400-A00	PAPER PULP BOX	1	

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
4	62-1200802-A00	PE PVC BAG: 80*120mm (T=0.03mm 底封)	1	
5	62-1500902-A00	PE PVC BAG: 90*150mm (T=0.03mm)	1	
6	62-2500602-A00	PE PVC BAG: 60*250mm (T=0.03mm)	1	
7	62-2501402-A00	PE PVC BAG: 140*250mm (T=0.03mm)	1	
8	62-2502502-A00	PE PVC BAG: 250*250mm (T=0.03mm)	1	
9	63-1MRH400-A00	INSTRUCTION BOOKLET	1	
10	63-0MR340S-A00	SENSORMATIC DEVICE	1	
11	63-0MR340C-A00	CHECKPOINT DEVICE	1	
12	63-6MR340P-A00	PRODUCT REGISTRATION CARD	1	
13	63-03040C4-A00	CUSTOMER ASSISTANCE CARD	1	
14	64-1MRH400-A00	RATING LABEL	1	
15	64-6MRH340-A00	SERIAL NO. LABEL	3	FOR Transceiver/ G/B / Carton
16	64-5MRH400-A00	BAR CODE LABEL (TM886B-USA-1)	0.4	FOR CARTON

OTHER PARTS

1	10-6012B34-A00	NI-MH RECHARGEABLE BATTERY 1.2V 1300mAh AA BYD	6	
2	11-40HT321-A00	SPEAKER D40mm 8 OHM 1W THX404	1	SP1
3	14-1MR3400-A00	LCD DISPLAY	1	LCD
4	16-54LP451-A00	CONDENSER MIC EM-54L-P	1	M1
5	69-0320001-A00	HAND STRAP 180MM	1	

PCB BOARD

1	13-1M340M1-A00	MAIN PCB	1	
2	13-1M340P1-A00	PTT PCB	1	

CRADLE CHARGER PART

1	01-6036211-A00	LED LAMP RED D3mm L-934HDLK	1	
2	01-2400120-A00	DIODE IN4001	1	
3	06-2330434-A00	RESISTOR 33 OHM 1W	1	
4	06-5102731-A00	CHIP RES 1608 1K OHM 1/10W +/-5%	1	
5	08-11C0052-A00	CHARGER JACK DC-005	1	
6	13-1M340C1-A00	CHARGER PCB	1	
7	30-102806J-A00	SCREW 2.0*8.0mm PB (BLACK) IRON+NI	4	
8	30-1302355-A00	SCREW 3.0*23.0mm PA S/S	2	For Wall Hanger
9	35-3M34C13-A00	CHARGE CONTACT PLATE	2	
10	35-3M34L13-A00	CHARGER LOCK (ABS) (Q716-1-1 Black)	1	
11	40-1M34CB1-A00	CHARGER BASE (ABS) (Q716-1-1 Black)	1	
12	40-1M34CT1-A00	CHARGER TOP	1	
13	44-8060202-A00	RUBBER PAD D6.0*H2.0mm	4	
14	64-1M400C1-A00	RATING LABEL FOR CHARGER	1	
15	67-5712087-A00	ADAPTOR AC:120V/60Hz DC:12V/200mA "UL APPROVAL"	1	

ALKALINEBATTERY CASE ASSEMBLY

TEKCOM CODE NO.: TM886B-USA-1

CUSTOMER MODEL : MRHH400

ISSUE: 3.01 22 JUL, 03

CUSTOMER : Cobra

ISSUE: 4.01 22 AUG, 03

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 7.2V Ni-MH Batt.

MARINE USA VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
1	01-2400120-A00	DIODE IN4001	1	
2	06-1470436-A00	RESISTOR 47 OHM 1W +/-5% (S.S)	1	
3	35-3M34B15-A00	METAL CONTACT PLATE (B)	3	
4	35-3M34C15-A00	METAL CONTACT PLATE (C)	1	
5	35-3M34D15-A00	METAL CONTACT PLATE (D)	1	
6	35-3M34E15-A00	METAL CONTACT PLATE (E)	1	
7	35-3M34F15-A00	METAL CONTACT PLATE (F)	1	
8	35-3M34G15-A00	METAL CONTACT PLATE (G)	2	
9	35-3M34H15-A00	METAL CONTACT PLATE (H)	2	
10	35-3M34BP5-A00	BATTERY POSITIVE POWER CONTACT PLATE	1	
11	35-3M34BN5-A00	BATTERY NEGATIVE POWER CONTACT PLATE	1	
12	40-2M34B19-A00	ALKALINE BATTERY CASE (PC) (Q716-1-1 Black)	1	
13	40-5M34B02-A00	RUBBER RING FOR BATTERY (Silicone) (Q716-1-1 Black)	1	
14	43-5006021-A00	SINGLE COATED SPONGE L6*W5*H2MM	6	
15	44-3M34004-A00	PVC PLATE (BLACK)	1	