

|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10061-CAB | IEEE 802.11b WiFi 2.4 GHz (DSSS, 11 Mbps)      | X | 2.76 | 84.27 | 25.47 | 2.04 | 110.0 | ± 9.6 % |
|           |  | Y | 1.28 | 69.73 | 17.60 |      | 110.0 |         |
|           |  | Z | 1.42 | 71.23 | 18.32 |      | 110.0 |         |
| 10062-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 6 Mbps)       | X | 4.61 | 66.98 | 16.85 | 0.49 | 100.0 | ± 9.6 % |
|           |  | Y | 4.32 | 66.36 | 16.16 |      | 100.0 |         |
|           |  | Z | 4.28 | 66.74 | 16.27 |      | 100.0 |         |
| 10063-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 9 Mbps)       | X | 4.62 | 67.08 | 16.96 | 0.72 | 100.0 | ± 9.6 % |
|           |  | Y | 4.33 | 66.45 | 16.25 |      | 100.0 |         |
|           |  | Z | 4.29 | 66.82 | 16.35 |      | 100.0 |         |
| 10064-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 12 Mbps)      | X | 4.87 | 67.29 | 17.16 | 0.86 | 100.0 | ± 9.6 % |
|           |  | Y | 4.56 | 66.65 | 16.45 |      | 100.0 |         |
|           |  | Z | 4.49 | 66.97 | 16.51 |      | 100.0 |         |
| 10065-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 18 Mbps)      | X | 4.74 | 67.16 | 17.27 | 1.21 | 100.0 | ± 9.6 % |
|           |  | Y | 4.42 | 66.44 | 16.50 |      | 100.0 |         |
|           |  | Z | 4.36 | 66.72 | 16.54 |      | 100.0 |         |
| 10066-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 24 Mbps)      | X | 4.75 | 67.16 | 17.44 | 1.46 | 100.0 | ± 9.6 % |
|           |  | Y | 4.42 | 66.41 | 16.63 |      | 100.0 |         |
|           |  | Z | 4.35 | 66.64 | 16.63 |      | 100.0 |         |
| 10067-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 36 Mbps)      | X | 5.04 | 67.40 | 17.92 | 2.04 | 100.0 | ± 9.6 % |
|           |  | Y | 4.70 | 66.70 | 17.12 |      | 100.0 |         |
|           |  | Z | 4.60 | 66.86 | 17.06 |      | 100.0 |         |
| 10068-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 48 Mbps)      | X | 5.05 | 67.29 | 18.09 | 2.55 | 100.0 | ± 9.6 % |
|           |  | Y | 4.73 | 66.60 | 17.28 |      | 100.0 |         |
|           |  | Z | 4.64 | 66.84 | 17.26 |      | 100.0 |         |
| 10069-CAC | IEEE 802.11a/h WiFi 5 GHz (OFDM, 54 Mbps)      | X | 5.13 | 67.33 | 18.28 | 2.67 | 100.0 | ± 9.6 % |
|           |  | Y | 4.78 | 66.61 | 17.46 |      | 100.0 |         |
|           |  | Z | 4.68 | 66.78 | 17.39 |      | 100.0 |         |
| 10071-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 9 Mbps)  | X | 4.88 | 67.04 | 17.75 | 1.99 | 100.0 | ± 9.6 % |
|           |  | Y | 4.60 | 66.44 | 17.02 |      | 100.0 |         |
|           |  | Z | 4.54 | 66.74 | 17.05 |      | 100.0 |         |
| 10072-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 12 Mbps) | X | 4.84 | 67.31 | 17.97 | 2.30 | 100.0 | ± 9.6 % |
|           |  | Y | 4.53 | 66.60 | 17.17 |      | 100.0 |         |
|           |  | Z | 4.46 | 66.83 | 17.17 |      | 100.0 |         |
| 10073-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 18 Mbps) | X | 4.89 | 67.45 | 18.31 | 2.83 | 100.0 | ± 9.6 % |
|           |  | Y | 4.58 | 66.75 | 17.49 |      | 100.0 |         |
|           |  | Z | 4.51 | 67.00 | 17.49 |      | 100.0 |         |
| 10074-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 24 Mbps) | X | 4.87 | 67.33 | 18.46 | 3.30 | 100.0 | ± 9.6 % |
|           |  | Y | 4.58 | 66.69 | 17.64 |      | 100.0 |         |
|           |  | Z | 4.53 | 67.00 | 17.66 |      | 100.0 |         |
| 10075-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 36 Mbps) | X | 4.88 | 67.32 | 18.73 | 3.82 | 90.0  | ± 9.6 % |
|           |  | Y | 4.59 | 66.65 | 17.86 |      | 90.0  |         |
|           |  | Z | 4.54 | 66.96 | 17.87 |      | 90.0  |         |
| 10076-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 48 Mbps) | X | 4.90 | 67.13 | 18.86 | 4.15 | 90.0  | ± 9.6 % |
|           |  | Y | 4.63 | 66.53 | 18.03 |      | 90.0  |         |
|           |  | Z | 4.58 | 66.82 | 18.03 |      | 90.0  |         |
| 10077-CAB | IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 54 Mbps) | X | 4.93 | 67.21 | 18.97 | 4.30 | 90.0  | ± 9.6 % |
|           |  | Y | 4.66 | 66.62 | 18.15 |      | 90.0  |         |
|           |  | Z | 4.61 | 66.93 | 18.16 |      | 90.0  |         |



|           |   |   |        |        |       |      |       |         |
|-----------|---|---|--------|--------|-------|------|-------|---------|
| 10081-CAB | CDMA2000 (1xRTT, RC3)                               | X | 1.07   | 70.22  | 14.02 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.39   | 60.00  | 6.38  |      | 150.0 |         |
|           |   | Z | 0.41   | 60.91  | 7.03  |      | 150.0 |         |
| 10082-CAB | IS-54 / IS-136 FDD (TDMA/FDM, PI/4-DQPSK, Fullrate) | X | 0.52   | 60.00  | 3.80  | 4.77 | 80.0  | ± 9.6 % |
|           |   | Y | 2.72   | 114.02 | 6.45  |      | 80.0  |         |
|           |   | Z | 10.47  | 60.22  | 1.52  |      | 80.0  |         |
| 10090-DAC | GPRS-FDD (TDMA, GMSK, TN 0-4)                       | X | 100.00 | 126.73 | 31.07 | 6.56 | 60.0  | ± 9.6 % |
|           |   | Y | 7.92   | 79.96  | 14.13 |      | 60.0  |         |
|           |   | Z | 20.99  | 87.17  | 15.81 |      | 60.0  |         |
| 10097-CAB | UMTS-FDD (HSDPA)                                    | X | 2.04   | 70.25  | 17.01 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 1.56   | 66.55  | 14.12 |      | 150.0 |         |
|           |   | Z | 1.74   | 68.77  | 15.28 |      | 150.0 |         |
| 10098-CAB | UMTS-FDD (HSUPA, Subtest 2)                         | X | 2.00   | 70.23  | 17.01 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 1.53   | 66.47  | 14.09 |      | 150.0 |         |
|           |   | Z | 1.71   | 68.71  | 15.26 |      | 150.0 |         |
| 10099-DAC | EDGE-FDD (TDMA, 8PSK, TN 0-4)                       | X | 6.64   | 89.05  | 33.56 | 9.56 | 60.0  | ± 9.6 % |
|           |   | Y | 4.75   | 79.08  | 27.95 |      | 60.0  |         |
|           |   | Z | 4.90   | 80.64  | 28.79 |      | 60.0  |         |
| 10100-CAD | LTE-FDD (SC-FDMA, 100% RB, 20 MHz, QPSK)            | X | 3.25   | 71.52  | 17.63 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.67   | 68.54  | 15.77 |      | 150.0 |         |
|           |   | Z | 2.78   | 69.71  | 16.57 |      | 150.0 |         |
| 10101-CAD | LTE-FDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM)          | X | 3.25   | 68.03  | 16.46 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.91   | 66.53  | 15.30 |      | 150.0 |         |
|           |   | Z | 2.96   | 67.22  | 15.75 |      | 150.0 |         |
| 10102-CAD | LTE-FDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM)          | X | 3.35   | 67.97  | 16.53 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 3.02   | 66.60  | 15.44 |      | 150.0 |         |
|           |   | Z | 3.06   | 67.28  | 15.86 |      | 150.0 |         |
| 10103-CAD | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, QPSK)            | X | 5.90   | 76.94  | 21.81 | 3.98 | 65.0  | ± 9.6 % |
|           |   | Y | 4.31   | 71.44  | 18.81 |      | 65.0  |         |
|           |   | Z | 4.43   | 72.32  | 19.13 |      | 65.0  |         |
| 10104-CAD | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM)          | X | 5.43   | 72.89  | 20.74 | 3.98 | 65.0  | ± 9.6 % |
|           |   | Y | 4.54   | 69.79  | 18.71 |      | 65.0  |         |
|           |   | Z | 4.61   | 70.44  | 18.87 |      | 65.0  |         |
| 10105-CAD | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM)          | X | 5.36   | 72.38  | 20.79 | 3.98 | 65.0  | ± 9.6 % |
|           |   | Y | 4.32   | 68.52  | 18.39 |      | 65.0  |         |
|           |   | Z | 4.39   | 69.21  | 18.58 |      | 65.0  |         |
| 10108-CAE | LTE-FDD (SC-FDMA, 100% RB, 10 MHz, QPSK)            | X | 2.82   | 70.93  | 17.54 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.28   | 67.91  | 15.54 |      | 150.0 |         |
|           |   | Z | 2.38   | 69.19  | 16.38 |      | 150.0 |         |
| 10109-CAE | LTE-FDD (SC-FDMA, 100% RB, 10 MHz, 16-QAM)          | X | 2.90   | 68.12  | 16.43 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.54   | 66.41  | 15.02 |      | 150.0 |         |
|           |   | Z | 2.59   | 67.32  | 15.54 |      | 150.0 |         |
| 10110-CAE | LTE-FDD (SC-FDMA, 100% RB, 5 MHz, QPSK)             | X | 2.31   | 70.47  | 17.26 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 1.78   | 66.93  | 14.73 |      | 150.0 |         |
|           |   | Z | 1.87   | 68.46  | 15.64 |      | 150.0 |         |
| 10111-CAE | LTE-FDD (SC-FDMA, 100% RB, 5 MHz, 16-QAM)           | X | 2.69   | 69.71  | 16.91 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.21   | 67.19  | 14.84 |      | 150.0 |         |
|           |   | Z | 2.33   | 68.71  | 15.55 |      | 150.0 |         |



|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10112-CAE | LTE-FDD (SC-FDMA, 100% RB, 10 MHz, 64-QAM)     | X | 3.03 | 68.11 | 16.46 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.67 | 66.55 | 15.14 |      | 150.0 |         |
|           |  | Z | 2.72 | 67.46 | 15.64 |      | 150.0 |         |
| 10113-CAE | LTE-FDD (SC-FDMA, 100% RB, 5 MHz, 64-QAM)      | X | 2.84 | 69.80 | 17.00 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.36 | 67.44 | 15.03 |      | 150.0 |         |
|           |  | Z | 2.46 | 68.88 | 15.67 |      | 150.0 |         |
| 10114-CAC | IEEE 802.11n (HT Greenfield, 13.5 Mbps, BPSK)  | X | 5.07 | 67.36 | 16.73 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.83 | 66.85 | 16.25 |      | 150.0 |         |
|           |  | Z | 4.79 | 67.12 | 16.39 |      | 150.0 |         |
| 10115-CAC | IEEE 802.11n (HT Greenfield, 81 Mbps, 16-QAM)  | X | 5.32 | 67.42 | 16.76 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.07 | 66.92 | 16.28 |      | 150.0 |         |
|           |  | Z | 5.02 | 67.21 | 16.41 |      | 150.0 |         |
| 10116-CAC | IEEE 802.11n (HT Greenfield, 135 Mbps, 64-QAM) | X | 5.16 | 67.57 | 16.76 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.89 | 66.99 | 16.25 |      | 150.0 |         |
|           |  | Z | 4.85 | 67.29 | 16.40 |      | 150.0 |         |
| 10117-CAC | IEEE 802.11n (HT Mixed, 13.5 Mbps, BPSK)       | X | 5.06 | 67.30 | 16.72 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.80 | 66.72 | 16.20 |      | 150.0 |         |
|           |  | Z | 4.77 | 67.02 | 16.36 |      | 150.0 |         |
| 10118-CAC | IEEE 802.11n (HT Mixed, 81 Mbps, 16-QAM)       | X | 5.40 | 67.64 | 16.88 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.14 | 67.13 | 16.40 |      | 150.0 |         |
|           |  | Z | 5.07 | 67.35 | 16.49 |      | 150.0 |         |
| 10119-CAC | IEEE 802.11n (HT Mixed, 135 Mbps, 64-QAM)      | X | 5.15 | 67.55 | 16.76 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.91 | 67.02 | 16.27 |      | 150.0 |         |
|           |  | Z | 4.86 | 67.32 | 16.42 |      | 150.0 |         |
| 10140-CAD | LTE-FDD (SC-FDMA, 100% RB, 15 MHz, 16-QAM)     | X | 3.37 | 68.00 | 16.44 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.03 | 66.62 | 15.34 |      | 150.0 |         |
|           |  | Z | 3.07 | 67.31 | 15.77 |      | 150.0 |         |
| 10141-CAD | LTE-FDD (SC-FDMA, 100% RB, 15 MHz, 64-QAM)     | X | 3.50 | 68.11 | 16.61 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.16 | 66.84 | 15.57 |      | 150.0 |         |
|           |  | Z | 3.20 | 67.55 | 15.99 |      | 150.0 |         |
| 10142-CAD | LTE-FDD (SC-FDMA, 100% RB, 3 MHz, QPSK)        | X | 2.13 | 71.07 | 16.98 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.48 | 66.20 | 13.48 |      | 150.0 |         |
|           |  | Z | 1.58 | 67.90 | 14.34 |      | 150.0 |         |
| 10143-CAD | LTE-FDD (SC-FDMA, 100% RB, 3 MHz, 16-QAM)      | X | 2.64 | 71.05 | 16.59 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.86 | 66.38 | 13.14 |      | 150.0 |         |
|           |  | Z | 1.94 | 67.74 | 13.60 |      | 150.0 |         |
| 10144-CAD | LTE-FDD (SC-FDMA, 100% RB, 3 MHz, 64-QAM)      | X | 2.21 | 67.53 | 14.37 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.63 | 64.02 | 11.37 |      | 150.0 |         |
|           |  | Z | 1.59 | 64.40 | 11.33 |      | 150.0 |         |
| 10145-CAE | LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, QPSK)      | X | 1.04 | 64.20 | 10.42 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.60 | 60.00 | 6.09  |      | 150.0 |         |
|           |  | Z | 0.55 | 60.00 | 5.71  |      | 150.0 |         |
| 10146-CAE | LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, 16-QAM)    | X | 1.22 | 62.30 | 8.55  | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.75 | 58.96 | 4.98  |      | 150.0 |         |
|           |  | Z | 0.74 | 60.00 | 4.89  |      | 150.0 |         |
| 10147-CAE | LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, 64-QAM)    | X | 1.32 | 63.10 | 9.10  | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.84 | 60.00 | 5.73  |      | 150.0 |         |
|           |  | Z | 0.75 | 60.00 | 4.93  |      | 150.0 |         |



|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10149-CAD | LTE-FDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM)  | X | 2.91 | 68.19 | 16.48 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.55 | 66.48 | 15.07 |      | 150.0 |         |
|           |  | Z | 2.60 | 67.39 | 15.59 |      | 150.0 |         |
| 10150-CAD | LTE-FDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM)  | X | 3.03 | 68.18 | 16.51 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.68 | 66.61 | 15.19 |      | 150.0 |         |
|           |  | Z | 2.73 | 67.53 | 15.69 |      | 150.0 |         |
| 10151-CAD | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, QPSK)    | X | 6.16 | 79.86 | 23.14 | 3.98 | 65.0  | ± 9.6 % |
|           |  | Y | 4.38 | 73.78 | 19.80 |      | 65.0  |         |
|           |  | Z | 4.56 | 74.89 | 20.13 |      | 65.0  |         |
| 10152-CAD | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM)  | X | 5.01 | 73.14 | 20.52 | 3.98 | 65.0  | ± 9.6 % |
|           |  | Y | 4.05 | 69.55 | 18.08 |      | 65.0  |         |
|           |  | Z | 4.10 | 70.17 | 18.13 |      | 65.0  |         |
| 10153-CAD | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM)  | X | 5.35 | 74.12 | 21.31 | 3.98 | 65.0  | ± 9.6 % |
|           |  | Y | 4.38 | 70.69 | 19.00 |      | 65.0  |         |
|           |  | Z | 4.45 | 71.38 | 19.08 |      | 65.0  |         |
| 10154-CAE | LTE-FDD (SC-FDMA, 50% RB, 10 MHz, QPSK)    | X | 2.36 | 70.91 | 17.52 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.81 | 67.24 | 14.94 |      | 150.0 |         |
|           |  | Z | 1.91 | 68.82 | 15.86 |      | 150.0 |         |
| 10155-CAE | LTE-FDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM)  | X | 2.70 | 69.75 | 16.94 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.22 | 67.24 | 14.88 |      | 150.0 |         |
|           |  | Z | 2.34 | 68.78 | 15.60 |      | 150.0 |         |
| 10156-CAE | LTE-FDD (SC-FDMA, 50% RB, 5 MHz, QPSK)     | X | 2.01 | 71.46 | 16.76 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.26 | 65.29 | 12.41 |      | 150.0 |         |
|           |  | Z | 1.33 | 66.85 | 13.15 |      | 150.0 |         |
| 10157-CAE | LTE-FDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM)   | X | 2.09 | 68.36 | 14.41 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.38 | 63.51 | 10.54 |      | 150.0 |         |
|           |  | Z | 1.32 | 63.75 | 10.39 |      | 150.0 |         |
| 10158-CAE | LTE-FDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM)  | X | 2.85 | 69.89 | 17.06 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.36 | 67.52 | 15.09 |      | 150.0 |         |
|           |  | Z | 2.48 | 68.99 | 15.74 |      | 150.0 |         |
| 10159-CAE | LTE-FDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM)   | X | 2.20 | 68.80 | 14.66 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.43 | 63.65 | 10.65 |      | 150.0 |         |
|           |  | Z | 1.37 | 63.86 | 10.46 |      | 150.0 |         |
| 10160-CAD | LTE-FDD (SC-FDMA, 50% RB, 15 MHz, QPSK)    | X | 2.84 | 70.09 | 17.26 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.37 | 67.63 | 15.46 |      | 150.0 |         |
|           |  | Z | 2.42 | 68.64 | 16.10 |      | 150.0 |         |
| 10161-CAD | LTE-FDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM)  | X | 2.93 | 68.20 | 16.43 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.55 | 66.51 | 14.98 |      | 150.0 |         |
|           |  | Z | 2.60 | 67.48 | 15.47 |      | 150.0 |         |
| 10162-CAD | LTE-FDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM)  | X | 3.04 | 68.40 | 16.56 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.66 | 66.78 | 15.14 |      | 150.0 |         |
|           |  | Z | 2.71 | 67.76 | 15.63 |      | 150.0 |         |
| 10166-CAE | LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK)   | X | 3.25 | 69.06 | 19.20 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.94 | 68.01 | 18.42 |      | 150.0 |         |
|           |  | Z | 2.90 | 68.63 | 18.86 |      | 150.0 |         |
| 10167-CAE | LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM) | X | 3.79 | 71.60 | 19.54 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.35 | 70.37 | 18.63 |      | 150.0 |         |
|           |  | Z | 3.46 | 72.30 | 19.64 |      | 150.0 |         |



|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10168-CAE | LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM) | X | 4.21 | 73.97 | 20.97 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 3.79 | 73.15 | 20.31 |      | 150.0 |         |
|           |  | Z | 4.01 | 75.63 | 21.54 |      | 150.0 |         |
| 10169-CAD | LTE-FDD (SC-FDMA, 1 RB, 20 MHz, QPSK)      | X | 2.57 | 67.19 | 18.40 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.39 | 66.27 | 17.57 |      | 150.0 |         |
|           |  | Z | 2.47 | 67.68 | 18.40 |      | 150.0 |         |
| 10170-CAD | LTE-FDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)    | X | 3.15 | 71.78 | 20.37 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.93 | 70.96 | 19.61 |      | 150.0 |         |
|           |  | Z | 3.39 | 75.08 | 21.55 |      | 150.0 |         |
| 10171-AAD | LTE-FDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM)    | X | 2.70 | 68.54 | 17.89 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.45 | 67.27 | 16.80 |      | 150.0 |         |
|           |  | Z | 2.67 | 70.12 | 18.24 |      | 150.0 |         |
| 10172-CAD | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, QPSK)      | X | 4.82 | 85.26 | 28.07 | 6.02 | 65.0  | ± 9.6 % |
|           |  | Y | 2.61 | 72.63 | 21.78 |      | 65.0  |         |
|           |  | Z | 2.46 | 73.08 | 22.05 |      | 65.0  |         |
| 10173-CAD | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)    | X | 9.08 | 95.50 | 29.67 | 6.02 | 65.0  | ± 9.6 % |
|           |  | Y | 4.04 | 79.72 | 22.80 |      | 65.0  |         |
|           |  | Z | 4.69 | 84.40 | 24.38 |      | 65.0  |         |
| 10174-CAD | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM)    | X | 8.49 | 93.00 | 28.18 | 6.02 | 65.0  | ± 9.6 % |
|           |  | Y | 3.13 | 74.91 | 20.35 |      | 65.0  |         |
|           |  | Z | 3.11 | 76.92 | 21.01 |      | 65.0  |         |
| 10175-CAE | LTE-FDD (SC-FDMA, 1 RB, 10 MHz, QPSK)      | X | 2.55 | 66.96 | 18.19 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.37 | 66.01 | 17.33 |      | 150.0 |         |
|           |  | Z | 2.44 | 67.40 | 18.15 |      | 150.0 |         |
| 10176-CAE | LTE-FDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM)    | X | 3.16 | 71.80 | 20.38 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.94 | 70.98 | 19.62 |      | 150.0 |         |
|           |  | Z | 3.40 | 75.11 | 21.57 |      | 150.0 |         |
| 10177-CAG | LTE-FDD (SC-FDMA, 1 RB, 5 MHz, QPSK)       | X | 2.57 | 67.07 | 18.26 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.38 | 66.12 | 17.40 |      | 150.0 |         |
|           |  | Z | 2.46 | 67.50 | 18.22 |      | 150.0 |         |
| 10178-CAE | LTE-FDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM)     | X | 3.14 | 71.67 | 20.31 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.92 | 70.85 | 19.55 |      | 150.0 |         |
|           |  | Z | 3.38 | 74.97 | 21.49 |      | 150.0 |         |
| 10179-CAE | LTE-FDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM)    | X | 2.91 | 70.13 | 19.04 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.66 | 68.97 | 18.06 |      | 150.0 |         |
|           |  | Z | 2.99 | 72.45 | 19.75 |      | 150.0 |         |
| 10180-CAE | LTE-FDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM)     | X | 2.69 | 68.50 | 17.86 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.45 | 67.24 | 16.78 |      | 150.0 |         |
|           |  | Z | 2.67 | 70.09 | 18.21 |      | 150.0 |         |
| 10181-CAD | LTE-FDD (SC-FDMA, 1 RB, 15 MHz, QPSK)      | X | 2.56 | 67.05 | 18.25 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.38 | 66.10 | 17.40 |      | 150.0 |         |
|           |  | Z | 2.45 | 67.49 | 18.21 |      | 150.0 |         |
| 10182-CAD | LTE-FDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM)    | X | 3.13 | 71.65 | 20.30 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.92 | 70.83 | 19.53 |      | 150.0 |         |
|           |  | Z | 3.37 | 74.94 | 21.48 |      | 150.0 |         |
| 10183-AAC | LTE-FDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM)    | X | 2.69 | 68.48 | 17.85 | 3.01 | 150.0 | ± 9.6 % |
|           |  | Y | 2.44 | 67.22 | 16.77 |      | 150.0 |         |
|           |  | Z | 2.67 | 70.07 | 18.20 |      | 150.0 |         |



|           |   |   |      |       |       |      |       |         |
|-----------|---|---|------|-------|-------|------|-------|---------|
| 10184-CAD | LTE-FDD (SC-FDMA, 1 RB, 3 MHz, QPSK)          | X | 2.57 | 67.09 | 18.27 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 2.39 | 66.14 | 17.41 |      | 150.0 |         |
|           |   | Z | 2.46 | 67.52 | 18.23 |      | 150.0 |         |
| 10185-CAD | LTE-FDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM)        | X | 3.15 | 71.71 | 20.33 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 2.93 | 70.90 | 19.57 |      | 150.0 |         |
|           |   | Z | 3.39 | 75.03 | 21.52 |      | 150.0 |         |
| 10186-AAD | LTE-FDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM)        | X | 2.70 | 68.54 | 17.88 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 2.45 | 67.28 | 16.80 |      | 150.0 |         |
|           |   | Z | 2.68 | 70.13 | 18.24 |      | 150.0 |         |
| 10187-CAE | LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK)        | X | 2.58 | 67.15 | 18.34 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 2.40 | 66.22 | 17.50 |      | 150.0 |         |
|           |   | Z | 2.47 | 67.63 | 18.33 |      | 150.0 |         |
| 10188-CAE | LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM)      | X | 3.22 | 72.19 | 20.64 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 3.00 | 71.43 | 19.92 |      | 150.0 |         |
|           |   | Z | 3.50 | 75.72 | 21.92 |      | 150.0 |         |
| 10189-AAE | LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM)      | X | 2.75 | 68.87 | 18.12 | 3.01 | 150.0 | ± 9.6 % |
|           |   | Y | 2.50 | 67.60 | 17.05 |      | 150.0 |         |
|           |   | Z | 2.74 | 70.56 | 18.53 |      | 150.0 |         |
| 10193-CAC | IEEE 802.11n (HT Greenfield, 6.5 Mbps, BPSK)  | X | 4.47 | 66.98 | 16.45 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.21 | 66.45 | 15.84 |      | 150.0 |         |
|           |   | Z | 4.20 | 67.00 | 16.06 |      | 150.0 |         |
| 10194-CAC | IEEE 802.11n (HT Greenfield, 39 Mbps, 16-QAM) | X | 4.62 | 67.23 | 16.58 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.34 | 66.66 | 15.98 |      | 150.0 |         |
|           |   | Z | 4.31 | 67.15 | 16.19 |      | 150.0 |         |
| 10195-CAC | IEEE 802.11n (HT Greenfield, 65 Mbps, 64-QAM) | X | 4.66 | 67.26 | 16.60 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.37 | 66.67 | 15.99 |      | 150.0 |         |
|           |   | Z | 4.33 | 67.12 | 16.19 |      | 150.0 |         |
| 10196-CAC | IEEE 802.11n (HT Mixed, 6.5 Mbps, BPSK)       | X | 4.46 | 66.99 | 16.45 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.19 | 66.43 | 15.81 |      | 150.0 |         |
|           |   | Z | 4.17 | 66.94 | 16.02 |      | 150.0 |         |
| 10197-CAC | IEEE 802.11n (HT Mixed, 39 Mbps, 16-QAM)      | X | 4.63 | 67.24 | 16.59 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.34 | 66.66 | 15.99 |      | 150.0 |         |
|           |   | Z | 4.32 | 67.14 | 16.19 |      | 150.0 |         |
| 10198-CAC | IEEE 802.11n (HT Mixed, 65 Mbps, 64-QAM)      | X | 4.65 | 67.26 | 16.60 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.36 | 66.66 | 15.99 |      | 150.0 |         |
|           |   | Z | 4.32 | 67.11 | 16.18 |      | 150.0 |         |
| 10219-CAC | IEEE 802.11n (HT Mixed, 7.2 Mbps, BPSK)       | X | 4.41 | 67.03 | 16.42 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.14 | 66.47 | 15.78 |      | 150.0 |         |
|           |   | Z | 4.13 | 67.01 | 16.02 |      | 150.0 |         |
| 10220-CAC | IEEE 802.11n (HT Mixed, 43.3 Mbps, 16-QAM)    | X | 4.62 | 67.20 | 16.58 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.34 | 66.63 | 15.97 |      | 150.0 |         |
|           |   | Z | 4.31 | 67.10 | 16.18 |      | 150.0 |         |
| 10221-CAC | IEEE 802.11n (HT Mixed, 72.2 Mbps, 64-QAM)    | X | 4.66 | 67.19 | 16.59 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.38 | 66.62 | 15.99 |      | 150.0 |         |
|           |   | Z | 4.35 | 67.08 | 16.18 |      | 150.0 |         |
| 10222-CAC | IEEE 802.11n (HT Mixed, 15 Mbps, BPSK)        | X | 5.03 | 67.28 | 16.70 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.78 | 66.73 | 16.19 |      | 150.0 |         |
|           |   | Z | 4.75 | 67.03 | 16.34 |      | 150.0 |         |



|           |   |   |       |       |       |      |       |         |
|-----------|---|---|-------|-------|-------|------|-------|---------|
| 10223-CAC | IEEE 802.11n (HT Mixed, 90 Mbps, 16-QAM)  | X | 5.31  | 67.50 | 16.82 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.02  | 66.87 | 16.28 |      | 150.0 |         |
|           |   | Z | 4.95  | 67.08 | 16.37 |      | 150.0 |         |
| 10224-CAC | IEEE 802.11n (HT Mixed, 150 Mbps, 64-QAM) | X | 5.07  | 67.39 | 16.68 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.82  | 66.85 | 16.18 |      | 150.0 |         |
|           |   | Z | 4.79  | 67.17 | 16.34 |      | 150.0 |         |
| 10225-CAB | UMTS-FDD (HSPA+)                          | X | 2.78  | 66.87 | 15.63 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 2.43  | 65.35 | 14.02 |      | 150.0 |         |
|           |   | Z | 2.45  | 66.12 | 14.22 |      | 150.0 |         |
| 10226-CAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM)  | X | 9.71  | 96.92 | 30.23 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.26  | 80.72 | 23.28 |      | 65.0  |         |
|           |   | Z | 5.06  | 85.84 | 24.99 |      | 65.0  |         |
| 10227-CAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM)  | X | 10.65 | 97.21 | 29.57 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.23  | 79.84 | 22.26 |      | 65.0  |         |
|           |   | Z | 4.82  | 83.94 | 23.53 |      | 65.0  |         |
| 10228-CAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK)    | X | 5.06  | 86.61 | 28.66 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 3.02  | 75.86 | 23.24 |      | 65.0  |         |
|           |   | Z | 2.94  | 76.67 | 23.61 |      | 65.0  |         |
| 10229-CAB | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM)    | X | 9.15  | 95.60 | 29.71 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.07  | 79.81 | 22.84 |      | 65.0  |         |
|           |   | Z | 4.73  | 84.51 | 24.42 |      | 65.0  |         |
| 10230-CAB | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM)    | X | 9.85  | 95.67 | 29.01 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.01  | 78.86 | 21.82 |      | 65.0  |         |
|           |   | Z | 4.46  | 82.58 | 22.97 |      | 65.0  |         |
| 10231-CAB | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, QPSK)      | X | 4.89  | 85.81 | 28.28 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 2.94  | 75.24 | 22.90 |      | 65.0  |         |
|           |   | Z | 2.85  | 75.99 | 23.24 |      | 65.0  |         |
| 10232-CAD | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM)    | X | 9.13  | 95.58 | 29.70 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.06  | 79.79 | 22.83 |      | 65.0  |         |
|           |   | Z | 4.72  | 84.49 | 24.42 |      | 65.0  |         |
| 10233-CAD | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM)    | X | 9.80  | 95.61 | 29.00 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 3.99  | 78.83 | 21.81 |      | 65.0  |         |
|           |   | Z | 4.44  | 82.53 | 22.96 |      | 65.0  |         |
| 10234-CAD | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, QPSK)      | X | 4.77  | 85.21 | 27.94 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 2.87  | 74.77 | 22.58 |      | 65.0  |         |
|           |   | Z | 2.78  | 75.51 | 22.91 |      | 65.0  |         |
| 10235-CAD | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM)   | X | 9.14  | 95.63 | 29.72 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.06  | 79.81 | 22.84 |      | 65.0  |         |
|           |   | Z | 4.72  | 84.51 | 24.43 |      | 65.0  |         |
| 10236-CAD | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM)   | X | 9.98  | 95.90 | 29.08 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.03  | 78.96 | 21.85 |      | 65.0  |         |
|           |   | Z | 4.50  | 82.71 | 23.02 |      | 65.0  |         |
| 10237-CAD | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, QPSK)     | X | 4.89  | 85.85 | 28.31 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 2.93  | 75.24 | 22.91 |      | 65.0  |         |
|           |   | Z | 2.84  | 75.99 | 23.24 |      | 65.0  |         |
| 10238-CAD | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM)   | X | 9.10  | 95.55 | 29.70 | 6.02 | 65.0  | ± 9.6 % |
|           |   | Y | 4.05  | 79.76 | 22.82 |      | 65.0  |         |
|           |   | Z | 4.71  | 84.46 | 24.41 |      | 65.0  |         |



|           |  |   |      |       |       |      |      |         |
|-----------|--|---|------|-------|-------|------|------|---------|
| 10239-CAD | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM)    | X | 9.76 | 95.55 | 28.98 | 6.02 | 65.0 | ± 9.6 % |
|           |  | Y | 3.98 | 78.79 | 21.80 |      | 65.0 |         |
|           |  | Z | 4.42 | 82.49 | 22.95 |      | 65.0 |         |
| 10240-CAD | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, QPSK)      | X | 4.87 | 85.81 | 28.29 | 6.02 | 65.0 | ± 9.6 % |
|           |  | Y | 2.93 | 75.22 | 22.90 |      | 65.0 |         |
|           |  | Z | 2.84 | 75.98 | 23.24 |      | 65.0 |         |
| 10241-CAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM) | X | 6.64 | 80.22 | 25.81 | 6.98 | 65.0 | ± 9.6 % |
|           |  | Y | 5.47 | 76.94 | 23.75 |      | 65.0 |         |
|           |  | Z | 5.59 | 79.30 | 24.80 |      | 65.0 |         |
| 10242-CAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM) | X | 6.52 | 79.88 | 25.59 | 6.98 | 65.0 | ± 9.6 % |
|           |  | Y | 4.89 | 74.71 | 22.71 |      | 65.0 |         |
|           |  | Z | 4.82 | 76.36 | 23.52 |      | 65.0 |         |
| 10243-CAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK)   | X | 5.29 | 75.90 | 24.79 | 6.98 | 65.0 | ± 9.6 % |
|           |  | Y | 4.20 | 71.66 | 22.19 |      | 65.0 |         |
|           |  | Z | 4.11 | 72.66 | 22.76 |      | 65.0 |         |
| 10244-CAB | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 16-QAM)   | X | 4.65 | 74.33 | 17.54 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 2.46 | 65.20 | 11.64 |      | 65.0 |         |
|           |  | Z | 2.08 | 63.58 | 9.86  |      | 65.0 |         |
| 10245-CAB | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 64-QAM)   | X | 4.42 | 73.26 | 17.02 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 2.43 | 64.84 | 11.40 |      | 65.0 |         |
|           |  | Z | 2.06 | 63.31 | 9.66  |      | 65.0 |         |
| 10246-CAB | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, QPSK)     | X | 6.17 | 83.25 | 21.77 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 2.13 | 66.83 | 13.01 |      | 65.0 |         |
|           |  | Z | 1.89 | 65.44 | 11.64 |      | 65.0 |         |
| 10247-CAD | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM)   | X | 4.44 | 74.30 | 18.86 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 2.77 | 66.89 | 13.86 |      | 65.0 |         |
|           |  | Z | 2.59 | 66.14 | 12.80 |      | 65.0 |         |
| 10248-CAD | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM)   | X | 4.31 | 73.22 | 18.35 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 2.77 | 66.44 | 13.63 |      | 65.0 |         |
|           |  | Z | 2.57 | 65.63 | 12.54 |      | 65.0 |         |
| 10249-CAD | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, QPSK)     | X | 7.74 | 87.86 | 24.78 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 3.19 | 72.50 | 17.17 |      | 65.0 |         |
|           |  | Z | 3.06 | 71.92 | 16.36 |      | 65.0 |         |
| 10250-CAD | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM)  | X | 5.14 | 76.27 | 21.80 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 3.88 | 71.37 | 18.57 |      | 65.0 |         |
|           |  | Z | 3.93 | 71.90 | 18.38 |      | 65.0 |         |
| 10251-CAD | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM)  | X | 4.85 | 73.82 | 20.27 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 3.69 | 69.32 | 17.15 |      | 65.0 |         |
|           |  | Z | 3.67 | 69.58 | 16.84 |      | 65.0 |         |
| 10252-CAD | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, QPSK)    | X | 6.69 | 84.36 | 24.85 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 4.05 | 75.21 | 20.08 |      | 65.0 |         |
|           |  | Z | 4.23 | 76.24 | 20.21 |      | 65.0 |         |
| 10253-CAD | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM)  | X | 4.93 | 72.71 | 20.24 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 4.01 | 69.29 | 17.80 |      | 65.0 |         |
|           |  | Z | 4.05 | 69.88 | 17.79 |      | 65.0 |         |
| 10254-CAD | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM)  | X | 5.24 | 73.58 | 20.93 | 3.98 | 65.0 | ± 9.6 % |
|           |  | Y | 4.29 | 70.24 | 18.57 |      | 65.0 |         |
|           |  | Z | 4.33 | 70.86 | 18.55 |      | 65.0 |         |



|           |   |   |      |       |       |      |      |         |
|-----------|---|---|------|-------|-------|------|------|---------|
| 10255-CAD | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, QPSK)     | X | 5.77 | 78.78 | 22.88 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.20 | 73.17 | 19.64 |      | 65.0 |         |
|           |   | Z | 4.35 | 74.23 | 19.90 |      | 65.0 |         |
| 10256-CAA | LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, 16-QAM) | X | 3.07 | 68.20 | 13.47 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 1.77 | 61.88 | 8.49  |      | 65.0 |         |
|           |   | Z | 1.48 | 60.73 | 6.90  |      | 65.0 |         |
| 10257-CAA | LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, 64-QAM) | X | 2.92 | 67.18 | 12.84 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 1.77 | 61.61 | 8.23  |      | 65.0 |         |
|           |   | Z | 1.48 | 60.53 | 6.68  |      | 65.0 |         |
| 10258-CAA | LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, QPSK)   | X | 3.62 | 74.14 | 16.97 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 1.51 | 62.54 | 9.43  |      | 65.0 |         |
|           |   | Z | 1.33 | 61.51 | 8.12  |      | 65.0 |         |
| 10259-CAB | LTE-TDD (SC-FDMA, 100% RB, 3 MHz, 16-QAM)   | X | 4.77 | 75.28 | 20.02 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 3.20 | 68.71 | 15.65 |      | 65.0 |         |
|           |   | Z | 3.09 | 68.37 | 14.88 |      | 65.0 |         |
| 10260-CAB | LTE-TDD (SC-FDMA, 100% RB, 3 MHz, 64-QAM)   | X | 4.75 | 74.77 | 19.78 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 3.24 | 68.51 | 15.54 |      | 65.0 |         |
|           |   | Z | 3.12 | 68.15 | 14.74 |      | 65.0 |         |
| 10261-CAB | LTE-TDD (SC-FDMA, 100% RB, 3 MHz, QPSK)     | X | 6.64 | 84.80 | 24.23 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 3.45 | 73.19 | 18.15 |      | 65.0 |         |
|           |   | Z | 3.45 | 73.32 | 17.72 |      | 65.0 |         |
| 10262-CAD | LTE-TDD (SC-FDMA, 100% RB, 5 MHz, 16-QAM)   | X | 5.12 | 76.21 | 21.75 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 3.86 | 71.29 | 18.50 |      | 65.0 |         |
|           |   | Z | 3.92 | 71.80 | 18.32 |      | 65.0 |         |
| 10263-CAD | LTE-TDD (SC-FDMA, 100% RB, 5 MHz, 64-QAM)   | X | 4.83 | 73.79 | 20.26 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 3.69 | 69.30 | 17.14 |      | 65.0 |         |
|           |   | Z | 3.66 | 69.57 | 16.84 |      | 65.0 |         |
| 10264-CAD | LTE-TDD (SC-FDMA, 100% RB, 5 MHz, QPSK)     | X | 6.60 | 84.09 | 24.72 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.01 | 75.00 | 19.97 |      | 65.0 |         |
|           |   | Z | 4.19 | 76.03 | 20.09 |      | 65.0 |         |
| 10265-CAD | LTE-TDD (SC-FDMA, 100% RB, 10 MHz, 16-QAM)  | X | 5.01 | 73.14 | 20.52 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.05 | 69.56 | 18.09 |      | 65.0 |         |
|           |   | Z | 4.10 | 70.17 | 18.14 |      | 65.0 |         |
| 10266-CAD | LTE-TDD (SC-FDMA, 100% RB, 10 MHz, 64-QAM)  | X | 5.35 | 74.11 | 21.30 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.37 | 70.68 | 18.99 |      | 65.0 |         |
|           |   | Z | 4.44 | 71.37 | 19.07 |      | 65.0 |         |
| 10267-CAD | LTE-TDD (SC-FDMA, 100% RB, 10 MHz, QPSK)    | X | 6.15 | 79.79 | 23.11 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.37 | 73.73 | 19.78 |      | 65.0 |         |
|           |   | Z | 4.55 | 74.84 | 20.11 |      | 65.0 |         |
| 10268-CAD | LTE-TDD (SC-FDMA, 100% RB, 15 MHz, 16-QAM)  | X | 5.58 | 72.77 | 20.75 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.72 | 69.94 | 18.84 |      | 65.0 |         |
|           |   | Z | 4.79 | 70.63 | 19.00 |      | 65.0 |         |
| 10269-CAD | LTE-TDD (SC-FDMA, 100% RB, 15 MHz, 64-QAM)  | X | 5.57 | 72.33 | 20.57 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.76 | 69.68 | 18.74 |      | 65.0 |         |
|           |   | Z | 4.84 | 70.41 | 18.91 |      | 65.0 |         |
| 10270-CAD | LTE-TDD (SC-FDMA, 100% RB, 15 MHz, QPSK)    | X | 5.83 | 75.90 | 21.57 | 3.98 | 65.0 | ± 9.6 % |
|           |   | Y | 4.63 | 71.95 | 19.20 |      | 65.0 |         |
|           |   | Z | 4.79 | 72.95 | 19.55 |      | 65.0 |         |



|           |  |   |        |        |       |      |       |         |
|-----------|--|---|--------|--------|-------|------|-------|---------|
| 10274-CAB | UMTS-FDD (HSUPA, Subtest 5, 3GPP Rel8.10)                          | X | 2.64   | 67.67  | 15.79 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.27   | 65.84  | 14.01 |      | 150.0 |         |
|           |  | Z | 2.32   | 66.86  | 14.40 |      | 150.0 |         |
| 10275-CAB | UMTS-FDD (HSUPA, Subtest 5, 3GPP Rel8.4)                           | X | 1.80   | 70.59  | 17.09 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.29   | 65.97  | 13.76 |      | 150.0 |         |
|           |  | Z | 1.43   | 68.02  | 14.99 |      | 150.0 |         |
| 10277-CAA | PHS (QPSK)   | X | 1.46   | 60.00  | 5.37  | 9.03 | 50.0  | ± 9.6 % |
|           |  | Y | 1.26   | 58.24  | 3.50  |      | 50.0  |         |
|           |  | Z | 1.18   | 57.45  | 2.39  |      | 50.0  |         |
| 10278-CAA | PHS (QPSK, BW 884MHz, Rolloff 0.5)                                 | X | 4.52   | 73.48  | 15.27 | 9.03 | 50.0  | ± 9.6 % |
|           |  | Y | 2.20   | 63.01  | 8.77  |      | 50.0  |         |
|           |  | Z | 1.90   | 61.81  | 7.50  |      | 50.0  |         |
| 10279-CAA | PHS (QPSK, BW 884MHz, Rolloff 0.38)                                | X | 4.70   | 73.94  | 15.54 | 9.03 | 50.0  | ± 9.6 % |
|           |  | Y | 2.26   | 63.19  | 8.94  |      | 50.0  |         |
|           |  | Z | 1.94   | 61.93  | 7.64  |      | 50.0  |         |
| 10290-AAB | CDMA2000, RC1, SO55, Full Rate                                     | X | 1.70   | 71.93  | 14.73 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.60   | 60.98  | 7.34  |      | 150.0 |         |
|           |  | Z | 0.57   | 61.36  | 7.44  |      | 150.0 |         |
| 10291-AAB | CDMA2000, RC3, SO55, Full Rate                                     | X | 1.03   | 69.73  | 13.78 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.39   | 60.00  | 6.36  |      | 150.0 |         |
|           |  | Z | 0.40   | 60.81  | 6.94  |      | 150.0 |         |
| 10292-AAB | CDMA2000, RC3, SO32, Full Rate                                     | X | 3.83   | 87.63  | 20.75 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.41   | 60.95  | 7.21  |      | 150.0 |         |
|           |  | Z | 0.51   | 63.49  | 8.77  |      | 150.0 |         |
| 10293-AAB | CDMA2000, RC3, SO3, Full Rate                                      | X | 100.00 | 132.84 | 32.68 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.53   | 63.17  | 8.86  |      | 150.0 |         |
|           |  | Z | 1.11   | 71.16  | 12.60 |      | 150.0 |         |
| 10295-AAB | CDMA2000, RC1, SO3, 1/8th Rate 25 fr.                              | X | 74.23  | 122.96 | 34.73 | 9.03 | 50.0  | ± 9.6 % |
|           |  | Y | 19.85  | 92.80  | 23.42 |      | 50.0  |         |
|           |  | Z | 21.39  | 92.20  | 22.34 |      | 50.0  |         |
| 10297-AAC | LTE-FDD (SC-FDMA, 50% RB, 20 MHz, QPSK)                            | X | 2.84   | 71.05  | 17.61 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.29   | 68.01  | 15.61 |      | 150.0 |         |
|           |  | Z | 2.39   | 69.30  | 16.45 |      | 150.0 |         |
| 10298-AAC | LTE-FDD (SC-FDMA, 50% RB, 3 MHz, QPSK)                             | X | 1.59   | 69.17  | 14.29 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.82   | 61.77  | 8.70  |      | 150.0 |         |
|           |  | Z | 0.78   | 61.98  | 8.59  |      | 150.0 |         |
| 10299-AAC | LTE-FDD (SC-FDMA, 50% RB, 3 MHz, 16-QAM)                           | X | 1.90   | 66.73  | 12.14 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 1.12   | 61.45  | 7.84  |      | 150.0 |         |
|           |  | Z | 0.95   | 60.64  | 6.63  |      | 150.0 |         |
| 10300-AAC | LTE-FDD (SC-FDMA, 50% RB, 3 MHz, 64-QAM)                           | X | 1.42   | 62.71  | 9.31  | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 0.97   | 60.00  | 6.35  |      | 150.0 |         |
|           |  | Z | 0.81   | 59.28  | 5.19  |      | 150.0 |         |
| 10301-AAA | IEEE 802.16e WiMAX (29:18, 5ms, 10MHz, QPSK, PUSC)                 | X | 4.62   | 65.84  | 17.67 | 4.17 | 50.0  | ± 9.6 % |
|           |  | Y | 4.14   | 64.69  | 16.63 |      | 50.0  |         |
|           |  | Z | 3.98   | 64.74  | 16.55 |      | 50.0  |         |
| 10302-AAA | IEEE 802.16e WiMAX (29:18, 5ms, 10MHz, QPSK, PUSC, 3 CTRL symbols) | X | 5.05   | 66.26  | 18.29 | 4.96 | 50.0  | ± 9.6 % |
|           |  | Y | 4.60   | 65.19  | 17.29 |      | 50.0  |         |
|           |  | Z | 4.43   | 65.29  | 17.26 |      | 50.0  |         |



|           |   |   |       |        |       |       |       |         |
|-----------|---|---|-------|--------|-------|-------|-------|---------|
| 10303-AAA | IEEE 802.16e WiMAX (31:15, 5ms, 10MHz, 64QAM, PUSC)                 | X | 4.79  | 65.85  | 18.07 | 4.96  | 50.0  | ± 9.6 % |
|           |   | Y | 4.38  | 65.09  | 17.25 |       | 50.0  |         |
|           |   | Z | 4.21  | 64.96  | 17.02 |       | 50.0  |         |
| 10304-AAA | IEEE 802.16e WiMAX (29:18, 5ms, 10MHz, 64QAM, PUSC)                 | X | 4.63  | 65.84  | 17.62 | 4.17  | 50.0  | ± 9.6 % |
|           |   | Y | 4.19  | 64.78  | 16.61 |       | 50.0  |         |
|           |   | Z | 4.06  | 65.02  | 16.64 |       | 50.0  |         |
| 10305-AAA | IEEE 802.16e WiMAX (31:15, 10ms, 10MHz, 64QAM, PUSC, 15 symbols)    | X | 4.10  | 67.08  | 19.12 | 6.02  | 35.0  | ± 9.6 % |
|           |   | Y | 3.65  | 65.55  | 17.41 |       | 35.0  |         |
|           |   | Z | 3.37  | 64.81  | 16.72 |       | 35.0  |         |
| 10306-AAA | IEEE 802.16e WiMAX (29:18, 10ms, 10MHz, 64QAM, PUSC, 18 symbols)    | X | 4.47  | 66.42  | 18.98 | 6.02  | 35.0  | ± 9.6 % |
|           |   | Y | 4.06  | 65.26  | 17.65 |       | 35.0  |         |
|           |   | Z | 3.83  | 64.86  | 17.21 |       | 35.0  |         |
| 10307-AAA | IEEE 802.16e WiMAX (29:18, 10ms, 10MHz, QPSK, PUSC, 18 symbols)     | X | 4.34  | 66.41  | 18.87 | 6.02  | 35.0  | ± 9.6 % |
|           |   | Y | 3.93  | 65.17  | 17.49 |       | 35.0  |         |
|           |   | Z | 3.70  | 64.72  | 17.03 |       | 35.0  |         |
| 10308-AAA | IEEE 802.16e WiMAX (29:18, 10ms, 10MHz, 16QAM, PUSC)                | X | 4.32  | 66.61  | 19.02 | 6.02  | 35.0  | ± 9.6 % |
|           |   | Y | 3.90  | 65.32  | 17.61 |       | 35.0  |         |
|           |   | Z | 3.67  | 64.86  | 17.15 |       | 35.0  |         |
| 10309-AAA | IEEE 802.16e WiMAX (29:18, 10ms, 10MHz, 16QAM, AMC 2x3, 18 symbols) | X | 4.50  | 66.55  | 19.10 | 6.02  | 35.0  | ± 9.6 % |
|           |   | Y | 4.07  | 65.30  | 17.73 |       | 35.0  |         |
|           |   | Z | 3.84  | 64.89  | 17.30 |       | 35.0  |         |
| 10310-AAA | IEEE 802.16e WiMAX (29:18, 10ms, 10MHz, QPSK, AMC 2x3, 18 symbols)  | X | 4.42  | 66.45  | 18.95 | 6.02  | 35.0  | ± 9.6 % |
|           |   | Y | 4.01  | 65.28  | 17.63 |       | 35.0  |         |
|           |   | Z | 3.78  | 64.88  | 17.21 |       | 35.0  |         |
| 10311-AAC | LTE-FDD (SC-FDMA, 100% RB, 15 MHz, QPSK)                            | X | 3.21  | 70.10  | 17.14 | 0.00  | 150.0 | ± 9.6 % |
|           |   | Y | 2.64  | 67.31  | 15.38 |       | 150.0 |         |
|           |   | Z | 2.74  | 68.46  | 16.13 |       | 150.0 |         |
| 10313-AAA | iDEN 1:3  | X | 6.56  | 87.61  | 22.74 | 6.99  | 70.0  | ± 9.6 % |
|           |   | Y | 1.63  | 66.74  | 13.18 |       | 70.0  |         |
|           |   | Z | 1.93  | 68.92  | 14.31 |       | 70.0  |         |
| 10314-AAA | iDEN 1:6  | X | 13.08 | 104.18 | 31.28 | 10.00 | 30.0  | ± 9.6 % |
|           |   | Y | 3.00  | 75.10  | 19.52 |       | 30.0  |         |
|           |   | Z | 3.43  | 77.96  | 20.90 |       | 30.0  |         |
| 10315-AAB | IEEE 802.11b WiFi 2.4 GHz (DSSS, 1 Mbps, 96pc duty cycle)           | X | 1.12  | 64.78  | 16.24 | 0.17  | 150.0 | ± 9.6 % |
|           |   | Y | 0.94  | 62.46  | 13.94 |       | 150.0 |         |
|           |   | Z | 1.03  | 63.61  | 14.80 |       | 150.0 |         |
| 10316-AAB | IEEE 802.11g WiFi 2.4 GHz (ERP-OFDM, 6 Mbps, 96pc duty cycle)       | X | 4.51  | 66.98  | 16.61 | 0.17  | 150.0 | ± 9.6 % |
|           |   | Y | 4.22  | 66.34  | 15.91 |       | 150.0 |         |
|           |   | Z | 4.19  | 66.75  | 16.06 |       | 150.0 |         |
| 10317-AAC | IEEE 802.11a WiFi 5 GHz (OFDM, 6 Mbps, 96pc duty cycle)             | X | 4.51  | 66.98  | 16.61 | 0.17  | 150.0 | ± 9.6 % |
|           |   | Y | 4.22  | 66.34  | 15.91 |       | 150.0 |         |
|           |   | Z | 4.19  | 66.75  | 16.06 |       | 150.0 |         |
| 10400-AAD | IEEE 802.11ac WiFi (20MHz, 64-QAM, 99pc duty cycle)                 | X | 4.59  | 67.28  | 16.58 | 0.00  | 150.0 | ± 9.6 % |
|           |   | Y | 4.28  | 66.62  | 15.93 |       | 150.0 |         |
|           |   | Z | 4.23  | 67.02  | 16.11 |       | 150.0 |         |
| 10401-AAD | IEEE 802.11ac WiFi (40MHz, 64-QAM, 99pc duty cycle)                 | X | 5.28  | 67.19  | 16.63 | 0.00  | 150.0 | ± 9.6 % |
|           |   | Y | 4.97  | 66.45  | 16.02 |       | 150.0 |         |
|           |   | Z | 4.98  | 66.97  | 16.27 |       | 150.0 |         |



|           |   |   |        |        |       |      |       |         |
|-----------|---|---|--------|--------|-------|------|-------|---------|
| 10402-AAD | IEEE 802.11ac WiFi (80MHz, 64-QAM, 99pc duty cycle)                             | X | 5.58   | 67.57  | 16.70 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.34   | 67.07  | 16.25 |      | 150.0 |         |
|           |   | Z | 5.31   | 67.37  | 16.40 |      | 150.0 |         |
| 10403-AAB | CDMA2000 (1xEV-DO, Rev. 0)  | X | 1.70   | 71.93  | 14.73 | 0.00 | 115.0 | ± 9.6 % |
|           |   | Y | 0.60   | 60.98  | 7.34  |      | 115.0 |         |
|           |   | Z | 0.57   | 61.36  | 7.44  |      | 115.0 |         |
| 10404-AAB | CDMA2000 (1xEV-DO, Rev. A)  | X | 1.70   | 71.93  | 14.73 | 0.00 | 115.0 | ± 9.6 % |
|           |   | Y | 0.60   | 60.98  | 7.34  |      | 115.0 |         |
|           |   | Z | 0.57   | 61.36  | 7.44  |      | 115.0 |         |
| 10406-AAB | CDMA2000, RC3, SO32, SCH0, Full Rate  | X | 100.00 | 126.01 | 31.66 | 0.00 | 100.0 | ± 9.6 % |
|           |   | Y | 33.85  | 102.92 | 23.46 |      | 100.0 |         |
|           |   | Z | 100.00 | 105.43 | 21.55 |      | 100.0 |         |
| 10410-AAD | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, QPSK, UL Subframe=2,3,4,7,8,9, Subframe Conf=4) | X | 100.00 | 136.13 | 35.94 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 2.80   | 79.45  | 18.39 |      | 80.0  |         |
|           |   | Z | 5.17   | 86.91  | 20.17 |      | 80.0  |         |
| 10415-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 1 Mbps, 99pc duty cycle)                       | X | 1.06   | 64.13  | 15.71 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.91   | 62.09  | 13.58 |      | 150.0 |         |
|           |   | Z | 0.99   | 63.26  | 14.51 |      | 150.0 |         |
| 10416-AAA | IEEE 802.11g WiFi 2.4 GHz (ERP-OFDM, 6 Mbps, 99pc duty cycle)                   | X | 4.46   | 66.98  | 16.52 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.20   | 66.41  | 15.91 |      | 150.0 |         |
|           |   | Z | 4.18   | 66.90  | 16.11 |      | 150.0 |         |
| 10417-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 6 Mbps, 99pc duty cycle)                       | X | 4.46   | 66.98  | 16.52 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.20   | 66.41  | 15.91 |      | 150.0 |         |
|           |   | Z | 4.18   | 66.90  | 16.11 |      | 150.0 |         |
| 10418-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 6 Mbps, 99pc duty cycle, Long preamble)   | X | 4.46   | 67.20  | 16.58 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.19   | 66.62  | 15.97 |      | 150.0 |         |
|           |   | Z | 4.17   | 67.13  | 16.19 |      | 150.0 |         |
| 10419-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 6 Mbps, 99pc duty cycle, Short preamble)  | X | 4.48   | 67.12  | 16.57 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.21   | 66.55  | 15.95 |      | 150.0 |         |
|           |   | Z | 4.19   | 67.05  | 16.16 |      | 150.0 |         |
| 10422-AAB | IEEE 802.11n (HT Greenfield, 7.2 Mbps, BPSK)                                    | X | 4.58   | 67.09  | 16.57 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.31   | 66.54  | 15.97 |      | 150.0 |         |
|           |   | Z | 4.29   | 67.01  | 16.18 |      | 150.0 |         |
| 10423-AAB | IEEE 802.11n (HT Greenfield, 43.3 Mbps, 16-QAM)                                 | X | 4.72   | 67.36  | 16.66 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.42   | 66.78  | 16.06 |      | 150.0 |         |
|           |   | Z | 4.39   | 67.23  | 16.25 |      | 150.0 |         |
| 10424-AAB | IEEE 802.11n (HT Greenfield, 72.2 Mbps, 64-QAM)                                 | X | 4.65   | 67.32  | 16.64 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.36   | 66.72  | 16.03 |      | 150.0 |         |
|           |   | Z | 4.32   | 67.16  | 16.22 |      | 150.0 |         |
| 10425-AAB | IEEE 802.11n (HT Greenfield, 15 Mbps, BPSK)                                     | X | 5.27   | 67.51  | 16.80 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.01   | 66.94  | 16.30 |      | 150.0 |         |
|           |   | Z | 4.95   | 67.18  | 16.40 |      | 150.0 |         |
| 10426-AAB | IEEE 802.11n (HT Greenfield, 90 Mbps, 16-QAM)                                   | X | 5.30   | 67.62  | 16.85 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.05   | 67.11  | 16.37 |      | 150.0 |         |
|           |   | Z | 4.99   | 67.36  | 16.49 |      | 150.0 |         |



|           |  |   |        |        |       |      |       |         |
|-----------|--|---|--------|--------|-------|------|-------|---------|
| 10427-AAB | IEEE 802.11n (HT Greenfield, 150 Mbps, 64-QAM)                 | X | 5.26   | 67.41  | 16.75 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.00   | 66.85  | 16.24 |      | 150.0 |         |
|           |  | Z | 4.95   | 67.15  | 16.38 |      | 150.0 |         |
| 10430-AAB | LTE-FDD (OFDMA, 5 MHz, E-TM 3.1)                               | X | 4.36   | 72.46  | 18.78 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.95   | 71.52  | 17.57 |      | 150.0 |         |
|           |  | Z | 4.16   | 73.16  | 18.05 |      | 150.0 |         |
| 10431-AAB | LTE-FDD (OFDMA, 10 MHz, E-TM 3.1)                              | X | 4.11   | 67.69  | 16.50 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.76   | 66.86  | 15.60 |      | 150.0 |         |
|           |  | Z | 3.73   | 67.46  | 15.80 |      | 150.0 |         |
| 10432-AAB | LTE-FDD (OFDMA, 15 MHz, E-TM 3.1)                              | X | 4.42   | 67.45  | 16.60 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.11   | 66.79  | 15.89 |      | 150.0 |         |
|           |  | Z | 4.08   | 67.30  | 16.10 |      | 150.0 |         |
| 10433-AAB | LTE-FDD (OFDMA, 20 MHz, E-TM 3.1)                              | X | 4.67   | 67.35  | 16.66 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.38   | 66.75  | 16.05 |      | 150.0 |         |
|           |  | Z | 4.34   | 67.21  | 16.25 |      | 150.0 |         |
| 10434-AAA | W-CDMA (BS Test Model 1, 64 DPCH)                              | X | 4.53   | 73.61  | 18.74 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.88   | 71.64  | 16.92 |      | 150.0 |         |
|           |  | Z | 4.07   | 73.14  | 17.26 |      | 150.0 |         |
| 10435-AAC | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, QPSK, UL Subframe=2,3,4,7,8,9) | X | 100.00 | 135.86 | 35.81 | 3.23 | 80.0  | ± 9.6 % |
|           |  | Y | 2.67   | 78.72  | 18.07 |      | 80.0  |         |
|           |  | Z | 4.68   | 85.55  | 19.69 |      | 80.0  |         |
| 10447-AAB | LTE-FDD (OFDMA, 5 MHz, E-TM 3.1, Clipping 44%)                 | X | 3.40   | 67.82  | 15.63 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.91   | 66.11  | 13.93 |      | 150.0 |         |
|           |  | Z | 2.86   | 66.61  | 13.92 |      | 150.0 |         |
| 10448-AAB | LTE-FDD (OFDMA, 10 MHz, E-TM 3.1, Clipping 44%)                | X | 3.97   | 67.49  | 16.38 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.64   | 66.66  | 15.47 |      | 150.0 |         |
|           |  | Z | 3.62   | 67.28  | 15.69 |      | 150.0 |         |
| 10449-AAB | LTE-FDD (OFDMA, 15 MHz, E-TM 3.1, Clipping 44%)                | X | 4.25   | 67.29  | 16.51 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.96   | 66.60  | 15.79 |      | 150.0 |         |
|           |  | Z | 3.94   | 67.14  | 16.01 |      | 150.0 |         |
| 10450-AAB | LTE-FDD (OFDMA, 20 MHz, E-TM 3.1, Clipping 44%)                | X | 4.46   | 67.14  | 16.53 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.19   | 66.52  | 15.90 |      | 150.0 |         |
|           |  | Z | 4.17   | 66.99  | 16.11 |      | 150.0 |         |
| 10451-AAA | W-CDMA (BS Test Model 1, 64 DPCH, Clipping 44%)                | X | 3.24   | 67.81  | 15.03 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 2.64   | 65.47  | 12.88 |      | 150.0 |         |
|           |  | Z | 2.52   | 65.63  | 12.65 |      | 150.0 |         |
| 10456-AAB | IEEE 802.11ac WiFi (160MHz, 64-QAM, 99pc duty cycle)           | X | 6.23   | 68.15  | 17.01 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.99   | 67.59  | 16.55 |      | 150.0 |         |
|           |  | Z | 6.32   | 68.95  | 17.23 |      | 150.0 |         |
| 10457-AAA | UMTS-FDD (DC-HSDPA)  | X | 3.79   | 65.68  | 16.25 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.60   | 65.24  | 15.64 |      | 150.0 |         |
|           |  | Z | 3.62   | 65.83  | 15.88 |      | 150.0 |         |
| 10458-AAA | CDMA2000 (1xEV-DO, Rev. B, 2 carriers)                         | X | 4.04   | 72.33  | 17.68 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 3.05   | 68.37  | 14.62 |      | 150.0 |         |
|           |  | Z | 2.80   | 67.80  | 13.84 |      | 150.0 |         |
| 10459-AAA | CDMA2000 (1xEV-DO, Rev. B, 3 carriers)                         | X | 4.97   | 69.15  | 18.20 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.58   | 68.57  | 17.18 |      | 150.0 |         |
|           |  | Z | 4.37   | 68.40  | 16.57 |      | 150.0 |         |



|           |   |   |        |        |       |      |       |         |
|-----------|---|---|--------|--------|-------|------|-------|---------|
| 10460-AAA | UMTS-FDD (WCDMA, AMR)   | X | 1.17   | 73.55  | 19.20 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.69   | 65.37  | 13.60 |      | 150.0 |         |
|           |   | Z | 0.85   | 68.57  | 15.82 |      | 150.0 |         |
| 10461-AAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK, UL Subframe=2,3,4,7,8,9)   | X | 100.00 | 141.28 | 38.40 | 3.29 | 80.0  | ± 9.6 % |
|           |   | Y | 1.76   | 74.78  | 17.76 |      | 80.0  |         |
|           |   | Z | 1.76   | 75.94  | 17.96 |      | 80.0  |         |
| 10462-AAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9) | X | 100.00 | 111.72 | 24.78 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.63   | 60.00  | 7.07  |      | 80.0  |         |
|           |   | Z | 0.28   | 55.79  | 3.71  |      | 80.0  |         |
| 10463-AAA | LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9) | X | 1.59   | 67.85  | 11.93 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.65   | 60.00  | 6.35  |      | 80.0  |         |
|           |   | Z | 1.31   | 62.17  | 5.59  |      | 80.0  |         |
| 10464-AAA | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 100.00 | 138.52 | 36.90 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 1.25   | 70.26  | 15.26 |      | 80.0  |         |
|           |   | Z | 1.21   | 70.85  | 15.20 |      | 80.0  |         |
| 10465-AAA | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 30.72  | 98.91  | 21.78 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.63   | 60.00  | 7.00  |      | 80.0  |         |
|           |   | Z | 0.27   | 55.69  | 3.59  |      | 80.0  |         |
| 10466-AAA | LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 1.19   | 65.08  | 10.74 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.65   | 60.00  | 6.31  |      | 80.0  |         |
|           |   | Z | 1.85   | 63.59  | 6.08  |      | 80.0  |         |
| 10467-AAC | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 100.00 | 138.98 | 37.10 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 1.33   | 71.06  | 15.64 |      | 80.0  |         |
|           |   | Z | 1.29   | 71.78  | 15.63 |      | 80.0  |         |
| 10468-AAC | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 76.98  | 108.44 | 23.94 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.63   | 60.00  | 7.03  |      | 80.0  |         |
|           |   | Z | 0.27   | 55.71  | 3.62  |      | 80.0  |         |
| 10469-AAC | LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 1.21   | 65.20  | 10.80 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.65   | 60.00  | 6.31  |      | 80.0  |         |
|           |   | Z | 3.58   | 65.43  | 6.42  |      | 80.0  |         |
| 10470-AAC | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, QPSK, UL Subframe=2,3,4,7,8,9)    | X | 100.00 | 139.06 | 37.12 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 1.32   | 71.07  | 15.64 |      | 80.0  |         |
|           |   | Z | 1.29   | 71.81  | 15.63 |      | 80.0  |         |
| 10471-AAC | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)  | X | 73.65  | 107.90 | 23.80 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.63   | 60.00  | 7.01  |      | 80.0  |         |
|           |   | Z | 0.27   | 55.71  | 3.62  |      | 80.0  |         |
| 10472-AAC | LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)  | X | 1.19   | 65.08  | 10.73 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.65   | 60.00  | 6.29  |      | 80.0  |         |
|           |   | Z | 1.57   | 62.83  | 5.79  |      | 80.0  |         |
| 10473-AAC | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, QPSK, UL Subframe=2,3,4,7,8,9)    | X | 100.00 | 139.02 | 37.10 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 1.32   | 71.02  | 15.61 |      | 80.0  |         |
|           |   | Z | 1.29   | 71.75  | 15.60 |      | 80.0  |         |
| 10474-AAC | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)  | X | 68.67  | 107.20 | 23.65 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.63   | 60.00  | 7.01  |      | 80.0  |         |
|           |   | Z | 0.27   | 55.70  | 3.61  |      | 80.0  |         |
| 10475-AAC | LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)  | X | 1.18   | 65.03  | 10.71 | 3.23 | 80.0  | ± 9.6 % |
|           |   | Y | 0.65   | 60.00  | 6.29  |      | 80.0  |         |
|           |   | Z | 1.97   | 63.77  | 6.11  |      | 80.0  |         |



|           |   |   |       |        |       |      |      |         |
|-----------|---|---|-------|--------|-------|------|------|---------|
| 10477-AAC | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)    | X | 35.28 | 100.26 | 22.06 | 3.23 | 80.0 | ± 9.6 % |
|           |   | Y | 0.63  | 60.00  | 6.98  |      | 80.0 |         |
|           |   | Z | 0.27  | 55.66  | 3.55  |      | 80.0 |         |
| 10478-AAC | LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)    | X | 1.17  | 64.89  | 10.64 | 3.23 | 80.0 | ± 9.6 % |
|           |   | Y | 0.65  | 60.00  | 6.28  |      | 80.0 |         |
|           |   | Z | 1.78  | 63.33  | 5.95  |      | 80.0 |         |
| 10479-AAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK, UL Subframe=2,3,4,7,8,9)   | X | 35.57 | 114.76 | 31.71 | 3.23 | 80.0 | ± 9.6 % |
|           |   | Y | 3.95  | 79.78  | 19.79 |      | 80.0 |         |
|           |   | Z | 4.53  | 82.88  | 20.60 |      | 80.0 |         |
| 10480-AAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9) | X | 38.88 | 104.98 | 26.14 | 3.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.74  | 65.59  | 11.83 |      | 80.0 |         |
|           |   | Z | 1.34  | 64.00  | 10.40 |      | 80.0 |         |
| 10481-AAA | LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9) | X | 15.80 | 91.83  | 22.10 | 3.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.34  | 62.56  | 9.98  |      | 80.0 |         |
|           |   | Z | 0.98  | 60.86  | 8.40  |      | 80.0 |         |
| 10482-AAA | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 4.83  | 81.02  | 20.08 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 0.99  | 60.60  | 9.42  |      | 80.0 |         |
|           |   | Z | 0.88  | 60.00  | 8.54  |      | 80.0 |         |
| 10483-AAA | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.99  | 73.64  | 16.29 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.21  | 60.00  | 8.36  |      | 80.0 |         |
|           |   | Z | 1.11  | 60.00  | 7.47  |      | 80.0 |         |
| 10484-AAA | LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.44  | 71.51  | 15.46 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.24  | 60.00  | 8.35  |      | 80.0 |         |
|           |   | Z | 1.14  | 60.00  | 7.46  |      | 80.0 |         |
| 10485-AAC | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 4.45  | 80.81  | 21.58 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.56  | 65.26  | 13.48 |      | 80.0 |         |
|           |   | Z | 1.52  | 65.39  | 13.15 |      | 80.0 |         |
| 10486-AAC | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.46  | 72.56  | 17.41 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.57  | 62.14  | 11.00 |      | 80.0 |         |
|           |   | Z | 1.40  | 61.37  | 10.05 |      | 80.0 |         |
| 10487-AAC | LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.35  | 71.66  | 16.99 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 1.59  | 61.93  | 10.85 |      | 80.0 |         |
|           |   | Z | 1.41  | 61.12  | 9.88  |      | 80.0 |         |
| 10488-AAC | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, QPSK, UL Subframe=2,3,4,7,8,9)    | X | 3.67  | 75.52  | 20.64 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 2.17  | 67.32  | 16.01 |      | 80.0 |         |
|           |   | Z | 2.20  | 68.10  | 16.24 |      | 80.0 |         |
| 10489-AAC | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)  | X | 3.39  | 70.55  | 18.29 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 2.41  | 65.58  | 14.94 |      | 80.0 |         |
|           |   | Z | 2.42  | 66.16  | 14.95 |      | 80.0 |         |
| 10490-AAC | LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)  | X | 3.45  | 70.24  | 18.13 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 2.49  | 65.52  | 14.91 |      | 80.0 |         |
|           |   | Z | 2.48  | 66.02  | 14.86 |      | 80.0 |         |
| 10491-AAC | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, QPSK, UL Subframe=2,3,4,7,8,9)    | X | 3.68  | 72.54  | 19.53 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 2.56  | 66.97  | 16.21 |      | 80.0 |         |
|           |   | Z | 2.58  | 67.61  | 16.44 |      | 80.0 |         |
| 10492-AAC | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)  | X | 3.60  | 68.93  | 17.94 | 2.23 | 80.0 | ± 9.6 % |
|           |   | Y | 2.85  | 65.57  | 15.57 |      | 80.0 |         |
|           |   | Z | 2.86  | 66.13  | 15.66 |      | 80.0 |         |



|           |  |   |      |       |       |      |      |         |
|-----------|--|---|------|-------|-------|------|------|---------|
| 10493-AAC | LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.65 | 68.74 | 17.84 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.91 | 65.51 | 15.54 |      | 80.0 |         |
|           |  | Z | 2.91 | 66.04 | 15.60 |      | 80.0 |         |
| 10494-AAC | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 4.07 | 74.42 | 20.20 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.69 | 67.87 | 16.56 |      | 80.0 |         |
|           |  | Z | 2.72 | 68.54 | 16.85 |      | 80.0 |         |
| 10495-AAC | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.62 | 69.21 | 18.16 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.87 | 65.77 | 15.81 |      | 80.0 |         |
|           |  | Z | 2.89 | 66.32 | 15.94 |      | 80.0 |         |
| 10496-AAC | LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.69 | 68.87 | 18.01 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.97 | 65.70 | 15.81 |      | 80.0 |         |
|           |  | Z | 2.98 | 66.24 | 15.93 |      | 80.0 |         |
| 10497-AAA | LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, QPSK, UL Subframe=2,3,4,7,8,9)   | X | 2.43 | 70.80 | 14.69 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 0.87 | 60.00 | 7.40  |      | 80.0 |         |
|           |  | Z | 0.84 | 60.00 | 6.67  |      | 80.0 |         |
| 10498-AAA | LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9) | X | 1.15 | 60.00 | 8.26  | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 1.07 | 60.00 | 6.17  |      | 80.0 |         |
|           |  | Z | 1.09 | 60.00 | 5.31  |      | 80.0 |         |
| 10499-AAA | LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9) | X | 1.17 | 60.00 | 8.07  | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 1.10 | 60.00 | 6.00  |      | 80.0 |         |
|           |  | Z | 1.14 | 60.00 | 5.11  |      | 80.0 |         |
| 10500-AAA | LTE-TDD (SC-FDMA, 100% RB, 3 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 3.92 | 77.92 | 20.96 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 1.82 | 66.27 | 14.58 |      | 80.0 |         |
|           |  | Z | 1.82 | 66.79 | 14.52 |      | 80.0 |         |
| 10501-AAA | LTE-TDD (SC-FDMA, 100% RB, 3 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.47 | 71.98 | 17.83 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 1.94 | 63.86 | 12.69 |      | 80.0 |         |
|           |  | Z | 1.82 | 63.61 | 12.10 |      | 80.0 |         |
| 10502-AAA | LTE-TDD (SC-FDMA, 100% RB, 3 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.50 | 71.66 | 17.60 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 1.97 | 63.71 | 12.53 |      | 80.0 |         |
|           |  | Z | 1.83 | 63.39 | 11.89 |      | 80.0 |         |
| 10503-AAC | LTE-TDD (SC-FDMA, 100% RB, 5 MHz, QPSK, UL Subframe=2,3,4,7,8,9)     | X | 3.62 | 75.27 | 20.52 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.15 | 67.15 | 15.91 |      | 80.0 |         |
|           |  | Z | 2.18 | 67.92 | 16.14 |      | 80.0 |         |
| 10504-AAC | LTE-TDD (SC-FDMA, 100% RB, 5 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.37 | 70.44 | 18.22 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.40 | 65.48 | 14.88 |      | 80.0 |         |
|           |  | Z | 2.40 | 66.05 | 14.87 |      | 80.0 |         |
| 10505-AAC | LTE-TDD (SC-FDMA, 100% RB, 5 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9)   | X | 3.43 | 70.14 | 18.07 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.48 | 65.44 | 14.85 |      | 80.0 |         |
|           |  | Z | 2.47 | 65.93 | 14.80 |      | 80.0 |         |
| 10506-AAC | LTE-TDD (SC-FDMA, 100% RB, 10 MHz, QPSK, UL Subframe=2,3,4,7,8,9)    | X | 4.03 | 74.26 | 20.11 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.67 | 67.75 | 16.49 |      | 80.0 |         |
|           |  | Z | 2.70 | 68.42 | 16.78 |      | 80.0 |         |
| 10507-AAC | LTE-TDD (SC-FDMA, 100% RB, 10 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9)  | X | 3.61 | 69.15 | 18.12 | 2.23 | 80.0 | ± 9.6 % |
|           |  | Y | 2.86 | 65.71 | 15.77 |      | 80.0 |         |
|           |  | Z | 2.87 | 66.26 | 15.90 |      | 80.0 |         |



|           |   |   |      |       |       |      |       |         |
|-----------|---|---|------|-------|-------|------|-------|---------|
| 10508-AAC | LTE-TDD (SC-FDMA, 100% RB, 10 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9) | X | 3.68 | 68.80 | 17.97 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 2.96 | 65.63 | 15.76 |      | 80.0  |         |
|           |   | Z | 2.96 | 66.17 | 15.88 |      | 80.0  |         |
| 10509-AAC | LTE-TDD (SC-FDMA, 100% RB, 15 MHz, QPSK, UL Subframe=2,3,4,7,8,9)   | X | 4.26 | 72.20 | 19.19 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 3.16 | 67.48 | 16.47 |      | 80.0  |         |
|           |   | Z | 3.18 | 68.06 | 16.73 |      | 80.0  |         |
| 10510-AAC | LTE-TDD (SC-FDMA, 100% RB, 15 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9) | X | 4.03 | 68.46 | 17.90 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 3.36 | 65.76 | 16.06 |      | 80.0  |         |
|           |   | Z | 3.36 | 66.20 | 16.19 |      | 80.0  |         |
| 10511-AAC | LTE-TDD (SC-FDMA, 100% RB, 15 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9) | X | 4.09 | 68.19 | 17.80 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 3.45 | 65.68 | 16.05 |      | 80.0  |         |
|           |   | Z | 3.44 | 66.13 | 16.18 |      | 80.0  |         |
| 10512-AAC | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, QPSK, UL Subframe=2,3,4,7,8,9)   | X | 4.55 | 74.17 | 19.89 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 3.13 | 68.19 | 16.64 |      | 80.0  |         |
|           |   | Z | 3.17 | 68.78 | 16.93 |      | 80.0  |         |
| 10513-AAC | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM, UL Subframe=2,3,4,7,8,9) | X | 3.93 | 68.71 | 18.04 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 3.25 | 65.77 | 16.08 |      | 80.0  |         |
|           |   | Z | 3.26 | 66.20 | 16.22 |      | 80.0  |         |
| 10514-AAC | LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM, UL Subframe=2,3,4,7,8,9) | X | 3.95 | 68.24 | 17.86 | 2.23 | 80.0  | ± 9.6 % |
|           |   | Y | 3.31 | 65.57 | 16.03 |      | 80.0  |         |
|           |   | Z | 3.32 | 66.00 | 16.17 |      | 80.0  |         |
| 10515-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 2 Mbps, 99pc duty cycle)           | X | 1.02 | 64.43 | 15.85 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.87 | 62.20 | 13.57 |      | 150.0 |         |
|           |   | Z | 0.95 | 63.43 | 14.56 |      | 150.0 |         |
| 10516-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 5.5 Mbps, 99pc duty cycle)         | X | 1.13 | 82.75 | 23.62 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.43 | 66.13 | 13.76 |      | 150.0 |         |
|           |   | Z | 0.58 | 70.25 | 17.11 |      | 150.0 |         |
| 10517-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 11 Mbps, 99pc duty cycle)          | X | 0.91 | 67.50 | 17.20 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 0.69 | 63.31 | 13.63 |      | 150.0 |         |
|           |   | Z | 0.79 | 65.08 | 15.11 |      | 150.0 |         |
| 10518-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 9 Mbps, 99pc duty cycle)           | X | 4.46 | 67.09 | 16.52 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.19 | 66.52 | 15.90 |      | 150.0 |         |
|           |   | Z | 4.17 | 67.03 | 16.12 |      | 150.0 |         |
| 10519-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 12 Mbps, 99pc duty cycle)          | X | 4.61 | 67.26 | 16.61 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.32 | 66.68 | 15.99 |      | 150.0 |         |
|           |   | Z | 4.29 | 67.16 | 16.19 |      | 150.0 |         |
| 10520-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 18 Mbps, 99pc duty cycle)          | X | 4.47 | 67.21 | 16.53 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.18 | 66.59 | 15.89 |      | 150.0 |         |
|           |   | Z | 4.15 | 67.08 | 16.10 |      | 150.0 |         |
| 10521-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 24 Mbps, 99pc duty cycle)          | X | 4.40 | 67.20 | 16.52 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.11 | 66.53 | 15.85 |      | 150.0 |         |
|           |   | Z | 4.08 | 67.00 | 16.06 |      | 150.0 |         |
| 10522-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 36 Mbps, 99pc duty cycle)          | X | 4.46 | 67.33 | 16.62 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 4.15 | 66.62 | 15.93 |      | 150.0 |         |
|           |   | Z | 4.10 | 67.02 | 16.09 |      | 150.0 |         |



|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10523-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 48 Mbps, 99pc duty cycle) | X | 4.38 | 67.30 | 16.53 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.10 | 66.70 | 15.90 |      | 150.0 |         |
|           |  | Z | 4.09 | 67.25 | 16.15 |      | 150.0 |         |
| 10524-AAB | IEEE 802.11a/h WiFi 5 GHz (OFDM, 54 Mbps, 99pc duty cycle) | X | 4.41 | 67.28 | 16.61 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.11 | 66.63 | 15.95 |      | 150.0 |         |
|           |  | Z | 4.08 | 67.11 | 16.17 |      | 150.0 |         |
| 10525-AAB | IEEE 802.11ac WiFi (20MHz, MCS0, 99pc duty cycle)          | X | 4.43 | 66.37 | 16.22 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.16 | 65.76 | 15.59 |      | 150.0 |         |
|           |  | Z | 4.15 | 66.30 | 15.83 |      | 150.0 |         |
| 10526-AAB | IEEE 802.11ac WiFi (20MHz, MCS1, 99pc duty cycle)          | X | 4.57 | 66.67 | 16.34 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.26 | 66.00 | 15.69 |      | 150.0 |         |
|           |  | Z | 4.23 | 66.49 | 15.92 |      | 150.0 |         |
| 10527-AAB | IEEE 802.11ac WiFi (20MHz, MCS2, 99pc duty cycle)          | X | 4.50 | 66.64 | 16.28 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.19 | 65.96 | 15.63 |      | 150.0 |         |
|           |  | Z | 4.17 | 66.49 | 15.87 |      | 150.0 |         |
| 10528-AAB | IEEE 802.11ac WiFi (20MHz, MCS3, 99pc duty cycle)          | X | 4.51 | 66.66 | 16.32 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.21 | 65.98 | 15.66 |      | 150.0 |         |
|           |  | Z | 4.18 | 66.49 | 15.89 |      | 150.0 |         |
| 10529-AAB | IEEE 802.11ac WiFi (20MHz, MCS4, 99pc duty cycle)          | X | 4.51 | 66.66 | 16.32 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.21 | 65.98 | 15.66 |      | 150.0 |         |
|           |  | Z | 4.18 | 66.49 | 15.89 |      | 150.0 |         |
| 10531-AAB | IEEE 802.11ac WiFi (20MHz, MCS6, 99pc duty cycle)          | X | 4.48 | 66.70 | 16.31 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.16 | 65.96 | 15.62 |      | 150.0 |         |
|           |  | Z | 4.14 | 66.45 | 15.84 |      | 150.0 |         |
| 10532-AAB | IEEE 802.11ac WiFi (20MHz, MCS7, 99pc duty cycle)          | X | 4.36 | 66.57 | 16.24 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.05 | 65.82 | 15.55 |      | 150.0 |         |
|           |  | Z | 4.04 | 66.34 | 15.78 |      | 150.0 |         |
| 10533-AAB | IEEE 802.11ac WiFi (20MHz, MCS8, 99pc duty cycle)          | X | 4.52 | 66.74 | 16.32 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.21 | 66.06 | 15.66 |      | 150.0 |         |
|           |  | Z | 4.19 | 66.59 | 15.90 |      | 150.0 |         |
| 10534-AAB | IEEE 802.11ac WiFi (40MHz, MCS0, 99pc duty cycle)          | X | 5.06 | 66.61 | 16.33 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.80 | 66.02 | 15.81 |      | 150.0 |         |
|           |  | Z | 4.77 | 66.37 | 15.98 |      | 150.0 |         |
| 10535-AAB | IEEE 802.11ac WiFi (40MHz, MCS1, 99pc duty cycle)          | X | 5.11 | 66.77 | 16.41 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.83 | 66.12 | 15.86 |      | 150.0 |         |
|           |  | Z | 4.79 | 66.46 | 16.03 |      | 150.0 |         |
| 10536-AAB | IEEE 802.11ac WiFi (40MHz, MCS2, 99pc duty cycle)          | X | 5.01 | 66.77 | 16.39 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.72 | 66.10 | 15.82 |      | 150.0 |         |
|           |  | Z | 4.69 | 66.46 | 16.01 |      | 150.0 |         |
| 10537-AAB | IEEE 802.11ac WiFi (40MHz, MCS3, 99pc duty cycle)          | X | 5.06 | 66.74 | 16.38 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.81 | 66.18 | 15.87 |      | 150.0 |         |
|           |  | Z | 4.78 | 66.54 | 16.05 |      | 150.0 |         |
| 10538-AAB | IEEE 802.11ac WiFi (40MHz, MCS4, 99pc duty cycle)          | X | 5.13 | 66.70 | 16.40 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.85 | 66.09 | 15.86 |      | 150.0 |         |
|           |  | Z | 4.81 | 66.40 | 16.01 |      | 150.0 |         |
| 10540-AAB | IEEE 802.11ac WiFi (40MHz, MCS6, 99pc duty cycle)          | X | 5.06 | 66.67 | 16.40 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.78 | 66.04 | 15.86 |      | 150.0 |         |
|           |  | Z | 4.75 | 66.37 | 16.02 |      | 150.0 |         |



|           |  |   |      |       |       |      |       |         |
|-----------|--|---|------|-------|-------|------|-------|---------|
| 10541-AAB | IEEE 802.11ac WiFi (40MHz, MCS7, 99pc duty cycle)  | X | 5.04 | 66.56 | 16.33 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.78 | 65.98 | 15.81 |      | 150.0 |         |
|           |  | Z | 4.75 | 66.35 | 15.98 |      | 150.0 |         |
| 10542-AAB | IEEE 802.11ac WiFi (40MHz, MCS8, 99pc duty cycle)  | X | 5.19 | 66.66 | 16.39 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 4.92 | 66.09 | 15.88 |      | 150.0 |         |
|           |  | Z | 4.89 | 66.42 | 16.04 |      | 150.0 |         |
| 10543-AAB | IEEE 802.11ac WiFi (40MHz, MCS9, 99pc duty cycle)  | X | 5.27 | 66.72 | 16.45 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.01 | 66.24 | 15.99 |      | 150.0 |         |
|           |  | Z | 4.95 | 66.50 | 16.11 |      | 150.0 |         |
| 10544-AAB | IEEE 802.11ac WiFi (80MHz, MCS0, 99pc duty cycle)  | X | 5.40 | 66.66 | 16.30 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.16 | 66.08 | 15.82 |      | 150.0 |         |
|           |  | Z | 5.15 | 66.40 | 15.97 |      | 150.0 |         |
| 10545-AAB | IEEE 802.11ac WiFi (80MHz, MCS1, 99pc duty cycle)  | X | 5.60 | 67.15 | 16.51 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.35 | 66.58 | 16.03 |      | 150.0 |         |
|           |  | Z | 5.29 | 66.80 | 16.14 |      | 150.0 |         |
| 10546-AAB | IEEE 802.11ac WiFi (80MHz, MCS2, 99pc duty cycle)  | X | 5.44 | 66.80 | 16.34 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.19 | 66.19 | 15.84 |      | 150.0 |         |
|           |  | Z | 5.16 | 66.49 | 15.99 |      | 150.0 |         |
| 10547-AAB | IEEE 802.11ac WiFi (80MHz, MCS3, 99pc duty cycle)  | X | 5.52 | 66.91 | 16.39 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.30 | 66.44 | 15.97 |      | 150.0 |         |
|           |  | Z | 5.28 | 66.77 | 16.13 |      | 150.0 |         |
| 10548-AAB | IEEE 802.11ac WiFi (80MHz, MCS4, 99pc duty cycle)  | X | 5.71 | 67.68 | 16.76 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.40 | 66.91 | 16.18 |      | 150.0 |         |
|           |  | Z | 5.30 | 66.99 | 16.22 |      | 150.0 |         |
| 10550-AAB | IEEE 802.11ac WiFi (80MHz, MCS6, 99pc duty cycle)  | X | 5.51 | 67.01 | 16.46 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.29 | 66.55 | 16.04 |      | 150.0 |         |
|           |  | Z | 5.27 | 66.87 | 16.20 |      | 150.0 |         |
| 10551-AAB | IEEE 802.11ac WiFi (80MHz, MCS7, 99pc duty cycle)  | X | 5.44 | 66.78 | 16.31 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.17 | 66.12 | 15.79 |      | 150.0 |         |
|           |  | Z | 5.14 | 66.41 | 15.93 |      | 150.0 |         |
| 10552-AAB | IEEE 802.11ac WiFi (80MHz, MCS8, 99pc duty cycle)  | X | 5.41 | 66.76 | 16.30 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.17 | 66.21 | 15.83 |      | 150.0 |         |
|           |  | Z | 5.15 | 66.55 | 16.00 |      | 150.0 |         |
| 10553-AAB | IEEE 802.11ac WiFi (80MHz, MCS9, 99pc duty cycle)  | X | 5.47 | 66.72 | 16.31 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.21 | 66.14 | 15.82 |      | 150.0 |         |
|           |  | Z | 5.19 | 66.45 | 15.97 |      | 150.0 |         |
| 10554-AAC | IEEE 802.11ac WiFi (160MHz, MCS0, 99pc duty cycle) | X | 5.82 | 66.99 | 16.37 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.60 | 66.44 | 15.92 |      | 150.0 |         |
|           |  | Z | 5.58 | 66.70 | 16.04 |      | 150.0 |         |
| 10555-AAC | IEEE 802.11ac WiFi (160MHz, MCS1, 99pc duty cycle) | X | 5.93 | 67.26 | 16.49 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.68 | 66.64 | 16.01 |      | 150.0 |         |
|           |  | Z | 5.65 | 66.86 | 16.11 |      | 150.0 |         |
| 10556-AAC | IEEE 802.11ac WiFi (160MHz, MCS2, 99pc duty cycle) | X | 5.97 | 67.36 | 16.54 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.74 | 66.82 | 16.09 |      | 150.0 |         |
|           |  | Z | 5.70 | 67.03 | 16.19 |      | 150.0 |         |
| 10557-AAC | IEEE 802.11ac WiFi (160MHz, MCS3, 99pc duty cycle) | X | 5.92 | 67.20 | 16.47 | 0.00 | 150.0 | ± 9.6 % |
|           |  | Y | 5.68 | 66.62 | 16.01 |      | 150.0 |         |
|           |  | Z | 5.65 | 66.87 | 16.12 |      | 150.0 |         |



|           |   |   |      |        |       |      |       |         |
|-----------|---|---|------|--------|-------|------|-------|---------|
| 10558-AAC | IEEE 802.11ac WiFi (160MHz, MCS4, 99pc duty cycle)              | X | 5.94 | 67.30  | 16.54 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.66 | 66.60  | 16.01 |      | 150.0 |         |
|           |   | Z | 5.62 | 66.81  | 16.11 |      | 150.0 |         |
| 10560-AAC | IEEE 802.11ac WiFi (160MHz, MCS6, 99pc duty cycle)              | X | 5.95 | 67.19  | 16.52 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.69 | 66.58  | 16.04 |      | 150.0 |         |
|           |   | Z | 5.66 | 66.81  | 16.15 |      | 150.0 |         |
| 10561-AAC | IEEE 802.11ac WiFi (160MHz, MCS7, 99pc duty cycle)              | X | 5.88 | 67.20  | 16.56 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.63 | 66.58  | 16.07 |      | 150.0 |         |
|           |   | Z | 5.59 | 66.79  | 16.16 |      | 150.0 |         |
| 10562-AAC | IEEE 802.11ac WiFi (160MHz, MCS8, 99pc duty cycle)              | X | 5.94 | 67.39  | 16.65 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.66 | 66.69  | 16.12 |      | 150.0 |         |
|           |   | Z | 5.63 | 66.91  | 16.22 |      | 150.0 |         |
| 10563-AAC | IEEE 802.11ac WiFi (160MHz, MCS9, 99pc duty cycle)              | X | 6.04 | 67.34  | 16.59 | 0.00 | 150.0 | ± 9.6 % |
|           |   | Y | 5.79 | 66.75  | 16.12 |      | 150.0 |         |
|           |   | Z | 5.78 | 67.06  | 16.27 |      | 150.0 |         |
| 10564-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 9 Mbps, 99pc duty cycle)  | X | 4.77 | 67.10  | 16.65 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.50 | 66.55  | 16.05 |      | 150.0 |         |
|           |   | Z | 4.47 | 66.98  | 16.22 |      | 150.0 |         |
| 10565-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 12 Mbps, 99pc duty cycle) | X | 4.97 | 67.50  | 16.95 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.68 | 66.96  | 16.38 |      | 150.0 |         |
|           |   | Z | 4.64 | 67.39  | 16.55 |      | 150.0 |         |
| 10566-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 18 Mbps, 99pc duty cycle) | X | 4.81 | 67.34  | 16.77 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.52 | 66.74  | 16.16 |      | 150.0 |         |
|           |   | Z | 4.48 | 67.17  | 16.33 |      | 150.0 |         |
| 10567-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 24 Mbps, 99pc duty cycle) | X | 4.85 | 67.74  | 17.14 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.56 | 67.16  | 16.55 |      | 150.0 |         |
|           |   | Z | 4.53 | 67.58  | 16.73 |      | 150.0 |         |
| 10568-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 36 Mbps, 99pc duty cycle) | X | 4.71 | 67.11  | 16.54 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.40 | 66.39  | 15.84 |      | 150.0 |         |
|           |   | Z | 4.34 | 66.71  | 15.95 |      | 150.0 |         |
| 10569-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 48 Mbps, 99pc duty cycle) | X | 4.83 | 67.94  | 17.27 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.55 | 67.43  | 16.72 |      | 150.0 |         |
|           |   | Z | 4.53 | 67.91  | 16.92 |      | 150.0 |         |
| 10570-AAA | IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 54 Mbps, 99pc duty cycle) | X | 4.84 | 67.74  | 17.16 | 0.46 | 150.0 | ± 9.6 % |
|           |   | Y | 4.54 | 67.18  | 16.58 |      | 150.0 |         |
|           |   | Z | 4.50 | 67.60  | 16.76 |      | 150.0 |         |
| 10571-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 1 Mbps, 90pc duty cycle)       | X | 1.17 | 65.10  | 16.50 | 0.46 | 130.0 | ± 9.6 % |
|           |   | Y | 0.97 | 62.53  | 14.02 |      | 130.0 |         |
|           |   | Z | 1.05 | 63.59  | 14.78 |      | 130.0 |         |
| 10572-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 2 Mbps, 90pc duty cycle)       | X | 1.18 | 65.74  | 16.92 | 0.46 | 130.0 | ± 9.6 % |
|           |   | Y | 0.97 | 62.95  | 14.31 |      | 130.0 |         |
|           |   | Z | 1.06 | 64.07  | 15.11 |      | 130.0 |         |
| 10573-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 5.5 Mbps, 90pc duty cycle)     | X | 5.34 | 108.13 | 32.25 | 0.46 | 130.0 | ± 9.6 % |
|           |   | Y | 0.69 | 70.54  | 16.41 |      | 130.0 |         |
|           |   | Z | 0.98 | 75.87  | 19.68 |      | 130.0 |         |
| 10574-AAA | IEEE 802.11b WiFi 2.4 GHz (DSSS, 11 Mbps, 90pc duty cycle)      | X | 1.34 | 72.87  | 20.71 | 0.46 | 130.0 | ± 9.6 % |
|           |   | Y | 0.93 | 66.58  | 16.31 |      | 130.0 |         |
|           |   | Z | 1.06 | 68.52  | 17.62 |      | 130.0 |         |