1.4

Connection Status Screen

This screen displays:

The connection name

The remote device's name

The connection status: Connected/Not Connected

The length of time the connection has been active

Activity information:

The amount of data sent

The amount of data received.

A graphic signal strength indicator.



Network sharing setting for WinCE

Explore Bluetooth device in your range

1. You can check all the available Bluetooth devices by using **"Connection Wizard"**. To start **"Connection wizard"**, please tap the **"star B"** icon at bottom bar of the **"Bluetooth Manager"**.

2	Bluetooth Manager	1:52p	(ok)
*	Bluetooth My Shortcuts		

Connecti wizard	.on			V ca exch	ird ange	
My Shortcuts	Acti	e Co	nn	octions		
New Tools V	iew		J=			3 -

2. There are many connection types to choose from in the **"Connection Wizard"**. The first connection type explores all available Bluetooth devices within the Bluetooth connectivity range. Other connection types explores specific services in the Bluetooth device, e.g. Dial-Up, Information Synchronization (ActiveSync), File transfer.. etc. Please click **"Explore a Bluetooth device"** then click **"Next"**.



3. Follow the **"Connection Wizard"**, tap the device selection box in the middle of the screen, it will jump to the next page.

Ð	Connection Wizard	1:55p 🛞
*	Bluetooth Connect Explore a Bluetooth dev	t ion Wizard ice
De	vice:	
(Source selecters of the select of the sel	d> device
— <mark>Ho</mark> To seli cho	w to use this screen — select a device, tap inside ection box above. After the pose a device.	the device e list appears,
Tap the wit 'Ca	'Next' to continue or 'Back previous screen. To exit thout completing the conner ncel'.	< to return to his wizard ction, tap
	Cancel Back	Next
		E

4. All the Bluetooth enabled devices within the discoverable range will be shown.

In this example we will select the access point icon "R_8001d5[172.18...".



5. All the available services for this device are shown as below. Select the service that you'd like to use and create a connection shortcut for this device, then tap **"Next"** to the next step.

🋃 Conn	ection Wizard	5:19p			
Blu Exp	Jetooth Connect plore a Bluetooth dev	tion Wizard			
E annia	R_8001d5 [172.]	18.3.2]			
Se LAN	Access Using PPP up Networking				
Please select the service(s) offered by this device you would like to create connection shortcuts for.					
Use a	y a secure, encrypted (connection			
🕄 Canc	el 🔷 🏟 Bacl	k Next 🗳			
		■			

8. Tap **"Finish"** to create a shortcut to the Access Point on the Bluetooth manager.



Finish 裬
₩

9. If you want to use this service, double-tap the icon, or tap-and-hold the connection icon and select "Connect" from the menu. Then you can access the Internet.



My Shortcuts	Active Connections	
New Tools V	iew 🥙 🖭	₩

Note: Consult the MIS personnel in your company for proxy setting if necessary. For setting up the Proxy to surf the Internet via a Bluetooth Access Point:

1. Click on "Start" button, click "Settings", and "Connections" tab. Click on the "Connections" icon.

2. Change the "My network card connects to:" drop-down list to "Work", change the "When needed, automatically connect to Work using these settings:" drop-down list to "Work Settings", and click "Modify".

🍠 Se	tings 🛛 📢 10:04 🐽
Conne	tions
1	When needed, automatically connect to The Internet using these settings:
_	Internet Settings 🛛 👻
	Modify Connect
-0	When needed, automatically connect to Work using these settings:
	Work Settings 🗾 👻
	Modify Connect
8_	My network card connects to:
т.	Work 👻
Connect	ons Dialing Locations

3. Click on the "Proxy Settings" tab, and select both checkboxes, then enter the Proxy IP address obtained from your MIS personnel.

🎊 Settings	◀€ 10:04	•
Work Settings		

This network connects to the Internet

This network uses a proxy server to connect to the Internet

Proxy server:

172.18.0.11	

Advanced...

Ger	hei	ral		Mo	der	n	V	PN] Р	rc	ху	Se	tt	ing	js 🛛			
123	1		2	3	4	ł	5	6	7	'	8	9		0	-	=	ŀ	÷
Tat	2	q	۷	٧	е	ľ	·	t	y.		u	İ	1	D	р] []
CA	Ρ	а		s	d		f	g	h		j	k		T	;		•	
Shi	ft		Z	х	0	:	۷	b	1	ı	m		,			/	4	
Ctl	á	iü	ŀ	•	١								,	۶I	1	+		→
																₽	ġ	•

File transfer setting for WinCE

File transfer service lets you transfer pictures, documents or music files to other Bluetooth devices. Starting file transfer by using "Connection wizard" from Bluetooth manager. 1. At "Connection wizard", tap "Browse files on a remote device", then tap "Next".



3. Then select a device that you want to transfer the file(s) to.

🎊 Connection Wizard	∢ € 1	2:33 🐽	8 7	Connectior	Wizard	4 € 12:37	
Bluetooth Browser Please select a device:			*	Bluetoo Browse file	th Connec s on a remo	ction Wizard Ite device	
S				J 1800T			
1800T			- 5h	Create a sho Connection Files on 180	i tion ortcut for thi name: 0T ecure, encry	is connection pted connection]
			— Re You dev Tap	ady to con are now rea vice and start) 'Finish' to ini	nect dy to conne sending and tiate the cor	ect to the selected d receiving files! nnection.	
Computers	•	Cancel	0	Cancel	🔷 Bac	ck 🛛 Finish ờ	
View 🐵							*

4. Follow the instructions to complete the connection setting, and now you can transfer files between the two devices.

🎊 Bluetooth File Explore: 📢 12:38	@
1800T -	

Local Folder: \My Documents	
File Tools	

Change the Remote Device Folder

To move down in the directory structure of the remote device, tap the new folder in the main portion of the Bluetooth File Explorer window.

To move up in the directory structure of the remote device, tap the down-arrow to the right of the currently selected folder and select the new folder from the drop-down list. File Menu

All of the following instructions in the subsections assume that there is an open File Transfer connection with a remote device.

Send a File to the Remote Device

To send a file to the remote device, from the File menu, tap Send a File to display the Open screen.

The options on the Open screen are:

* Folder-tap the down-arrow and select the folder that contains the file to be sent.

* Type-the only option is "All Files (*. *)"

* A list of files in the selected folder; tap the file to be sent

* Cancel button-aborts the Send a File operation.

The selected file is sent automatically when it is tapped, without further intervention, and the Bluetooth File Explorer main screen reappears.

Create a Folder on the Remote Device

To create a folder on the remote device, navigate to the folder in which the new folder will be placed, and then, from the File menu, tap Create a Folder. Enter a name for the new folder while the default name (New Folder) is highlighted.

Get a File From the Remote Device

To get a file from the remote device:

1. Navigate to the folder on the remote device that contains the file

2. Tap the desired file to highlight it

3. From the File menu, tap Get.

The file is copied to the local folder listed in the Local Folder field near the top of the screen. This operation can also be performed using the tap-and-hold technique: tap-and-hold the desired file and select Get from the pop-up menu.

27	Bluetooth File Ex	kplorer 📢	3:23 🐽
POF	RTATIL-MIO +		
B C	liff in Clouds.jpg	07/26/	122K
💕 D)iagonal Sand	07/26/	126K
📑 Io	ceberg.jpg	07/26/	177K
🛃 S	ample.jpg	07/26/	9.66K
🔊 T	"humbs.db	07/26/	19.0K

Local Folder: \My Documents	
File Tools	₩ *

Delete a File on the Remote Device

To delete a file on the remote device: tap the file to be deleted to highlight it, then, from the File menu, tap delete. Tap OK in the confirmation dialog box.

This operation can also be performed using the tap-and-hold technique: tap-and-hold the desired file and select Delete from the pop-up menu. Tap OK in the confirmation dialog box.

🎊 Bluetooth File Ex	/ Bluetooth File Explorer 📢 3:25 🐽			
Portatil-Mio 🔻				
🛃 Cliff in Clouds.jpg	07/26/	122K		
🛃 Diagonal Sand	07/26/	126K		
💕 Iceberg.jpg	07/26/	177K		
Sample.jpg	07/26/	9.66K		
🔊 Thumbs.db	07/26/	19.0K		

Get]
Rename	
Delete	
Send a File	
Create a Folder	nents
File Tools	

Dial-up networking setting for WinCE

Dial-up Networking allows you to connect to a remote computer that is connected to a phone line. Once connected, you can browse the Internet, check your email, etc. The remote Bluetooth device that will provide the Dial-up Networking service must have access to a telephone system (either a physical or cellular connection).

Devices that might provide the Dial-up Networking service include:

* Bluetooth-enabled cellular telephones

- * Bluetooth-enabled desktop computers that are attached to a telephone system
- * Bluetooth modems.

The remote computer to which you are connecting must also be attached to the phone system and capable of answering a call.

1. To begin dial-up networking setup for using a cell phone, please tap "Partner with a cell phone" from Bluetooth connection wizard, and click "Next".

NOTE: For some mobile phones, e.g. Ericsson, we recommend you use the "Explore a Bluetooth device" option rather than the "Partner with a cell phone" option when pairing.

<i>8</i> 9 c	Connection Wizard 🛛 📢 11:03	
*	Bluetooth Connection Wizard	
Ŵ	Partner with a cell phone Establish a partnership with a cell phone and setup the Bluetooth services it offers.	•
0	ActiveSync via Bluetooth Setup an ActiveSync partnership with a Bluetooth enabled computer.	
Ó	Browse files on a remote device Connect to a remote Bluetooth device to list, send and receive files.	=
		•
O C	ancel 🛛 Next 💠	
		•

2. And prepare your cell phone in Bluetooth function enable mode, (To enable your cell phone's Bluetooth function, please refer to the user's guide of your cell phone) and tap "Next" to continue.

🌮 Connection Wizard 💦 📢 🚯	🍠 Connection Wizard 💦 📢 6:44 🐽
Bluetooth Connection Wizard Partner with a cell phone	Bluetooth Connection Wizard Partner with a cell phone
Prepare your phone Step 1 - Phone selection	Prepare your phone Step 2 - Preparing Bluetooth
This wizard helps you to explore your Bluetooth enabled cell phone and to create connection shortcuts for the services it has to	Before you can utilize the services your phone offers, you have to enable Bluetooth on the phone and "pair" the devices.
Orier. Phone selection: <unknown, listed="" not="" or="" phone=""> 🔻</unknown,>	In order to explore the services your phone has to offer, it needs to be "Discoverable" and "Pairable". Please refer to your phone's manual to find out how to enable these features.
Please select your Bluetooth enabled phone from the list above and tap 'Next' to continue.	Once the phone is "Discoverable" and "Pairable", press "Next" to continue.
Cancel Back Next	Cancel Back Next
E	₩

3. After searching, the Bluetooth manager will display the cell phones in range. Double-tap the cell phone icon that you wish to connect to and continue to the next step to pair with this cell phone.

Connection Wizard	📢 6:45 🛛 🚯	<i>ß</i> Connection Wizard 🛛 📢 10:15 🚳
Bluetooth Browser Please Select a device:		Bluetooth Connection Wizard Partner with a cell phone
Nokia 8910		Device: Nokia 8910 Phone 00:02:EE:38:68:8B
		 How to use this screen Select the phone prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list.
		Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap
Phones View ©		Cancel Back Next

4. Please key in a passkey when prompted, and key in the same passkey on the cell phone to complete the pairing process.

🎢 Connection Wizard 👘 📢 10:15 🐽
Bluetooth Connection Wizard Partner with a cell phone
🗯 Nokia 8910
Passkey:
 How to use this screen Please enter a passkey, which will be used to authenticate the connection and to encrypt data transferred.
The passkey needs to be numbers only (no letters), as you will have to enter it again on your cell phone.
Check your phone after you hit 'Next' and re- enter the passkey when prompted.
Cancel Back Next
► [
5. Tap "Finish" to complete this step
🎢 Connection Wizard 🛛 📢 10:18 🐠
Connection Wizard Image: Connection Wizard Bluetooth Connection Wizard Partner with a cell phone
Connection Wizard
Connection Wizard ♦ Bluetooth Connection Wizard Partner with a cell phone Nokia 8910 − Shortcuts created
Connection Wizard
Connection Wizard ✓€ 10:18 With a cell phone With a cell phone With a cell phone With a cell phone With a cell phone Nokia 8910 Shortcuts created Shortcuts created Connection shortcut(s) have been created for every supported service your phone offers. To connect: From the Bluetooth Manager "My Connections" screen, double-tap the connection. Or tap-and-hold the connection icon and select 'Connect' from the menu.
Connection Wizard ✓€ 10:18 Image: Solution Wizard Partner with a cell phone Image: Solution Partner With a cell phone Connection shortcut(s) have been created for every supported service your phone offers. To connect: From the Bluetooth Manager "My Connections" screen, double-tap the connection. Or tap-and-hold the connection icon and select 'Connect' from the menu. Cancel Back Finish

Create a Bluetooth Dial-up connection

1. Create a connection to the device that will provide telephone access.

2. From the Bluetooth Manager, My Connections tab, tap-and-hold the Dial-up Networking connection shortcut, and then select Connect from the pop-up menu.

3. On the first Bluetooth: New Dial-up Connection screen, double-tap New Connection.



- 4. On the second Bluetooth: New Dial-up Connection screen:
- a) Enter a name for the connection
- b) If dialing outside of the default country setting, enter the country code
- c) If dialing outside of the default area code setting, enter the area code
- d) Enter the phone number to be dialed.
- 5. Tap OK

Please follow the Dial-Up connection procedures above to complete the Dial-Up settings. Refer to the PocketPC documentation for assistance.

After the connection is active, open a web browser on the PocketPC.

Alternatively, you could set up the connection the traditional way, if the above method did not work for you.

1. Click on "Start" button on the top of the menu bar.

2. Select "Settings", click on the "Connections" tab.

ह Settings		◀€ 10:23 🚫
20		1200 B
AvantGo Connect	Beam	Connections
13 Network		
Adapters		
Personal System		tions

14

3. Click on the "Connections" icon. On the top "Internet Settings", click "Modify".

S. CIIC	K OH THE CONNECTIONS ICON. OH THE
🔏 Se	ttings
Conne	ctions
1	When needed, automatically connect to The Internet using these settings:
	Internet Settings 👻
	Modify Connect
10	When needed, automatically connect to Work using these settings:
	Internet Settings 🛛 👻
	Modify Connect
8-	My network card connects to:
ц	Work 🗾 🔻
Connect	tions Dialing Locations
	· · · · · · · · · · · · · · · · · · ·
4. Clic	k "New" to start a new connection.
🍠 Se	ttings
Intern	net Settings
Create existing	a connection, or tap and hold on an g connection and select a desired action.
Name	e Number
New.	
1	
21 201	1.0
When a	dialing: Automatically dial the best number
General	Modem
	▲

5. Give the new connection a name, select "Bluetooth Dialup Modem", and set the baud rate at "115200".

🛃 Settings	4 € 10:34
BT GPRS Connection	n j
Enter a name for the c	onnection:
BT GPRS Connectio	n
Select a modem:	- 10
Bluetooth Dialup Mo	odem 👻
Baud rate: 115200 ▼	Advanced
Cancel	Back Next

₩|•

6. Click "Advanced...", change the "Parity" to "Even", "Stop Bits" to "1", and "Flow Control" to "None".

ह Setting	5	- {€ 10:	27 🐽
Advanced			
Connection	prefere	ences	
Data Bi	ts:	8	-
Paril	ty:	Even	•
Stop Bi	ts:	1	•
Flow Control:		None	-
Terminal			
Use term	inal befor inal after ling comn	re connecting connecting hands manually	
Port Settings	TCP/IP	Name Servers	
			=

7. Click on the "TCP/IP" tab, and make sure both "Use software compression" and "Use IP header compression" checkboxes are selected.

💱 Settings	∢ € 10:28	•
Advanced		
Use server-assigned	IP address	
Use specific IP addre	SS	
2 4 3]	
Use Slip		
Use software compre	ession	
Use IP header compr	ession	



8. Click on the "Name Servers" tab. Some GPRS service may require you to enter the DNS addresses, please check with your GPRS ISP before making the changes. Otherwise, leave the radio button selected at "Use server-assigned addresses" and click "OK".

Settings	∢ € 10:30 🐽
Advanced	
Use server	-assigned addresses c server address
DNS:	145.93.192.1
Alt DNS:	145.93.1.1
WINS:	0.0.0.0
Alt WINS:	0.0.0.0

Port Settings	TCP/IP	Name Servers	
			=

9. Click "Next", enter the phone number for your GPRS connection. Then click "Next".

ह Settings	┥ € 10:31	
BT GPRS Connection	1	
Country code:		
Area code:	_	
Phone number: *99#		
	20	
Cancel	Back Next	
Curren	Duck	
	- E	
10. Leave the set	tings as it is in th	is page, and click "Finish".
ह Settings	∢ € 10:32	
BT GPRS Connection		
Cancel call if not cor	nected within	
seconds		
Wait for dial tone be	fore dialing	
Wait for credit card tone	: 0 seconds	
Extra dial-string modem		
Cancol	Pack Einich	
Lancei	Dack	

11. Click "OK", and in the Connections page, click on the "Dialing Locations" tab. a) Change the "Location:" to "Home".

b) Delete the entries in "Area code:" and "Country code:".

c) Select the "Disable call waiting;" checkbox.

d) Enter the phone number of your GPRS service again. Then click on "Dialing Patterns...".

🖅 Settings		∢ € 10:33 0	
Connecti	ons		
Location:	Home	÷	
	New	Remove	
Local Set	tings	115	
Area	code:) 🖲 Tone dialing	
Count	ry code:	O Pulse dialing	
🗸 Disable	e call waiting;	dial *99# ▼	
	Di	ialing Patterns	



12. Change all entries to "G", assuming you are making a local GPRS phone call. Then click "OK".

87	Settings	∢ € 10:34	•
Dia	ling Patterns		
For	local calls, dial:		
3			
For	long distance calls, dial:		
G			
For	international calls, dial:		
G			
(E,e nun	e = country code; F,f = a nber)	rea code; G,g	=

Edit 🔤 🔺

13. Now you have set up a GPRS Bluetooth Connection. Click the "Connect" button and click "OK" without entering any user name or password, within a few seconds you should be connected to the Internet.

14. Open "Internet Explorer" and start surfing the net.

Serial port setting for WinCE

The use of a Bluetooth wireless serial port connection is identical to the use of a physical cable serial port connection between two devices.

As with a physical connection, the application that will use the connection must be configured to use the correct serial port.

To determine the COM port assigned to the Bluetooth serial port:

1. From the Today Screen, tap the Bluetooth icon to open the Bluetooth Control Panel.

2. Use the scroll arrows at the bottom-right of the screen to expose the Serial Port tab, and then select the Serial Port tab. The Outbound COM Port is listed in the lower portion of the screen. Configure the application that will use the Bluetooth Serial Port to send data to this port.

ActiveSync setting for WinCE

1. To establish the ActiveSync connection on a PDA, please tap "ActiveSync via Bluetooth" from the Bluetooth connection wizard, and click "Next".



2. Make sure your computer is capable of accessing your PDA, and determine which "COM" port number (For example "COM6") is used for incoming Bluetooth connections (refer to ActiveSync setting for Windows section). You will need this information later. Tap "Next" to next step.

Connection Wizard ♦ 12:17 ■ Bluetooth Connection Wizard ActiveSync via Bluetooth ■ Prepare the computer Step 1 - Bluetooth setup

Step 1 - Bluetooth setup To use ActiveSync via Bluetooth, your computer has to be able to access incoming Serial Port Profile connections.

Determine which serial or "COM" port number is used for incoming Bluetooth connections. You will need this port number later. For example "COM4".

Consult your computer's Bluetooth software manual if necessary.

🕄 Cancel	💠 Back	Next 💠
		E

3. Make sure your PC side's ActiveSync "Connection Settings" is using the right COM port, click "Next".

Image: Connection Wizard ActiveSync via Bluetooth Image: Connection Wizard ActiveSync via Bluetooth Image: Connection Sync via Bluetooth Image: Connection Settings" from the "File" menu. Note: If the "Get Connected" wizard appears, connect your handheld to the computer via the cradle or a cable once and try again. In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1. Image: Connection Wizard Image: Connection Wizard Image: Conned the screen Tm	
Subscription Bluetooth Connection Wizard ActiveSync via Bluetooth Step 2 - ActiveSync setup Open ActiveSync on the computer and select "connection Settings" from the "File" menu. Note: If the "Get Connected" wizard appears, connect your handheld to the computer via the cradle or a cable once and try again. In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1. Cancel Back Next (*) Connection Wizard ActiveSync via Bluetooth Discourd (*) 12:20 Connection Wizard Connection Wizard ActiveSync via Bluetooth Discourd (*) 12:20 Discourd Wizard (*) 12:20 Discourd (*) 12:20 Discourd Wizard (*) 12:20<	🎥 Connection Wizard
Prepare the computer Step 2 - ActiveSync setup Open ActiveSync on the computer and select "connection Settings" from the "File" menu. Note: If the "Get Connected" wizard appears, connect your handheld to the computer via the cradle or a cable once and try again. In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1. Image: Cancel Back Next Image: Connection Wizard Methods assigned in Step 1. Image: Cancel Back Next Image: Connection Wizard Methods assigned in Step 1. Image: Connection Wizard Image: Connection Wizard Methods assigned activeSync via Bluetooth Image: Connection Wizard Image: Connection Wizard Methods activeSync via Bluetooth Image: Connection Wizard Image: Connection Wizard Methods activeSync via Bluetooth Image: Connection Wizard Image: Connection Wizard Methods activeSync via Bluetooth Image: Connection Wizard Image: Connection Wizard Methods activeSync via Bluetooth Image: Connection Settings connection Wizard Methods activeSync via Bluetooth Image: Connection Settings connection Settings connection Settings connection Set activeSet and set as a set and connection Set activeSet and connection set as a set se	Bluetooth Connection Wizard ActiveSync via Bluetooth
Open ActiveSync on the computer and select "Connection Settings" from the "File" menu. Note: If the "Get Connected" wizard appears, connect your handheld to the computer via the cradle or a cable once and try again. In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1. Image: Cancel Image: Connection Vizard Image: Connection Wizard Image: Connection Wizard Image: Connection Wizard Connection Wizard ActiveSync via Bluetooth Image: Connection Settings creen Image: Connection Step 1 Image: Connection Wizard Image: Connection Wizard ActiveSync via Bluetooth Image: Connection Settings creen Image: Connection Settings creen Image: Connection Settings creen Image: Connection Wizard Image: Connection Wizard ActiveSync via Bluetooth Image: Connection Settings creen Image: Connection Setting connection Setings Image: Connection Settings Image: Connection Setting: Connection Wizard ActiveSync via Bluetooth Image: Connection Settings Image: Connection Settings Image: Connection Settings Image: Connection Seting Connection Seting image: Connection Seti	Step 2 - ActiveSync setup
Note: If the "Get Connected" wizard appears, connect your handheld to the computer via the cradle or a cable once and try again. In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1. Connection Wizard Section Section Connection Wizer A. Tap screeen and choose a device on the list. Connection Wizard Section Wizer A. Tap screeen and choose a device on the list. Connection Wizard Section Wizer ActiveSync via Bluetooth Device: Connect consected Tap here to choose a device Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel Active Next Section	Open ActiveSync on the computer and select "Connection Settings" from the "File" menu.
In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1. Cancel ● Back Next ●	Note: If the "Get Connected" wizard appears, connect your handheld to the computer via the cradle or a cable once and try again.
 Cancel	In the Connection Settings screen, enable "Allow serial cable or infrared connection to this COM port" and select the COM port assigned in Step 1.
Image: A. Tap screen and choose a device on the list. Image: Connection Wizard Connection Wizard ActiveSync via Bluetooth Image: Connection Wizar	😮 Cancel 🛛 🧔 Back Next 🖏
 4. Tap screen and choose a device on the list. Connection Wizard <≤ 12:20 Bluetooth Connection Wizard ActiveSync via Bluetooth Device: No device selected> Tap here to choose a device How to use this screen Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cance'. Cancel Active Select 	
Connection Wizard 4 € 1220 Image: Provide the selected and the selected and the selected and the selected and the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cance'. Image: Provide the select of the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cance'.	4. Tap screen and choose a device on the list.
Bluetooth Connection Wizard ActiveSync via Bluetooth Device: Image: Constant of the selected in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel'. Image: Concel Image: Cancel	Lonnection Wizard
Oevice: Image: Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel'. Image: Cancel Image: Amage:	ActiveSync via Bluetooth
No device selected> Tap here to choose a device How to use this screen Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel'. Cancel Pack	Device:
How to use this screen Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel'. Cancel Pack	Solution of the selected se
Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list. Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel'. Cancel Cancel Pack Next	- How to use this screen
Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap 'Cancel'. Cancel Pack Next	Select the computer prepared in the previous steps of the wizard by tapping the selection box above and locating it in the list.
😮 Cancel 🛛 🗇 Back Next 💠	Tap 'Next' to continue or 'Back' to return to the previous screen. To exit this wizard without completing the connection, tap
	'Cancel'.
<u>▲</u>	Cancel Cancel Cancel

5. Select a device you want to use.

🎊 Connection Wizard 🛛 📢 12:22 🐽	
Bluetooth Browser	
	-
1800T HPXE2 IVT NAP~	
Z	
Computers Cancel	
View ②	
6. Follow the instructions to create	a shortcut for the Bluetooth ActiveSync connection
🎊 Connection Wizard 🛛 📢 12:23	👔 🎊 Bluetooth Passkey 🛛 📢 12:24 💿
Bluetooth Connection Wizard ActiveSync via Bluetooth	Bluetooth Authentication
1800T	Device: 1800T
- Shortcut creation	– Passkev:
Create a shortcut for this connection	
Connection name:	Cancel
ActiveSync with 1800T	- How to use this screen
Use a secure, encrypted connection	establishes a secret key that is used in
- Ready to connect	 all future connections to authenticate
the device above! Tap 'Finish' to initiate the	uevice identity and encrypt data.
connection.	Enter your passkey in the field above
🞖 Cancel 🛛 💠 Back 🛛 Finish ờ	relationship with this device.
	· 🔺



7. After the shortcut is created, you can see your device is connected with your computer. You can tap "Active Connections" to check the signal strength.



My Shortcuts	Active Connections	
New Tools	3 💷	

Hosting a Personal Area Network

To host a personal network, go to the Bluetooth Manager, choose New > Connect > Join a personal network > Next. The following screen will be shown:



Choose Host a personal network and tap Next. You will then be shown the following screen, which allows you to "bring in" one or more guests, if desired. This step is optional, since guests can join later on as long as the personal network is active (more details in the following section).

🎊 Bluetooth Network Mar 🍕 1:26 🛛 🐽
Bluetooth Personal Network Manager
Connected devices:
Add Remove
How to use this screen
Tap "Add" to connect other devices to your
delete to disconnect it.
Devices may also join this personal network
at any time.

Adding devices to a personal network.

Joining a Personal Area Network

BTW-CE makes it easy to join an existing personal network, hosted by another Bluetooth device (PocketPC, desktop, etc.) From the Bluetooth Manager, choose New > Connect > Join a personal network > Next, but choose Join a personal network this time. The Bluetooth Browser will be shown for you to select the device that is hosting the personal

network. After selecting the host, choose Next. A connection will then be established between your PocketPC and the host over the personal network.

At this moment, you might be prompted to enter IP network settings ; if this is the case, choose "Use server-assigned IP address" and tap OK.

The following warning may also be shown to you. As instructed, change the name of your device and tap OK.



Since the network is established via Bluetooth, the network host's service availability, authorization and/or authentication security settings are in effect and may prevent you from joining the network.

🎊 Start	∢ € 1:02 🐽		
Bluetooth PAN User Driver			
Use server-assigned IP address			
🔿 Use specific IP address			
IP address:,			
Subnet mask;,			
Default gateway:,			
IP Address Name Servers 123 1 2 3 4 5 6 7 8 Tab q w e r t y u CAP a s d f g h j Shift z x c v b n m Ctl áŭ ` \	9 D - = + i o p [] k l ; ' , . / +		

PAN network settings.

After joining the personal network, you can use any application that requires an underlying network connection. For instance, you can view a remote folder via the File Explorer by choosing Open and entering a remote, accessible device path.



Browsing files on a remote device (via the PocketPC File Explorer) after joining a personal network.

5

Chapter5

How to pair with my mobile phone?

How to pair with Nokia 6310

(1). To activate Bluetooth on your Nokia 6310, press "Menu", select "Bluetooth" and "On".
(2). From your notebook or PDA, begin a Bluetooth device search. A mobile phone icon will show up in the right pane of the Bluetooth software window with the name of your Nokia 6310.

(3). Double click the mobile phone icon to discover the services it provides. You should see COM, Dial-up networking, Fax, or more, depending on the model of your Nokia mobile phone.

. (4). From your Nokia 6310, select "Search for Bluetooth accessories", the phone starts searching for devices and accessories.

(5). Scroll to the device you want and press "Select".

(6). If devices have not been paired, the user is asked to enter the passcode of the desired device. (The Nokia Bluetooth Passcode is a 1 to 16 character-long numeric code of your choice)

(7). A Passkey dialog box will pop up on your notebook or PDA, type in the same passkey you've entered on your mobile to complete pairing.

(8). If pairing was successful, a "Paired with ***" message box will pop up on your mobile phone. You should also see a tick on the side of the mobile phone icon in your notebook or PDA.

(9). You are now able to use the services of your mobile phone.

How to pair with Nokia 8910

(1). To activate Bluetooth on your Nokia 8910, press "Menu", select "Bluetooth" and "On".

(2). From your notebook or PDA, begin a Bluetooth device search for your Nokia 8910.

(3). A mobile phone icon will show up in the right pane of the Bluetooth software window with the name of your Nokia 8910.

(4). Double click the mobile phone icon to discover the services it provides. You should see COM, Dial-up networking, Fax, or more, depending on the model of your Nokia mobile phone.

(5). From your notebook or PDA, double click on the service you wish to use and it will trigger a dialog box "Connect with ***?" on your mobile phone. (where *** is the name of your notebook or PDA)

(6). Push the "Accept" button, and enter a passcode, e.g. 55 and push the OK button. (The Nokia Bluetooth Passcode is a 1 to 16 character-long numeric code of your choice)

(7). A Passkey dialog box will pop up on your notebook or PDA, type in the same passkey you've entered on your mobile.

(8). If pairing was successful, a "Paired with ***" message box will pop up on your mobile phone. You should also see a tick on the side of the mobile phone icon in your notebook or PDA.

(9). You are now able to use the services of your mobile phone.

For further Bluetooth functions on your Nokia mobile phone, please refer to Nokia's User's Guide

How to pair with Ericsson T39m

(1). On your mobile phone, push the "Menu" button, scroll to "Extras", "Yes", "Bluetooth", "Yes", "Discoverable", "Yes" to make your Ericsson mobile phone detectable by other Bluetooth devices.

(2). "Discoverable for 3 minutes" message box will pop up.

(3). From your notebook or PDA, begin a Bluetooth device search for your Ericsson T39.(4). A mobile phone icon will show up in the right pane of the Bluetooth software window with the name of your Ericsson T39.

(5). Double click the mobile phone to discover the services it provides. You should see Serial Port, Dial-up Networking, Fax, and more, depending on the model of your mobile phone.

. (6). From your mobile phone, scroll to "Extras", "Yes", "Bluetooth", "Yes", "Discover", "Yes". A list of discovered devices appears.

(7). You can now choose the Bluetooth device you wish to connect to, then select "Add to paired", the mobile phone will prompt you for a "Passkey". Type in a passkey, e.g. 55 and push "Yes".

(8). A Passkey dialog box will pop up on your notebook or PDA, type in the same passkey you've entered on your mobile. A "Pairing Succeeded" message box will pop up.

(9). On your mobile phone, enter a name for your notebook or PDA, or push the Yes button to accept the default Name tag.

(10). If the pairing process is successful, you should see a tick on the side of the mobile phone icon on your notebook or PDA.

(11). You should now be able to use the services of your mobile phone.

For further Bluetooth functions on your Ericsson mobile phone, please refer to Ericsson's User's Guide

How to pair with Ericsson T68

(1). On your mobile phone, scroll to "Connect", "Yes", "Bluetooth", "Yes", "Discoverable", "Yes" to make your Ericsson mobile phone detectable by other Bluetooth devices.

(2). "Discoverable for 3 minutes" message box will pop up.

(3). From your notebook or PDA, begin a Bluetooth device search for your Ericsson T68.(4). A mobile phone icon will show up in the right pane of the Bluetooth software window with the name of your Ericsson T68.

(5). Double click the mobile phone to discover the services it provides. You should see Serial Port, Dial-up Networking, Fax, and more, depending on the model of your mobile phone.

(6). From your mobile phone, scroll to "Connect", "Yes", "Bluetooth", "Yes", "Discover", "Yes". A list of discovered devices appears.

(7). You can now choose the Bluetooth device you wish to connect to, then select "Add to paired", the mobile phone will prompt you for a "Passkey". Type in a passkey, e.g. 55 and push "Yes".

(8). A Passkey dialog box will pop up on your notebook or PDA, type in the same passkey you've entered on your mobile. A "Pairing Succeeded" message box will pop up.

(9). On your mobile phone, enter a name for your notebook or PDA, or push the Yes button to accept the default Name tag.

(10). If the pairing process is successful, you should see a tick on the side of the mobile phone icon on your notebook or PDA.

(11). You should now be able to use the services of your mobile phone.

For further Bluetooth functions on your Ericsson mobile phone, please refer to Ericsson's User's Guide

How to sync with Ericsson T68 via XTNDConnectPC

(A) Assign COM port

(1) After you have installed Microsoft Outlook and XTNDConnectPC_R2A04_English, you would need to install a new modem to communicate with your mobile phone.

(2) Go into Start->Settings->Control Panel->Phone and Modem Options, under "Modems" tab, click on "Add", tick the "Do not detect my modem, I will choose from list" and click "Next".

(3) Choose Ericsson and Ericsson T68 Bluetooth (TM) Modem, then click "Next".

Add Hardware Wizard	
Install New Modem	
Select the manufacture have an installation disk	r and model of your modem. If your modem is not listed, or if you c, click Have Disk.
Manufacturer	Models
(Standard Modem Types) Ericsson Widcomm	Ericsson T68 Bluetooth (TM) Modem Ericsson T68 Cable Modem Ericsson T68 IR Modem Version: 1.23.8.1 [8/23/2001]
	< >
This driver is not digita <u>Tell me why driver signing is</u>	Ily signed! important
	<u> </u>

(4) Select and assign a COM port (e.g COM10) to the newly added Modem. Click "Next".

Install New Moder Select the port(s)	n you want to install the	e modem on.	E Contraction of the contraction
	You have sele	ected the following modem:	
	Ericsson T68	Bluetooth (TM) Modem	
	On which por	ts do you want to install it?	
dit of the			
	• Selected	ports	
	COM8 COM9		~
	COM10		
	CUM11 COM12		=
	COM13 COM14		~
	- COM14		()
		(Baals Naut)	Canaal

(5) Click "OK" to finish the set up process. Remember the port number as you will need it later.

Attached To
СОМб
COM7
COM8
COM10
properties

(B) Configure Bluetooth software

(1) Check the COM ports used by the Bluetooth software are correct.

(2) Go to Start->Settings->Control Panel->Bluetooth Configuration, on the "Local Services" tab, the COM port should be the one you have just assigned to your Ericsson phone (e.g. COM10).

(3) To change the assigned COM port, double click the "Bluetooth Serial Port" and choose the correct one from the "COM Port:" drop down list.

eneral Accessibility Dis	covery Loca	a Services Client Ap	olications Hard	ware
Select the services that this Double-click a service nan	s computer wil ne to set its se	l provide to other Blue curity, start-up options	tooth devices. and properties.	
Service Name	Startup	Secure Connection	COM Port	
Audio Gateway	Auto	Not Required		
Headset	Auto	Not Required		
PIM Synchronization	Auto	Required		
Fax File Transfer	Auto	Required		
PIM Itom Transfor	Auto	Not Required		
Dial-up Networking	Auto	Required		
Network Access	Auto	Required		
Bluetooth Serial Port	Auto	Required	COM10	
Description		Add S	erial Service	Delete
		Auu or	shal Service	Delete

(4) Check the COM port used by "Bluetooth Serial Port" in the "Client Applications" tab (e.g. COM4), remember this COM port too.

(5) To change the assigned COM port, double click the "Bluetooth Serial Port" and choose the correct one from the "COM Port:" drop down list.

neral	Accessibility	Discovery	Local Servic	es	Client Appli	cations	Hardware
pecify	how this comp	uter will acce	ess services (on oth	ier Bluetoot	h device	es.
ouble	-click an applic	ation name :	to set its secu	rity ar	nd edit its pr	opertie	3.
Appli	cation Name	Se	cure Connect	tion	COM Port		
Huma	n Interface	No	t Required	and all a contract of			
Printer	r Olatannan	No	t Required				
Audio Head	Gateway	No No	t Required				
PIMS	vnchronization	Re	auired				
Fax	•	Re	quired				
File Ti	ransfer	Re	quired				
PIM Ite	em Transfer	Re	quired				
Diai-u Netwo	p Networking ork Access	Re Re	quirea auirea				
Blueto	oth Serial Port	Re	quired		COM4		
						2	
Pro	perties			Add	d COM port		Delete COM port
							-

(C) Configure Ericsson's Phone Monitor

(1) Go to Start->Settings->Control Panel->Phone Monitor Options.



(2) Enable the COM port you have just assigned the Ericsson Bluetooth Modem (e.g. COM10). This COM port is the one that you want to use to communicate with your phone. Make sure the COM port used by "Bluetooth Serial Port" in the "Client Applications" tab (e.g. COM4) is enabled as well. Click "OK" when finished.

Phone Monito	r Option	S (×
Mobile Phones	SIM Care	ds COM Ports Advanced Setup	
COM Ports:	Y s F	'ou can stop or start Phone Monitor from earching for connected phones on specific COM orts by disabling or enabling them in the list.	
COM Port	Status	Reserved	
COM1	Enabled	No	
COM10	Enabled	No	
COM11	Disabled	No	
COM12	Disabled	No	
COM13	Disabled	No	
COM14	Disabled	No	
COM3	Disabled	No	
COM4	Enabled	No	
COM5	Enabled	No	
COM6	Disabled	No	
COM7	Disabled	No	
COM8	Disabled	No	
COM9	Disabled	No	
<u>R</u> eserve		Inreserve Disable Enable	
	<u>0</u> K	CancelApplyHelp	

(D) Configure Ericsson's Mobile Modem Settings
(1) Go to "Start->Settings->Control Panel->Ericsson Mobile Modem Settings", "Modem Settings" tab and make sure the "Modem" dropdown list has the correct modem highlighted.

👋 Ericsso	n Mobile Mode	em Settings	? 🛛
Modem Sel	ttings		
	Note that these se connection.	ettings do NOT a	fect the GPRS
_ <u>M</u> odem-			
Ericsson	T68 Bluetooth (T	M) Modem	•
Settings Pref	ior Ericsson T68 E erred connection	3luetooth (TM) M speed: (GSM Da	odem ata)
9.6	14.4	19.2	28.8 kbit/s
Bea	rer service type:		
6	Analogue	O ISDN	Default
			Version 1.00.0015
ОК	Cancel	Apply	Help

(E) Configure Ericsson's XTNDConnectPC (1) Go to Start->Programs->XTNDConnectPC->Synchronize Ericsson Phone with Outlook.

	Aveilable Deers	
		<u>S</u> ynchronize
	Connacts Calendar Calendar C Tasks	Se <u>t</u> tings
		Help
New Profile		E <u>x</u> it
book and calen	dar in Lotus Notes Micros	off Outlook
Lotus	Organizer or Symantec AC	TI?

(2) Click on "Settings", "Data Sources" tab and assign data sources to "Outlook Contacts", "Outlook Calendar", and "Outlook Tasks". Then click "OK".

General	Auto 9	Synchronize	Conflicts	Translator
Mapping	,	Filters	D	ata Sources
 Ericsson F Dutlook C Ericsson F 	Phone Cor ontacts Phone Cale	Change data s Current File/Fo	ource. Ider Name:	<u>C</u> hange
Outlook C D Ericsson F D Outlook T	alendar Phone Tas asks	??? (Mailbox -	richard)	
<				

(2) With all the set up completed, reboot your system, the Phone Monitor should prompt you to enter some more information.

Phone Connection Wizard - Welc	ome 🛛 🔀
D	Welcome to the Phone Connection Wizard. This Wizard will try to identify the model and capabilities of the connected phone.
	The information in your phone will not be modified in any way.
	Click Next to continue.
	<u> ≺ B</u> ack <u>Next ></u> <u>C</u> ancel

(3) Just follow the Wizard and when the set up process is completed, you should be able to synchronize your Ericsson T68 with your system.

Phone Connection Wizard - SIM Ca	ard Name 🛛 🕅
	What do you want to call your Subscriber Identify Module (SIM card)?
	Press Next when you are satisfied with the name.
	K Back Next > Cancel
Phone Connection Wizard - Mo	obile Phone Name
	What do you want to call your phone?
0	My T68
	Press Finish when you are satisfied with the name.
	Kack Finish Cancel

X

How to sync with Nokia 7650 via Nokia PC Suite for 7650

Note: Please make sure you are using Nokia PC Suite for 7650 and not other versions of PC Suite. You can download the program from www.nokia.com/cda1/0,1080,2015,00.html

(1) Install Nokia PC Suite for 7650.

(2) Start up Bluetooth software, note the COM port used by your system (check the "Bluetooth Serial Port" under "Local Services" tab in "Bluetooth Configuration, e.g. COM10).

General	Accessibility	Discovery	Loce	d Services	Client App	olications	Hardware	
Select t Double	Select the services that this computer will provide to other Bluetooth devices. Double-click a service name to set its security, start-up options and properties.							
Servi	ce Name	St	artup	Secure C	onnection	COM Por	t	
Audio Head: PIM S Fax File Tr PIM Ite Dial-u Netwo Blueto	Gateway set ynchronization ransfer em Transfer p Networking ork Access soth Serial Port	Au Au Au Au Au Au Au	to to to to to to to	Not Requi Not Requi Required Required Not Requi Required Required Required	red red	COM10		
Pro	perties				Add Se	erial Servic	ce Dela	ite
		OK		Can		Apply		Holp

(3) Right click mRouter on the task bar and select Properties.



(4) Tick the COM port from step (2) then click "Close". If you are still unsure of which one to select, just tick every Bluetooth COM ports first.

Select the ports you want PC Suite to use to search for devices.					
Connection	COM Port	Status		i	
Cable	COM1	Not connected			
Unknown	COM3	Not connected			
Bluetooth	COM7	Not connected			
Bluetooth	COM8	Not connected			
🔲 Bluetooth	COM9	Not connected			
✓ Bluetooth	COM10	Not connected			
Bluetooth	COM11	Not connected			
Bluetooth	COM12	Not connected			
Bluetooth	COM13	Not connected			
🔲 Bluetooth	COM14	Not connected			
Bluetooth	COM15	Not connected			
Bluetooth	COM16	Not connected			
Bluetooth	COM17	Not connected			
lnfrared		Not connected			
	-				
Close				<u>H</u> elp	

(5) Launch "PC Suite for Nokia 7650" from Start->Programs->PC Suite for Nokia 7650->PC Suite for Nokia 7650.

(5) Switch to the Bluetooth software, double click the "Bluetooth Serial Port On Nokia 7650" icon to establish serial connection with 7650.

(6) Key in the same passkey on both of your system and Nokia 7650 to complete the pairing process.

(7) Click "OK" when the following dialog box appears.



(8) Ignore the error message below and click "OK".



(9) "PC Suite for Nokia 7650" will now take over. Click "OK" when the dialog box below appears.

PC Suite - Going online					
į)	You are about to g	go online. s dialog again.			
	ОК	<u>H</u> elp			

(10) Click "OK" when the dialog box below appears.

Welcome to PC Suite for Nokia 7650						
Please enter a name for PC Suite to use the future.	in order to identify y	our Nokia 7650 in				
Name (maximum 16 characters - e.g. "Amanda's WID"):						
ОК	Cancel	Help				

(10) Select the functions you wish to use with Nokia PC Suite.



(11) Select the program you wish to Synchronize with your system, in our case we use Microsoft Outlook 2000.

Select PC Scheduler		×
	Contacts Synchronisation Select the PC scheduler you want to synchronise your handheld data with from the list below. (The scheduler must be installed on your PC, or on a network to which you have access.) Lotus Notes 4.5/4.6 Lotus Notes 5.0 Lotus Organizer 5.0 Lotus Organizer 5.0 Lotus Organizer 6.0 Lotus Organizer 97 Lotus Organizer GS/4.0 Microsoft Outlook 97/98/2000 Microsoft Schedule+	h
<u>Cancel</u>	Help	

(9) Once connected, you should see the Connected icon on the right bottom corner.

PC Suite for Nok	kia 7650 - Backup/	/Restore		
<u>File E</u> dit <u>V</u> iew <u>T</u> oo	ls <u>B</u> ackup/Restore	Help		
2 🛛 🗖 🗖				
Backup/Restore Backup/Restore Control Panel Data Import Oata Import	Last E 10/4/2002	Backup: 211:21:09 AM	Restore All data including settings Calendar data Contacts Documents Images	
Image Transfer	Backup	Restore		
Ready			Nokia 7650 (Online) Cor	inected 🍡 🏒

- (10) Now you are ready to configure, Synchronize your Nokia 7650 with your system.
- (11) To disconnect, uncheck the COM port in "Connection Properties".

C	Connection Properties					
	Select the ports	you want P	C Suite to use to search for devices.			
	Connection	COM Port	: Status			
	Cable	COM1	Not connected			
	Unknown	COM3	Not connected			
	Bluetooth	COM7	Not connected			
	Blueto	ice disco	nnected			
	Blueto	Ð	Your device has been disconnected.			
	Blueto	•	Do not show this dialog box again.			
	Blueto		OK Help	s		
	Bluetooth	COM16	Not connected			
	Bluetooth	COM17	Not connected			
	Infrared		Not connected			
	Close]		Help		

How to establish Bluetooth connection with Nokia PC Suite for Nokia 3650

Please install Bluetooth software and Nokia PC Suite for Nokia 3650 before proceeding. (1) Launch Bluetooth software program, click "Search for devices in range" in the left pane of "My Bluetooth Places" to find your Nokia 3650.



(2) Double click your Nokia 3650 to find the services it provides.

🔋 My Bluetooth Places\Entire	Bluetooth Neighborhood Wokia 🔳 🗖 🔀
<u>File E</u> dit <u>V</u> iew <u>B</u> luetooth F <u>a</u>	vorites Iools Help 🥂
🌀 Back 🔹 🕥 - 🏂 🔎	Search 🎼 Folders 🛛 🗰 🔹
Address 📓 My Bluetooth Places\Ent	ire Bluetooth Neighborhood\Nokia3650 🛛 💽 🕞 Go
Bluetooth Tasks 🙁	Bluetooth Dial-up Fax on Serial Port Networking Nokia3650
Other Places 🛞	1 1 1
Desktop	OBEX File OBEX Object Transfer Push on N
😼 My Computer	
Bluetooth Exchange Folder	
Wy Bluetooth Places	~

(3) Before proceeding, double check the Bluetooth Serial Port in use by the Bluetooth software by clicking Bluetooth-> Advanced Configuration on the menu bar in the "My Bluetooth Places" window. In this case, COM5 is being used as the Bluetooth Serial Port.

luetooth	Configura	tion			?
General	Accessibility	Discovery	Local Service	es Client Applications	Hardware
Select th Double-o	ne services tha click a service	at this compu name to set	iter will provide its security, sta	to other Bluetooth dev art-up options and prop	vices. ierties.
Servic	e Name		Startup	Secure Connection	COM Port
Audio (Gateway		Auto	Not Required	
Heads PIM Sy Fax File Tra PIM Ite Dial-up Netwo Blueton	et ansfer em Transfer Networking rk Access oth Serial Port		Auto Auto Auto Auto Auto Auto Auto	Not Hequired Required Required Not Required Required Required Required	COM5
Prope	erties			Add Serial Service	Delete
		ОК	Can	cel Apply	Help

(4) On the task bar right click the mRouter icon and select "Properties".



(5) Select COM5 as the port for PC Suite. If you're not sure select all ports as below.

Connection	COM port	Status	
Cable	COM1	Not connected	
Unknown	COM3	Not connected	
Bluetooth	COM4	Not connected	
🗸 Bluetooth	COM5	Not connected	
Bluetooth	COM6	Not connected	
Bluetooth	COM7	Not connected	
🗹 Bluetooth	COM8	Not connected	
Bluetooth	COM9	Not connected	
Bluetooth	COM10	Not connected	
Bluetooth	COM11	Not connected	
Bluetooth	COM12	Not connected	
Bluetooth	COM13	Not connected	
Bluetooth	COM14	Not connected	
Infrared		Not connected	

(6) Double click the "Bluetooth Serial Port on Nokia 3650" icon in "My Bluetooth Places" window to initiate a connection. Press "Yes" on your Nokia 3650 to accept the connection request from your system when the following window pops up.

Connect	ing	? 🛛
	Status: Connecting Bluetooth Serial Port on Nokia3650	

(7) Click the balloon and type in a PIN Code as required. Key-in the same PIN Code on your Nokia 3650.

Bluetootl Bluetootl compute To deny	etooth PIN Code Required h device "Nokia3650" is attemp r. Click here to proceed with t access, ignore this prompt.	ting to connect to this he connection.			
	840	2 & 2++12 B			
Bluetoot	h PIN Code Request	? 🛛			
P	Device Name:	Nokia3650			
	established, this computer and the device				
	ure creates a secret key that is used in all hese two devices to establish identity and evices exchange.				
	To create the paired relationship, enter the PIN code and click OK.				
	Bluetooth PIN Code:				
	ОК	Cancel <u>H</u> elp			

(7) Click "OK" when the window below pops up.



(8) Ignore the error message below and click "OK" to continue.

My Bluetooth Places	
The Bluetooth Serial Port connection	n failed: The remote device closed the connection

(9) Check "Always allow this device to access this service" and click "OK" to continue.



(10) Nokia PC Suite will now take over the connecting process.



(11) Notice the change of icon once the connection is established.



(12) Launch Nokia PC Suite for 3650 by clicking the Start button-> PC Suite for Nokia 3650 -> PC Suite for Nokia 3650. The following window will pop up, click "OK" to continue.



(13) Click "OK" to continue.

Change device	×
To connect to a device, select from the list of known devices below and press OK. Press Cancel to close the dialog without selecting a device. Known devices:	
Known devices:	_
Unknown devices:	
Unknown device 1 (Cable)	
<u>QK</u> <u>C</u> ancel <u>R</u> efresh <u>H</u> elp	

(14) Type the name of your preference, otherwise click "OK" to continue,



(15) Click "OK" to continue.



(16) Select the PC scheduler of your choice for Calendar synchronization and click "OK" to continue.

	Calendar/To-do Synchronisation
0	From the list below, select the PC scheduler with which you want to synchronise your handheld data. (The scheduler must be installed on your PC, or on a network to which you have access.)
	Lotus Notes 4.5/4.6 Lotus Notes 5.0 Lotus Notes 6.0 Lotus Organizer 5.0 Lotus Organizer 6.0 Lotus Organizer 97 Lotus Organizer 97 Lotus Organizer 97 Microsoft Outlook 97/98/2000/XP Microsoft Schedule+
1	

(17) Click "OK" to continue.

Calendar synchronisation o	otions	×
1	Summary	
	Synchronising : Meetings, Memos, Anniversaries, To-dos Range : 1 Week(s) in the past to 6 Month(s) in the future.	
	Privacy : All specified entries, making entries outside work hours private. Work Days : Mon. Tue, Wed. Thu, Fri	
	Work Hours : 09:00 - 17:30	
	Direction : Synchronise information in both directions.	
	Calendar Folder : (Default Calendar Folder) Tasks Folder : (Default Tasks Folder)	
	Click "Change" to alter these settings.	
	<u>O</u> K <u>Cancel</u> <u>H</u> elp	

(18) Select the PC scheduler of your choice for Contacts synchronization and click "OK" to continue.

	Contacts Synchronisation
0	From the list below, select the PC contacts application with which you want to synchronise your handheld data. (The contacts application must be installed on your PC, or on a network to which you have access.)
	Lotus Notes 4.5/4.6 Lotus Notes 5.0 Lotus Notes 6.0 Lotus Organizer 5.0 Lotus Organizer 6.0 Lotus Organizer 97 Lotus Organizer 97 Lotus Organizer 97 GS/4.0 GS/4.1 Microsoft Outlook 97/98/2000/XP Microsoft Schedule+

(19) Click "OK" to continue.

Contacts synchronisation	options 🛛 🔀
	Summary
	Details : All Details
	Direction : Synchronise information in both directions.
0	Contacts Folder: (Default Contacts Folder)
	Click "Change" to alter these settings.
	<u>OK</u> <u>Cancel</u> <u>H</u> elp

(20) Now you should be able to utilize Nokia PC Suite for 3650.



(21) Please note for some reason the "File Transfer" and "Image Transfer" function in Nokia PC Suite does not seem to work.

File Tra	nsfer 🛛 🔀
	File Transfer engine operation failed
	ОК

(22) You may have to use the "OBEX File Transfer on Nokia 3650" in "My Bluetooth Places" window to transfer files to your Nokia 3650.

A My Bluetooth Places\Entire E	3luetooth Neighborhood\Nokia3650	
<u>File E</u> dit <u>V</u> iew <u>B</u> luetooth F <u>a</u> ve	orites <u>T</u> ools <u>H</u> elp	.
🕝 Back 🔹 🕥 🖓 🥬	Search 😥 Folders 🛄 🔻	
Address 🛔 My Bluetooth Places\Entire	e Bluetooth Neighborhood',Nokia3650	💌 🄁 Go
Bluetooth Tasks	Bluetooth Dial-up Fax on OBEX File Serial Port Networking Media 2650 Trapfer	OBEX Object
Other Places (\$	Senarport Networking Noka3030 Transfer	Pasiron M.
Desktop Jesktop My Computer Bluetooth Exchange Folder	~	

How to connect to Ericsson P800 via serial port

1. Enable the Bluetooth function on your Ericsson P800. Please refer to your P800 user manual if you're uncertain of how to do so.

2. Make sure both the Bluetooth software and Sony Ericsson's PCSuiteForP800 are installed.

3. Check the inbound Bluetooth Serial Port used by your system in Bluetooth (on menu bar)-> Advanced Configurations-> Local Services->Bluetooth Serial Port. (e.g. COM6 in this case)

Service Name	Startup	Secure Connection	COM Port
Audio Gateway	Auto	Not Required	
Headset	Auto	Not Required	
PIM Synchronization	Auto	Required	
Fax	Auto	Required	
File Transfer	Auto	Required	
PIM Item Transfer	Auto	Not Required	
Dial-up Networking	Auto	Required	
Network Access	Auto	Required	
Bluetooth Serial Port	Auto	Required	COM6

4. Double click the Phone Connection Link icon (double arrow) on the taskbar to bring out the following window, and tick the COM port used in step 3. We do recommend, however, to tick all the COM ports listed to make the process easier.



elect the ports on hones.	which you want Ph	one Connection Link to se	arch for
Connection	COM Port	Status	
🗖 Cable	COM1	Not Connected	
🗖 Unknown	COM3	Not Connected	
🗹 Bluetooth	COM6	Connected	
🗖 Bluetooth	COM7	Not Connected	
Bluetooth	COM8	Not Connected	
Infrared		Not Connected	
			<u>H</u> elp

5. Double click the Bluetooth Serial Port icon in My Bluetooth Places of your P800.



6. The following dialog box will appear, ignore it and click OK to continue.



7. The following dialog box will appear, ignore it and click OK to continue.



8. When the balloon appears, click it to accept the request.



9. The following dialog box will appear, click OK to continue.



10. Your system and P800 is now connected.



11. The following dialog box will appear. Click Next to continue.

Phone Connection Mon	itor - Connection Wizard 🛛 🛛 🔀	
Sony incourse Sony incourse Sony incourse incour	Welcome! This wizard will help the system identify your phone. It can also replace your current phone with a previously connected phone. To identify your phone, click Next.	
< Back Next> Cancel		

12. Click Next to continue.



13. Click Next to continue.

Phone Connection Monitor - Connection Wizard		
Sarry Encado Vedore Booy Election Uro22001	You have to identify your phone with a name. Enter a name and then click Next. Phone Name: My P800	
	< <u>B</u> ack <u>N</u> ext > Cancel	