

Parts List

LOC	PART-CODE	PART-NAME	PART-DESC	Model
D001	97P9553714	MANUAL OWNERS	ART PAPER	VR637HF
D002	97P880RN10	CABLE RF	NTSC 1.0M	VR637HF
D003	97P0424100	COVER ACCESSORY	LD-PE T0.1(TCE)	VR637HF
D004	486A716202	BATTERY	AAA 1.5V(SUPERGARD)	VR637HF
D007	97P9408200	IMPORTANT SAFEGUARDS PAPER	PAPER	VR637HF
C001	97P4929500	PAD L/R	EPS	VR637HF
C002	97P4809200	POLY BAG FOR SET	800X650XT0.5 PE-FOAM	VR637HF
C003	97P505160C	BOX CARTON	430X295X135	VR637HF
C004	97P9359114	LABEL POS	PAPER	VR637HF
C005	6520010020	STAPPLE	M20	VR637HF
A001	97P061111B	CHASSIS MAIN	HI-PS(V0), GD301A	VR637HF
A0011	97P0800602	LEG	PLASTOMER	VR637HF
A002	97P9359214	LABEL SPEC	PAPER	VR637HF
A003	97P9358200	LABEL CLOCK	REMOVABLE 5X1.8	VR637HF
A004	97P9359314	LABEL SERVICE	PAPER	VR637HF
A005	97P9408814	CARD POP	ART PAPE(T9G4N-GQ)	VR637HF
A017	97P0919100	PLATE EARTH AB	SUS 304 CSP T=0.2	VR637HF
A040	97P0478008	COVER TOP	SECC T0.5+PT(GD327C)	VR637HF
A041	7173401212	SCREW TAPPTITE	TT2 BIN 4X12 BK	VR637HF
A060	97P0478100	COVER BOTTOM	ET T0.4	VR637HF
A061	7174301011	SCREW TAPPTITE	TT2 RND 3X10 MFZN	VR637HF
D005	97P9406200	REGISTRATION CARD	PAPER	VR637HF
D006	97P9359014	LABEL SERIAL REGIST	PAPER	VR637HF
D100	97P1R2HA03	REMOCON HANDSET AS	VR-F2HA(CRK235BL)	VR637HF
M01	97PP32421D	PANEL FRONT AS	T9G4N-GQ	VR637HF
M01A	97P9360501	LABEL PATENT	PAPER(CA/MA)	VR637HF
M01B	7174301011	SCREW TAPPTITE	TT2 RND 3X10 MFZN	VR637HF
M021	7173401211	SCREW TAPPTITE	TT2 BIN 4X12 MFZN	VR637HF
AD001	97PA285201	DRUM PRICE AS	CYN-T610C	VR637HF
AD002	7004300511	SCREW MACHINE	RND 3X5 MFZN	VR637HF
AD003	97P88F0B20	CABLE FFC	1.25K 11P 200MM	VR637HF
AF001	97SA261010	F/LOADING AS	T-MECHA	VR637HF
AF002	7274300511	SCREW TAPPTITE	TT3 RND 3X5 MFZN	VR637HF
AN002	2291131304	GREASE	DELUXE 5221G(NAM-YOUNG)	VR637HF
A0100	97SA318100	MAIN BASE AS	T-MECHA	VR637HF
A011	97P93B2102	LABEL CD(DECK)	PAPER(13X56) ALL MODEL	VR637HF
A0200	97SA316500	S SLANT POLE AS	T-MECHA	VR637HF
A0300	97SA316600	T SLANT POLE AS	T-MECHA	VR637HF
A0400	97S8103000	MOTOR CAPSTAN	DMVCMC-09D	VR637HF
A0401	97S3102000	SCREW TAPPTITE	TT2 BIN-P 2.6X7 MFZN	VR637HF
A0600	97SA320500	AC HEAD AS	T-MECHA	VR637HF
B0610	97SA326800	HEAD A/C	HVMXA1101A(ALPS)	VR637HF
A0601	7004300511	SCREW MACHINE	RND 3X5 MFZN	VR637HF
A1000	97SA316800	L LOADING AS	T-MECHA	VR637HF
A1100	97SA316900	R LOADING AS	T-MECHA	VR637HF
A1200	97S2709510	RACK LOADING	SECC T1.2	VR637HF
A1201	7008301911	SCREW MACHINE	WAS M3*19 MFZN	VR637HF
A1400	97S0904310	PLATE CONNECT-H	SECC T1.0	VR637HF
A1500	97SA319410	REEL BRKT TOTAL AS	T2-MECHA	VR637HF
A1501	7274300511	SCREW TAPPTITE	TT3 RND 3X5 MFZN	VR637HF
A1700	97S5500400	BELT REEL	CR68	VR637HF
A1800	97S2623200	LEVER RELAY	SECC T1.2	VR637HF
A1900	97S2709600	RACK FL	PBT(DY4410GF) NATURAL	VR637HF
A2000	97S2708200	GEAR CAM	DERLIN 100	VR637HF
A2100	97SA317150	PINCH LEVER TOT AS	T-MECHA	VR637HF
B1910	97SA481050	PINCH ROLLER AS	D15(DAEJIN D2.6*D7*T4.5)	VR637HF
A2200	97SA318050	LC BRKT AS	T5-MECHA	VR637HF
A2201	7274300611	SCREW TAPPTITE	TT3 RND 3X6 MFZN	VR637HF
A2400	97SA317310	IDLER PLATE TOT AS	T2-MECHA	VR637HF
A2401	97S3108200	POLYWASHER	D2.6XD6.0XT0.5	VR637HF
A2600	97S2909400	TABLE REEL	POM(F20-03) BLACK	VR637HF
A2700	97SA317200	TENSION LVR TOT AS	T-MECHA	VR637HF
A2800	97SA317400	S BRAKE AS	T-MECHA	VR637HF
A2900	97SA317510	T BRAKE AS	T2-MECHA	VR637HF
A3000	97S8023700	HEAD FE	HVFHP0042A	VR637HF
A3001	7274300811	SCREW TAPPTITE	TT3 RND 3X8 MFZN	VR637HF
PW01	97P69BY910	CORD POWER AS	USA LP-11W YH396 1.7M	VR637HF
PW01A	47P1503600	CLAMP WIRE A	NYLON 66	VR637HF
AM01	2193100801	SOLDER WIRE	SN:PB=63:37 3PI(NO FLUX)	VR637HF
AM02	2193011100	SOLDER WIRE	60 SNA 1.2D	VR637HF
AM03	2291050305	FLUX LIQUID	RF-800KN	VR637HF
AM04	2291050306	FLUX THINNER	RF-800ADD	VR637HF
AM05	2291140501	WAX COVER	DS-102AN	VR637HF
AM06	97P93B2101	LABEL CD(PCB)	PAPER(13X48) ALL MODEL	VR637HF
BA01	97P072781B	BOARD ANT	HI-PS(V0),GD301A	VR637HF
BA01A	7175300812	SCREW TAPPTITE	TT2 FLT 3X8 MFZN BK	VR637HF

Parts List

LOC	PART-CODE	PART-NAME	PART-DESC	Model
C801	CL2EE3104M	C LINE ACROSS	AC 275V 0.1MF M PCX2 335M	VR637HF
C804	CH1CEE332M	C CERA AC	2.5KV 3300PF M DE AC250V	VR637HF
C805	CH1TFE332M	C CERA AC	4.0KV 3300PF M AD AC250V	VR637HF
C806	CEXF2E680V	C ELECTRO	250V RSS 68MF 16X25(SG)	VR637HF
C813	CEXK1C681L	C ELECTRO	16V 680UF KXL	VR637HF
C814	CEXK1E681L	C ELECTRO	25V 680UF KXL	VR637HF
D809	D31DQ03L-F	DIODE SCHOTTKY	31DQ03L-FC5	VR637HF
D810	DRGP20D- - -	DIODE	RGP20D	VR637HF
H701	1TS0P2256W	IC UNIT R/RECEIVER	TSOP2256WE1	VR637HF
IC801	1TCET1103G	IC PHOTO COUPLER	TCET1103G(K643PG)4P DIP	VR637HF
JK101	97P6315800	JACK PIN	DPAE-9641	VR637HF
JK731	97P6316000	JACK PIN	DPAE-9930	VR637HF
LD701	DLDVST7X3D	LED DISPLAY	DVST7X3D	VR637HF
L801	5PLFSF212A	FILTER LINE	SF-2120A	VR637HF
PT01	97P6269000	CONN WAFER	00-8283-0612-00000	VR637HF
P201	97P62Y1318	CONN WAFER	DVW250 PLUG 2.5MM 8P	VR637HF
P202	97P62T14B2	CONN HOUSING	TMC-EX-B1 RECEP 2.0MM 2P	VR637HF
P301	97P62G06DA	CONN HOUSING	GF120 FPC 1.25MM 10P	VR637HF
P501	97P62T152C	CONN B/B	TMC-JP PLUG 2.0MM 12P	VR637HF
P701	97P885X117	CONN AS	2S-2S 80MM	VR637HF
P801	97P62Y04X4	CONN WAFER	YW396 4P NC	VR637HF
Q801	TKSC5021FR	TR	KSC5021F-R	VR637HF
RF101	97P7613500	TUNER 3 IN 1	LGTMI-US2-S	VR637HF
R805	RS02F473JS	R M-OXIDE FILM	2W 47K OHM J SMALL	VR637HF
SW501	5S10104100	SW MODE	MMS00402ZMB0	VR637HF
SW601	5SD0101100	SW DETE	MXS00921MPC0	VR637HF
S603	97P0S02500	SENSOR REEL	RPI-303N	VR637HF
S604	97P0S02500	SENSOR REEL	RPI-303N	VR637HF
T801	57M8282300	TRANS SMPS	TSW-T8G5N	VR637HF
VA801	D1NR10D471	VARISTOR	1NR10D471	VR637HF
CS03	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
CS04	HCBK471KBA	C CHIP CERA	50V X7R 470PF K 1608	VR637HF
CS07	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
CS09	HCQK201JBA	C CHIP CERA	50V CH 200PF J 1608	VR637HF
C103	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C104	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C107	HCQK809DBA	C CHIP CERA	50V CH 8PF D 1608	VR637HF
C109	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C120	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C121	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C201	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C203	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608	VR637HF
C211	HCBK471KBA	C CHIP CERA	50V X7R 470PF K 1608	VR637HF
C216	HCBK471KBA	C CHIP CERA	50V X7R 470PF K 1608	VR637HF
C217	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C220	HCBK391KBA	C CHIP CERA	50V X7R 390PF K 1608	VR637HF
C262	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C264	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C276	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C277	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C278	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C280	HCBK562KBA	C CHIP CERA	X7R 50V 5600PF K 1608	VR637HF
C282	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C291	HCBK562KBA	C CHIP CERA	X7R 50V 5600PF K 1608	VR637HF
C294	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C297	HCBK562KBA	C CHIP CERA	X7R 50V 5600PF K 1608	VR637HF
C302	HCBK391KBA	C CHIP CERA	50V X7R 390PF K 1608	VR637HF
C303	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C311	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C318	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C319	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C325	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C328	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C330	HCFH473ZBA	C CHIP CERA	25V Y5V 0.047MF Z 1608	VR637HF
C332	HCFH473ZBA	C CHIP CERA	25V Y5V 0.047MF Z 1608	VR637HF
C333	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C335	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C336	HCQK180JBA	C CHIP CERA	50V CH 18PF J 1608	VR637HF
C337	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C341	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C342	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C501	HCBK222KBA	C CHIP CERA	50V X7R 2200PF K 1608	VR637HF
C502	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608	VR637HF
C503	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C508	HCFH104ZBA	C CHIP CERA	25V Y5V 0.1MF Z 1608	VR637HF
C511	HCBK102KBA	C CHIP CERA	50V X7R 1000PF K 1608	VR637HF

Parts List

LOC	PART-CODE	PART-NAME	PART-DESC	Model
C512	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C514	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C519	HCBK472KBA	C CHIP CERA	50V X7R 4700PF K 1608	VR637HF
C610	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C614	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C628	HCQK130JBA	C CHIP CERA	50V CH 13PF J 1608	VR637HF
C641	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C642	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C643	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C644	HCFH223ZBA	C CHIP CERA	25V Y5V 0.022MF Z 1608	VR637HF
C703	HCBK103KBA	C CHIP CERA	50V X7R 0.01MF K 1608	VR637HF
C809	HCBK472KBA	C CHIP CERA	50V X7R 4700PF K 1608	VR637HF
C810	HCFH473ZBA	C CHIP CERA	25V Y5V 0.047MF Z 1608	VR637HF
C819	HCBF683KBA	C CHIP CERA	X7R 16V 0.068MF K 1608	VR637HF
IC251	1AN3663- - -	IC HIFI	AN3663	VR637HF
IC301	1LA71205- -	IC A/V	LA71205M	VR637HF
IC603	14ATM24D08	IC EPROM	ATM24D08	VR637HF
IC701	1PT6955- - -	IC DRIVER	PT6955(LED DRIVR)	VR637HF
RJ003	HRFS000-BA	R CHIP	1/16 0 OHM 1608	VR637HF
RJ004	HRFS000-BA	R CHIP	1/16 0 OHM 1608	VR637HF
RS02	HRFS102JBA	R CHIP	1/16 1K OHM J 1608	VR637HF
RS03	HRFS222JBA	R CHIP	1/16 2.2K OHM J 1608	VR637HF
R103	HRFS102JBA	R CHIP	1/16 1K OHM J 1608	VR637HF
R104	HRFS102JBA	R CHIP	1/16 1K OHM J 1608	VR637HF
R109	HRFS750JBA	R CHIP	1/16W 75 OHM J 1608	VR637HF
R201	HRFS912JBA	R CHIP	1/16 9.1K OHM J 1608	VR637HF
R202	HRFS912JBA	R CHIP	1/16 9.1K OHM J 1608	VR637HF
R203	HRFS334JBA	R CHIP	1/16 330K OHM J 1608	VR637HF
R205	HRFS273JBA	R CHIP	1/16 27K OHM J 1608	VR637HF
R206	HRFS821JBA	R CHIP	1/16 820 OHM J 1608	VR637HF
R212	HRFS113JBA	R CHIP	1/16 11K OHM J 1608	VR637HF
R220	HRFS223JBA	R CHIP	1/16 22K OHM J 1608	VR637HF
R221	HRFS273JBA	R CHIP	1/16 27K OHM J 1608	VR637HF
R223	HRFS103JBA	R CHIP	1/16 10K OHM J 1608	VR637HF
R229	HRFS103JBA	R CHIP	1/16 10K OHM J 1608	VR637HF
R230	HRFS223JBA	R CHIP	1/16 22K OHM J 1608	VR637HF
R231	HRFS181JBA	R CHIP	1/16 180 OHM J 1608	VR637HF
R235	HRFS622JBA	R CHIP	1/16W 6.2K OHM J 1608	VR637HF
R253	HRFS123JBA	R CHIP	1/16 12K OHM J 1608	VR637HF
R255	HRFS123JBA	R CHIP	1/16 12K OHM J 1608	VR637HF
R257	HRFS123JBA	R CHIP	1/16 12K OHM J 1608	VR637HF
R259	HRFS123JBA	R CHIP	1/16 12K OHM J 1608	VR637HF
R265	HRFS362JBA	R CHIP	1/16 3.6K OHM J 1608	VR637HF
R270	HRFS362JBA	R CHIP	1/16 3.6K OHM J 1608	VR637HF
R301	HRFS363JBA	R CHIP	1/16 36K OHM J 1608	VR637HF
R302	HRFS202JBA	R CHIP	1/16 2K OHM J 1608	VR637HF
R303	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608	VR637HF
R305	HRFS104JBA	R CHIP	1/16 100K OHM J 1608	VR637HF
R309	HRFS182JBA	R CHIP	1/16 1.8K OHM J 1608	VR637HF
R310	HRFS684JBA	R CHIP	1/16 680K OHM J 1608	VR637HF
R313	HRFS822JBA	R CHIP	1/16 8.2K OHM J 1608	VR637HF
R322	HRFS132JBA	R CHIP	1/16 1.3K OHM J 1608	VR637HF
R329	HRFS472JBA	R CHIP	1/16 4.7K OHM J 1608	VR637HF
R333	HRFS102JBA	R CHIP	1/16 1K OHM J 1608	VR637HF
R335	HRFS104JBA	R CHIP	1/16 100K OHM J 1608	VR637HF
R501	HRFS332JBA	R CHIP	1/16 3.3K OHM J 1608	VR637HF
R514	HRFS103JBA	R CHIP	1/16 10K OHM J 1608	VR637HF
R516	HRFS431JBA	R CHIP	1/16 430 OHM J 1608	VR637HF
R601	HRFS102JBA	R CHIP	1/16 1K OHM J 1608	VR637HF
R602	HRFS103JBA	R CHIP	1/16 10K OHM J 1608	VR637HF
R618	HRFS201JBA	R CHIP	1/16 200 OHM J 1608	VR637HF
R619	HRFS273JBA	R CHIP	1/16 27K OHM J 1608	VR637HF
R620	HRFS201JBA	R CHIP	1/16 200 OHM J 1608	VR637HF
R621	HRFS273JBA	R CHIP	1/16 27K OHM J 1608	VR637HF
R706	HRFS473JBA	R CHIP	1/16 47K OHM J 1608	VR637HF
R728	HRFS473JBA	R CHIP	1/16 47K OHM J 1608	VR637HF
R729	HRFS473JBA	R CHIP	1/16 47K OHM J 1608	VR637HF
R733	HRFS750JBA	R CHIP	1/16W 75 OHM J 1608	VR637HF
CS05	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP	VR637HF
CS08	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C101	CEXF1A471V	C ELECTRO	10V RSS 470MF 8X11.5	VR637HF
C108	CEXF1C331V	C ELECTRO	16V RSS 330MF (8X11.5) TP	VR637HF
C110	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C111	CEXF1H220V	C ELECTRO	50V RSS 22MF (5X11) TP	VR637HF
C112	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C202	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF

LOC	PART-CODE	PART-NAME	PART-DESC	Model
C206	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C208	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C210	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP	VR637HF
C212	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7	VR637HF
C218	CEXF1E470V	C ELECTRO	25V RSS 47MF (5X11) TP	VR637HF
C219	CMXM2A153J	C MYLAR	100V 0.015MF J (TP)	VR637HF
C221	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C223	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7	VR637HF
C252	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C253	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7	VR637HF
C254	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C255	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7	VR637HF
C256	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C257	CEXF1C330A	C ELECTRO	16V RSM 33MF (6.3X7) TP	VR637HF
C258	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C259	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C263	CCXF1H103Z	C CERA	50V F 0.01MF Z (TAPPING)	VR637HF
C266	CEXF1H228A	C ELECTRO	50V RSM 0.22MF (4X7)	VR637HF
C268	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C269	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C270	CEXF1C330A	C ELECTRO	16V RSM 33MF (6.3X7) TP	VR637HF
C272	CEXE0J221S	C ELECTRO	6.3V RSA 220MF 6.3X7	VR637HF
C273	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7	VR637HF
C274	CCXF1H473Z	C CERA	50V F 0.047MF Z (TAPPING)	VR637HF
C275	CEXF1H339A	C ELECTRO	50V RSM 3.3MF 4X7	VR637HF
C279	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C281	CEXF1H229A	C ELECTRO	50V RSM 2.2MF (4X7) TP	VR637HF
C284	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C286	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP	VR637HF
C287	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C288	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C289	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C290	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C293	CEXF1H339A	C ELECTRO	50V RSM 3.3MF 4X7	VR637HF
C301	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C305	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C306	CEXP1A101A	C ELECTRO	10V REM 100MF 6.3X5 5T	VR637HF
C307	CEXF1C220A	C ELECTRO	16V RSM 22MF (5X7)	VR637HF
C308	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C309	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C310	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C312	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C313	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C314	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C315	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C316	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C322	CEXP1A101A	C ELECTRO	10V REM 100MF 6.3X5 5T	VR637HF
C323	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C324	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C326	CEXF1H109A	C ELECTRO	50V RSM 1MF (4X7) TP	VR637HF
C327	CEXP1A101A	C ELECTRO	10V REM 100MF 6.3X5 5T	VR637HF
C331	CCXF1H473Z	C CERA	50V F 0.047MF Z (TAPPING)	VR637HF
C334	CEXP1A101A	C ELECTRO	10V REM 100MF 6.3X5 5T	VR637HF
C338	CEXF1H478A	C ELECTRO	50V RSM 0.47MF 4X7	VR637HF
C344	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C504	CEXP1A470A	C ELECTRO	10V REM 47MF	VR637HF
C507	CEXP1A101A	C ELECTRO	10V REM 100MF 6.3X5 5T	VR637HF
C515	CEXF1E470A	C ELECTRO	25V RSM 47MF 6.3*7	VR637HF
C516	CEXP1A470A	C ELECTRO	10V REM 47MF	VR637HF
C517	CEXF1E470A	C ELECTRO	25V RSM 47MF 6.3*7	VR637HF
C601	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP	VR637HF
C603	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP	VR637HF
C604	CEXE0J221S	C ELECTRO	6.3V RSA 220MF 6.3X7	VR637HF
C616	CCXB1H471K	C CERA	50V B 470PF K (TAPPING)	VR637HF
C633	CEXF1E470V	C ELECTRO	25V RSS 47MF (5X11) TP	VR637HF
C701	CEXF1C100A	C ELECTRO	16V RSM 10MF 4X7	VR637HF
C704	CEXF1A471V	C ELECTRO	10V RSS 470MF 8X11.5	VR637HF
C807	CBXB3A331K	C CERA SEMI	1KV RR 330PF K	VR637HF
C808	CMXL2G333K	C MYLAR	400V MEU 0.033MF K	VR637HF
C811	CMXM2A393J	C MYLAR	100V 0.039MF J (TP)	VR637HF
C812	CEXF1H479A	C ELECTRO	50V RSM 4.7MF 4X7	VR637HF
C815	CEXK1J220L	C ELECTRO	63V 22UF KXL	VR637HF
C816	CEXF1A471V	C ELECTRO	10V RSS 470MF 8X11.5	VR637HF
C817	CEXF1E101V	C ELECTRO	25V RSS 100MF (6.3X11) TP	VR637HF
C822	CEXF1C470A	C ELECTRO	16V RSM 47MF (5X7) TP	VR637HF
C824	CEXF1E470V	C ELECTRO	25V RSS 47MF (5X11) TP	VR637HF

Parts List

LOC	PART-CODE	PART-NAME	PART-DESC	Model
C828	CEXF1A471V	C ELECTRO	10V RSS 470MF 8X11.5	VR637HF
C829	CEXF1E470V	C ELECTRO	25V RSS 47MF (5X11) TP	VR637HF
F801	5FWPS2022L	FUSE PLASTIC TUBE	WRL 2A 250V TL LT-5, SR-5	VR637HF
IC802	1KA431AZ--	IC REGULATOR	KA431AZ	VR637HF
LS02	5CPX680J2T	COIL PEAKING	68UH(BLU-BLK)	VR637HF
L101	5CPX150J--	COIL PEAKING	15UH J (RADIAL)	VR637HF
L102	5CPX100J2T	COIL PEAKING	10UH(BRN-BLK)	VR637HF
L103	5CPX688K2T	COIL PEAKING	0.68UH(BLU-SILV)	VR637HF
L104	5CPX561J--	COIL PEAKING	560UH 5MM J RADIAL	VR637HF
L202	5CPX820J--	COIL PEAKING	82UH J (RADIAL)	VR637HF
L251	5CPX680J2T	COIL PEAKING	68UH(BLU-BLK)	VR637HF
L252	5CPX680J2T	COIL PEAKING	68UH(BLU-BLK)	VR637HF
L304	5CPX101J--	COIL PEAKING	PL 100UH J (TAPPING)	VR637HF
L305	5CPX101J2T	COIL PEAKING	100UH(BRN-BRN)	VR637HF
L307	5CPX101J2T	COIL PEAKING	100UH(BRN-BRN)	VR637HF
L601	5CPX120J--	COIL PEAKING	12UH J (RADIAL)	VR637HF
L804	56C220K686	COIL CHOKE	22UH K 27.5X0.4D	VR637HF
Q101	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)	VR637HF
Q201	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)	VR637HF
Q202	TZTC3202Y-	TR	KTC3202Y (AUTO)(1959Y)	VR637HF
Q203	TZTC3198Y-	TR	KTC3198Y-(1815Y) (AUTO)	VR637HF
Q204	TZTC3198Y-	TR	KTC3198Y-(1815Y) (AUTO)	VR637HF
Q205	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)	VR637HF
Q206	TZTC3198Y-	TR	KTC3198Y-(1815Y) (AUTO)	VR637HF
Q301	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)	VR637HF
Q302	TZTC3198Y-	TR	KTC3198Y-(1815Y) (AUTO)	VR637HF
Q304	TZSR1004--	TR	KSR1004 (AUTO)	VR637HF
Q305	TZTA1266Y-	TR	KTA1266Y- (AUTO)(1015Y)	VR637HF
Q602	TZTC3198Y-	TR	KTC3198Y-(1815Y) (AUTO)	VR637HF
Q802	TZTC3203Y-	TR	KTC3203Y (2120Y)	VR637HF
Q804	TZTC3205Y-	TR	KTC3205Y (2236Y)	VR637HF
Q805	TZTC3205Y-	TR	KTC3205Y (2236Y)	VR637HF
Q806	TZTC3203Y-	TR	KTC3203Y (2120Y)	VR637HF
Q807	TZTC3205Y-	TR	KTC3205Y (2236Y)	VR637HF
SW703	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW705	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW706	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW708	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW709	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW711	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW712	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
SW718	5S50101Z90	SW TACT	THVV502GDA	VR637HF
SW724	5S50101Z97	SW TACT	THVV952GBA 9.5M AUTO	VR637HF
X301	5XE3R579TB	CRYSTAL QUARTZ	HC-49/U 3.579545MHZ 15PPM	VR637HF
AM31	2TM1456000	TAPE MASKING	SI-602	VR637HF
AM31A	2TM110620R	TAPE MASKING	SI-600N RED	VR637HF
AM31B	2TM1106200	TAPE MASKING	SI-600N	VR637HF
C204	CCZB1H391K	C CERA	50V B 390PF K	VR637HF
C209	CCZF1H104Z	C CERA	50V HIKF 0.1MF Z	VR637HF
C251	CCZF1H104Z	C CERA	50V HIKF 0.1MF Z	VR637HF
C260	CCZB1H153K	C CERA	50V HIKB 0.015MF K AXL 52	VR637HF
C261	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C267	CCZB1H153K	C CERA	50V HIKB 0.015MF K AXL 52	VR637HF
C285	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C292	CCBF1E223Z	C CERA SEMI	25V Y5V 0.022MF Z	VR637HF
C299	CCZF1H104Z	C CERA	50V HIKF 0.1MF Z	VR637HF
C304	CCZB1H181K	C CERA	50V B 180PF K AXIAL	VR637HF
C317	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C329	CCZF1H104Z	C CERA	50V HIKF 0.1MF Z	VR637HF
C339	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C340	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C505	CCZB1H102K	C CERA	50V B 1000PF K AXIAL	VR637HF
C606	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C612	CBZP1C103M	C CERA SEMI	16V Y5S 0.01MF M	VR637HF
C615	CCZB1H102K	C CERA	50V B 1000PF K AXIAL	VR637HF
C617	CCZF1H104Z	C CERA	50V HIKF 0.1MF Z	VR637HF
D101A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D102A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D103A	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D104A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D105A	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D150A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D205A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D206A	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D250A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D251	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF

Parts List

LOC	PART-CODE	PART-NAME	PART-DESC	Model
D301	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D601	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D602	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D603	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D607	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D660	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D701	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D711	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D712	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D713	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D715	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D716	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D731A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D732A	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D735A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D736A	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D801	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D802	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D803	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D804	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D805	DZEG01C---	DIODE	EG01C	VR637HF
D806	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D807	DZUZ3R0BSB	DIODE ZENER	UZ-3.0BSB(3.01-3.22V)	VR637HF
D808	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D811	DZGDZP18B-	DIODE ZENER	GDZP18B1	VR637HF
D812	D1SS244---	DIODE	1SS244	VR637HF
D815	DZUZ5R1BSB	DIODE ZENER	UZ-5.1BSB(4.97-5.18V)	VR637HF
D816	DZN4148---	DIODE	1N4148 AUTO 52MM	VR637HF
D817	DZUZ13BSB-	DIODE ZENER	UZ-13BSB(12.59-13.16V)	VR637HF
D819	DZUZ33BSB-	DIODE ZENER	UZ-33BSB(30.32-31.38V)	VR637HF
D821	DZ1F3E----	DIODE FR	1F3E	VR637HF
D824	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
D825	DZN4004---	DIODE	1N4004(AUTO),(DAEBO)	VR637HF
L303	5PB13857--	COIL BEAD	B13857(AXIAL)	VR637HF
L306	5PB13857--	COIL BEAD	B13857(AXIAL)	VR637HF
L603	5PB13857--	COIL BEAD	B13857(AXIAL)	VR637HF
L805	5PB13857--	COIL BEAD	B13857(AXIAL)	VR637HF
L806	5CPZ680K04	COIL PEAKING	68UH K (AXIAL 3.5MM)	VR637HF
L807	85801060TA	WIRE COPPER	0.6X52MM TAPING	VR637HF
L808	85801060TA	WIRE COPPER	0.6X52MM TAPING	VR637HF
R101	RD-AZ243J-	R CARBON FILM	1/6 24K OHM J	VR637HF
R102	RD-AZ750J-	R CARBON FILM	1/6 75 OHM J	VR637HF
R106	RD-4Z471J-	R CARBON FILM	1/4 470 OHM J	VR637HF
R107	RD-4Z471J-	R CARBON FILM	1/4 470 OHM J	VR637HF
R108	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J	VR637HF
R111	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R112	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R158	RD-AZ303J-	R CARBON FILM	1/6 30K OHM J	VR637HF
R204	RD-AZ111J-	R CARBON FILM	1/6 110 OHM J	VR637HF
R211	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R213	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R222	RD-AZ561J-	R CARBON FILM	1/6 560 OHM J	VR637HF
R224	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J	VR637HF
R227	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R228	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R254	RD-AZ563J-	R CARBON FILM	1/6 56K OHM J	VR637HF
R256	RD-AZ563J-	R CARBON FILM	1/6 56K OHM J	VR637HF
R258	RD-AZ563J-	R CARBON FILM	1/6 56K OHM J	VR637HF
R260	RD-AZ563J-	R CARBON FILM	1/6 56K OHM J	VR637HF
R263	RD-AZ333J-	R CARBON FILM	1/6 33K OHM J	VR637HF
R264	RD-AZ561J-	R CARBON FILM	1/6 560 OHM J	VR637HF
R266	RD-AZ561J-	R CARBON FILM	1/6 560 OHM J	VR637HF
R268	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R269	RD-AZ392J-	R CARBON FILM	1/6 3.9K OHM J	VR637HF
R271	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R273	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R304	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J	VR637HF
R306	RD-AZ823J-	R CARBON FILM	1/6 82K OHM J	VR637HF
R307	RD-AZ222J-	R CARBON FILM	1/6 2.2K OHM J	VR637HF
R308	RD-AZ182J-	R CARBON FILM	1/6 1.8K OHM J	VR637HF
R311	RD-AZ122J-	R CARBON FILM	1/6 1.2K OHM J	VR637HF
R312	RD-AZ182J-	R CARBON FILM	1/6 1.8K OHM J	VR637HF
R314	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R315	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R316	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R317	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF

Parts List

LOC	PART-CODE	PART-NAME	PART-DESC	Model
R318	RD-AZ183J-	R CARBON FILM	1/6 18K OHM J	VR637HF
R319	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R320	RD-AZ183J-	R CARBON FILM	1/6 18K OHM J	VR637HF
R323	85801060TA	WIRE COPPER	0.6X52MM TAPING	VR637HF
R324	RD-AZ473J-	R CARBON FILM	1/6 47K OHM J	VR637HF
R325	RD-AZ393J-	R CARBON FILM	1/6 39K OHM J	VR637HF
R326	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R330	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R331	RD-AZ363J-	R CARBON FILM	1/6 36K OHM J	VR637HF
R332	RD-AZ132J-	R CARBON FILM	1/6 1.3K OHM J	VR637HF
R502	RD-AZ131J-	R CARBON FILM	1/6 130 OHM J	VR637HF
R503	RD-AZ131J-	R CARBON FILM	1/6 130 OHM J	VR637HF
R504	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R507	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R508	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R509	RD-AZ473J-	R CARBON FILM	1/6 47K OHM J	VR637HF
R510	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R511	RD-AZ473J-	R CARBON FILM	1/6 47K OHM J	VR637HF
R512	RD-AZ912J-	R CARBON FILM	1/6 9.1K OHM J	VR637HF
R513	RN-AZ103F-	R METAL FILM	1/6 10K OHM F	VR637HF
R515	RD-AZ203J-	R CARBON FILM	1/6 20K OHM J	VR637HF
R519	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R605	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R606	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R607	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R608	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R609	RD-AZ201J-	R CARBON FILM	1/6 200 OHM J	VR637HF
R610	RD-AZ105J-	R CARBON FILM	1/6 1M OHM J	VR637HF
R611	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R626	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J	VR637HF
R627	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J	VR637HF
R628	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J	VR637HF
R629	RD-AZ244J-	R CARBON FILM	1/6 240K OHM J	VR637HF
R632	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J	VR637HF
R633	RD-AZ474J-	R CARBON FILM	1/6 470K OHM J	VR637HF
R639	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J	VR637HF
R640	RD-AZ202J-	R CARBON FILM	1/6 2K OHM J	VR637HF
R641	RD-AZ472J-	R CARBON FILM	1/6 4.7K OHM J	VR637HF
R642	RD-AZ104J-	R CARBON FILM	1/6 100K OHM J	VR637HF
R649	RD-AZ102J-	R CARBON FILM	1/6 1K OHM J	VR637HF
R650	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J	VR637HF
R660	RD-AZ113J-	R CARBON FILM	1/6 11K OHM J	VR637HF
R661	RD-AZ203J-	R CARBON FILM	1/6 20K OHM J	VR637HF
R662	RD-AZ203J-	R CARBON FILM	1/6 20K OHM J	VR637HF
R668	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R730	RD-AZ101J-	R CARBON FILM	1/6 100 OHM J	VR637HF
R801	RC-2Z335KP	R CARBON COMP	1/2 3.3M OHM K	VR637HF
R802	RD-4Z104J-	R CARBON FILM	1/4 100K OHM J	VR637HF
R803	RD-4Z104J-	R CARBON FILM	1/4 100K OHM J	VR637HF
R804	RD-AZ103J-	R CARBON FILM	1/6 10K OHM J	VR637HF
R806	RD-2Z560JS	R CARBON FILM	1/2 56 OHM J SMALL	VR637HF
R807	RD-2Z560JS	R CARBON FILM	1/2 56 OHM J SMALL	VR637HF
R808	RD-AZ681J-	R CARBON FILM	1/6 680 OHM J	VR637HF
R809	RD-4Z100J-	R CARBON FILM	1/4 10 OHM J	VR637HF
R810	RD-AZ470J-	R CARBON FILM	1/6 47 OHM J	VR637HF
R811	RD-AZ470G-	R CARBON FILM	1/6 47 OHM G	VR637HF
R812	RD-AZ182G-	R CARBON FILM	1/6 1.8K OHM G	VR637HF
R813	RD-AZ132G-	R CARBON FILM	1/6 1.3K OHM G	VR637HF
R814	RD-4Z201J-	R CARBON FILM	1/4 200 OHM J	VR637HF
R815	RD-4Z123J-	R CARBON FILM	1/4 12K OHM J	VR637HF
R816	RD-4Z123J-	R CARBON FILM	1/4 12K OHM J	VR637HF
R819	RD-AZ272J-	R CARBON FILM	1/6 2.7K OHM J	VR637HF
U001	97P65302MA	PCB MAIN	330X199X1.6T	VR637HF
D823	85801065GY	WIRE COPPER	AWG22 1/0.65 TIN COATING	VR637HF