



### ELECTRICAL SPECIFICATIONS

SPECIFICATION	ANT-418-MHW-RPS	ANT-433-MHW-RPS	ANT-916-MHW-RPS
Frequency Range	410-426	425-441	881-951
Bandwidth	16	16	70
Gain	2dBi	2dBi	2dBi
V.S.W.R.	<1.5	<1.5	<1.5
Impedance	50Ω	50Ω	50Ω
Max Power	50W	50W	50W
Length	6.9"	6.3"	3.9"
Connector	RP-SMA or SMA	RP-SMA or SMA	RP-SMA or SMA
Cable	79' or 15'	79' or 15'	79' or 15'

### ORDERING INFORMATION

PART #	DESCRIPTION
ANT-xxx-MHW-***-‡	MHW Series Antenna
xxx = 418, 433 or 916 • *** = RPS (RP-SMA) or SMA	
‡ = S (79") or L (15')	

RP-SMA Connector Standard.

Other terminations available for volume orders.

For additional information, please contact Antenna Factor at 800-489-1634

Revised 3/27/03

Recipient understands any or all of the above specifications are subject to change without notice and proceeds with integration at own risk.