

Monitoring mode

Every time the parent unit is turned on, it displays a baby unit in SINGLE-CAM mo You can also monitor your baby in PATROL or SPLIT-VIEW mode.

SINGLE-CAM The screen displays a single baby unit in full A single cam view that PATROL ransits to a different baby init every 10 seconds. SPLIT-VIEW M The screen displays all baby units (up to four) on

In SPI IT-VIEW mode: Press A. V. 4 or > to select a baby unit. Press to view the selected baby unit temporarily in SINGLE-CAM mode. It returns to SPLIT-VIEW mode after



Zoom Press PATROL to switch to PATROL mode You can zoom in or out while viewing imag if you are in SINGLE-CAM mode, and vice from baby unit in SINGLE-CAM and PATROL mode

Talk

10 seconds



You can use the TALK function of the parent unit to comfort your baby in SINGLE-CAM and PATROL mode. Press and hold TALK on the parent unit The TALK light turns on.

Speak towards the microphone on the parent unit. Your voice is broadcast to the

aby unit. 3. Release the TALK key to stop the

personal computers, kitchen appliances and cordless telephones.

broadcast The TALK light goes off

17. This product should not be placed in any area I'ms product should not be placed in any area where proper ventilation is not provided. Slots and openings in the back or bottom of this product are provided for ventilation. To protect them from overheating, these openings must not be blocked by placing the product on a soft surface such as a bed, soft or rug. This product should never be placed near or over a radiator o Precautions for users of implanted cardiac pacemakers Cardiac pacemakers (applies only to digital cordless

devices): Wireless Technology Research, LLC (WTR), an independent research entity, led a multidisciplinary evaluation of the interference between portable wireless devices and implanted cardiac pacemakers. Supported by the U.S. Food and Drug Administration, WTR recommends to physicians that heat register. 18. Never push objects of any kind into this product through the slots because they may touch dangerous voltage points or create a short circuit. Never spill liquid of any kind on the

roduct. o reduce the risk of electric shock, do not isassemble this product, but take it to an

disassemble this product, but take it to an authorized service facility. Opening or re-parts of the product other than specified access doors may expose you to danger voltages or other risks. Incorrect reassen

21. Periodically examine all components for

lamage.

ners, etc

Pacemaker patients

Should keep wireless devices at least six inches from the pacemaker Should NOT place wireless devices directly over the pacemaker, such as in a breast pocket, when it is turned ON. cause electric shock when the product is equently used. WTR's evaluation did not identify any risk to subsequently used. You should test the sound reception every time you turn on the units or move one of the

Electromagnetic fields (EME)

ment to protecting our envi

BBBC[®] and 1 (800) 8 BATTERY

th product complies with all standards electromagnetic fields (EMF). If handled Be aware of possible loss of privacy while using regarding electromagnetic fields (EMF). It handled properly and according to the instructions in this user's manual, the product is safe to be used based on scientific evidence available today. public airwayes. Conversations may be pick up by other nursery monitors, cordless phor

 Children should be supervised to ensure that they do not play with the product. The RBRC[®] seal 24. The product is not intended for use by persons Interproduct is not internated for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for The RBRC® seal on the lithium-ion battery indicates The hold of the second second

SAVE THESE INSTRUCTIONS

Cautions

The RBRC[®] program provides a convenient alternative to placing used lithium-ion batteries in the trash or municipal waste, which may be illega Use and store the product at a temperature between 32°F and 104°F. VTech's participation in RBRC® makes it easy for ween 321+ and 1041+. not expose the product to extreme cold, heat firect sunlight. Do not put the product close to

VTech's participation in RBRC[®] makes it easy for you to drop of the spent battery at local retailers participating in the RBRC[®] program or at authorized VTech product service centers. Please call **1 (800) 8 BATTERY[®]** for information on Li-ion battery recycling and disposal bans/restrictions in your area. VTech's involvement in this program is a heating source. Batteries should not be exposed to excessive heat such as bright sunshine or fire. Make sure the baby unit(s) and the adapter cord(s) are always out or reach of the baby, at least 3 feet away from the baby or crib, to avoid a a heating source

art of its comm possible strangulation hazard. Never place the baby unit(s) inside the baby's crib or playpen. Never cover the baby unit(s) or parent maypen, rever cover the baby unit(s) or pain init with anything such as a towel or a blanket

are registered trademarks of the Rechargeable Battery Recycling Corporation. Other electronic products may cause interference with your baby monitor. Try installing your baby monitor as far away from these electronic devices as possible eless routers, radios, cellular telephones

Press SPLIT to enter the SPLIT-VIEW mode. Set alert tone Low battery tone

press SELECT

No link alert

press SELECT to confirm your sel

. Press MENU when the parent unit is idle.

Press ▼ or ▲ to choose Alert Tone, then press SELECT to select.

Press SELECT to select.
 Press ▼ or ▲ to choose Sound alert in split-view, then press SELECT.
 Press ♥ or ▲ to choose On or Off, then press SELECT to confirm your selection.

The sound alert feature is only available in SPLIT-VIEW mode.

FCC and IC regulation

FCC Part 15 This equipment has been tested and found to comply with the requirements for a Class B digital down under FCC 16 de Testederi Communications interado to provide reasonable protection against interado to provide reasonable protection against mediate the second second second second second testederic second second second second testederic second second second testederic second second second testederic second testederic

llowing measures: Reorient or relocate the receiving antenna

Increase the separation between the equipment and receiver.
 Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

To ensure safety of users, the FCC has established criteria for the amount of radio frequency energy

that can be safely absorbed by a user or bystar according to the intended usage of the product product has been tested and found to comply v

and used such that parts of all persons' body are maintained at a distance of approximately 8 in (20 cm) or more. The transmitter and antenna of parent unit shall be held at least 1 in (2.5 cm) from

This Class B digital apparatus complies with

Canadian requirement: CAN ICES-3 (B)/NMB-3(B)

he FCC criteria. The baby unit shall be ins

your face

Sound alert in split-view

ic loct

(PNOTE

FCC Part 15

SPUT

Press PATROL to enter PATROL mode

Press SPLIT to return to the mode (SINGLE-CAM or PATROL) used before

The parent unit is muted while in SPI IT-VIEW

Press and hold ▲, ♥, ◀ or ► to move the

zoomed image upward, down or rightward correspondingly.

Press @ again to zoom out

entering SPLIT-VIEW mode.

Your baby unit monitors the temperature of our baby's room with its built-in temperature You can set the parent unit to beep when the parent unit operates in low battery condition. isor. If the detected temperature is outside . Press MENU when the parent unit is idle. of the preset temperature range, the parent unit will display alert message. 2. Press V or A to choose Alert Tone, then Set temperature range

3. Press SELECT again to choose You can set the desired room temperature alert range. The minimum temperature can b set between 52 °F (11 °C) and 69 °F (20 °C). Press SELECT again to choose Low Battery Tone.
 Press ♥ or ▲ to choose On or Off, then press SELECT to confirm your selection The maximum temperature can be set between 70 °F (21 °C) and 86 °F (30 °C). 1. Press MENU when the parent unit is idle.

You can set the parent unit to been when the link between the parent unit and the baby unit 2. Press ▼ or ▲ to choose Temperature, then 1 Press MENU when the parent unit is idle

press SELECT. 3. Press ♥ or ▲ to choose Minimum or Maximum, then press SELECT. 4. Press ♥ or ▲ to choose ALL CAM or CAM #, then press SELECT. Press ▼ or ▲ to choose Alert Tone, then press SELECT Press ♥ or ▲ to choose No Link Alert, then press SELECT. 5. Press ▼ or ▲ to choose the desire 4 Press ▼ or ▲ to choose On or Off then minimum or maximum temperature, then press SELECT to confirm your selection.

Temperature alert tone

Monitor the temperature

You can turn on the sound alert feature so that, while in SPLIT-VIEW mode, the parent unit beeps and displays Sound detected at CAM # whenever the baby unit detects sounds. You can turn on the temperature alert tone so that the parent unit will emit an alert tone if the detected temperature is out of range. Press MENU when the parent unit is idle. Press ▼ or ▲ to choose Temperature, then press SELECT. Press ▼ or ▲ to choose Alert Tone, then press SELECT. 4. Press ♥ or ▲ to choose ALL CAM or CAM #, then press SELECT. Press ♥ or ▲ to choose On or Off, then press SELECT to confirm your selection Temperature format You can choose to display the temperature in

Fabrenheit (°F) or Celcius (°C) 1 Press MENII when the parent unit is idle Press ♥ or ▲ to choose Temperature, then press SELECT. 3. Press ▼ or ▲ to choose Format, then press SELECT Press ▼ or ▲ to choose Fahrenheit or Celsius, then press SELECT to confirm

This device complies with Industry Canada licence-exempt RSS standard(s).

peration is subject to the following two conditions:) this device may not cause harmful interference,

and (2) this device must accept any interference, ncluding interference that may cause undesired

operation. The term "IC:" before the certification/registration number only signifies that the Industry Canada technical specifications were met. This product meets the applicable Industry Canada technical specifications.

The baby unit complies with ECC BE radiation

order accessories may not ensure compliance with FCC RF exposure guidelines. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment complies also with Industry Canada RSS-102 with respect to Canada's Health Code 6 for Exposure of

RF radiation exposure statement

Humans to RE Fields

Industry Canada

Turn on or off the vibration You can turn on the vibration feature so that a carrian on the vibration leature so that a parent unit vibrates when it receives any o Low battery tone No link alert Sound alert in split-view or Temperature alert after turning on the respective alert tones.

1. Press MENU when the parent unit is idle Press ▼ or ▲ to choose Vibration, then press SELECT Press ♥ or ▲ to choose On or Off.

4 Press SELECT to confirm your selection Rename the baby units

You can rename each baby unit. Once the baby unit is renamed, its new name together with the baby unit number will appear in the sub-menu of below options: Sensitivity
 Rename

Temperature
 Pair/Unpair

1. Press MENU when the parent unit is idle. Press ♥ or ▲ to choose Rename, then press SELECT

 SELECT.
 Press ▼ or ▲ to choose the desired baby unit, then press SELECT.
 Press ▼ or ▲ to choose the desired name for the baby unit, then press SELECT to confirme an end with the press SELECT to confirm your selection

Night vision

NIGNT VISION The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the baby unit being viewed detects low light levels, the infrared LEDs are switched on automatically. The images from this baby unit is in black and white, and J RNOTES It is normal if you see a short white glare on you parent unit screen as the baby unit is adapting t

when the infrared LEDs are on, the image is in black and white. This is normal due to external linht sources. **N**TIP

Depending on the surroundings and other interfering factors, like lightings, objects, colors and backgrounds, the display resolution may vary. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display

For cETL compliance of

Mesures de sécurité importantes

Mesures de sécurité importantes Lorque vous utilise voite appareil, vous devrie toujours suivre certaines mesures de précaution de lasse afin de réduite les risques de foncertie, eux qui suivret: 1. Observez obtes les instructions et mises en garde inscrites sur fappareil. 2. L'installation par un aduite est requise. 3. Ce produit a été conçu pour être un dispositi d'apport esdement. Il n'est pais le remplacem

d'une supervision responsable et adéquate par un adulte et ne devrait pas être utilisé comme telle. The baby unit complex with FCC HF radiation xposure limits set forth for an uncontrolled nivronment. The baby unit should be installed and perated with a minimum distance of 8 in (20 cm) etween the baby unit and all persons' body. Use of ther accessories may not ensure compliance with Ce produit n'est pas conçu pour être utilisé en tant que moniteur médical.

tard que monteur messar pues entre utilité en 5. Multiser para ce que la terra de la terra ri de torne balgiones, con a la testavé, deré de cualina, dans un bausad humide ou une doubré. MISE EN AGNET i pod y avait de la terra de dans un bausad humide ou une doubré. MISE EN AGNET i pod y avoir en réspen d'argonolos ni vous allistes (en manuels type de réspectoris ni vous allistes (en manuels type de terra de la terra de la terra de la teory de la terra bible pièse (enterna de la teory de la teory de la teory bible pièse (enterna de la teory de la teory

es piles usées selon les renseignements suivant s sceu du RBRC[®].

California Energy Commissio battery charging testing mod N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur dont la prodult. L'utilisation d'un adaptateur dont la polarité ou la tension serait inadéquate risque d'endommager sérieusement le produit et met votre sécurité en péril. Adaptateur de l'unité du bébé : Sortie : 5 V CC 1A Adaptateur de l'unité du parent : Sortie : 5 V CC 1A

This baby monitor meets the California Energy consumption. Your baby monitor is set up to comply with the energy-conserving standards right out of the box. sion (CEC) regulations for energy

Follow the instructions to install and charge the battery. The CEC battery charging testing mode is Lorequ'ile cont branchée dans une price de

ated while charging Even if the parent unit is paired to baby units, the CEC battery charging testing mode is activated w it is powered off and charging.

Lorsqu'ils sont branchés dans une prise de courant, les adgatateurs secteur ont été conçus pour être orientés correctement, soit à la verticale ou au plancher. Les broches n'ont pas été conçues pour supporter le poids du bloc d'alimentation et le mainterim en place si celuici est branché dans une prise au plafond, sous une table ou dans un meuble.

- Pour les PRODUITS À BRANCHER À UNE PRISE DE COURANT, la prise de courant doit être installée près du produit, afin d'assurer une accessibilité sécuritaire à la prise de courant.
 - Débranchez ce produit de la prise de courant avant de procéder au patrouage. N'utilisez pa uvarin de procéder au nettoyage. N'utilisez pas de nettoyants en aérosols. Utilisez un chiffon humide pour le nettoyer.
- pour le nettoyer. 11. Débranchez les cordons d'alimentation avant de remplacer le bloc-piles. 12. Ne coupez pas les cordons d'alimentation pour remplacer les fiches, car ceci peut présenter un

oflow these guidelines: Avoid putting it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps). DO NOT expose it to direct sunlight or moisture. DO NOT expose it to direct sunlight or molsture.
 Avoid dropping the product or treating it roughly.
 Clean with a solt cloth.
 DO NOT immerse the parent unit and the baby unit in water and do not clean them under the taby.
 DO NOT use cleaning spray or liquid cleaners.
 Make sure the baby unit and parent unit are dry before you connect them to the mains again. When you are not going to use the baby monitor for some time, remove the rechargeable battery from the parent unit. Store the parent unit, the baby unit and the adapters in a cool and dry place.

Add new baby unit (VM306)

The baby units and parent unit provided are

The baby units and parent unit provided are already paired. You can add or replace any baby units (VM306, purchased separately) to your video and audio monitor system. You can pair a maximum of four baby units to your parent unit.

neral product care

To keep this product working well and looking good,

For more details, refer to the user's manual that comes with your VM306 new baby unit

room, the surroundings and oti interfering factors, like lightings objects, colors and background may affect the image quality or your parent unit screen. Adjust the baby unit's angle or place the baby unit's angle or place the baby unit at a higher level I prevent glare and blurry display Ne laissez aucun objet reposer ni appuyer sur le cordon d'alimentation. N'installez pas cet appareil dans un endroit où l'on risque d'écrase le cordon d'alimentation ou de le piètiner. Mises en garde

Utilisez et entreposez le produit à une température entre 0° C (32°F) et 40°C (104° F)

equently <u>asked questio</u>

Below are the questions most frequently asked about

the baby monitor. If you cannot find the answer to your question, visit our website at www.vtechphones.com or contact 1 (800) 595-9511 for customer service.

. Disconnect the power to the baby units and the parent units

. Remove the batteries in the parent unit. Then install the batteries

Wait unit. Then install the batteries again. Use Wait a few seconds before connecting power back to the baby units and the parent unit. Turm on the baby units and the parent unit.

parent unit. Wait for the parent unit to synchronize with the baby units. Allow up to one minute

Perhaps the parent unit is not

e appliance plug into the pare it and put the adapter in a w

init and put the adapter in a wa socket. Then press and hold o switch on the parent unit and o setablish connection with the

Perhaps the baby unit is not

he baby unit to the mains. The set the ON/OFF switch to ON

o switch on the baby unit and sestablish connection with the arent unit.

Make sure the battery is correctl installed in your parent unit.

fou may have used the battery or a long time. Replace a new

The screen is in black and whit

uring nighttime or in a dark com. This is normal due to xternal light sources.

During nighttime or in a dark room, the surroundings and other

Make sure the power is not controlled by a wall switch.

this to take place.

by unit

Why don't

light of the

go on when I

Why doesn't my parent un charge while connected to

Why is m

screen in black and white?

Why do I get

behv at night

Why does the baby monitor listed) for common cure:

Why does the

Why does the

The ON/OF

ght on the aby unit

he parent unit and baby units

Move the parent unit away from the baby units until the

Turn down the volume of you parent unit.

oser to the baby units (but not ss than 3 feet).

e provided battery, it may sve enough charge for the

Charge the battery in the parent unit for up to 3 hours.

If your parent unit is in SPLIT-VIEW mode, some of you baby units may detect sounds.

e temperature of your baby's om may be too high or too low.

The baby unit is unpaired from the parent unit. Follow below steps to pair the baby unit. Make sure both parent unit and baby unit are on before pairing.

it are on before pairing. Press MENU when the paren unit is idle. Press ▼ or ▲ to choose Pair/Unpair CAM, then press SELECT.

SELECT. Press SELECT again to choose Pair CAM. Press V or A to choose an empty baby unit slot, then press SELECT. The parent unit screen displays Press

unit screen displays Press and hold the pair button at the CAM for 5 seconds until the power indicator

Immediately press and hold PAIR on the bottom of the

baby unit with a narrow nointed object such as a

paired baby unit in SINGLE-CAM mode. The LED light on the new baby unit remains on

If pairing fails, the screen displays Pairing failed. Try the

Only one baby unit can be paired at a time.

Limited warrant

and Canada

What does this limited warranty cover?

What does this limited warranty cover? The manufacture of this VTceh Product warrants to the holder of a valid proof of purchase ("Consumer" or "you") that the Product and all accessories provide in the sales package ("Product") are provided in the Product and all accessories provide the Product and all accessories provide on the Product and all accessories provide the Product and all accessories provide the Product and and conditions, when installed and used normality and in accordance warranty extends only to the Consumer for Product parchased and used in the Dinte Sales of Americ

What will VTech do if the Product is not free from

defects in materials and workmanship during the limited warranty period ("Materially Defective Product")2

During the limited warranty period, VTech's

authorized service representative will repair or replace at VTech's option, without charge a Materially Defective Product. If we repair the Product, we may use new or refurbishe replacement parts. If we choose to replace

How long is the limited warranty period?

90 days from the date the repaired or repla Product is shipped to you or (b) the time re on the original one-year warranty; whichev longer.

This limited warranty does not cover

What is not covered by this limited warranty?

1. Product that has been subjected to misuse.

replacement parts. If we choose to replace the Product, we may replace it with a new or refurbable Product of the same or similar design. We will Repair or replacement of the Product, at VTech will repair or replacement of the Product, at VTech will return the repaired or replacement Products to you in working condition. You should expect the repair or replacement to lake approximately 30 days.

The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase. If VTech repairs or replaces a Materially Defective Product under the terms of this limited warranty, this limited warranty,

nited warranty also applies to the repaired lacement Product for a period of either (a)

pointed object such as a pencil. The LED light flas

When pairing is successful, t

The baby units may be out of range. Move the parent unit

the parent unit is pow

 N'exposez pas cel appreil à des trois ou des chaleurs extrêmes, ainsi qu'à la lumière directe du soleil. Ne l'installez pas près d'une source de chauffage.
 Le bloc-piles ne doit pas être exposé à la te cordon d aimentation ou de la pleatiner. 14. Ne faites fonctionner cet appareil qu'avec le type d'alimentation indiqué sur l'étiquette. Si vous ne connaissez pas le type d'alimentation que vous possédez à votre domicile, consultez votre marchand ou votre compagnie locale d'électricité. Ne surchargez pas les prises de courant murales ni les rallonnes électriques ou su feu Assurez-vous que le moniteur et le cordor

de l'adaptateur sont toujours hors de portée des enfants, à au moins 1 mètre (3 pieds) de l'enfant ou du berceau, pour éviter tout risqui Ne placez pas cet appareil sur un chariot, meuble, trépied, support de montage ni table meuble, tépied, support de montage ni tibble chancelants. Les troues et ouvertures du boliter, situés à l'antrés de l'agraphie du saux celuis, sevent à rainte de l'agraphie du saux celuis, sevent à ne bloquez sous aucun prétente ces ouvertures et nempéchez pas fariation adquite de l'appareil en le plaçant sur uil d'avan, tapis o uote aute surface santaire. De mêne, ne le source de chaleuro ou d'un catoritere. De plas, par place pas l'appareil dans un endorit avant de vous assure raj'ni y ait une bonne circuitaton dan. Ne iamais placer le moniteur à l'intérieur du Ne jamais placer le monteur a inteneur du berceau ou du par de bêbé. Ne jamais couvrir le moniteur ou l'unifé (s) portative avec un article tel une serviette ou une couverture. D'autres équipements électroniques peuvent produire des interférences sur votre moniteur vidéo et audio. Tentez d'installer votre moniteur vidéo ou audio à l'écart des appareils électroniques tels que des routeurs sans fil, artins téléphones caludaires intemboner.

moniteurs, téléphones, ordinateurs pers électroménagers et téléphones sans fil. N'enfoncez jamais d'objets à travers les ouvertures de cet appareil, car ils pourra

ouvertures de cet appareil, car ils pourraient entrer en contact avec des points de tension dangereux ou causer des courts-circuits qui peuvent déginérer en incendies ou en risques d'électrocution. Ne renversaz jamais de liquide dans ce produit. Alin de réduire les risques d'électrocution, ne démontez pas cet appareil, mais apportez-le

Avis aux détenteurs de stimulateurs cardiaques

Vous devriez maintenir les dispositifs sans fil à au moins six pouces du simulateur cardiague. Ils ne doivent PAS placer le téléphone sans fil en marche. L'étude effectuée par l'organisme WRS n'a pas

dentifié de risque pour les détenteurs de simulateur cardiaques causés par les gens qui utilisen dispositifs sans fil à proximité de ceux-ci.

Le produit n'est pas conçu pour être utilisé par des personnes (incluant des enfants) aux capacités physiques, sensorielles ou mentale Champs electromagnetuques (EMP) Ce produit de VTech est conforme à toutes les normes se rapportant aux champs électromagnétiques (EMP) standard. Si vous le manipulez correctement en suivant les instructik de ce guide, son utilisation sera sécuritaire pent de nombreuese années, selon les meilleures capacités physiques, sensorielles ou mentales réduites ou qui manquent d'expérience et de connaissances, à moins qu'on leur ait donné suffisamment de supervision ou d'instructions relativement à l'utilisation de l'appareil par une des para actuels de la para des terretter terretter sensor actuels de la para des terretter te

personne responsable de leur sécurit CONSERVEZ CES INSTRUCTIONS évidences scientifiques dont nous disposons

Stimulateurs cardiaques implantés dans Forganisme Les simulateurs cardiaques (ne s'applique qu'aux dispositifs numériques sans fil) : L'organisme Wireless Technology Research, LLC (WTR), une time de recherche indépendante, a mené une évaluation pluridisciplinaire des interférences entre les téléphones sans fil portatifs et les stimulateurs cardiaques implantés dans l'organisme. Appuyée par l'Administration des aliments et drogues (FDA) des États-Unis, la firme WTR recommande aux médecins:

directement sur le stimulateur cardiaque, tel que dans une poche de chemise, lorsque celui-ci est

accident, shipping or other physical damage, improper installation, abnormal operation or handling, neglect, inundation, fire, water or other liquid intrusion; or 2. Product that has been damaged due to repair. Champs électromagnétiques (EME)

 Product that has been carningted use to repain, alteration or modification by anyone other than an authorized service representative of VTech; or
 Product to the extent that the problem experienced is caused by signal conditions, network reliability. is caused by signal conditions, r or cable or antenna systems; or

Product to the extent that the problem is caused by use with non-VTech accessories; or
 Product whose warrantv/quality stickers. product

ou may have set the sound

Why does th

frequently in

Why does the parent

Why don't I hear a sound/

Why can't I hear my bab

connection Why is the

connection lost every now and then? Why are there sound interruptions?

Isitivity level to Highest v sound alert (and vibratic ture are turned on. The p t notifies you of all sound luding background noise eps (or vibrations). Adjust When using your equipment, basic safety precautions should always be followed to reduce the risk of fire, ound sensitivity to a lower leve electric shock and injury, including the following: The baby unit also picks up othe sounds than those of your baby. Adjust the sensitivity level to a lower level or adjust the speaker volume on the parent unit. Follow all warnings and instructions marked on Adult setup is required. This product is intended as an aid. It is not a substitute for responsible and proper adult supervision and should not be used as such The parent unit speaker volum may be too low or off. Press +/VOL to increase the volume. This product is not intended for use as a medic 5 Do not use this product near water. For example rou may have set a low sound sensitivity level. See Adjust the do not use it next to a bath tub, wash bowl, kitchen sink, laundry tub or swimming pool, or in a wet basement or shower sound sensitivity of the baby unit to set to a higher level. a wet basemient or shower. CAUTION: Use only the batteries indicated in this manual. There may be a risk of explosion if wrong type of battery is used for the parent unit. Use only the supplied rechargeable battery or replacement battery pack (BT0655/BT266555 for the parent unit. Do not dispose of batteries in a fire. They may explode. Dispose of used battery according to the information in **The RBRC⁶** seals on batteries with this expected The baby units may be out of range. Move the parent unit loser to the baby units (but no Other electronic products may cause interference with your bab monitor. Try installing your baby monitor as far away from these electronic devices as possible. Use only the adapters included with this product Incorrect adapter polarity or voltage can seriously damage the product. Baby unit power adapter: Output: SV DC 1A Parent unit power adapter: Output: SV DC 1A. The power adapters are intended to be correctly oriented in a vertical or floor mount position. The prongs are not designed to hold the plug in place if it is plugged into a ceiling, under-the-table or

capitet outlet. For pluggable equipment, the socket-outlet shall be installed near the equipment and shall be easily accessible

easily accessible. 10. Unplug this product from the wall outlet before cleaning. Do not use liquid or aerosol cleaners Use a damp cloth for cleaning. 11. Unplug the power cords before replacing

batteries.
 Do not cut off the power adapters to replace them with other plugs, as this causes a hazardous situation.

hazardous situation. 13. Do not allow anything to rest on the power cords. Do not install this product where the cords may be walked on or crimped. 14. This product should be operated only from the time of enume neuros indicated on the marking.

type of power source indicated on the marking label. If you are not sure of the type of power supply in your home, consult your dealer or loca

power company. 15. Do not overload wall outlets or use an extension

Do not place this product on an unstable table, shelf, stand or other unstable surfaces.

Limitations: Implied warranties, including those of fitness for a particular purpose and merchantability (au unwritten warranty that the Product is fit for ordinary use) are limited to one year from the date of purchase Some states/provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you. In on event shall limitation may not apply to you. In no event shall VTech be liable for any indirect, special, incidental, consequential, or similar damages (including, but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of substitute equipment, and claims by third parties) resulting from the use of this Production or limitation of provinces do not allow the exclusion or limitation

cidental or consequential damages, so the abov nitation or exclusion may not apply to you. Please retain your original sales receipt as proo of purchase.

chnical specifications Frequency Crustal controlled PLL synthesizer Transmit Baby unit: 2406 - 2475 MHz Parent unit: 2406 - 2475 MHz frequency Channels 24 4.3" Color LCD (WQVGA 480x272 pixel)

Maximum power allowed by FCC and IC. Actual operating range ma vary according to environmental conditions at the time of use.

Parent unit: 3.7V Li-polymer batter Baby unit power adapter: Output: 5V DC @ 1A

Parent unit power adapter Output: 5V DC @ 1A

or amicuity; and 2. Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or receipt; and 3. Provide your name, complete and correct mailing address, and telephone number. Credite-The Background Noise sound file was created by Carolin Ford, and is used under the Creative Commons license. The Stream Noise sound file was created by Caroline Ford and is used under the Creative Commons license.

Other limitations Other limitations This warranty is the complete out settistive This warranty is the complete of the transmission all other within or oral communications related to this product. Utch for yourkers no deriv warrantelles for this product. The product on other warrantelles for this product. The product of the setting of the product. These are no other express warranties. No one authorized to make modifications is this limited warranty and your setting the product of the product. These are no other express warranties. No one authorized to make modifications is the limited warranty and your specific lengt rights. The warranty drives you specific lengt rights, and you may also have other rights. Wich way from table to table or province to province. The Crickets At Night sound file was created by Mike Koenig and is used under the Creative Commons license.

serial number plates or electronic serial numbers have been removed, altered or rendered illegible;

Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or

used for rential purposes); or 7. Product returned without a valid proof of purchase (see item 2 on the next page); or 8. Charges for installation or set up, adjustment of customer controls, and installation or repair of systems outside the unit.

How do you get warranty service? To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or call 1 (800) 267-7377.

www.vtechcanada.com or call (800) 287-7377. MOTE: Bedroc ealing for service, jaces erview the user's manual - a check of the Product's controls and features may area you as ervice call, smith transportation and are responsible for delivery or handling changes incurred in the transport of the rangened or regissed Product under this limited warranty, ransportation, delivery or handling changes are prejaid. VTech Product under this limited warranty, ransportation, delivery or handling changes are prejaid. VTech South Change the product of the this product on the transport of the similar is not covered by this limited warranty, or pool of purchase does not meet the terms of the limited

is not covered by this infined warranty, or proof of purchase does not meet the terms of this limited warranty, VTech will notify you and will request tha you authorize the cost of repair orior to any further

you authorize the cost of repair prior to any jurner repair activity. You must pay for the cost of repair and return shipping costs for the repair of Products that

What must you return with the Product to get

varranty service? . Return the entire original package and contents including the Product to the VTech service

ocation along with a description of the malfunction or difficulty; and

How do you get warranty service?

Æ

Specifications are subject to change without no @ 2016 for VTech Communications, Inc. All rights reserved. 02/16. VM346-X_CIB_V1.0

démontez pas cel appareil, mais apportez-le dans un centre de service autorisé. L'ouvertur du bolitier ou le retrait de toutes pièces que contient cet appareil, à l'exception de faccès autorisé à certaines portes ou ouvertures, risque de vous exposer à des points de tensio dangereux ou d'autres dangers. Un remontage incorrect peut par la suite présenter des risque d'électriocution. d'électrocution.
20. Vous devriez tester la réception chaque fois que vous mettez l'appareil en fonction.
21. Examinez les composantes afin de vérifier si celles-ci ne sont pas endommagées. celles-ci ne sont pas endommagées.
22. Soyez avisé de la perte de la confidentialité lorsque vous utilisez les ondes publiques. Les conversations peuvent être entendues par d'autres moniteurs de bébé, des téléphones sans fil, des scanneurs, etc.

Les enfants devraient être supervisés afin de vous assurer qu'ils ne jouent pas avec l'appa