

All-In-One POS



POS HK570F

Key Features

- ✓ Low-Profile, foldable base, die-cast aluminum housing for high reliable ;
- ✓ With compact footprint and sleek design elements ;
- ✓ Carries the full suite of multiple ports: USB2.0&USB3.0, Serial, Cash Drawer and Network LAN ;
- ✓ Multiple Height Adjustments and VESA mount Capability ;

Model Name	HK570F
Processor	Intel Bay Trail Celeron Quad core J4125, 2.0 GHz up to 2.7 GHz
Chipset	CPU Integrated
System Memory	SO-DIMM DDR4 2400MHz 4GB, up to 8GB
Display Panel	15 "TFT LCD (LED back light) /4:3 /resolution: 1024 x 768 (optional) Brightness :400 cd/m ²
Touch Screen	True flat Capacitive Touch screen
Hard disk	SATA SSD 64GB, up to 256GB
	SATA HDD 2.5 inch 500GB
Power supply	Adapter (DC 24V 2.5A)
I/O ports(standard)	4* USB 2.0; 4* USB 3.0(6 Rear ,2 Front)
	3* RJ48 COM Ports (COM4 is optional power input for VFD)
	1* RJ45 100M/1000M Gigabit LAN
	1*VGA
	1*12V DC Output for second screen
	1*Audio,3.5mm
	1*24V RJ11 for Cash drawer (support dual cash drawer)
Standard Peripherals	2x3W,8Ω Speaker
Optional Peripherals	3 tracks MSR (single MSR, OPOS)
	3 tracks MSR+RFID (multi-function card reader, OPOS)
	15" LED Second Display (Touch/ non-touch)
	Fingerprint Reader
EMC & Safety	FCC, Class-B/CE, Class-B/ RoHS
Operating Environment	0°C - 40°C/20%-80%WIF RH non-condensing

All product specifications are subject to change without notice.

Storage Environment	-20°C - 60°C/10%-90% RH non-condensing
Equipment Textures	Main Unit: Die-casting aluminum; I/O Cover: Plastic
Color	Black
Tilt Adjustment	0°- 60° (Vertical)
Dimension (WxDxH)	400 × 250 × 330 mm
Weight	11KG
OS Supported	Windows 10/Linux

Disclaimer: This product specification is subject to change without prior notice.

FCC Requirement

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.