



ECEN ELECTRONICS CO., LTD.

原盛電子股份有限公司 **SEN RUN**

No. 32-1, Lane 38, Li-Der St., Taiping City, Taichung, Taiwan 411

Tel : 886-4-2395-6895 / 2395-1231 / 23952371

Fax: 886-4-2395-3815

Http:// www.ecen.com.tw

EMAIL: ecen@ms8.hinet.net

SPECIFICATION of Assistant listening System

MODEL	ET-218S-2/ER-218S-2
Microphone type	Condenser microphone
Oscillation mode	Crystal synthesized
Carrier Frequency Range	174.4-213.4 MHz
S/N ratio	80dB OVERALL
Spurious	<-50dBc
Power Requirement	10mW
Bandwidth	Max 150KHz
Current consumption	25mA
Stability	<0.005%
T.H.D	LESS THAN 0.5% (AT 1 KHz)
Frequency response	50KHz-15 Hz(+/-3dB)
Antenna	Built in
Battery	1.5V*2 (UM-4)
Weight	60 G