

POS	EDX-13 PARTS LIST
R1	0.47O 1/2W FUSING RESISTOR
R2 R3	470KO 1/4W CARBON FILM RESISTOR
R4	NONE
R5,R6	2.7O 1/4W CARBON FILM RESISTOR
R7	NONE
C1,C2	0.1µF 250V ±10% POLYEST FILM CAPACITOR
C3	NONE
C4	0.1µF 400V ±10% POLYEST FILM CAPACITOR
C5	10µF 200V ELECTROLYTIC CAPACITOR
C6	0.1µF 50-100V ±10% POLYEST FILM CAPACITOR
C7	6800PF 1KV ±5% POLYP. FILM CAPACITOR
C9, C10	820PF 1KV ±5% CERAMIC CAPACITOR
D1-4, D6	IN4005 DIODE
D5	NONE
D7	DB3 DIAC
Q1 Q2	13003 TRANSISTOR
L1	2mH FILTER CHOKE CORE:DR3V WIRE INSULATION: POLYURETHANE BASECOAT ONLY ANSI MW 79 TYPE VARNISHES: DOLPH BC-363
L2	0.7 mH INDUCTOR CORE: R2KDP WIRE INSULATION: POLYURETHANE BASECOAT ONLY ANSI MW 79 TYPE BOBBIN: VALOX 451E-1001 TAPE: 3M NO. 5 VARNISHES: DOLPH BC-363
T1	BASE DRIVE TRANSFORMER CORE: 572480 WIRE INSULATION: TEFLON MISCELLANEOUS
PCB	MATERIAL : R8700
WIRE	18AWG STYLE 1569 105 DEG
HOUSING	MATERIAL: G.E. LEXAN 943