

## Hop Sequence Example

The following table presents sequence of transmitted frequencies.  
This table is an example only because the frequencies are randomly changed according to a frequency-hopping algorithm.

No	Frequency (MHz)
1.	907.8
2.	904.2
3.	909.6
4.	906.6
5.	910.8
6.	906.0
7.	904.8
8.	907.2
9.	913.2
10.	913.8
11.	914.4
12.	912.0
13.	905.4
14.	909.0
15.	911.4
16.	910.2
17.	918.0
18.	915.6
19.	917.4
20.	918.6
21.	912.6
22.	908.4
23.	916.2
24.	919.2
25.	922.2
26.	920.4
27.	923.4
28.	922.8
29.	921.0
30.	915.0
31.	924.6
32.	907.8
33.	924.0
34.	921.6
35.	925.8
36.	904.2
37.	925.2
38.	919.8
39.	906.0

40.	906.6
41.	914.4
42.	909.6
43.	904.8
44.	912.0
45.	905.4
46.	913.2
47.	907.2
48.	911.4
49.	917.4
50.	910.2
51.	918.0
52.	912.6
53.	908.4
54.	913.8
55.	916.2
56.	909.0
57.	910.8
58.	923.4
59.	916.8
60.	922.2
61.	915.0
62.	915.6
63.	907.8
64.	924.0
65.	919.2
66.	921.0
67.	925.8
68.	919.8
69.	920.4
70.	922.8
71.	918.6
72.	909.6
73.	904.2
74.	925.2
75.	921.6
76.	905.4
77.	906.6
78.	906.0
79.	904.8
80.	910.2
81.	912.0
82.	911.4
83.	908.4
84.	913.2
85.	907.2
86.	913.8
87.	912.6

88.	914.4
-----	-------