

## **Operation Manual for KFTX100 Remote Control Tracker**

### **Introduction:**

To press the button on the transmitter of KFTX100, the receiver will have the Bi-Bi sound to indicate the location of the object that is to be tracked.

### **Learning Mode:**

After the battery insert into the receiver, immediately press & hold the button of the transmitter within 3 seconds to get into the learning mode. When hear the Bi-Bi sound, the learning mode is complete.

### **Operation:**

1. Once the learning mode complete, the receiver will be into the searching mode. If it doesn't find any signal from transmitter in 5 seconds, it will automatically turn into the sleeping mode.
2. To wake up the receiver, please press & hold the transmitter button for 3 seconds and the receiver will have 3 Bi-Bi sounds at the same time. After hearing the Bi-Bi sound, the receiver is waked up.
3. Without finding the receiver, you have to continuously press the transmitter button with in every 5-second to keep looking.
4. If there's no any continue action within 5 seconds after the pervious press, the receiver will go back to sleeping mode. So, in order to keep tracking, please press the transmitter button one more time for 3 second to wake up the receiver.

**\*\*The longest remote control distance is 6 meters ~ 10 meters. (The effective range will subject to the environment.)**

Notice : The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

THIS DEVICE COMPLIES WITH PART 15 OF THE  
FCC RULES. OPERATIONS IS SUBJECT TO THE  
FOLLOWING TWO CONDITIONS: ( 1 ) THIS DEVICE  
MAY NOT CAUSE HARMFUL INTERFERENCE AND  
( 2 ) THIS DEVICE MUST ACCEPT ANY INTERFERENCE  
RECEIVED, INCLUDING INTERFERENCE THAT MAY  
CAUSE UNDESIRE OPERATION