

Instruction Manuel

Introduction:

1. The code duplication of each set of this light control unit (one remote + one receiver) will be duplicated before shipping. This means the transmitter doesn't require to program first before using.
2. The receiver of this unit can be used with 4 transmitters (the same as the original ones) at one time.
3. If you loose your transmitter and get a new one, or you wish to use more than one remote control to operation one receiver, please follow the instruction listed below to duplicate the code to the new transmitter before using.
4. Remember it takes 4 times to press the button of the remote control(s) in total for a complete duplication

Operation for duplicating one extra remote control besides the original remote which comes along with the receiver. This means that you wish to use two remote controls to control the same light(s). At this time both the original remote control and the extra one must RE-PROGRAM together. Please note.

1. Unplug jumper from the receiver..
2. Power off the receiver for at least 5 seconds, the plug the power back again.
At this time, the light(s) which connects to the receiver will all be on for only as short as 6 seconds before it (they) goes off. You will have to start step #3 before the light(s) goes off.
3. Press one of the buttons on the original remote control once (it could be the bigger button or the smaller button), the light(s) which connects to the receiver will be flashing twice.
4. Press the same button on the original remote control again, the light(s) which connects to the receiver will be flashing three times.
5. Press one of the buttons on the extra remote control (it could be the bigger button or the smaller button) for the third time, the light(s) which connects to the receiver will be flashing 4 times .
6. Press the same buttons on the extra remote control for the 4th time,

the light(s) which connects to the receiver will be off.

Please be noted that it doesn't matter, which remote control you start programming from step 3 to step 6. But please make sure that one of the buttons of each remote will be pressed/programmed at least once during the programming process.

7. This remote control is duplicated completely

8. Plug the jumper back to the receiver.

You can start using this remote to control your light(s) together with the original one..

Operation for duplicating extra 2 or 3 remote controls, this means that you wish to use 3 or 4 remote control (including the original one) to control the same light(s) at the same time.

1. Repeat step 1 and 2 mentioned as above.

2. Repeat step 3 to step 5 as duplicating one extra remote mentioned above for programming, but make sure that one of the buttons on each of the remote control which wants to be duplicated must be (pressed) /programmed at least once.

Repeat step 7 and 8 listed above.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) This device must accept any interference received, including interference that may cause undesired operation.

Note: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the users's authority to operate the equipment.