

6 Randolph Way Hillsborough, NJ 08844 Tel: (908) 927 9288 Fax: (908) 927 0728

ELECTROMAGNETIC EMISSION COMPLIANCE REPORT

of

Proforce Debris Blower MODEL: 44538 & 07066

FCC ID: OF7PFB1

December 10, 2008

This report concerns (check one): O Equipment type: TRANSMITTER	riginal grant X Class II change
Company agrees to notify the Commi	es, defer until:(date)
Transition Rules Request per 15.37? If no, assumed Part 15, Subpart B for [10-1-90 Edition] provision.	yes nox unintentional radiators - the new 47 CFR
Report prepared for: Report prepared by: Report number:	THE TORO COMPANY Advanced Compliance Lab 0048-080206-02



The test result in this report IS supported and covered by the NVLAP accreditation

Table of Contents

Report Cover Page1
Table of Contents2
Figures
1. GENERAL INFORMATION
1.1 Verification of Compliance
1.2 Equipment Modifications
1.3 Product Information
1.4 Test Methodology
1.5 Test Facility
1.6 Test Equipment
1.7 Statement of the Document Use7
2. PRODUCT LABELING8
3. SYSTEM TEST CONFIGURATION9
3.1 Justification9
3.2 Special Accessories9
3.3 Configuration of Tested System9
4. SYSTEM SCHEMATICS12
5. RADIATED EMISSION DATA
5.1 Field Strength Calculation13
5.2 Test Methods and Conditions13
5.3 Test Data13
5.4 Occupied Bandwidth15
6. PHOTOS OF TESTED EUT

Figures

Figure 2.1 FCC ID Label	8
Figure 2.2 Location of Label on Bottom of the EUT	8
Figure 3.1 Radiated Test Setup	10
Figure 3.2 Radiated Test Setup, X-Axis	10
Figure 3.3 Radiated Test Setup Y-Axis	11
Figure 3.4 Radiated Test Setup Z-Axis	11
Figure 4.1 EUT Schematics	12
Figure 5.1 Pulse Train Timing	17
Figure 5.2 Occupied Bandwidth	17
Figure 6.1 Front View	18
Figure 6.2 Open View	19
Figure 6.3 Component Side	20
Figure 6.4 Foil Side	21

1. GENERAL INFORMATION

1.1 Verification of Compliance

EUT: TRANSMITTER

Model: 44538 & 07066 (electronically identical)

Applicant: THE TORO COMPANY

Test Type: FCC Part 15C CERTIFICATION

Result: PASS

Tested by: ADVANCED COMPLIANCE LAB

Test Date: 02/19/2008 - 02/29/2008

Report Number: 0048-080206-02

The above equipment was tested by Advanced Compliance Laboratory for compliance with the requirement set forth in the FCC rules and regulations Part 15, subpart C. This said equipment in the configuration described in the report, shows the maximum emission levels emanating from equipment are within the compliance requirements.

The estimated uncertainty of the test result is given as following. The method of uncertainty calculation is provided in Advanced Compliance Lab. Doc. No. 0048-01-01.

	Prob. Dist.	Uncertainty(dB)	Uncertainty(dB)	Uncertainty(dB)
		30-1000MHz	1-6.5GHz	Conducted
Combined Std. Uncertainty u_c	norm.	±2.36	±2.99	±1.83

Wei Li

Lab Manager

Advanced Compliance Lab

Date: December 10, 2008

1.2 Equipment Modifications

N/A

1.3 Product Information

System Configuration

ITEM	DESCRIPTION	FCC ID	CABLE
Product	TRANSMITTER	OF7PFB1	
Housing	PLASTICS		
Power Supply	BATTERY 4.5VDC		
Clock/OSC Freq.	433.87 MHz		
Device Type	Periodic Operation		
RX	DoC		

(1) EUT submitted for grant.

1.4 Test Methodology

Radiated tests were performed according to the procedures in ANSI C63.4-2003 at an antenna to EUT distance of 3 meters.

1.5 Test Facility

The open area test site and conducted measurement facility used to collect the radiated and conducted data are located at Hillsborough, New Jersey. This site has been accepted by FCC to perform measurements under Part 15 or 18 in a letter dated May 19, 1997 (Refer to: 31040/PRV 1300F2). The NVLAP Lab code for accreditation of FCC EMC Test Method is: 200101-0.

1.6 Test Equipment

1.0 Test Equip	110110				
Manufacture	Model	Serial No.	Serial No. Description		Cal Due
				dd/mm/yy	dd/mm/yy
Hewlett-Packard	HP8546A	3448A00290	EMI Receiver	12/01/08	12/01/09
EMCO	3104C	9307-4396	20-300MHz Biconical Antenna	12/02/08	12/02/09
EMCO	3146	9008-2860	200-1000MHz Log-Periodic Antenna	09/02/08	09/02/09
Fischer Custom	LISN-2	900-4-0008	Line Impedance Stabilization Networks	23/08/08	23/08/09
Fischer Custom	LISN-2	900-4-0009	Line Impedance Stabilization Networks	23/08/08	23/08/09
EMCO	6502	2665	10KHz-30MHz Active Loop Antenna	27/02/08	27/02/09
EMCO	3115	4945	Double Ridge Guide Horn Antenna	11/08/08	11/08/09

All Test Equipment Used are Calibrated Traceable to NIST Standards.

1.7 Statement for the Document Use

This report shall not be reproduced except in full, without the written approval of the laboratory. And this report must not be used by the client to claim product endorsement by NVLAP or any agency of the U.S. Government.

2. PRODUCT LABELING

FCC ID: OF7PFB1

This device complies with part 15 of the FCC Rules. Operating is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Fig 2.1 FCC Label (Statement shown in user manual)



Fig 2.2 Location of the Label

3. SYSTEM TEST CONFIGURATION

3.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it). Its antenna is integrated on PCB and the transmission will be deactivated with 5s (or immediately) after the operation button is released.

Testing was performed as EUT was operated continuously. Fresh batteries are used during the test in order to generate maximum emission from EUT.

3.2 Special Accessories

N/A

3.3 Configuration of Tested System

Figure 3.1 and Figure 3.3 illustrate this system, which is tested standing along.



Figure 3.1 Radiated Test Setup



Figure 3.2 Radiated Test Setup – X axis



Figure 3.3 Radiated Test Setup – Y axis



Figure 3.4 Radiated Test Setup – Z axis

4. SYSTEM SCHEMATICS

See attachment.

Figure 4.1 System Schematics

5. RADIATED EMISSION DATA

5.1 Field Strength Calculation

The corrected field strength is automatically calculated by EMI Receiver using following:

$$FS = RA + AF + CF + AG$$

where FS: Corrected Field Strength in dBµV/m

RA: Amplitude of EMI Receiver before correction in dBµV

AF: Antenna Factor in dB/m

CF: Cable Attenuation Factor in dB

AG: Built-in Preamplifier Gain in dB (Stored in receiver as part of the calibration data)

The pulse train timing plots are showed in Figure 5.1.

The maximum average field strength should be 0.3146 of the peak field strength measured. So we use peak value minus 10dB as calculated maximum average field strength.

5.2 Test Methods and Conditions

The initial step in collecting radiated data is an EMI Receiver scan of the measurement range 30MHz - 5GHz using peak detector. IF bandwidth is 120KHz and video bandwidth is 300KHz for measuring 30MHz-1GHz. Both bandwidths are 1MHz for above 1GHz measurement.

5.3 Test Data

Test Personnel:

The following data lists the significant emission frequencies, polarity and position, peak reading of the EMI Receiver, calculated average reading, the FCC limit, and the difference between the peak reading and the limit. Explanation of the correction and calculation are given in section 5.1.

Tester SignatureDavid Tu		
Typed/Printed Name: David Tu	Date:	December 10, 2008

Radiated Test Data @3m

					Cal cul ated		
Frequency	Pol ari ty	Hei ght	Azi muth	Peak	Average	FCC	Di fference
	[H or V],	3		Readi ng	Readi ng	3m Limit	from limit
(MHz)	Position	(m)	(Degree)	(dBmV/m)	(dBmV/m	(dBmV/m)	(dB)
	(X, Y, Z) (1)	` ,	, ,		,	,	` ,
433. 87	H, X(1)	1.6	180	85.6	75.6	80.8(3)	-5.2
867.74	H, X	1.0	270	67.5	57.5	60.8(4)	-3.3
1301.61	H, X	1.2	280	57.2	47.2	54(2)	42.2
1735. 48	H, X	1.2	280	43.3	33.3	60.8	-27.5
2169. 35	H, X	1.2	330	48.9	38.9	60.8	-21.9
2603.22	H, X	1.2	000	46.1	36.1	60.8	-24.7
433.87	V, X	2.5	330	75.1	65.1	80.8	-15.7
867.74	V, X	1.0	040	64.2	54.2	60.8	-6.6
1301.61	V, X	1.2	350	56.3	46.3	54	-7.7
1735. 48	V, X	1.1	000	43.8	33.8	60.8	-27
2169. 35	V, X	1.1	000	50.2	40.2	60.8	-20.6
2603.22	V, X	1.0	000	45.8	35.8	60.8	-25
433.87	H, Y	2.1	000	85.2	75.2	80.8	-5.6
867.74	H, Y	1.0	180	66.2	56.2	60.8	-4.6
1301.61	H, Y	1.3	350	57.8	47.8	54	-6.2
1735. 48	H, Y	1.3	000	47.9	37.9	60.8	-22.9
2169. 35	H, Y	1.3	210	52.6	42.6	60.8	-18.2
2603.22	H, Y	1.3	200	48.2	38.2	60.8	-22.6
433. 87	V, Y	2.6	060	81.6	71.6	80.8	-9.2
867.74	V, Y	1.9	120	66.3	56.3	60.8	-4.5
1301.61	V, Y	1.4	270	52.8	42.8	54	-11.2
1735. 48	V, Y	1.4	130	45.5	35.5	60.8	-25.3
2169. 35	V, Y	1.2	270	48.7	38.7	60.8	-22.1
2603.22	V, Y	1.0	260	46.5	36.5	60.8	-24.3
433.87	H, Z	2.7	000	83.5	73.5	80.8	-7.3
867.74	H, Z	1.1	220	59.1	49.1	60.8	-11.7
1301.61	H, Z	1.4	000	51.6	41.6	54	-12.4
1735. 48	H, Z	1.3	010	43.5	33.5	60.8	-27.3
2169. 35	H, Z	1.3	000	49.2	39.2	60.8	-21.6
2603.22	H, Z	1.2	190	48.7	38.7	60.8	-22.1
433. 87	V, Z	1.2	200	82.9	72.9	80.8	-7.9
867. 74	V, Z	1.2	040	69.5	59.5	60.8	-1.3
1301.61	V, Z	1.3	100	58	48	54	-6
1735. 48	V, Z	1.1	100	44.5	34.5	60.8	-26.3
2169. 35	V, Z	1.2	000	50.4	40.4	60.8	-20.4
2603.22	V, Z	1.2	160	46.1	36.1	60.8	-24.7

- (1) See Figure 3.1, 3.2 and 3.3 for definition of position X-1, Y-2, Z-3.
- (2) Restricted band.
- (3) Fundamental limit is 3750-12500 microvolts/meter linear interpolations (average reading). Per FCC 15.231(a).
- (4) Spurious limit is 375-1250 microvolts/meter linear interpolations (average reading). Per 15.231(a).

5.4 Occupied Bandwidth

The bandwidth of the emission shall be no wider than 0.25% of the center frequency, in this case, 1.0846F7MHz(433.87x0.25%). Bandwidth is determined at the points 20dB down from the modulated carrier. Figure 5.2 shows the occupied bandwidth plot.

E

Commercial Equipment Remote Pulse Train and Duty Cycle Calculation over 100ms Worst Case Window

Figure 5.1 Pulse Train Timing




Figure 5.2 Occupied Bandwidth