

SNYDER ANTENNA SYSTEMS

2082 Lincoln Ave.
Altadena, CA 91001

snyderelectronics@sbcglobal.net

626.794.7139



Data Sheet – UHF Antenna

Part Number: ANT-UHF-1x4-yyy-zzz
Where yyy indicates connector type
And zzz indicates cable length if specified

Frequency: 902 to 928 MHz
(Please specify if 867 or 960 MHz is required.)

Input Return Loss: 14 dB minimum

Gain: 2 dBi Typical

Directivity: Dipole Pattern

Power Handling: 4 Watts Max.

Size: 1.00" wide by 4.00" long, .062 thick plus connector
Mounting is by 2 flush through holes.

Connector Interface: Straight SMA female jack is standard.
R/A SMA is optional.
Pendant cable of any length is optional.
RG188/U is recommended.
Please specify length and connector type.

Temperature: -40 to +60 C.