

# **EMISSION TEST REPORT**

**Test Report No. : 19H0013-02**

**Applicant:** SHINKO ELECTRIC CO., LTD.

**Type of Equipment:** SELOHT

**Model No.:** COM, CMC

**Test standard:** FCC Part 15 Subpart C

**Test Result:** Complies

This report may not be reproduced in full, partial reproduction may only be made with the written consent of the laboratory.

The results in this report apply only to the sample tested.

Date of test: August 7, 1999

**Tested by:** \_\_\_\_\_  
Hironobu Shimoji

**Approved by:** \_\_\_\_\_  
Kazutoyo Nakanishi  
Group Leader of EMC section

Issued date: September 10, 1999

Testing Laboratory

**A-pex International Co., Ltd.**

Telephone: +81 596 39 1485

108 Yokowa-cho, Ise-shi Mie-ken 516-1106 JAPAN Facsimile: +81 596 39 0232

<b>Table of Contents</b>	<b>Page</b>
<b>1 GENERAL INFORMATION</b>	<b>3</b>
1.1 Tested Methodology	4
1.2 Test Facility	4
<b>2 PRODUCT DESCRIPTION</b>	<b>5</b>
<b>3 TESTED SYSTEM DETAILS</b>	<b>5</b>
<b>4 SYSTEM TEST CONFIGURATION</b>	<b>6</b>
4.1 Justification	6
4.2 Test Procedure	6
Figure 4.2 Configuration of Tested System	7
<b>5 MAGNETIC FIELD MEASUREMENT PHOTOS</b>	<b>8</b>
Figure 5.1 Magnetic Field Measurement Photos	8
5.1 Measurement Uncertainty	9
<b>6 MAGNETIC FIELD TEST DATA</b>	<b>10</b>
6.1 Field Strength Calculation	11
<b>7 TEST EQUIPMENT USED</b>	<b>12</b>
<b>APPENDIX</b>	<b>13</b>
Test Data	<b>A1 - A20</b>

## 1 GENERAL INFORMATION

APPLICANT : SHINKO ELECTRIC CO., LTD.

ADDRESS : 100, Takegahana-cho, Ise-city, Mie  
516-0005 Japan  
Tel: +81-596-36-3974  
Fax: +81-596-36-3180

REGULATION(S) : FCC Part 15 Subpart C

MODEL NUMBER : COM, CMC

SERIAL NUMBER : -

KIND OF EQUIPMENT : SELOHT

TESTED DATE : August 7, 1999

RECEIPT DATE OF SAMPLE : August 7, 1999

REPORT FILE NUMBER : 19H0013-02

TEST SITE : A-PEX Yokowa NO.1 Open Test Site

## 1.1 Tested Methodology

Radiated testing were performed according to the procedures in FCC/ANSI C63.4(1992).  
Radiated testing was performed at a distance of 3 meters from the antenna to EUT.

## 1.2 Test Facility

The open area site measurement facility used to collect the radiated data is located on 108, Yokowa-cho, Ise-shi, Mie-ken, 516-1106 Japan.  
This site has been fully described in a report dated Aug. 1, 1997 submitted to FCC office, and listed dated Sep. 16, 1997 (31040/SIT 1300F2).

## 2 Product Description

SHINKO ELECTRIC CO., LTD., Model: COM, CMC (referred to as the EUT in this report) is a SELOHT.

Clock Frequency (CPU) : 66MHz

### COM

Main device of the system is an OHT Vehicle, which is hung from the OHT track and travels through the track. OHV has a hoisting mechanism and a FOUP is hoisted down/up to the port of the process tool.

### CMC

Communication between OHT Vehicle and the ground side controller (OHVC) is realized by power line communication. About 300kHz-350kHz signals are superposed on the power line of non-contact power supply power line.

## 3 Tested Equipment Details

The FCC IDs for all equipment, plus description of all cables used in the tested system are:

Model	FCC ID	Description	Cable description	Backshell Material
(1) SHINKO M/N: COM S/N: - (EUT)		SELOHT	-	-
(2) SHINKO M/N: CMC S/N: - (EUT)		SELOHT	Shielded Coaxial Cable	-

## 4 SYSTEM TEST CONFIGURATION

### 4.1 Justification

The measurement was performed with the system configuration shown in Figure 4.2.  
Running mode was taken for the EUT operation mode.

### 4.2 Test Procedure

The loop antenna shall be positioned with its plane vertical at the specified distance from the EUT and rotated about its vertical axis for maximum response at each azimuth about the EUT.  
For certain applications, the loop antenna may also need to be positioned horizontally at the specified distance from the EUT.  
The center of the loop shall be 1m above the ground.

## Figure 4.2 Configuration of Tested System

Front View

Top View

## **5 MAGNETIC FIELD MEASUREMENT PHOTOS**

### **Figure 5.1 Magnetic Field Measurement Photos**

## 5.1 Measurement Uncertainty

### Magnetic Field Test

The measurement uncertainty (with a 95% confidence level) for this test was  $\pm 3.3\text{dB}$ .

The data listed in this test report has enough margin, more than 3.3dB.

## 6 MAGNETIC FIELD TEST DATA

The initial step in collecting radiated data was a spectrum analyzer peak scan of the measurement range (30MHz-1000MHz).

The final data was reported in the worst-case emissions. (Running/HOR (315.8kHz))

The minimum margin to the limit is as follows :

Frequency (GHz)	Receiver Reading (dBuV)	Correction Factor (dBuV)	Field Strength (dBuV/m)	Limit (dBuV/m)	Margin (dBuV)
1.5790	60.2	-3.5	56.6	63.6	7.0

The Fundamental Frequency of this equipment is 307.9MHz. The peak of output level of fundamental frequency was confirmed at the 307.9MHz by performing the measurement.

It was corroborated that equipment was within of the tolerance which is prescribed in the FCC regulation Part 15 Subpart C sec. 15.231 (c).

Since the fundamental frequency is 307.9MHz, the upper limit could be 308.6 MHz and lower limit could be 307.2MHz.

The measurement result was 308.1MHz when the limit was 308.6MHz and also another measurement result was 307.6 MHz when the limit was 307.2MHz.

Any spurious emissions did not detect except fundamental frequency's spurious.

## 6.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor, Cable Factor and Antenna Pad, and subtracting the Amplifier Gain from the measured reading. The sample calculation is as follows :

$$FS = RA + AF + CF + AT - AG$$

where FS = Field Strength

RA = Receiver Reading

AF = Antenna Factor

CF = Cable Factor

AT = Antenna Pad

AG = Amplifier Gain

Assume a receiver reading of 60.2 dBuV is obtained. The antenna Factor of 19.7 dB, Cable Factor of 0.7 dB is added. The Antenna Pad of 6.0 dB and Amplifier Gain of 29.9 dB is subtracted, giving a field strength of 56.6 dBuV/m.

$$FS = 60.2 + 19.7 + 0.7 + 6.0 - 29.9 = 56.6 \text{ dBuV/m}$$

## 7 TEST EQUIPMENT USED

NAME	MANUFACTURER	MODEL	Control No.	Calibrated Until
Pre Amplifier	Hewlett Puckered	8447D	AF2	November 30, 1999
Biconical Antenna	Schwarzbeck	BBA9106	BA1	April 30, 2000
Logperiodic Antenna	Schwarzbeck	UKLP9140-ALA7		February 14 , 2000
Loop Antenna	Rohde & Schwarz	HFH2-Z2	LP1	October 20, 1999
Spectrum Analyzer	Hewlett Packard	8567A	SA1	November 30, 1999
Test Receiver	Rohde & Schwarz	ESHS-20	TR1	March 31, 2000
Test Receiver	Rohde & Schwarz	ESVS-30	TR2	July 4, 2000

indicates EMI Test Equipment used.

All measurement equipment is traceable to national standard

## APPENDIX

### Test Data

#### Magnetic Field Test:

HOR (285.7kHz)	<u>A 1 - A 2</u>
HOR (315.8kHz)	<u>A 3 - A 4</u>
HOR (342.9kHz)	<u>A 5 - A 6</u>
HOR (363.6kHz)	<u>A 7 - A 8</u>
VER (285.7kHz)	<u>A 9 - A10</u>
VER (315.8kHz)	<u>A11 - A12</u>
VER (342.9kHz)	<u>A13 - A14</u>
VER (363.6kHz)	<u>A15 - A16</u>
HOR/VER	<u>A17</u>
FCC Part15 Subpart B Class A	<u>A18 - A19</u>