

PART LIST

MX-700

07/02/2002

no	item	loca	spec	unix	pqty	rpat
1	TOP CASE		ABS HF-380	EA	1	
2	BOTTOM CASE		ABS HF-380	EA	1	
3	BATTERY COVER		ABS HF-380	EA	1	
4	WINDOW FILTER		PC LN-2250	EA	1	
5	LIGHTING HOLDER		ACRYL (...)	EA	1	
6	RUBBER BUTTON		SILICONE RUBBER	EA	1	
7	COIL SPRING(C)		STS 304 SCO D=0.6	EA	1	
8	PCB		154X155/4X1.6t	EA	1	
9	I.C	IC1	S3C80F9	EA	1	
10	I.C	IC2	SST39VF040	EA	1	
11	I.C	IC3	MAX3221	EA	1	
12	DC CONVERTOR	IC4	S-8321AIMP-DNI-T	EA	1	
13	T.R	TR1,TR2,TR6,TR7	KTD1304 RTK	EA	4	
14	T.R	TR3	KTN2907AS RTK	EA	1	KST2907A
15	T.R	TR4	STA1037Y(2SA1980SF-Y)	EA	1	
16	T.R	TR5	STC2412Y(2SC5343SF-Y)	EA	1	
17	SCHOTTKY DIODES	D4	B140	EA	1	
18	DIODE	D5	DA227	EA	1	
19	DIODE	D6	SDS511	EA	1	
20	DUAL LED	D7	SAM2333-(T)	EA	1	
21	LED(\$□ēh)	D8,D9,D10,D11,D12	LTST-190YKT(1608)	EA	5	HI-LH10Y
22	ELEC' CAPACITOR(S)	C1	220uF/10V(8x6.3)	EA	1	
23	ELEC' CAPACITOR(S)	C2	470uF/16V(8x10.2)	EA	1	
24	ELEC' CAPACITOR(S)	C4	47uF/16V(6.3x5.2)	EA	1	
25	ELEC' CAPACITOR(S)	C5,C6,C8	0.47uF/50V(4x5)	EA	3	
26	ELEC' CAPACITOR(S)	C7	0.1uF/50V(4x5.2)	EA	1	
27	CERA' CAPACITOR	C9,C10,C11,C14	0.1uF.50V(25V)(1608)	EA	4	
28	CERA' CAPACITOR	C12,C13	22pF.50V(1608)	EA	2	
29	CERA' CAPACITOR	C16,C17	220pF.50V(1608)	EA	2	
30	MICRO CHIP RESISTOR	R1	1 OHM 1/16W(1608)	EA	1	
31	MICRO CHIP RESISTOR	R2,R34	470 OHM 1/16W(1608)	EA	2	
32	MICRO CHIP RESISTOR	R3,R13,R14,R33	1K OHM 1/16W(1608)	EA	4	
33	MICRO CHIP RESISTOR	R4,R8	10K OHM 1/16W(1608)	EA	2	
34	MICRO CHIP RESISTOR	R5,R7,R23~R32	4.7K OHM 1/16W(1608)	EA	12	
35	MICRO CHIP RESISTOR	R6	1.2K OHM 1/16W(1608)	EA	1	
36	MICRO CHIP RESISTOR	R9	15K OHM 1/16W(1608)	EA	1	
37	MICRO CHIP RESISTOR	R10,R17,R18,R20,R22	100 OHM 1/16W(1608)	EA	5	
38	MICRO CHIP RESISTOR	R11	1M OHM 1/16W(1608)	EA	1	
39	MICRO CHIP RESISTOR	R12	2.2K OHM 1/16W(1608)	EA	1	
40	MICRO CHIP RESISTOR	R15,R16,R19,R21	47 OHM 1/16W(1608)	EA	4	

41	JACK	JACK1	ST-3009-02G(AJ330-4T-SMT)	EA	1	
42	IR LED	D1,D2	HI-I535FL	EA	2	
43	PHOTO DIODE	D3	HI-D470R	EA	1	
44	RESONATOR	X1	ZTA8.0MT(8MHz)	EA	1	
45	COIL	L1	100uH(5X8)	EA	1	
46	ELEC' CAPACITOR	C3	0.1uF/50V(3X5)	EA	1	
47	COIL SPRING(+)	+	STS 304 NICO D=0.6	EA	1	
48	COIL SPRING(-)	-	STS 304 NICO D=0.6	EA	1	