450W x 55H_mm 45W x 55H mm



Appearance -1. microUSB port 4. Earpiece 6. Volume 2. Status indicator 5. Microphone plus/minus 3. Multifuction 53.6mm x 16.3mm x 20.3mm

Functions and Features -

- · Support connecting Bluetooth devices and playing stereo music.
- · Built in imported high-sensitive microphone with smart voice prompt. · Multipoint function, available to connect two cellphones
- simultaneously. . It can be used to answer the phone or to call.
- Indicator Lights · The pair: red and blue lights flashing alternately
- The pairing is successful; blue light flashing · The music: blue light flashing into music
- · The state of charge: the red light · The full power; blue light

User auide Basic operation -

- The boot: press the multifunction key for about 2 seconds to boot
- The turn off; press the multifunction key for about 3 seconds off
 - The pairing mode: press the multifunction key for about 5 seconds into the match state
 - The answer / hang up: click the multifunction button to achieve incoming call and hang up
 - The incoming call blocking: call for short press the multifunction key 2 times to loosen the realization of incoming call blocking
 - The heavy tail number: double click on the pull connected multi function key to open the tail number of redrawing language
 - · The on / off song: long press the key to realize the song like
 - · The big / small volume: short press the volume / volume reduction and achieve volume large, small

Pairing to the phone -

Make sure the distance between headphone and cellphone or other devices is within 1 meter. Turn on the headphone and long press multifunctional button for about 5 seconds until red/blue light flashes alternately The headphone enters pairing mode and wait for p

- airing: Start the Wireless function of cellphone or other devices and search for the headphone. Then the blue light flashes. Which means successfully paired. *A device that has been matched successfully, and the
 - Wireless headset will be automatically connected after restarting, and no longer need to be paired. When the wireless version of the device is 2.1 or lower it is necessary to enter a password (0000) when pairing is used. The headset will turn off automatically after 5 minutes of unconnected state.

Connecting with two devices -

Make sure the headphone successfully connects the first cell phone(already connected but not playing music). Press volume up button and volume down button simultaneously for about 3 seconds and the headphone enters pairing mode again (red/blue light flashes alternately). Start Wireless function of the other cellphone and select the headphone to pair and

connect. Then the headphone connects two cel I

phones simultaneously and starts multi-point function. Note: When the headphone starts again, it will only connect the first cellphone automatically. Only by clicking the Wireless interface. Can you connect the second cellphone.

Questions & Solutions -

Hear noise while using.

The operation range of this headphone is up to 10M obstacles, while human body is also an obstacle. For hetter use it is recommended that you'd better out the headphone on the same side of your cellphone to get better using effect.

Can't hear any sound? Please make sure you've already turned on your

headphone with full charged. Please make sure the headphone has already connected the cellp hone.

Please make sure that the earphones are properly

Failed to connect the headphone with cellphone? Please make sure that the earphones are fully charged.

matched with the mobile phone Please make sure that the Wireless function of the mobile phone has been started

Please refer to the instructions of the mobile phone user for the detailed operation.

Please make sure that the headphones are within the range of 10 meters, and there are no barriers, such as walls or other electronic devices.

Cautions -

headphones.

· Do not put the headset in the position of the safety air bag in the car, because when the safety air bag is unfolded, it may cause the damage of the air bag. Do not let children play with this headset, small parts may make children have a risk of suffocation.

Do not try to make any changes to the headset.

· Do not put the headset in a liquid or wet place.

charging state. First, you should separate the

in the fire to avoid the explosion.

· Do not clean the earphones when they are in the

headphones and chargers and then clean them up.

· Do not use a abrasiveness cleaning agent to clean the

· Do not let the earphones close to the fire or discarded

Please do not receive direct sunlight for a long time. If

you don't use this headphone for a long time, please

store it in a dry environment and charge at least once

a month for the earphone to extend your life.

Article 14 influence aircraft security and interfere legal communications: If found, the user shall cease

Article 12

- operating immediately until no interference is
- The said legal communications means radio communications is operated in compliance with the Telecommunications Act
- The low power radio-frequency devices must be susceptible with the interference from legal communications or ISM radio wave radiated devices.

Administrative Regulations on Low Power Radio

Without permission granted by the NCC, any company, enterprise, or user is not allowed to change

frequency, enhance transmitting power or alter

original characteristic as well as performance to a

The low power radio-frequency devices shall no

approved low power radio-frequency devices.

Waves Radiated Devices warning:

This device complies with Part 15 of the ECC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Gigastone

BLUETOOTH HEADSET

單耳藍牙耳機

使用手冊 User Guide

產品介紹

產品規格 -無線版本 兼容的配置協議 A2DP / AVRCP / HSP / HFP 丁作範圍 高達10米 (無障礙空間) 内置電池 3.7V/55mAh 通話時長 長達4-6小時(具體時間視 使用環境而定 音樂時間 長達4-6小時(具體時間視 使用環境而定 長達120小時 待機時間 充電標準 DC5V-500mA 充電時間約 工作環境 -10°C~40°C 頻率音度 50Hz-20KHz 產品淨重 9g (内含鋰電池) 53.6mm x 16.3mm x 20.3mm

產品結構 -

3. 多功能按鈕

button(MFB)



- 支持連接無線設備及立體聲高保直音樂播放
- 内置進□高清晰麥克風,智能語音提示
- 智能—對一功能 ·接打電話 電話重播
- 提示燈 配對狀態:紅藍燈交替閃爍
- 配對成功:藍燈閃爍
- 在雷狀能:紅陰長高

- 吾樂狀態:進入吾樂時藍燈閃爍
- 充滿電後: 藍燈長亮

使用指南

基本操作 ----開機:長按多功能鍵約2秒開機

- · 關機:長按多功能键約3秒關機
- · 配對模式:長按多功能鍵約5秒進入配對 狀態
- 接聽/掛斷:單擊多功能鍵實現來電接聽與
- · 來電拒接: 來電時連續短按多功能鍵2次 鬆開實現來電拒接
- 尾號重拔: 在已連接時雙鑿多功能鍵開啓 尾號重播
- ・上/下曲:長按+/=鍵實現切歌 · 音量大/小: 短按音量加/音量減實現 音量大/小

藍牙耳機連接手機

將無線耳機和手機或其他的連接設備的距離 定在1米的範圍内,確保耳機在關機狀態,長 按多功能約5秒直到紅/藍燈交替閃爍,此時 進入配對狀態等待連接;開格手機或其他無 線設備的無線功能,進行搜索或掃描,點選 搜索到的 互機名稱成功對配對連接後, 互機 提示燈轉為藍燈閃動,表示配對連接成功。

*已經成功配對過的設備,在重新啓動後無線 巨機會白動連接,無須再次配對。設備無線 版本在2.1或更低時,配對時需輸入密碼 (0000) 即可連接使用。耳機在未連接狀 態超出5分鐘後會自動關機

藍牙耳機1對2 ----

一對二(同時雙點連接)先確保耳機已連接 第一台手機成功後, 互機關機重新配對連接 第二台手機,此時再打開第一台手機,點選 已有連接記憶的耳機,連接成功後,耳機就 能同時連接兩台手機。當第二台手機成功連 接後,此時耳機已同時連接兩台手機,進行 一對二功能。

註: 巨機再次開機時只會自動向連第一個手 機,第二個手機只能通過手機無線接口 點選後才會連接。

常見問題及解決方案 ----

語到宮宮書音

因無線的協議距離是空牖地段,無障礙情況 下可以達到10米,其中人體對無線目機也是 一種最大的干擾障礙,為了您的使用效果, 我們建議你把耳機戴在手機的同一邊,以達

到最佳接收效果。 日機沒馨吾?

請確保耳機已啟動並完全充電。 請確保耳機是否已與手機連接。

手機與巨機連接不上 請確保耳機完全充雷。 請確保耳機與手機適當配接。 請確保手機的無線功能已啓動,詳細操作請

参閱手機用戶使用說明 請確保耳機在手機10米範圍之内,沒有任何 障礙物,例如牆壁或其它電子設備。

注意事項 —————

- 切勿把耳機放在重内安全氣袋的位置上,因 為當安全氣袋展開時,可能會引起氣袋的 傷害。 切勿讓兒童玩耍本目機,細小的零件可能令
- 兒童有窒息的危險。
- 切勿試圖對本耳機做出任何修改。

把耳機及充電器分開,再進行清理.

- 切勿把耳機放在液體或潮濕的地方 ・ 営虚於充電狀能時,請勿清潔本巨機,應先
- 請勿使用且有整蝕性的清潔劑清理巨機。
- 請勿讓且機靠近明火或棄置於火中,辦冕發 牛爆炸。
- 請勿長時間受陽光直接照射,如果長時間内 不使用本目機,請儲存在乾燥的環境中,並 每月至少為耳機充電-次以延長壽命。

低功率電波輻射性電機管理辦法 第十一條

經型式認證合格之低功率射頻雷機,非經許可, 公司、商號或使用者均不得擅自變更頻率、加大 功率或變更原設計之特件及功能。 第十四條

低功率射頻雷機之使用不得影響飛航安全及干擾 合法涌信;經發現有干擾現象時,應立即停用, 並改善至無干擾時方得繼續使用。前項合法涌 信,指依雷信法規定作業之無線雷涌信。低功率 射類雷機須忍受合法涌信或工業、科學及醫療用

該裝置符合FCC規則第15部分。運作須符合以下兩

(1) 本裝置不得造成有害幹擾

電波輻射性電機設備之干擾。

(2)本設備必須接受接收到的任何幹擾,包括可能 導致不希望的操作的幹擾。



www.gigastone.com



NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.