

Prepared (also subject responsible if other)
SEM/BGLDB, Leif Hedin
Approved
SEM/BGLDB (Leif Hedin)

Company Internal MARKING DRAWING

1214-1588 Uen

Rev

Reference

2008-09-25 3

Approved according to 000 21-LXE 107 42/1

Checked

Le_a Mobile Phone label content, Made in...

Le-850 Type Number: Le-AAA-1042092-BV

1 General information

Core Unit label part no	1209-4425	
Bar code	Standard: according to Ericsson corporate standard 102 01–109 Uen	
	 Print quality: C, according to ANSI X3.182-1990 as stated in Ericsson corporate standard 102 01– 1003 Uen 	
	Quiet zone: No bar codes are allowed to be closer to a label edge than 2 mm!	
Text	If applicable, or nothing else specified, Zebra printer Scaleable Smooth Font CG Triumvirate Bold Condensed is imposed. When needed, the text is adjusted to fit the label.	
Coordinates	"(x/y)" under each line number specifies the bottom / left alignment for text, graphics and bar codes, x is measured vertically, and y horizontally from the upper left corner of the label (landscape format), both in mm. When needed, the alignment is adjusted to fit the label.	

MLCI= Main Label Content Information-document.

2 Printing information

	Content	Format
Line 1a (3,5/2,0)	Sony Ericsson stylized name.	Graphics, height 1,5 mm. According to 1200-1925.
Line 1b (3,5/18)	Model Name "J132a"	Text, height 1,2 mm. According to Chapter 1 in MLCI.
Line 2a (6,0/2,0)	"TYPE: AAA-1042092-BV"	Text, height 1,2 mm. According to Chapter 1 in MLCI.
Line 2b (6,0/18,0)	HW & SW identification field, if applicable; "FFGG"	Text, height 1,2 mm. According to Type-testing report under specifying document in product model.
Line 2c (6,0/25,0)	Location code of where the phone is flashed, if applicable, "FFF"	Text, height 1,2 mm.
Line 3a (7,7/2,0)	"FCC ID: PY7A1042092"	Text, height 1,2 mm. According to Chapter 1 in MLCI.
Line 3b (7,7/17,7)	Production week (flash), "yy'W'ww" (yy = year, ww = week)	Text, height 1,2 mm.
Line 3c (7,7/24,7)	Repair week, if applicable. "Ry'W'ww" (y = year, ww = week)	Text, height 1,2 mm.
Line 4a (9,5/2,0)	"IC: 4170B-A1042092"	Text, height 1,2 mm. According to Chapter 1 in MLCI.
Line 4b (9,5/17,7)	Product number without revision of the Sales Item in which the phone is packed, if applicable. "SI XXXX-XXXX"	Text, height 1,2 mm.



Prepared (also subject responsible if other)

SEM/BGLDB, Leif Hedin

Approved
SEM/BGLDB (Leif Hedin)

Company Internal MARKING DRAWING

1214-1588 Uen

Checked

ate Rev Reference


2008-09-25 3

	Content	Format
Line 5 (12,5/3,5)	Line 6a in bar code. As desired by supplier (e.g. only actual number).	Bar code, height 2,0 mm. As desired by supplier (e.g. Code 128 symbology).
Line 6a (14,7/2,0)	Supplier's identification for trace-ability of the telephone, as desired by supplier (e.g. "S/N: nnn" for serial number).	Text, height 1,2 mm. Defined by supplier.
Line 6b (14,7/14,0)	Actual electronic serial number (IMEI) of the Mobile Phone, "00000000-000000-0"	Text, height 1,2 mm. In the format TAC-SNR-CD. TAC and SNR derived from pos 500 in BOM. CD = check digit according to the Luhn formula (ISO/IEC 7812), GSM 02.16.
Line 7 (17,5/3,5)	Line 6b in bar code (only actual number, without data identifier).	Bar code, height 2,0 mm. Code 128 symbology, code C subset. If uneven number of digits, code B subset shall be used for the last digit.
Line 8a (24,0/2,0)	Marking of origin: "Xxx"= actual country of production of the included telephone, in English.	Text, height 1,2 mm.
Line 8b (24,0/10,0)	WEEE trashcan without bar symbol.	Graphics, min. height 5mm, according to 1202-5537.

3 Layout

The conceptual picture (for Zebra 90XiII printer, or equivalent) should not be considered as specifications, but as an additional help for setting up the label.

3.1 Conceptual picture



<u>double underlined</u> = major changes since last revision.



Prepared (also subject responsible if other)

SEM/BGLDB, Leif Hedin

SEM/BGLDB (Leif Hedin)

Company Internal MARKING DRAWING

1214-1588 Uen

Date Rev Reference

2008-09-25 3

4

Label placement

To find the label follow these steps:

Checked

- 1. Remove the cover on the rear side of the product.
- 2. Remove the battery.
- 3. The label is located behind the battery.

