



EX3DV4- SN:3759

December 15, 2015

Appendix: Modulation Calibration Parameters

UID	Communication System Name		A dB	B dB μ V	C	D dB	VR mV	Max Unc ^E (k=2)
0	CW	X	0.00	0.00	1.00	0.00	137.4	$\pm 3.5\%$
		Y	0.00	0.00	1.00		148.5	
		Z	0.00	0.00	1.00		142.2	
10010- CAA	SAR Validation (Square, 100ms, 10ms)	X	3.46	69.97	12.84	10.00	20.0	$\pm 9.6\%$
		Y	3.56	70.15	13.09		20.0	
		Z	3.97	71.55	14.16		20.0	
10011- CAB	UMTS-FDD (WCDMA)	X	0.95	64.62	13.58	0.00	150.0	$\pm 9.6\%$
		Y	0.94	64.12	13.29		150.0	
		Z	0.89	62.25	11.72		150.0	
10012- CAB	IEEE 802.11b WiFi 2.4 GHz (DSSS, 1 Mbps)	X	1.19	62.77	14.17	0.41	150.0	$\pm 9.6\%$
		Y	1.18	62.39	13.90		150.0	
		Z	1.18	61.47	12.83		150.0	
10013- CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS-OFDM, 6 Mbps)	X	4.80	66.41	16.69	1.46	150.0	$\pm 9.6\%$
		Y	4.81	66.26	16.58		150.0	
		Z	4.81	65.99	16.26		150.0	
10021- DAB	GSM-FDD (TDMA, GMSK)	X	100.00	113.42	27.36	9.39	50.0	$\pm 9.6\%$
		Y	55.77	106.43	25.91		50.0	
		Z	18.93	93.26	22.95		50.0	
10023- DAB	GPRS-FDD (TDMA, GMSK, TN 0)	X	58.52	106.35	25.67	9.57	50.0	$\pm 9.6\%$
		Y	29.55	97.95	23.72		50.0	
		Z	14.95	89.78	21.91		50.0	
10024- DAB	GPRS-FDD (TDMA, GMSK, TN 0-1)	X	100.00	112.07	25.64	6.56	60.0	$\pm 9.6\%$
		Y	100.00	112.77	25.99		60.0	
		Z	13.59	90.28	20.87		60.0	
10025- DAB	EDGE-FDD (TDMA, 8PSK, TN 0)	X	9.80	95.07	37.43	12.57	50.0	$\pm 9.6\%$
		Y	4.43	69.49	24.68		50.0	
		Z	7.03	82.68	31.43		50.0	
10026- DAB	EDGE-FDD (TDMA, 8PSK, TN 0-1)	X	8.61	89.61	31.48	9.56	60.0	$\pm 9.6\%$
		Y	6.90	83.14	28.50		60.0	
		Z	7.07	83.35	28.61		60.0	
10027- DAB	GPRS-FDD (TDMA, GMSK, TN 0-1-2)	X	100.00	112.51	25.09	4.80	80.0	$\pm 9.6\%$
		Y	100.00	113.33	25.44		80.0	
		Z	8.57	86.56	19.18		80.0	
10028- DAB	GPRS-FDD (TDMA, GMSK, TN 0-1-2-3)	X	100.00	114.16	25.17	3.55	100.0	$\pm 9.6\%$
		Y	100.00	115.07	25.54		100.0	
		Z	4.52	81.54	17.36		100.0	
10029- DAB	EDGE-FDD (TDMA, 8PSK, TN 0-1-2)	X	5.41	79.01	26.03	7.80	80.0	$\pm 9.6\%$
		Y	4.78	75.56	24.25		80.0	
		Z	4.78	75.09	23.94		80.0	
10030- CAA	IEEE 802.15.1 Bluetooth (GFSK, DH1)	X	100.00	110.43	24.44	5.30	70.0	$\pm 9.6\%$
		Y	44.16	102.43	22.81		70.0	
		Z	6.07	81.13	17.44		70.0	
10031- CAA	IEEE 802.15.1 Bluetooth (GFSK, DH3)	X	100.00	114.78	24.24	1.88	100.0	$\pm 9.6\%$
		Y	6.35	89.05	18.68		100.0	
		Z	0.93	68.71	12.20		100.0	



EX3DV4- SN:3759

December 15, 2015

10032-CAA	IEEE 802.15.1 Bluetooth (GFSK, DH5)	X	5.75	92.88	20.09	1.17	100.0	± 9.6 %
		Y	1.27	77.94	16.10		100.0	
		Z	0.47	65.20	10.94		100.0	
10033-CAA	IEEE 802.15.1 Bluetooth (PI/4-DQPSK, DH1)	X	4.88	79.14	19.56	5.30	70.0	± 9.6 %
		Y	3.87	75.70	18.33		70.0	
		Z	3.16	72.00	16.77		70.0	
10034-CAA	IEEE 802.15.1 Bluetooth (PI/4-DQPSK, DH3)	X	1.90	69.58	14.48	1.88	100.0	± 9.6 %
		Y	1.70	68.18	14.00		100.0	
		Z	1.46	65.25	12.40		100.0	
10035-CAA	IEEE 802.15.1 Bluetooth (PI/4-DQPSK, DH5)	X	1.47	67.57	13.41	1.17	100.0	± 9.6 %
		Y	1.37	66.58	13.09		100.0	
		Z	1.21	64.01	11.56		100.0	
10036-CAA	IEEE 802.15.1 Bluetooth (8-DPSK, DH1)	X	5.54	81.22	20.38	5.30	70.0	± 9.6 %
		Y	4.25	77.30	19.02		70.0	
		Z	3.33	72.95	17.23		70.0	
10037-CAA	IEEE 802.15.1 Bluetooth (8-DPSK, DH3)	X	1.81	69.08	14.24	1.88	100.0	± 9.6 %
		Y	1.64	67.76	13.79		100.0	
		Z	1.42	65.00	12.26		100.0	
10038-CAA	IEEE 802.15.1 Bluetooth (8-DPSK, DH5)	X	1.47	67.67	13.56	1.17	100.0	± 9.6 %
		Y	1.37	66.65	13.21		100.0	
		Z	1.20	64.02	11.65		100.0	
10039-CAB	CDMA2000 (1xRTT, RC1)	X	1.31	67.25	13.15	0.00	150.0	± 9.6 %
		Y	1.31	66.96	13.14		150.0	
		Z	1.12	63.89	11.31		150.0	
10042-CAB	IS-54 / IS-136 FDD (TDMA/FDM, PI/4-DQPSK, Halfrate)	X	100.00	110.37	25.17	7.78	50.0	± 9.6 %
		Y	50.75	103.30	23.75		50.0	
		Z	13.62	88.84	20.46		50.0	
10044-CAA	IS-91/EIA/TIA-553 FDD (FDMA, FM)	X	0.04	83.16	2.99	0.00	150.0	± 9.6 %
		Y	0.05	85.78	2.29		150.0	
		Z	0.07	79.92	0.01		150.0	
10048-CAA	DECT (TDD, TDMA/FDM, GFSK, Full Slot, 24)	X	13.64	84.78	20.90	13.80	25.0	± 9.6 %
		Y	11.80	82.44	20.33		25.0	
		Z	10.74	81.50	20.54		25.0	
10049-CAA	DECT (TDD, TDMA/FDM, GFSK, Double Slot, 12)	X	16.41	89.18	21.23	10.79	40.0	± 9.6 %
		Y	13.15	86.27	20.53		40.0	
		Z	11.03	84.39	20.43		40.0	
10056-CAA	UMTS-TDD (TD-SCDMA, 1.28 Mcps)	X	11.79	88.00	23.02	9.03	50.0	± 9.6 %
		Y	9.09	83.74	21.62		50.0	
		Z	7.76	81.04	20.84		50.0	
10058-DAB	EDGE-FDD (TDMA, 8PSK, TN 0-1-2-3)	X	4.22	74.24	23.18	6.55	100.0	± 9.6 %
		Y	3.87	71.93	21.91		100.0	
		Z	3.85	71.25	21.43		100.0	
10059-CAB	IEEE 802.11b WiFi 2.4 GHz (DSSS, 2 Mbps)	X	1.20	63.46	14.52	0.61	110.0	± 9.6 %
		Y	1.19	62.95	14.17		110.0	
		Z	1.18	61.87	13.02		110.0	
10060-CAB	IEEE 802.11b WiFi 2.4 GHz (DSSS, 5.5 Mbps)	X	1.73	75.17	18.04	1.30	110.0	± 9.6 %
		Y	1.32	71.18	16.40		110.0	
		Z	1.02	65.90	13.47		110.0	



EX3DV4- SN:3759

December 15, 2015

10061-CAB	IEEE 802.11b WiFi 2.4 GHz (DSSS, 11 Mbps)	X	1.91	71.56	17.96	2.04	110.0	± 9.6 %
		Y	1.68	69.19	16.83		110.0	
		Z	1.51	66.25	14.95		110.0	
10062-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 6 Mbps)	X	4.60	66.40	16.16	0.49	100.0	± 9.6 %
		Y	4.62	66.29	16.08		100.0	
		Z	4.60	65.95	15.71		100.0	
10063-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 9 Mbps)	X	4.61	66.47	16.24	0.72	100.0	± 9.6 %
		Y	4.63	66.34	16.15		100.0	
		Z	4.61	66.00	15.78		100.0	
10064-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 12 Mbps)	X	4.87	66.70	16.45	0.86	100.0	± 9.6 %
		Y	4.90	66.59	16.37		100.0	
		Z	4.88	66.28	16.02		100.0	
10065-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 18 Mbps)	X	4.75	66.57	16.52	1.21	100.0	± 9.6 %
		Y	4.76	66.43	16.42		100.0	
		Z	4.75	66.13	16.07		100.0	
10066-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 24 Mbps)	X	4.76	66.57	16.66	1.46	100.0	± 9.6 %
		Y	4.77	66.42	16.55		100.0	
		Z	4.77	66.14	16.21		100.0	
10067-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 36 Mbps)	X	5.05	66.81	17.13	2.04	100.0	± 9.6 %
		Y	5.06	66.63	16.99		100.0	
		Z	5.07	66.40	16.70		100.0	
10068-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 48 Mbps)	X	5.09	66.78	17.30	2.55	100.0	± 9.6 %
		Y	5.10	66.60	17.16		100.0	
		Z	5.11	66.40	16.89		100.0	
10069-CAB	IEEE 802.11a/h WiFi 5 GHz (OFDM, 54 Mbps)	X	5.17	66.83	17.51	2.67	100.0	± 9.6 %
		Y	5.18	66.63	17.35		100.0	
		Z	5.19	66.45	17.09		100.0	
10071-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 9 Mbps)	X	4.89	66.48	16.98	1.99	100.0	± 9.6 %
		Y	4.90	66.31	16.84		100.0	
		Z	4.90	66.08	16.54		100.0	
10072-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 12 Mbps)	X	4.86	66.73	17.15	2.30	100.0	± 9.6 %
		Y	4.86	66.53	17.00		100.0	
		Z	4.86	66.29	16.69		100.0	
10073-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 18 Mbps)	X	4.92	66.88	17.46	2.83	100.0	± 9.6 %
		Y	4.91	66.66	17.28		100.0	
		Z	4.92	66.43	16.99		100.0	
10074-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 24 Mbps)	X	4.91	66.81	17.61	3.30	100.0	± 9.6 %
		Y	4.91	66.57	17.42		100.0	
		Z	4.92	66.37	17.15		100.0	
10075-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 36 Mbps)	X	4.95	66.90	17.89	3.82	90.0	± 9.6 %
		Y	4.94	66.64	17.69		90.0	
		Z	4.97	66.47	17.44		90.0	
10076-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 48 Mbps)	X	4.98	66.77	18.05	4.15	90.0	± 9.6 %
		Y	4.97	66.49	17.83		90.0	
		Z	5.00	66.36	17.61		90.0	
10077-CAB	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 54 Mbps)	X	5.01	66.86	18.16	4.30	90.0	± 9.6 %
		Y	5.00	66.56	17.93		90.0	
		Z	5.03	66.44	17.71		90.0	



EX3DV4– SN:3759

December 15, 2015

10081-CAB	CDMA2000 (1xRTT, RC3)	X	0.73	63.46	10.92	0.00	150.0	± 9.6 %
		Y	0.75	63.35	11.00		150.0	
		Z	0.70	61.50	9.66		150.0	
10082-CAB	IS-54 / IS-136 FDD (TDMA/FDM, PI/4-DQPSK, Fullrate)	X	0.68	58.87	4.28	4.77	80.0	± 9.6 %
		Y	0.65	58.57	4.16		80.0	
		Z	0.75	59.37	5.01		80.0	
10090-DAB	GPRS-FDD (TDMA, GMSK, TN 0-4)	X	100.00	112.05	25.65	6.56	60.0	± 9.6 %
		Y	100.00	112.74	25.99		60.0	
		Z	13.27	89.95	20.78		60.0	
10097-CAB	UMTS-FDD (HSDPA)	X	1.73	66.15	14.58	0.00	150.0	± 9.6 %
		Y	1.72	65.74	14.38		150.0	
		Z	1.62	64.07	13.12		150.0	
10098-CAB	UMTS-FDD (HSUPA, Subtest 2)	X	1.69	66.08	14.54	0.00	150.0	± 9.6 %
		Y	1.68	65.67	14.33		150.0	
		Z	1.59	64.00	13.06		150.0	
10099-DAB	EDGE-FDD (TDMA, 8PSK, TN 0-4)	X	8.67	89.71	31.51	9.56	60.0	± 9.6 %
		Y	6.93	83.22	28.52		60.0	
		Z	7.10	83.42	28.62		60.0	
10100-CAB	LTE-FDD (SC-FDMA, 100% RB, 20 MHz, QPSK)	X	2.89	68.66	15.83	0.00	150.0	± 9.6 %
		Y	2.86	68.31	15.63		150.0	
		Z	2.68	66.73	14.55		150.0	
10101-CAB	LTE-FDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM)	X	3.14	66.73	15.39	0.00	150.0	± 9.6 %
		Y	3.14	66.54	15.27		150.0	
		Z	3.06	65.69	14.56		150.0	
10102-CAB	LTE-FDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM)	X	3.25	66.76	15.51	0.00	150.0	± 9.6 %
		Y	3.25	66.59	15.40		150.0	
		Z	3.18	65.77	14.71		150.0	
10103-CAB	LTE-TDD (SC-FDMA, 100% RB, 20 MHz, QPSK)	X	5.77	73.71	19.33	3.98	65.0	± 9.6 %
		Y	5.18	71.67	18.40		65.0	
		Z	5.04	70.75	17.81		65.0	
10104-CAB	LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 16-QAM)	X	5.99	72.52	19.60	3.98	65.0	± 9.6 %
		Y	5.76	71.57	19.10		65.0	
		Z	5.67	70.92	18.65		65.0	
10105-CAB	LTE-TDD (SC-FDMA, 100% RB, 20 MHz, 64-QAM)	X	5.98	72.36	19.83	3.98	65.0	± 9.6 %
		Y	5.43	70.29	18.80		65.0	
		Z	5.33	69.55	18.29		65.0	
10108-CAC	LTE-FDD (SC-FDMA, 100% RB, 10 MHz, QPSK)	X	2.52	67.89	15.60	0.00	150.0	± 9.6 %
		Y	2.50	67.54	15.40		150.0	
		Z	2.36	65.96	14.28		150.0	
10109-CAC	LTE-FDD (SC-FDMA, 100% RB, 10 MHz, 16-QAM)	X	2.78	66.49	15.20	0.00	150.0	± 9.6 %
		Y	2.79	66.28	15.08		150.0	
		Z	2.71	65.30	14.28		150.0	
10110-CAC	LTE-FDD (SC-FDMA, 100% RB, 5 MHz, QPSK)	X	2.03	66.91	15.06	0.00	150.0	± 9.6 %
		Y	2.02	66.53	14.85		150.0	
		Z	1.91	64.92	13.66		150.0	
10111-CAC	LTE-FDD (SC-FDMA, 100% RB, 5 MHz, 16-QAM)	X	2.46	67.03	15.25	0.00	150.0	± 9.6 %
		Y	2.47	66.79	15.15		150.0	
		Z	2.35	65.35	14.09		150.0	



EX3DV4-SN:3759

December 15, 2015

10112-CAC	LTE-FDD (SC-FDMA, 100% RB, 10 MHz, 64-QAM)	X	2.91	66.57	15.29	0.00	150.0	± 9.6 %
		Y	2.92	66.38	15.19		150.0	
		Z	2.84	65.43	14.41		150.0	
10113-CAC	LTE-FDD (SC-FDMA, 100% RB, 5 MHz, 64-QAM)	X	2.61	67.25	15.42	0.00	150.0	± 9.6 %
		Y	2.62	67.03	15.33		150.0	
		Z	2.49	65.62	14.29		150.0	
10114-CAB	IEEE 802.11n (HT Greenfield, 13.5 Mbps, BPSK)	X	5.07	66.96	16.20	0.00	150.0	± 9.6 %
		Y	5.09	66.91	16.15		150.0	
		Z	5.06	66.56	15.78		150.0	
10115-CAB	IEEE 802.11n (HT Greenfield, 81 Mbps, 16-QAM)	X	5.32	67.04	16.25	0.00	150.0	± 9.6 %
		Y	5.36	67.00	16.21		150.0	
		Z	5.33	66.69	15.87		150.0	
10116-CAB	IEEE 802.11n (HT Greenfield, 135 Mbps, 64-QAM)	X	5.15	67.13	16.21	0.00	150.0	± 9.6 %
		Y	5.18	67.07	16.17		150.0	
		Z	5.14	66.72	15.79		150.0	
10117-CAB	IEEE 802.11n (HT Mixed, 13.5 Mbps, BPSK)	X	5.04	66.86	16.16	0.00	150.0	± 9.6 %
		Y	5.06	66.79	16.11		150.0	
		Z	5.03	66.45	15.74		150.0	
10118-CAB	IEEE 802.11n (HT Mixed, 81 Mbps, 16-QAM)	X	5.39	67.22	16.35	0.00	150.0	± 9.6 %
		Y	5.43	67.18	16.31		150.0	
		Z	5.39	66.85	15.96		150.0	
10119-CAB	IEEE 802.11n (HT Mixed, 135 Mbps, 64-QAM)	X	5.13	67.09	16.21	0.00	150.0	± 9.6 %
		Y	5.16	67.03	16.16		150.0	
		Z	5.12	66.68	15.78		150.0	
10140-CAB	LTE-FDD (SC-FDMA, 100% RB, 15 MHz, 16-QAM)	X	3.28	66.78	15.43	0.00	150.0	± 9.6 %
		Y	3.28	66.61	15.33		150.0	
		Z	3.20	65.79	14.65		150.0	
10141-CAB	LTE-FDD (SC-FDMA, 100% RB, 15 MHz, 64-QAM)	X	3.40	66.93	15.62	0.00	150.0	± 9.6 %
		Y	3.41	66.77	15.53		150.0	
		Z	3.33	65.96	14.85		150.0	
10142-CAC	LTE-FDD (SC-FDMA, 100% RB, 3 MHz, QPSK)	X	1.78	66.63	14.50	0.00	150.0	± 9.6 %
		Y	1.78	66.26	14.33		150.0	
		Z	1.66	64.45	13.03		150.0	
10143-CAC	LTE-FDD (SC-FDMA, 100% RB, 3 MHz, 16-QAM)	X	2.25	67.31	14.65	0.00	150.0	± 9.6 %
		Y	2.26	67.08	14.59		150.0	
		Z	2.09	65.25	13.36		150.0	
10144-CAC	LTE-FDD (SC-FDMA, 100% RB, 3 MHz, 64-QAM)	X	2.07	65.42	13.21	0.00	150.0	± 9.6 %
		Y	2.09	65.28	13.20		150.0	
		Z	2.00	64.08	12.32		150.0	
10145-CAC	LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, QPSK)	X	1.05	63.06	10.20	0.00	150.0	± 9.6 %
		Y	1.09	63.24	10.48		150.0	
		Z	1.04	61.94	9.58		150.0	
10146-CAC	LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, 16-QAM)	X	1.43	63.12	9.42	0.00	150.0	± 9.6 %
		Y	1.74	64.74	10.48		150.0	
		Z	1.57	63.26	9.55		150.0	
10147-CAC	LTE-FDD (SC-FDMA, 100% RB, 1.4 MHz, 64-QAM)	X	1.55	64.01	10.00	0.00	150.0	± 9.6 %
		Y	1.96	66.08	11.26		150.0	
		Z	1.69	63.99	10.04		150.0	



EX3DV4- SN:3759

December 15, 2015

10149-CAB	LTE-FDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM)	X	2.79	66.54	15.24	0.00	150.0	± 9.6 %
		Y	2.80	66.34	15.12		150.0	
		Z	2.71	65.34	14.31		150.0	
10150-CAB	LTE-FDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM)	X	2.92	66.61	15.33	0.00	150.0	± 9.6 %
		Y	2.93	66.43	15.23		150.0	
		Z	2.84	65.46	14.44		150.0	
10151-CAB	LTE-TDD (SC-FDMA, 50% RB, 20 MHz, QPSK)	X	5.94	75.70	20.19	3.98	65.0	± 9.6 %
		Y	5.51	74.19	19.51		65.0	
		Z	5.20	72.66	18.67		65.0	
10152-CAB	LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 16-QAM)	X	5.47	72.25	19.12	3.98	65.0	± 9.6 %
		Y	5.23	71.20	18.59		65.0	
		Z	5.14	70.47	18.11		65.0	
10153-CAB	LTE-TDD (SC-FDMA, 50% RB, 20 MHz, 64-QAM)	X	5.83	73.21	19.90	3.98	65.0	± 9.6 %
		Y	5.58	72.17	19.39		65.0	
		Z	5.45	71.30	18.83		65.0	
10154-CAC	LTE-FDD (SC-FDMA, 50% RB, 10 MHz, QPSK)	X	2.06	67.19	15.25	0.00	150.0	± 9.6 %
		Y	2.05	66.83	15.06		150.0	
		Z	1.93	65.11	13.81		150.0	
10155-CAC	LTE-FDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM)	X	2.47	67.05	15.27	0.00	150.0	± 9.6 %
		Y	2.47	66.81	15.17		150.0	
		Z	2.35	65.37	14.10		150.0	
10156-CAC	LTE-FDD (SC-FDMA, 50% RB, 5 MHz, QPSK)	X	1.61	66.39	14.08	0.00	150.0	± 9.6 %
		Y	1.61	66.05	13.95		150.0	
		Z	1.49	64.09	12.57		150.0	
10157-CAC	LTE-FDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM)	X	1.87	65.61	13.02	0.00	150.0	± 9.6 %
		Y	1.90	65.48	13.04		150.0	
		Z	1.79	64.01	12.02		150.0	
10158-CAC	LTE-FDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM)	X	2.62	67.31	15.46	0.00	150.0	± 9.6 %
		Y	2.62	67.09	15.37		150.0	
		Z	2.50	65.65	14.32		150.0	
10159-CAC	LTE-FDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM)	X	1.96	65.96	13.24	0.00	150.0	± 9.6 %
		Y	1.98	65.84	13.28		150.0	
		Z	1.85	64.27	12.21		150.0	
10160-CAB	LTE-FDD (SC-FDMA, 50% RB, 15 MHz, QPSK)	X	2.57	67.35	15.49	0.00	150.0	± 9.6 %
		Y	2.57	67.04	15.32		150.0	
		Z	2.44	65.67	14.31		150.0	
10161-CAB	LTE-FDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM)	X	2.81	66.53	15.22	0.00	150.0	± 9.6 %
		Y	2.82	66.34	15.12		150.0	
		Z	2.73	65.34	14.31		150.0	
10162-CAB	LTE-FDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM)	X	2.92	66.73	15.36	0.00	150.0	± 9.6 %
		Y	2.93	66.54	15.26		150.0	
		Z	2.84	65.53	14.45		150.0	
10166-CAC	LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK)	X	3.29	68.19	18.33	3.01	150.0	± 9.6 %
		Y	3.51	68.98	18.72		150.0	
		Z	3.40	67.92	17.89		150.0	
10167-CAC	LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM)	X	3.82	70.64	18.68	3.01	150.0	± 9.6 %
		Y	4.31	72.22	19.35		150.0	
		Z	4.06	70.75	18.41		150.0	



EX3DV4- SN:3759

December 15, 2015

10168-CAC	LTE-FDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM)	X	4.20	72.71	19.96	3.01	150.0	± 9.6 %
		Y	4.87	74.88	20.89		150.0	
		Z	4.45	72.72	19.62		150.0	
10169-CAB	LTE-FDD (SC-FDMA, 1 RB, 20 MHz, QPSK)	X	2.63	66.83	17.73	3.01	150.0	± 9.6 %
		Y	2.93	68.39	18.45		150.0	
		Z	2.81	67.22	17.54		150.0	
10170-CAB	LTE-FDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)	X	3.24	71.42	19.68	3.01	150.0	± 9.6 %
		Y	4.12	75.18	21.22		150.0	
		Z	3.67	72.59	19.71		150.0	
10171-AAB	LTE-FDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM)	X	2.76	68.22	17.25	3.01	150.0	± 9.6 %
		Y	3.29	70.52	18.19		150.0	
		Z	3.08	69.10	17.23		150.0	
10172-CAB	LTE-TDD (SC-FDMA, 1 RB, 20 MHz, QPSK)	X	5.47	82.72	25.06	6.02	65.0	± 9.6 %
		Y	4.20	76.96	22.67		65.0	
		Z	4.05	75.61	21.82		65.0	
10173-CAB	LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)	X	7.27	85.40	24.19	6.02	65.0	± 9.6 %
		Y	8.35	87.00	24.60		65.0	
		Z	6.50	82.14	22.62		65.0	
10174-CAB	LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 64-QAM)	X	5.74	80.70	22.00	6.02	65.0	± 9.6 %
		Y	5.36	79.02	21.33		65.0	
		Z	4.82	76.71	20.17		65.0	
10175-CAC	LTE-FDD (SC-FDMA, 1 RB, 10 MHz, QPSK)	X	2.61	66.61	17.52	3.01	150.0	± 9.6 %
		Y	2.89	68.08	18.20		150.0	
		Z	2.78	66.99	17.33		150.0	
10176-CAC	LTE-FDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM)	X	3.25	71.44	19.69	3.01	150.0	± 9.6 %
		Y	4.13	75.21	21.23		150.0	
		Z	3.67	72.61	19.72		150.0	
10177-CAE	LTE-FDD (SC-FDMA, 1 RB, 5 MHz, QPSK)	X	2.63	66.72	17.59	3.01	150.0	± 9.6 %
		Y	2.92	68.23	18.30		150.0	
		Z	2.80	67.10	17.40		150.0	
10178-CAC	LTE-FDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM)	X	3.23	71.31	19.61	3.01	150.0	± 9.6 %
		Y	4.08	74.97	21.11		150.0	
		Z	3.65	72.45	19.63		150.0	
10179-CAC	LTE-FDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM)	X	2.98	69.75	18.35	3.01	150.0	± 9.6 %
		Y	3.65	72.66	19.54		150.0	
		Z	3.34	70.72	18.33		150.0	
10180-CAC	LTE-FDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM)	X	2.76	68.18	17.22	3.01	150.0	± 9.6 %
		Y	3.29	70.46	18.14		150.0	
		Z	3.07	69.06	17.19		150.0	
10181-CAB	LTE-FDD (SC-FDMA, 1 RB, 15 MHz, QPSK)	X	2.62	66.70	17.59	3.01	150.0	± 9.6 %
		Y	2.91	68.21	18.29		150.0	
		Z	2.80	67.09	17.40		150.0	
10182-CAB	LTE-FDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM)	X	3.22	71.28	19.59	3.01	150.0	± 9.6 %
		Y	4.07	74.94	21.10		150.0	
		Z	3.64	72.43	19.62		150.0	
10183-AAA	LTE-FDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM)	X	2.76	68.16	17.21	3.01	150.0	± 9.6 %
		Y	3.28	70.43	18.13		150.0	
		Z	3.07	69.04	17.18		150.0	



EX3DV4- SN:3759

December 15, 2015

10184-CAC	LTE-FDD (SC-FDMA, 1 RB, 3 MHz, QPSK)	X	2.63	66.74	17.61	3.01	150.0	± 9.6 %
		Y	2.92	68.25	18.31		150.0	
		Z	2.81	67.12	17.42		150.0	
10185-CAC	LTE-FDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM)	X	3.23	71.35	19.63	3.01	150.0	± 9.6 %
		Y	4.10	75.03	21.14		150.0	
		Z	3.66	72.49	19.65		150.0	
10186-AAC	LTE-FDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM)	X	2.77	68.22	17.24	3.01	150.0	± 9.6 %
		Y	3.30	70.50	18.17		150.0	
		Z	3.08	69.09	17.21		150.0	
10187-CAC	LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK)	X	2.64	66.79	17.67	3.01	150.0	± 9.6 %
		Y	2.93	68.31	18.38		150.0	
		Z	2.82	67.18	17.48		150.0	
10188-CAC	LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM)	X	3.31	71.83	19.94	3.01	150.0	± 9.6 %
		Y	4.24	75.78	21.56		150.0	
		Z	3.75	73.03	19.98		150.0	
10189-AAC	LTE-FDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM)	X	2.82	68.54	17.47	3.01	150.0	± 9.6 %
		Y	3.37	70.94	18.46		150.0	
		Z	3.14	69.44	17.45		150.0	
10193-CAB	IEEE 802.11n (HT Greenfield, 6.5 Mbps, BPSK)	X	4.47	66.43	15.87	0.00	150.0	± 9.6 %
		Y	4.49	66.34	15.81		150.0	
		Z	4.46	65.95	15.40		150.0	
10194-CAB	IEEE 802.11n (HT Greenfield, 39 Mbps, 16-QAM)	X	4.62	66.71	16.00	0.00	150.0	± 9.6 %
		Y	4.64	66.62	15.94		150.0	
		Z	4.61	66.23	15.54		150.0	
10195-CAB	IEEE 802.11n (HT Greenfield, 65 Mbps, 64-QAM)	X	4.66	66.74	16.02	0.00	150.0	± 9.6 %
		Y	4.68	66.66	15.96		150.0	
		Z	4.65	66.27	15.56		150.0	
10196-CAB	IEEE 802.11n (HT Mixed, 6.5 Mbps, BPSK)	X	4.46	66.46	15.87	0.00	150.0	± 9.6 %
		Y	4.48	66.37	15.82		150.0	
		Z	4.45	65.98	15.41		150.0	
10197-CAB	IEEE 802.11n (HT Mixed, 39 Mbps, 16-QAM)	X	4.63	66.72	16.01	0.00	150.0	± 9.6 %
		Y	4.66	66.64	15.95		150.0	
		Z	4.62	66.25	15.55		150.0	
10198-CAB	IEEE 802.11n (HT Mixed, 65 Mbps, 64-QAM)	X	4.66	66.75	16.03	0.00	150.0	± 9.6 %
		Y	4.68	66.67	15.97		150.0	
		Z	4.65	66.28	15.57		150.0	
10219-CAB	IEEE 802.11n (HT Mixed, 7.2 Mbps, BPSK)	X	4.41	66.47	15.83	0.00	150.0	± 9.6 %
		Y	4.43	66.38	15.78		150.0	
		Z	4.40	65.97	15.35		150.0	
10220-CAB	IEEE 802.11n (HT Mixed, 43.3 Mbps, 16-QAM)	X	4.62	66.69	16.00	0.00	150.0	± 9.6 %
		Y	4.65	66.61	15.94		150.0	
		Z	4.62	66.22	15.54		150.0	
10221-CAB	IEEE 802.11n (HT Mixed, 72.2 Mbps, 64-QAM)	X	4.67	66.69	16.02	0.00	150.0	± 9.6 %
		Y	4.70	66.61	15.96		150.0	
		Z	4.67	66.23	15.56		150.0	
10222-CAB	IEEE 802.11n (HT Mixed, 15 Mbps, BPSK)	X	5.02	66.85	16.15	0.00	150.0	± 9.6 %
		Y	5.04	66.79	16.10		150.0	
		Z	5.01	66.45	15.73		150.0	



EX3DV4- SN:3759

December 15, 2015

10223-CAB	IEEE 802.11n (HT Mixed, 90 Mbps, 16-QAM)	X	5.31	67.09	16.29	0.00	150.0	± 9.6 %
		Y	5.34	67.04	16.25		150.0	
		Z	5.30	66.71	15.90		150.0	
10224-CAB	IEEE 802.11n (HT Mixed, 150 Mbps, 64-QAM)	X	5.06	66.96	16.14	0.00	150.0	± 9.6 %
		Y	5.08	66.89	16.09		150.0	
		Z	5.05	66.55	15.71		150.0	
10225-CAB	UMTS-FDD (HSPA+)	X	2.72	65.54	14.67	0.00	150.0	± 9.6 %
		Y	2.73	65.39	14.61		150.0	
		Z	2.68	64.57	13.91		150.0	
10226-CAA	LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 16-QAM)	X	7.63	86.31	24.59	6.02	65.0	± 9.6 %
		Y	8.86	88.13	25.08		65.0	
		Z	6.77	82.89	22.97		65.0	
10227-CAA	LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, 64-QAM)	X	7.45	84.85	23.48	6.02	65.0	± 9.6 %
		Y	8.67	86.63	23.98		65.0	
		Z	6.62	81.60	21.95		65.0	
10228-CAA	LTE-TDD (SC-FDMA, 1 RB, 1.4 MHz, QPSK)	X	5.56	83.10	25.23	6.02	65.0	± 9.6 %
		Y	5.57	82.43	24.85		65.0	
		Z	4.86	79.06	23.24		65.0	
10229-CAB	LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 16-QAM)	X	7.32	85.49	24.23	6.02	65.0	± 9.6 %
		Y	8.41	87.12	24.65		65.0	
		Z	6.54	82.23	22.66		65.0	
10230-CAB	LTE-TDD (SC-FDMA, 1 RB, 3 MHz, 64-QAM)	X	7.11	84.01	23.12	6.02	65.0	± 9.6 %
		Y	8.19	85.62	23.56		65.0	
		Z	6.36	80.93	21.64		65.0	
10231-CAB	LTE-TDD (SC-FDMA, 1 RB, 3 MHz, QPSK)	X	5.39	82.47	24.92	6.02	65.0	± 9.6 %
		Y	5.38	81.75	24.52		65.0	
		Z	4.74	78.57	22.98		65.0	
10232-CAB	LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 16-QAM)	X	7.30	85.47	24.22	6.02	65.0	± 9.6 %
		Y	8.40	87.10	24.64		65.0	
		Z	6.53	82.21	22.65		65.0	
10233-CAB	LTE-TDD (SC-FDMA, 1 RB, 5 MHz, 64-QAM)	X	7.09	83.98	23.11	6.02	65.0	± 9.6 %
		Y	8.17	85.59	23.55		65.0	
		Z	6.35	80.90	21.64		65.0	
10234-CAB	LTE-TDD (SC-FDMA, 1 RB, 5 MHz, QPSK)	X	5.25	81.89	24.59	6.02	65.0	± 9.6 %
		Y	5.23	81.13	24.18		65.0	
		Z	4.64	78.11	22.70		65.0	
10235-CAB	LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 16-QAM)	X	7.30	85.49	24.23	6.02	65.0	± 9.6 %
		Y	8.40	87.11	24.65		65.0	
		Z	6.53	82.22	22.66		65.0	
10236-CAB	LTE-TDD (SC-FDMA, 1 RB, 10 MHz, 64-QAM)	X	7.16	84.11	23.15	6.02	65.0	± 9.6 %
		Y	8.24	85.72	23.59		65.0	
		Z	6.40	81.00	21.67		65.0	
10237-CAB	LTE-TDD (SC-FDMA, 1 RB, 10 MHz, QPSK)	X	5.39	82.50	24.93	6.02	65.0	± 9.6 %
		Y	5.38	81.76	24.53		65.0	
		Z	4.74	78.58	22.98		65.0	
10238-CAB	LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 16-QAM)	X	7.29	85.45	24.21	6.02	65.0	± 9.6 %
		Y	8.37	87.06	24.63		65.0	
		Z	6.51	82.18	22.64		65.0	



EX3DV4- SN:3759

December 15, 2015

10239-CAB	LTE-TDD (SC-FDMA, 1 RB, 15 MHz, 64-QAM)	X	7.07	83.95	23.10	6.02	65.0	± 9.6 %
		Y	8.14	85.56	23.54		65.0	
		Z	6.33	80.87	21.62		65.0	
10240-CAB	LTE-TDD (SC-FDMA, 1 RB, 15 MHz, QPSK)	X	5.38	82.47	24.92	6.02	65.0	± 9.6 %
		Y	5.37	81.73	24.51		65.0	
		Z	4.73	78.56	22.97		65.0	
10241-CAA	LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 16-QAM)	X	7.17	79.14	24.28	6.98	65.0	± 9.6 %
		Y	7.29	78.93	24.09		65.0	
		Z	7.06	77.98	23.58		65.0	
10242-CAA	LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, 64-QAM)	X	6.66	77.62	23.56	6.98	65.0	± 9.6 %
		Y	6.18	75.54	22.58		65.0	
		Z	6.18	75.29	22.35		65.0	
10243-CAA	LTE-TDD (SC-FDMA, 50% RB, 1.4 MHz, QPSK)	X	5.52	74.33	22.97	6.98	65.0	± 9.6 %
		Y	5.14	72.24	21.90		65.0	
		Z	5.18	72.09	21.70		65.0	
10244-CAB	LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 16-QAM)	X	4.36	70.62	15.44	3.98	65.0	± 9.6 %
		Y	4.59	71.27	15.92		65.0	
		Z	4.21	69.60	15.06		65.0	
10245-CAB	LTE-TDD (SC-FDMA, 50% RB, 3 MHz, 64-QAM)	X	4.29	70.16	15.18	3.98	65.0	± 9.6 %
		Y	4.52	70.81	15.66		65.0	
		Z	4.18	69.28	14.87		65.0	
10246-CAB	LTE-TDD (SC-FDMA, 50% RB, 3 MHz, QPSK)	X	4.01	72.52	16.68	3.98	65.0	± 9.6 %
		Y	3.73	71.39	16.29		65.0	
		Z	3.40	69.47	15.35		65.0	
10247-CAB	LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 16-QAM)	X	4.34	70.86	16.59	3.98	65.0	± 9.6 %
		Y	4.15	70.08	16.32		65.0	
		Z	3.98	68.93	15.68		65.0	
10248-CAB	LTE-TDD (SC-FDMA, 50% RB, 5 MHz, 64-QAM)	X	4.35	70.49	16.41	3.98	65.0	± 9.6 %
		Y	4.19	69.76	16.16		65.0	
		Z	4.04	68.75	15.59		65.0	
10249-CAB	LTE-TDD (SC-FDMA, 50% RB, 5 MHz, QPSK)	X	5.03	76.01	19.12	3.98	65.0	± 9.6 %
		Y	4.53	74.20	18.43		65.0	
		Z	4.06	71.82	17.26		65.0	
10250-CAB	LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 16-QAM)	X	5.34	73.84	19.67	3.98	65.0	± 9.6 %
		Y	5.06	72.69	19.17		65.0	
		Z	4.84	71.36	18.39		65.0	
10251-CAB	LTE-TDD (SC-FDMA, 50% RB, 10 MHz, 64-QAM)	X	5.18	72.21	18.62	3.98	65.0	± 9.6 %
		Y	4.94	71.17	18.14		65.0	
		Z	4.81	70.28	17.59		65.0	
10252-CAB	LTE-TDD (SC-FDMA, 50% RB, 10 MHz, QPSK)	X	5.71	77.17	20.66	3.98	65.0	± 9.6 %
		Y	5.16	75.23	19.84		65.0	
		Z	4.74	73.12	18.75		65.0	
10253-CAB	LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 16-QAM)	X	5.40	71.87	18.90	3.98	65.0	± 9.6 %
		Y	5.16	70.85	18.40		65.0	
		Z	5.08	70.16	17.94		65.0	
10254-CAB	LTE-TDD (SC-FDMA, 50% RB, 15 MHz, 64-QAM)	X	5.72	72.73	19.59	3.98	65.0	± 9.6 %
		Y	5.48	71.72	19.10		65.0	
		Z	5.37	70.91	18.57		65.0	



EX3DV4- SN:3759

December 15, 2015

10255-CAB	LTE-TDD (SC-FDMA, 50% RB, 15 MHz, QPSK)	X	5.72	75.21	20.17	3.98	65.0	± 9.6 %
		Y	5.32	73.72	19.49		65.0	
		Z	5.06	72.29	18.68		65.0	
10256-CAA	LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, 16-QAM)	X	3.34	66.97	12.65	3.98	65.0	± 9.6 %
		Y	3.55	67.68	13.21		65.0	
		Z	3.38	66.73	12.71		65.0	
10257-CAA	LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, 64-QAM)	X	3.29	66.49	12.32	3.98	65.0	± 9.6 %
		Y	3.49	67.18	12.87		65.0	
		Z	3.36	66.37	12.44		65.0	
10258-CAA	LTE-TDD (SC-FDMA, 100% RB, 1.4 MHz, QPSK)	X	3.07	68.48	13.96	3.98	65.0	± 9.6 %
		Y	2.97	68.04	13.90		65.0	
		Z	2.82	66.85	13.31		65.0	
10259-CAB	LTE-TDD (SC-FDMA, 100% RB, 3 MHz, 16-QAM)	X	4.73	72.02	17.73	3.98	65.0	± 9.6 %
		Y	4.50	71.08	17.36		65.0	
		Z	4.31	69.85	16.67		65.0	
10260-CAB	LTE-TDD (SC-FDMA, 100% RB, 3 MHz, 64-QAM)	X	4.77	71.84	17.65	3.98	65.0	± 9.6 %
		Y	4.56	70.95	17.30		65.0	
		Z	4.38	69.78	16.64		65.0	
10261-CAB	LTE-TDD (SC-FDMA, 100% RB, 3 MHz, QPSK)	X	5.13	75.91	19.52	3.98	65.0	± 9.6 %
		Y	4.64	74.10	18.79		65.0	
		Z	4.24	71.97	17.71		65.0	
10262-CAB	LTE-TDD (SC-FDMA, 100% RB, 5 MHz, 16-QAM)	X	5.33	73.78	19.62	3.98	65.0	± 9.6 %
		Y	5.05	72.64	19.12		65.0	
		Z	4.83	71.32	18.35		65.0	
10263-CAB	LTE-TDD (SC-FDMA, 100% RB, 5 MHz, 64-QAM)	X	5.17	72.19	18.61	3.98	65.0	± 9.6 %
		Y	4.93	71.15	18.14		65.0	
		Z	4.81	70.26	17.59		65.0	
10264-CAB	LTE-TDD (SC-FDMA, 100% RB, 5 MHz, QPSK)	X	5.67	77.01	20.58	3.98	65.0	± 9.6 %
		Y	5.13	75.08	19.76		65.0	
		Z	4.72	73.01	18.69		65.0	
10265-CAB	LTE-TDD (SC-FDMA, 100% RB, 10 MHz, 16-QAM)	X	5.47	72.25	19.13	3.98	65.0	± 9.6 %
		Y	5.23	71.20	18.60		65.0	
		Z	5.14	70.47	18.11		65.0	
10266-CAB	LTE-TDD (SC-FDMA, 100% RB, 10 MHz, 64-QAM)	X	5.83	73.20	19.89	3.98	65.0	± 9.6 %
		Y	5.58	72.16	19.38		65.0	
		Z	5.45	71.29	18.82		65.0	
10267-CAB	LTE-TDD (SC-FDMA, 100% RB, 10 MHz, QPSK)	X	5.93	75.67	20.18	3.98	65.0	± 9.6 %
		Y	5.50	74.16	19.50		65.0	
		Z	5.20	72.64	18.66		65.0	
10268-CAB	LTE-TDD (SC-FDMA, 100% RB, 15 MHz, 16-QAM)	X	6.16	72.51	19.69	3.98	65.0	± 9.6 %
		Y	5.94	71.60	19.22		65.0	
		Z	5.86	70.98	18.79		65.0	
10269-CAB	LTE-TDD (SC-FDMA, 100% RB, 15 MHz, 64-QAM)	X	6.17	72.20	19.61	3.98	65.0	± 9.6 %
		Y	5.96	71.33	19.15		65.0	
		Z	5.89	70.77	18.75		65.0	
10270-CAB	LTE-TDD (SC-FDMA, 100% RB, 15 MHz, QPSK)	X	6.07	73.94	19.64	3.98	65.0	± 9.6 %
		Y	5.77	72.85	19.12		65.0	
		Z	5.58	71.81	18.48		65.0	



EX3DV4- SN:3759

December 15, 2015

10274-CAB	UMTS-FDD (HSUPA, Subtest 5, 3GPP Rel8.10)	X	2.51	65.84	14.58	0.00	150.0	± 9.6 %
		Y	2.52	65.60	14.47		150.0	
		Z	2.44	64.63	13.68		150.0	
10275-CAB	UMTS-FDD (HSUPA, Subtest 5, 3GPP Rel8.4)	X	1.48	65.87	14.27	0.00	150.0	± 9.6 %
		Y	1.47	65.43	14.03		150.0	
		Z	1.39	63.67	12.69		150.0	
10277-CAA	PHS (QPSK)	X	2.32	61.85	7.43	9.03	50.0	± 9.6 %
		Y	2.39	62.00	7.67		50.0	
		Z	2.59	62.64	8.34		50.0	
10278-CAA	PHS (QPSK, BW 884MHz, Rolloff 0.5)	X	4.01	69.23	13.78	9.03	50.0	± 9.6 %
		Y	4.05	69.29	13.97		50.0	
		Z	4.11	69.29	14.23		50.0	
10279-CAA	PHS (QPSK, BW 884MHz, Rolloff 0.38)	X	4.10	69.46	13.94	9.03	50.0	± 9.6 %
		Y	4.14	69.51	14.11		50.0	
		Z	4.20	69.48	14.36		50.0	
10290-AAB	CDMA2000, RC1, SO55, Full Rate	X	1.14	65.37	11.96	0.00	150.0	± 9.6 %
		Y	1.16	65.27	12.04		150.0	
		Z	1.04	63.04	10.62		150.0	
10291-AAB	CDMA2000, RC3, SO55, Full Rate	X	0.72	63.34	10.83	0.00	150.0	± 9.6 %
		Y	0.74	63.23	10.92		150.0	
		Z	0.70	61.43	9.60		150.0	
10292-AAB	CDMA2000, RC3, SO32, Full Rate	X	0.81	65.45	12.33	0.00	150.0	± 9.6 %
		Y	0.81	65.06	12.27		150.0	
		Z	0.72	62.22	10.36		150.0	
10293-AAB	CDMA2000, RC3, SO3, Full Rate	X	1.01	68.43	14.20	0.00	150.0	± 9.6 %
		Y	0.98	67.59	13.94		150.0	
		Z	0.79	63.25	11.26		150.0	
10295-AAB	CDMA2000, RC1, SO3, 1/8th Rate 25 fr.	X	8.27	81.58	21.80	9.03	50.0	± 9.6 %
		Y	7.31	79.27	20.97		50.0	
		Z	6.65	77.32	20.30		50.0	
10297-AAA	LTE-FDD (SC-FDMA, 50% RB, 20 MHz, QPSK)	X	2.52	67.96	15.65	0.00	150.0	± 9.6 %
		Y	2.51	67.62	15.46		150.0	
		Z	2.36	66.02	14.32		150.0	
10298-AAB	LTE-FDD (SC-FDMA, 50% RB, 3 MHz, QPSK)	X	1.31	65.03	12.32	0.00	150.0	± 9.6 %
		Y	1.34	64.95	12.39		150.0	
		Z	1.24	63.11	11.14		150.0	
10299-AAB	LTE-FDD (SC-FDMA, 50% RB, 3 MHz, 16-QAM)	X	1.94	65.97	11.96	0.00	150.0	± 9.6 %
		Y	2.37	67.93	13.07		150.0	
		Z	2.01	65.39	11.59		150.0	
10300-AAB	LTE-FDD (SC-FDMA, 50% RB, 3 MHz, 64-QAM)	X	1.58	63.06	9.76	0.00	150.0	± 9.6 %
		Y	1.84	64.23	10.55		150.0	
		Z	1.73	63.17	9.82		150.0	
10301-AAA	IEEE 802.16e WiMAX (29:18, 5ms, 10MHz, QPSK, PUSC)	X	4.65	65.37	17.24	4.17	50.0	± 9.6 %
		Y	4.53	64.58	16.80		50.0	
		Z	4.58	64.53	16.64		50.0	
10302-AAA	IEEE 802.16e WiMAX (29:18, 5ms, 10MHz, QPSK, PUSC, 3 CTRL symbols)	X	5.08	65.78	17.86	4.96	50.0	± 9.6 %
		Y	5.05	65.38	17.62		50.0	
		Z	5.09	65.33	17.48		50.0	