

Operational Description of the equipment

1. Install i-gotU Desktop

Insert the CD-ROM to the CD-ROM drive and follow the on-screen instructions to install **i-gotU Desktop**.

2. Charge i-gotU GT-100/ GT-200

i-gotU Dock/ i-gotU USB Cable serves as a charger as well as data transfer medium. Please follow the instructions shown in the illustrations below to connect **i-gotU GT-100/ GT-200** to your PC to fully charge your **i-gotU GT-100/ GT-200**.

It takes about 2 hours to fully charge your **i-gotU GT-100/ GT-200** for the first time. The red LED indicator stays on during charging, and goes off when charging is complete. Remove your **i-gotU GT-100/ GT-200** when charging is complete.

PRODUCT	i-gotU
MODEL NO.	GT-200
BUILD-IN BATTERY	Li-Polymer 3.7V, 750mAH
CHARGE POWER	USB Port Power(DC 5.0V, 500mA)
FREQUENCY BAND	2.402GHz~2.480GHz(Bluetooth) 1.57542GHz(GPS)
CARRIER FREQUENCY	FHSS(Frequency Hopping Spread Spectrum) (Bluetooth) NA (GPS)
NUMBER OF CHANNEL	79 (Bluetooth) NA (GPS)
CHANNEL SPACING	1 MHz (Bluetooth) NA (GPS)
RATED RF OUTPUT POWER	+4 dBm (Bluetooth) NA (GPS)
MODE OF OPERATION	duplex (Bluetooth) simplex (GPS)
MODULATION TYPE	Fully Qualified Bluetooth V2.0+EDR GFSK / EDR(τ /4DQPSK) (Bluetooth) GPS Receive(GPS)
BIT RATE OF TRANSMISSION	2 Mbps (Bluetooth) NA (GPS)
ANTENNA TYPE	PCB Layout Antenna (Bluetooth) PATCH Type Antenna (PA1575MJ2G-XXX-L6) (GPS)
ANTENNA GAIN	0 dBi (Bluetooth) 1.4 dBi (GPS)
CHANNEL BANDWIDTH	1MHz