

Channel Plan

Bandwidth	Channel #	Scanning	DFS
2.4GHz Band			
20MHz	1 - 11	Active	No - N/A
40MHz	3 - 9	Active	No - N/A
Operation on channels 12 & 13 for 20MHz and channels 10 & 11 for 40MHz is not supported.			
UNII1 Band			
20MHz	36 - 48	Active	No - N/A
40MHz	38, 46	Active	No - N/A
80MHz	42	Active	No - N/A
UNII2a Band (added via FCC C3PC)			
20MHz	52 - 64	Passive	DFS Master
40MHz	54, 62	Passive	DFS Master
80MHz	58	Passive	DFS Master
UNII2c Band (added via FCC C3PC)			
20MHz	100 – 144 (Channels 120 -128 not supported in Canada)	Passive	DFS Master
40MHz	102 – 142 (Channels 118 and 126 not supported in Canada)	Passive	DFS Master
80MHz	106 – 138 (Channel 122 not supported in Canada)	Passive	DFS Master
UNII3 Band			
20MHz	149 - 165	Active	No - N/A
40MHz	151, 159	Active	No - N/A
80MHz	155	Active	No - N/A