
















Shortcut key

You can assign two selected functions to the Right soft key and activate them by a **Short press** (press once) or a **Long press** (press and hold).

From **My Phone menu**

1.  move to **Shortcut key**
2. Press  (Select)
3.  move to **Short press** or **Long press**
4. Press  (Select)
5.  move to the required function
6. Press  (Select)

The following functions are available:

	Camera		Start Browser		Calendar
	Games		My Media		Calculator
	Contacts		Alarms		Sound recorder

Phone settings

You can customise each phone setting.

From **My Phone** menu

1. move to **Phone settings**
2. Press (Select)
3. move to the required settings
4. Press (Select)



Call services

From **Phone settings** menu

1. move to **Call services**
2. Press (Select)
3. move to the required setting
4. Press (Select)




Calls

You can check the call status.

From **Call services** menu

1. move to **Calls**
2. Press (Select)
3. move to the required status
4. Press (Select)



Last call	See the duration of the last call.
All calls	See the total duration of all calls. Reset the total by pressing (Reset).
Call waiting	Activate Call waiting and see the status.
Caller's ID	Check how Caller's ID is received.
Withhold ID	Check how your call ID is sent.
Active line	Select a line to activate (<input type="checkbox"/>).

Service charges

You can control the cost of calls by setting the limit on the cost of calls and charge units of call time.

From **Call services menu**

1. move to **Service charges**
2. Press (Select)
3. move to the required item to set
4. The current setting is displayed.

You need to enter the **PIN2** code to edit the **Max cost** and **Price unit**.

Cost left	Check the cost left.
Price unit	You can set the price per unit to add up the total by pressing (Edit).
Max cost	You can edit the Max cost by pressing (Edit).
Call meters	Check the total cost. You can reset the total cost by pressing (Reset).

Connections

You can see the amount of transferred data. You also can reset the total amount of transferred data shown in **All connections** menu.

From **Call services menu**

1. move to **Connections**
2. Press (Select)
3. move to **Last connections** or **All connections**
4. Press (Select)



Show my number

You can select whether your ID will be displayed or not.

From **Call services menu**

1. move to **Show my number**
2. Press (Select)
3. move to the required method
4. Press (Select)



Call diverts

You can divert calls by setting the condition according to the type of calls.

From **Phone settings** menu

1. move to **Call diverts**
2. Press (Select)
3. move to the required type of calls or **Cancel all**
4. Press (Select)
When you select **Voice calls**,
 move to the required type and press (Select)
5. move to **Status, On or Off**
6. Press (Select)
When you select **On**, enter the phone number to divert. Then press (OK)



Voice calls	<p>Voice calls will be diverted under the following conditions:</p> <p>Not reachable: When the phone is not in the network coverage area, all incoming voice calls will be diverted.</p> <p>No reply: Unanswered incoming voice calls will be diverted.</p> <p>Busy: When the lines are busy, all incoming voice calls will be diverted.</p> <p>All conditional: With above 3 conditions, all incoming voice calls will be diverted (<input type="checkbox"/>).</p> <p>All voice calls: All incoming voice calls will be diverted.</p>
Fax calls	Fax calls will be diverted.
Data calls	Data calls will be diverted.
Cancel all	No calls will be diverted.

Security

You can limit access to protect your phone, SIM, calls, information and data. You must enable the **PIN** before changing the code.



Phone lock

You can lock your phone, and you will be prompted to enter your unlock code when you switch on the phone with a different SIM inserted.

From **Security menu**

1. Press **[Select]**
2. **[Left Arrow]** move to **Status** or **Change code**



Note: You are advised to write down your unlock code for yourself. If you forget your unlock code, you will need to contact your service provider to unlock the phone.

Changing the Status

From **Phone lock menu**

1. Press **[Select]**
2. **[Left Arrow]** move to **On** or **Off**
3. Press **[Select]**
4. Enter the correct 4-digit unlock code
5. Press **[OK]**

OR

In **idle screen**

1. Press and hold **[Menu]**
2. **[Left Arrow]** move to **Phone lock**
3. Press **[On]**
4. Enter the correct 4-digit unlock code
5. Press **[OK]**

Changing the Unlock code

From **Phone lock** menu

1. move to **Change code**
2. Press (Select)
3. Enter old unlock code
4. Press (OK)
5. Enter new unlock code
6. Press (OK)
7. Enter new unlock code to verify
8. Press (OK)

Call bar

You can bar certain outgoing and/or incoming calls using a password supplied by your service provider. When updating/checking the **Call bar** status, the phone must be registered to a network.

From **Security** menu

1. move to **Call bar**
2. Press (Select)
3. move to the required function
4. Press (Select)



Bar voice	You can bar Voice calls and select the type from Incoming calls and/or Outgoing calls .
Bar data	You can bar Data calls and select the type from Off , International calls except home , International calls or All calls .
Cancel all	You can cancel all Call bar settings.
Change password	You can change the password.

PIN

You can protect your **SIM** against unauthorised use. Once you enable the **PIN**, you will be prompted to enter the **PIN** code each time you switch on the phone. You must enable the **PIN** before changing the **PIN** code, and you must enter the **PIN** code to unble the **PIN**.

From **Security menu**

1. move to **PIN**
2. Press (Select)
3. move to **Status** or **Change**
4. Press (Select)



Changing the PIN code

Ensure the **PIN Status** is **On** before changing the **PIN** code.

1. Enter old **PIN** code with -
2. Press (OK)
3. Enter new **PIN** code with -
4. Press (OK)
5. Enter new **PIN** code to verify
6. Press (OK)

Changing the Status

1. move to **On** or **Off**
2. Press (Select)
3. Enter the **PIN** code with -
4. Press (OK)

PIN2

You cannot change the **PIN2** code without the current **PIN2** code.

From **Security menu**

1. move to **PIN2**
2. Press (Select)
3. Enter old **PIN2** code with -
4. Press (OK)
5. Enter new **PIN2** code with -
6. Press (OK)
7. Enter new **PIN2** code to verify
8. Press (OK)



Fixed dial

The **Fixed dial** feature allows you to limit your outgoing calls to a certain set of numbers saved in FDN (Fixed Dial Numbers), which is located in your SIM. When this function is on, only FDN can be dialled, and any attempt to call other numbers will fail.

From **Security menu**

1. move to **Fixed dial**
2. Press (Select)
3. Enter **SIM PIN2** code with - (PIN2)
4. Press (OK)
5. move to **On** or **Off**
6. Press (Select)



Network

You can select a **Network** that is available in your current location.

From **Phone settings menu**

1. move to **Network**
2. Press (Select)
3. move to **New network** or **Search mode**
4. Press (Select)



New network	You can find a New network from the list.
Search mode	You can select an available network by Manual or Automatic .

Defaults









You can return all personal settings in **My Phone** menu to the factory default settings.

From **My Phone menu**


1. move to **Defaults**
2. Press (Select)
3. Press (Select)



Contacts

 Contacts list	page 46	Viewing the Contacts list 46 Viewing the entries in the Contacts list..... 46 Editing the Contacts list..... 47 Making a call using the Contacts list 47 Sending messages from the Contacts list 48 Deleting an entry from the Contacts list 48 Copying an entry to the other Contacts list 48
 Create	page 49	Creating a new entry 49
 Groups	page 51	Viewing the Group 51 Editing the Group 51
 Memory status	page 52	Copying all entries to the other Contacts list ... 52
 My numbers	page 53	Viewing My numbers 53 Editing My numbers..... 53
 Voicemail	page 54	Viewing Voicemail 54 Editing Voicemail 54
 Hot key dial	page 55	Assigning Hot keys..... 55 Viewing Hot key dial list..... 55
 My Contacts	page 55	

You can store phone numbers in two locations: the **SIM Contacts list** and the **Phone Contacts list**.

 **Note:** See “Text Entry” on page 26 for information on entering text.

Contacts list

You can browse the **SIM Contacts list** and the **Phone Contacts list** individually, or both **Contacts list** together.

Viewing the Contacts list

From **Contacts menu**

1. Press **(Select)**
2. **(Move)** move to the required entry
OR
Press the numeric key which contains the first letter of the required name



	Located in Phone Contacts list
	Located in SIM Contacts list

Viewing the entries in the Contacts list

From **Contacts list menu**

1. **(Move)** move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press **(Menu)**
3. Press **(Select)**



Editing the Contacts list

From **Contacts list menu**

1. move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press (Menu)
3. move to **Edit**
4. Press (Select)
5. move to the required item
6. Press (Edit)
7. Edit an entry item
8. Press (OK)
9. Press (Save)



Note: SIM Contacts list can contain only Name, Tel number 1 and Location No.

Making a call using the Contacts list

From **Contacts list menu**

1. move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press (Send)

From **Contacts list menu**

1. move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press (Menu)
3. move to **Call**
4. Press (Select)

Sending messages from the Contacts list

You can send messages via the **Contacts list** (see “Messages” on page 73).

From Contacts list menu

1. move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press (Menu)
3. move to **Create MMS** or **Create SMS/EMS**
4. Press (Select)
5. move to the required item
6. Press (Select)
7. Press (Done)
Follow the steps in **Messages** (see “Messages” on page 73).

Deleting an entry from the Contacts list

From Contacts list menu

1. move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press (Menu)
3. move to **Delete**
4. Press (Select)
5. Press (Yes)

Copying an entry to the other Contacts list

From Contacts list menu

1. move to the required entry
OR
Press the numeric key which contains the first letter of the required name
2. Press (Menu)
3. move to **Copy**
4. “Copy (entry name) to (SIM or Phone)?” is displayed.
5. Press (Yes)

Create


SIM Contacts list: You can store Name, Tel number and Location No.

Phone Contacts list: You can store Name, 3 Tel numbers, 2 E-mail addresses, Ringtone type, Group, Hot key dial, Photo, Note and Location No.

Creating a new entry

*From **Contacts** menu*

1. move to **Create**
2. Press (Select)
3. move to **SIM** or **Phone**
4. Press (Select)
5. move to the required item
6. Press (Edit)
7. Edit the entry item
8. Press (OK)
9. Press (Save)



*From **Contacts list** menu*

1. Press (Menu)
2. move to **Create**
3. Press (Select)
4. move to **SIM** or **Phone**
5. Press (Select)
6. move to the required item
7. Press (Edit)
8. Edit the entry item
9. Press (OK)
10. Press (Save)

*From **Contacts list** menu*

1. move to **[New entry]**
2. Press (Select)
3. move to **SIM** or **Phone**
4. Press (Select)
5. move to the required item
6. Press (Edit)
7. Edit the entry item
8. Press (OK)
9. Press (Save)



The following entry items are available:

Icon	Item	Icon	Item
	Name		Hot key dial
	Tel number 1 - 3		Photo
	E-mail address1, 2		Note
	Ringtone		Location in Phone Contacts list
	Groups		Location in SIM Contacts list

Groups

You can categorise the phone Contacts entries into 10 groups. You can name, select a particular ringtone, and insert a photo as an icon for each group to identify incoming calls. This function is available with **Phone Contacts list** only.

Viewing the Group

From **Contacts** menu

1. move to **Groups**
2. Press (Select)
3. move to the required group
4. Press (Menu)
5. move to **View**
6. Press (Select)



Editing the Group

You can change the name, ringtone and photo assigned to a group. You also can reset a group setting to the default.

From **Groups** menu



1. move to the required group
2. Press (Menu)
3. move to **Edit**
4. Press (Select)
5. move to the required item
To reset the group setting, select **Defaults**.
6. Press (Change)
7. Edit a group setting
8. Press (Save)



Memory status

Memory status shows how many locations are available in each **Contacts list**. You can copy entries of the **SIM Contacts list** to the **Phone Contacts list** and vice versa.





*From **Contacts** menu*

1.  move to **Memory status**
2. Press  (Select)
3. 2 bars indicating **Contacts list** memory status are displayed
(in use location(s) / maximum locations)



Copying all entries to the other Contacts list

*While displaying the **Memory status***

1. Press  (Menu)
2.  move to the required action
3. Press  (Select)
4. Press  (Yes)



Note: Original entries will not be deleted from the **Contacts list**.

My numbers

You can store and view your information such as your names and phone numbers in your **SIM**.

Viewing My numbers

From **Contacts menu**

1. move to **My numbers**
 2. Press (Select)
 3. move to **Line 1** or **Line 2**
 4. Press (Menu)
 5. move to **View**
 6. Press (Select)
- To edit the entry press (Edit)



Editing My numbers

From **My numbers menu**

1. move to **Line 1** or **Line 2**
2. Press (Menu)
3. move to **Edit**
4. Press (Select)
5. move to **Name** or **Tel number 1**
6. Press (Edit)
7. Enter the required name or number
8. Press (OK)
9. Press (Save)



Service dial

See "Service dial

 on page 18.

Voicemail

You can store the phone number to your **Voicemail** and make a call to check if you have **Voicemail**.

Viewing Voicemail

From **Contacts** menu

1. move to **Voicemail**
2. Press (Select)
3. Press (Menu)
4. move to **View**
5. Press (Select)
To edit the entry press (Edit)



Editing Voicemail

From **Voicemail** menu

1. Press (Menu)
2. move to **Edit**
3. Press (Select)
4. move to **Name** or **Tel number 1**
5. Press (Edit)
6. Enter the required name or number
7. Press (OK)
8. Press (Save)



Hot key dial

You can quickly dial the numbers which are assigned to each numeric key - (see "Hot key dial" on page 17). This function is available with **Phone Contacts list** only.

Assigning Hot keys

While editing the **Contacts list** entry

1. move to **<Hot key dial>**
2. Press (Edit)
3. Enter the required number -
4. Press (OK)



Note: To clear the **Hot key dial** assignment of an entry, enter + instead of the entry's original **Hot key dial** number. Then press (OK)

Viewing Hot key dial list

From **Contacts menu**

1. move to **Hot key dial**
2. Press (Select)
3. The **Hot key dial** list is displayed



My Contacts


You can select from **All**, **SIM** or **Phone** to display the entries in the **Contacts list** entries.

From **Contacts menu**

1. move to **My Contacts**
2. Press (Select)
3. move to **All**, **SIM** or **Phone**
4. Press (Select)



Games




 Games	page 56	Playing a game 56
		Viewing Help for a game 56
		Wall Breaker..... 57
		Move Box 58

Games

There are two preinstalled games in you phone.

Playing a game





From Games menu

1.  move to the required game
2. Press  (Select)
3. Press  (Select)



Viewing Help for a game

From Games menu

1.  move to the required game
2. Press  (Select)
3.  move to **Help**
4. Press  (Select)

















Wall Breaker

Move a board to deflect a ball towards rows of various coloured bricks. Some of the bricks release power up items, such as board extension, ball reduce, gun and more. But be careful: there are some items that works in the opposite way. The next level is achieved by removing all the bricks.



Key operation

Key	Function
 / 	Release a ball Shoot (if your board has gun)
 / 	Move left
 / 	Move right
 / 	Pause / Continue
 / 	Suicide a ball
	Exit and back to the Wall Breaker game menu
	Quit and back to the idle screen

Note: You can **Resume** your game from the moment you pressed  (exit) or  (quit). **Resume** is available as long as the phone is switched on.



Move Box

Arrange all the boxes into designated places. You can only push the boxes and only one at a time. So be careful not to push them into corners.






Key operation

Key	Function
/	Move up
/	Move down
/	Move left
/	Move right
	Restart the current stage from the beginning
	Return to the last step
	Save the current game
	Exit and back to the Move Box game menu
	Quit and back to the idle screen

Note: You can **Resume** your game from the point you pressed (exit) or (quit). **Resume** is available as long as the phone is switched on. Meanwhile, if you have saved your game by pressing , you can **Load** your saved data to continue from the stage you left off. The saved data is available even after the phone is switched off.





Browser

 Starting the Browser	page 59	Navigating contents.....	59
		Using the Browser.....	60
 Bookmarks	page 61	Managing Bookmarks in Browser	61
		Managing off-line Bookmarks.....	62
 Settings	page 64	Editing GPRS Connection	65
		Editing CSD Connection	65



You can access Internet services supported by the network, such as news, weather reports and sport.

Starting the Browser




From **Browser** menu





1. Press  (Select)
2. The WAP browser will start to connect to the network.
To exit the browser, press .



 **Note:** If the server is not responding, press  (Retry) or try again later.







Navigating contents

Use  to scroll through the contents on the screen. When linked text is highlighted, press  () to load the page.

	Scroll up Page up with Long press
	Scroll down Page down with Long press
	Scroll up Return to the previous object
	Scroll down Return to the next object

Using the Browser

While browsing the homepage

1. Press  (Menu) or  (Send)
2. Press  to move to **Browser Menu**
To exit the browser, select **Done**
OR
Press  (Power/End) or  (C).
3. Press  (✓)



Menu	Description
Back	Return to the previous page.
Go To URL	Enter URL and jump to the homepage.
Home	Jump to the homepage which is pre-defined in the browser settings.
Inbox	Store, view or delete WAP push messages from the network. Jump to the home page.
Bookmarks	Jump to a page by setting a bookmark. Add the current page to bookmarks. (see "Managing Bookmarks in Browser" on page 61)
Save Items	Save images or other items from the current page.
Snapshots	Capture the screen image of the current page and view or delete it.
Reload	Reload and update the current page.
Settings	Select and set the following: Homepage Downloads Restart Browser Security
About...	Information about the browser type and security options.

Bookmarks

Once you store your favourite page or a frequently accessed page as a bookmark, you can jump to the page quickly. This eliminates the need to enter the URL every time. You also can assign hot keys to jump to particular pages. There are 2 types of bookmarks, one is in **Browser** and the other is off-line **Bookmarks**.

Managing Bookmarks in Browser

You can add a bookmark by entering the URL.

From **Browser Menu in Browser**

1. move to **Bookmarks**
2. Press ()
3. Press (Menu)
4. Press ()
5. Enter the Title and URL with -
6. Select a folder
7. Press (Save)



Adding a current page as a bookmark

From **Browser Menu in Browser**

1. move to **Bookmarks**
2. Press ()
3. Press () to **Mark Site**

Using Bookmarks

From **Browser Menu in Browser**

1. move to **Bookmarks**
2. Press ()
3. move to the required bookmark
4. Press (Go)

Managing Bookmarks in Browser

*While viewing **Bookmarks***

1. move to the required bookmark
2. Press (Menu)
3. move to the required function
4. Press ()

The following functions are available:

Details	Display and edit the bookmark information
Delete	Delete the bookmark
New Bookmark	Add a new bookmark
New Folder	Add a new folder in which to save the bookmarks
Move	Move a bookmark in a folder
Move to folder	Move a bookmark into another folder
Delete all	Delete all bookmarks
Hotkeys	Assign bookmarks to keys

Managing off-line Bookmarks

You can store bookmarks in off-line **Bookmarks**. When you jump to the URL, the **Browser** will start up automatically.

Adding a new bookmark

*From **Browser** menu*

1. move to **Bookmarks**
2. Press (Select)
3. move to **[New entry]**
4. Press (Select)
5. move to **Title: or URL:**
6. Press (Select)
7. Enter the required **Title: or URL:**
8. Press (OK)
9. Press (Save)



Managing Bookmarks in off-line Bookmarks

From **Browser** menu

1. move to **Bookmarks**
2. Press (Select)
3. move to the required bookmark
4. Press (Menu)
5. move to the required function
6. Press (Select)



The following functions are available:

Select	Jump to the selected bookmark site.
Edit	Edit the Title and URL.
Delete	Delete the bookmark.
Delete all	Delete all bookmarks.

Settings

Before accessing the Internet services, you need to set up a subscription with your network operator or Internet Service Provider (ISP) to enable the relevant configuration information. If you have any trouble with your network settings, please contact your network service provider.



Note: Modifying default settings may cause failure of the **Browser**. See "Personal Settings" on page 106, for your details.

From **Browser** menu

1. move to **Settings**
 2. Press (Select)
 3. move to the required network
 4. Press (Select)
 5. move to **Activate** or **Edit**
To activate the selected network, select **Activate**.
To edit the network settings, select **Edit**.
 6. Press (Select)
 7. move to the required setting
 8. Press (Select)
- You can edit the following settings:
- **Server name**
 - **Primary IP**
 - **Primary port**
 - **Secondary IP**
 - **Secondary port**
 - **Linger time**
 - **Homepage**
 - **Connection**

In the **Connection** menu, you can edit **GPRS** and **CSD** connections. See the following section for details.

Editing GPRS Connection

From **Connection** menu

1. move to **GPRS**
2. Press (Select)
3. Press (Select) to **Edit**
 - Login name, Password, GPRS APN, Authentication






Editing CSD Connection

From **Connection** menu


1. move to **CSD**
2. Press (Select)
3. Press (Select) to **Edit**
 - Login name, Password, Dial number, Call type, Transfer rate











Camera

 Camera Appearance	page 66	Key functions..... 67 Status icons 68
 Preview mode	page 68	Launching the Camera Preview mode 68 Operating the Camera..... 69 Options..... 69
 Capture mode	page 72	

Camera Appearance









Key functions

Key	Function
	Zoom in
	Zoom out
	Brightness up
	Brightness down
	Shutter / Options (Capture mode)
	Options / Save a captured image
	Exit the camera mode / Delete a captured image
	Exit to the idle screen






Status icons


	Image size
	Quality
	Close up mode
	Brightness
	Zoom (only Wallpaper size)
	Twilight mode

Preview mode

Launching the Camera Preview mode

- In idle screen, press  (if **Camera** is selected as **Shortcut key**)
- From main menu, press  **Camera**

 **Note:** The quality of display images may vary depending on the object or environment.

 **Note:** Displayed images may distort when shooting moving objects especially in a fast moving environment.

Operating the Camera

Brightness

In Preview mode

- ⬆ brightness up
- ⬇ brightness down


Zoom

In Preview mode

- ⬆ zoom in
- ⬇ zoom out

Taking a picture

In Preview mode

Press  (Shutter) to take a picture



Note: See "Image size" below for changing the size of images

Options

In Preview mode





1. Press  ()
The option menu is displayed
2.  move to the required function
3. Press  (Select)



Image size





From options menu

1. Press  (Select)
2.  move to the required size
3. Press  (Select)
The following image sizes are available:
 - Wallpaper size (128 x 128 pixels)
 - CIF (352 x 288 pixels)

Close up mode

Close up mode can be used to take pictures at a close range.





From options menu

1.  move to **Close up mode**
2. Press  (Select)
3.  move to **On or Off**
4. Press  (Select)

Twilight mode

Twilight mode can be used to take pictures in low light conditions.





From options menu

1.  move to **Twilight mode**
2. Press  (Select)
3.  move to **On or Off**
4. Press  (Select)

Quality

You can choose the image quality of your picture.





From options menu

1.  move to **Quality**
2. Press  (Select)
3.  move to **Fine, Normal or Economy**
4. Press  (Select)

Effect

You can enjoy various effects on your picture.

From options menu

1.  move to **Effect**
2. Press  (Select)
3.  move to the required effect
4. Press  (Select)





The following effects are available:

- **Normal**
- **Sunset**
- **Monochrome**
- **Inverse**
- **Emboss**
- **Cold**

Self timer

Self timer automatically takes a picture after a 10 second delay. After pressing the shutter, a series of ringtone will begin. The picture will be taken when you hear the shutter sound.





From options menu

1.  move to **Self timer**
2. Press  (Select)
3.  move to **On** or **Off**
4. Press  (Select)

Shutter sound

You can change the sound of the shutter.





From options menu

1.  move to **Shutter sound**
2. Press  (Select)
3.  move to the required sound
4. Press  (Select)

Anti flicker

If the display flickers, you can change **Anti flicker** to **50Hz** or **60Hz**. Choosing **50Hz** or **60Hz** is country dependent.


From options menu



1.  move to **Anti flicker**
2. Press  (Select)
3.  move to **50Hz** or **60Hz**
4. Press  (Select)



Note: When taking a picture, flicker may appear in certain environments.





Exit

Use to **Exit** the camera mode. You can also **Exit** by pressing  (Power/End) anytime.








Capture mode

When you press the shutter, all images are saved in **My Pictures** (see “My Media” on page 85). You can confirm and control the image before you save it.
In Capture mode







1. Press  ()
2.  move to the required function
3. Press  (Select)

The following functions are available for a picture:

- **Create MMS**
- **Set as wallpaper**
- **Set as caller ID**
- **Set as group ID**
- **Effect** (available only in Wallpaper size)
- **Rename**
- **Properties**
- **Delete**



Messages

 Settings	page 73	<table border="1"> <tr> <td>MMS settings</td> <td>74</td> </tr> <tr> <td>SMS/EMS settings</td> <td>75</td> </tr> <tr> <td>Receiving messages.....</td> <td>76</td> </tr> </table>	MMS settings	74	SMS/EMS settings	75	Receiving messages.....	76		
MMS settings	74									
SMS/EMS settings	75									
Receiving messages.....	76									
 Create	page 77									
 Inbox and Outbox	page 78									
 Chat SMS	page 79									
 User messages	page 79									
 Cell Broadcast	page 80	<table border="1"> <tr> <td>Receiving Cell Broadcast messages</td> <td>80</td> </tr> <tr> <td>Reading Cell Broadcast messages.....</td> <td>80</td> </tr> <tr> <td>Topic list</td> <td>80</td> </tr> <tr> <td>Languages</td> <td>81</td> </tr> </table>	Receiving Cell Broadcast messages	80	Reading Cell Broadcast messages.....	80	Topic list	80	Languages	81
Receiving Cell Broadcast messages	80									
Reading Cell Broadcast messages.....	80									
Topic list	80									
Languages	81									





Your phone has various messaging features, including **SMS/EMS** and **MMS**. You need to customise the settings of **Messages** and **Network** before you start.

SMS/EMS – You can send short text messages with media attached to phone numbers whose network support **SMS/EMS**.

MMS – You can send media attached messages to phone numbers whose network support **MMS** or E-mail address.

Settings

From **Messages** menu

1.  move to **Settings**
2. Press  (Select)
3.  move to **MMS** or **SMS/EMS**
4. Press  (Select)

MMS settings

Server list

You can configure up to 5 server profiles.

From **Settings** menu

1. Press **Enter** (Select)
2. Press **Enter** (Select)
3. **Left Arrow** move to the required network
4. Press **Enter** (Select)
5. **Left Arrow** move to **Activate** or **Edit**
6. Press **Enter** (Select)
To activate the selected network, select **Activate**.
To edit the network settings, select **Edit**.
7. **Left Arrow** move to the required setting
8. Press **Enter** (Select)

You can edit the following settings:

- **Server name**
- **Primary IP**
- **Primary port**
- **Secondary IP**
- **Secondary port**
- **Linger time**
- **MMS centre**
- **Connection**



Other settings for MMS


Signature	You can set a signature to add to your message.
Reply text	You can select On or Off to add the reply text to the messages.
Receive setting	You can select, accept or reject anonymous messages.
Auto reception	You can select On , Off or Interactive .
Mail settings	<p>Validity period: Set the duration that your message is stored at the message centre. Select Maximum or Manual.</p> <p>Delivery report: Request a report on the delivery status of your message. Select On or Off.</p> <p>Sender visibility: Select Show or Hide your address to the recipient.</p>
Restore settings	Reset the MMS settings to the factory default settings.

SMS/EMS settings

You can change the following settings:

Validity period	You can select from Defaults , 1 hour , 12 hours , 1 day , 1 week or Maximum .
Message centre	You can change the server's service number.
Protocol	You can select the type of protocol from SMS , Fax , Email , Paging , X.400 , ERMES or Voice .
Delivery report	You can select from On , Off or Ask .

Receiving messages



When one or more messages arrive, **New Message(s)!** dialogue and the message indicator () will appear in the screen together with a message tone (see "Message tone" on page 32).





Note: Please be sure to keep enough free memory for new messages.

When the phone memory is full, () will be displayed in the upper left of the display. Delete unnecessary messages from the **Inbox** or **Outbox**.

Reading received messages

When **New Message(s)!** is displayed, press  (Read). If you have more than one message, use  to move to the required message.

If you press other keys without reading new messages, the idle screen will be displayed. To read new received messages, press  () and check the **Inbox**.

The following functions are available for received messages:

Reply	Create a reply message to the sender.
Call	Call back to the sender.
Forward	Forward the selected message.
Chat	Send a chat message to the sender. (SMS only)
Extract number	Save the sender's phone number in Contacts list .
Delete	Delete the message.
Delete all	Delete all messages in Inbox .
Extract media	Save the attached image in My Media .
Move to SIM	Move the message to the SIM memory.  (SMS only)
Message info	View information about the message.