

AP3715i UNII & DTS Channel Usage Plan

5 GHz CHANNEL PLAN													
MODEL: AP3715i													
BW= 20MHz													
Mode = A													
Frequency	5180	5200	5220	5240	5260	5280	5300	5320	5500	5520	5540	5560	5580
Channel used	36	40	44	48	52	56	60	64	100	104	108	112	116
Frequency	5660	5680	5700	5720	5745	5765	5785	5805	5825				
Channel used	132	136	140	144	149	153	157	161	165				
*** Channels 120, 124, 128 and 145 are restricted and are NOT in use.													
MODEL: AP3715i													
BW= 20MHz													
Mode = AN-HT20													
Frequency	5180	5200	5220	5240	5260	5280	5300	5320	5500	5520	5540	5560	5580
Channel used	36	40	44	48	52	56	60	64	100	104	108	112	116
Frequency	5660	5680	5700	5720	5745	5765	5785	5805	5825				
Channel used	132	136	140	144	149	153	157	161	165				
*** Channels 120, 124, 128 and 145 are restricted and are NOT in use.													
MODEL: AP3715i													
BW= 40MHz													
Mode = AN-HT40													
Frequency	5180	5200	5220	5240	5260	5280	5300	5320	5500	5520	5540	5560	
Channel used	36	40	44	48	52	56	60	64	100	104	108	112	
Frequency	5660	5680	5745	5765	5785	5805							
Channel used	132	136	149	153	157	161							
*** Channels 116, 120, 124, 128, 140 and 144 are restricted and are NOT in use.													