

PROGRAMME NAME

Bud – Bluetooth headset

TITLE Quick Start Guide

CONTENT:

This document provides a guideline in terms of functioning features of Bluetooth headset and legal declaration.



HISTORIC

Version	Date	Author	Modification object	
0.1	06/01/2011	Damon Xi	Creation of the document from BH30 QSG	
0.2	10/01/2011	Damon Xi	Update to v0.1 after the MMI confirmation	
0.3	12/01/2011	Damon Xi	Update Volume key function by removing 'call reject and	
			transfer' and add it to MFB.	
0.4	16/01/2011	Damon Xi	Update Bluetooth version to V3.0;	
			Update talk time, standby time and weight	
			Add 'mark of FCC declaration'.	
0.41	19/01/2011	Damon Xi	Update new logo, 'Alcatel' and 'one touch'	
0.42	23/02/2011	Damon Xi	Add legal notice of 'IC' of Industry Canada	
0.43	28/02/2011	Damon Xi	Add 'operation and storage temperature'	

ALCATEL one touch.

ALCATEL



onetouch BH50 Bluetooth Headset User Guide

Contents

Product Specifications

one touch BH50 Overview

Getting Started

Charging Your Headset

Pairing Your Headset with a Bluetooth Mobile Phone

Using Your Headset

Factory Reset

Troubleshooting

Safety Information

Declaration of Conformity

Guarantee

Product Specifications

Bluetooth Specification: V3.0 with V2.1 EDR features, Class 2

Bluetooth Profiles Supported: Headset & Handsfree

All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



Range of Frequency: 2.4GHz spectrum

Nominal Charging Time: Within 30minutes

Talk Time*: Up to 6 hours Standby Time*: Up to 270 hours


Dimensions: 55 (L) x 16.4 (W) x 9.2 (T) mm

Weight: 8.5 grams

Operating temperature range: -20°C to 55°C Storage temperature range: -30°C to 70°C

* may vary due to the user's habit, different modes of operation, and mobile phone settings.

onetouch BH50 Overview



- A. Multi-function Button (MFB)
 - Power On / Off
 - Pair with mobile phone
 - Answer / End a call
 - Reject / Transfer a call
- B. Volume
 - Adjust volume
- C. Status Indicator
- D. Microphone
- E. Speaker
- F. Micro USB Charging Socket

All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



Getting Started


To use your **one touch** BH50 Bluetooth headset ("headset"), please follow the steps below:

- 1. Ensure your headset is fully charged and power on.
- 2. Pair your charged headset with a Bluetooth-enabled mobile phone.

Charging Your Headset

The headset comes with a built-in rechargeable battery. Prior to using the headset for the first time, it is recommended to fully charge the battery.

Insert the microUSB tip into the headset's charging socket (see fig.2) and plug the charger into the charging socket or USB charging cable into PC/notebook.



Use only the charger / USB charging cable in the package to charge the headset.

Indicator Light

Headset Status		Status Indicator Light (fig.1)			
•	Standby Mode (Operating)	Flashing Blue			
•	Standby Mode (Out of Range)	• Flashing PURPLE 4 times each 15 sec			
		until reconnect (after 10mins without			
		connection, headset turns off)			
•	Off Mode Charging	Solid Red			
	Off Mode Fully Charged	Solid Blue			
•	Standby Mode Charging	• Flashing PURPLE with RED LED on			

All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



Standby Mode Fully Charged	 Flashing Blue
Low battery	 Flashing Red
Out of battery	 The light turns off

♦ Charging indication will be delayed for a few seconds if the headset has not been used for a long time or the battery is drained.

Talk and Standby Time

A fully charged battery can offer up to 6 hours of talk time and up to 270 hours of standby time. The headset remains in standby mode after being turned on.

Pairing Your Headset with a Bluetooth Mobile Phone

standby mode. Repeat steps 1 to 3 to pair the devices again.

- 1) Ensure the headset is off.
- 2) To activate the pairing mode, press and hold the headset's MFB without releasing your finger until its status indicator flashes red/blue.
- 3) Activate your mobile phone's Bluetooth, search Bluetooth devices, select "Onetouch BH50" and enter the passcode "0000". When the pairing is completed, the headset's status indicator will flash blue light rapidly five times. If the pairing cannot be completed within three minutes after the pairing mode has been activated, the headset's status indicator will flash purple 5 times and then turns to

Using your headset

Function Button		Audio Status indictor			
POWER ON	Press and hold the	a short beep	Flashing blue light		
	MFB		3 times		
When you turn on your headset for the first time, the headset proceeds into pairing					
mode, i.e. the status indicator flashes red and blue alternately, so that you can					
immediately pair it with your mobile phone.					
POWER OFF	WER OFF Press and hold the		Red light for six		
	MFB until the		seconds and then		
	LED turns		the light goes off		
	red				
Incoming call		Ringtone on	Quick flashing		
		earphone	purple light		

All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



A 11	D 41 MED		El 1: 11 1:14			
Answer a call	Press the MFB		Flashing blue light			
	once					
End a call	End a call Press the MFB		Flashing blue light			
	once					
Adjust Volume	Press the volume		Flashing blue light			
	control button to					
	turn volume up or					
	down					
Voice Dialing*	Press the MFB	a short beep	Flashing blue light			
	once					
Say the voice tag as soon as you hear the short beep and you must have recorded the						
voice tag into your mobile phone.						
Last no. Redial*	t no. Redial* Double click the		Flashing blue light			
	MFB					
Reject a call* Press and hold the		a short beep	Flashing blue light			
	Volume Key for 2					
	seconds					
Call Transfer	Call Transfer While speaking,		Flashing blue light			
(headset to mobile	press and hold the					
phone)*	volume Key for 2					
	seconds					
Call Transfer	While speaking,		Flashing blue light			
(mobile phone to	press MFB once					
headset)*						
* Subject to mobile support						

Factory Reset

You may reset **one touch** BH50 to its default settings. Resetting will also remove the pairing history of your headset with the mobile phone.

- 1. Keep **one touch** BH50 in "power on" mode
- 2. Remove the Bluetooth® connection to **One touch** BH50on your phone or other devices
- 3. Hold the button of "Volume up", "Volume down" and "MFB" simultaneously

All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



4. Headset will restart by flashing blue 3 times then goes into paring mode automatically.

one touch BH50 Bluetooth headset is designed to work with Alcatel Bluetooth devices. Due to large variability between different Bluetooth devices from different manufacturers, interoperability between the headset and non-Alcatel Bluetooth-enabled products is not guaranteed.

Troubleshooting

I can hear crackling noise.

To receive the best audio quality, it is recommended to wear your headset on the same side of the body as your mobile phone.

I can't hear anything in my headset.

- Ensure the headset is turned on and is properly charged.
- Ensure the headset is properly paired with the mobile phone.
- Ensure that the mobile phone is connected with the headset if it does not connect, either refer to the mobile phone's Bluetooth menu or by pressing the MFB once (see "Using Your Headset" and "Pairing Your Headset with a Bluetooth Mobile Phone").

I can't connect my headset with my mobile phone.

- Ensure your headset is turned off and is properly charged.
- Ensure the headset is properly paired with your mobile phone.
- Ensure your mobile phone's Bluetooth feature is activated. Please refer to your mobile phone user guide for specific instruction.
- Ensure the headset is within ten meters range of your mobile phone and there are no obstructions, such as walls or other electronic devices in between.

If the above steps do not solve your problem, please recharge the headset and remove your mobile phone's battery for a while.

Safety Information

Check and observe local laws regarding the use of a mobile phone and a
headset while driving. If you use the headset while driving, ensure your full
attention and focus. It is your responsibility to drive safely. Consider to pull off
the road before making or answering a call.

All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd

ALCATEL one touch.

- Never leave your headset above any air bag deployment area inside your car as serious injury may result when an air bag deploys.
- Never allow children to play with the headset small parts may be of choking hazard.
- Observe all signs and displays that require an electrical device or RF radio product to be switched off in designated areas. These could include hospitals, blasting areas, and potentially explosive atmospheres.
- Turn off your headset prior to boarding an aircraft. Do not use your headset inside an aircraft.
- To prevent damage to your hearing, please do not set the listening volume too high.
- Do not attempt to modify the headset.
- Do not keep the headset near a wash basin or other wet places.
- Do not use the headset outdoors in the rain.
- Do not use the headset in stormy weather.
- Do not clean the headset while it is being charged. Always disconnect the charger from the headset before cleaning.
- Do not attempt to force open the built-in battery.
- Only charge the headset's built-in battery in accordance with the instructions described in this user guide.
- Excessive sound pressure may harm your hearing.

Declaration of Conformity

Hereby, TCT Mobile Limited, declares that this product is in conformity with the following essential requirements of Council Directive 1999/5/EC (referred to as R&TTE Directive): Article 3.1a, 3.1.

Federal Communications Commission (FCC) Statement

one touch BH50 complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- -Consult the dealer or an experienced radio/TV technician for help

Industry Canada (IC) statement

One touch BH50 complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Guarantee

Your accessory is guaranteed against all manufacturing defects for six (6) months from the date of purchase shown on your invoice. Nevertheless, if the legal warranty period in force in your country exceeds six (6) months, the legal warranty alone shall be applicable.

Hot Line Number: see "TCT Mobile Services" leaflet or go to our Internet site. On our Internet site (www.alcatel-mobilephones.com), you will find our FAQ (Frequently Asked Questions) section. You can also contact us by e-mail to ask any questions you may have.

Alcatel is trademark of Alcatel-Lucent and is used under license by TCT Mobile All rights reserved. Passing on and copying of this document, use and communication of this contents not permitted without written authorisation of TCL Communication Ltd



Limited. All rights reserved Copyright 2011 TCT Mobile Limited. TCT Mobile Limited reserves the right to alter material or technical specification without prior notice.



Dispose of the packaging and this product in accordance with the latest provisions. The Bluetooth® word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by TCT Mobile Limited is under license.