

60001 | Heavy Duty Tag

The 60001 Heavy Duty Tag offers the highest standard in state of the art radio frequency signaling, utilizing a combination of 900MHz direct sequence spread spectrum frequency technology and 2.4 GHz RF location technology.

The Heavy Duty Tag provides different alarming options and will provide location data in an alarm situation when used in conjunction with other ATLAS components and Crisis Controller Software.



Features and Benefits

- Compatible with the ATLAS System components
- Dual band RF transmitter returns accurate RF location
- Long range transmission with the use of wireless locators for full site coverage
- Panic Button, Emergency Pull Cord and Person Down Alarms standard features
- Guard Tour options are available
- Rugged 1-piece design using Lexan high impact plastic
- Extended battery life (up to 9 months depending on features and usage)
- Full transmitter supervision includes alarms for low battery, tamper and inactivity



Accurate Location

Affordable System

24/7 Support

Improved Safety

Optimize Workflow

Valuable Data

Specifications

DIMENSIONS
Height 3.75" Width 1.75" Depth .875"
CASE
Lexan ABS/Polycarbonate Plastic, Black
Weight
Approximately 4 ounces
OPERATING TEMPERATURE
0° to 50° Centigrade
BATTERY TYPE
V Lithium Battery, Duracell 123A/Panasonic (or approved equivalent)
DATA TRANSMISSION SETTINGS
PAN ID, Ch 1 – 10, power +1dB to -25dBm

*Battery Life when deployed will vary as a function of duty time used frequency of alarm transmissions sent, LED brightness/frequency, location broadcast interval settings and environmental conditions at your site. Based upon a 1470mAh 123A (Duracell). Ask your Actall Sales Representative for more details.



Supplier's Declaration of Conformity

47 CFR, § 2.1077 Compliance Information



Unique Identifier:

Trade Name: PMT/HDT

Model Number: 60001- Rev

Responsible Party – U.S. Contact Information:

Name: Actall Corporation

Address: 2017 Curtis St.

Denver, CO 80205

Phone/Fax: (303) 226-4781/(303) 650-4523

Email contact: jdavenport@actall.com

FCC Compliance Statement:

This device complies with Part 15 of the FCC Rules. Operation is subject to the two following conditions:(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by manufacturer could void the user's authority to operate the equipment.