


Model Name: BTH-11 Bluetooth Headset

Quick User Guide

● Vibration Power Bank Overview

- 1. NOKIA Charger port
- 2. Charging point
- 3. Indicator light



● Charging Your BTH-11

The BTH-11 comes with two built-in rechargeable Li-ion batteries, one is in the headset and another is in the power bank. We recommend charging both batteries until the indicator light turns off before using the headset in the first time.

Charging headset

When the headset power is on, and the headset indicator LED flashes red, please charge your headset according to the following steps

4

BTH-11 User Manual

● Introduction

Imagine something that is practically weightless, something that is so small, and something that can give you peace of mind, all built into one. Do not imagine anymore, experience the future today with this innovative breakthrough, the BTH-11 Bluetooth Headset. Crafted for the most elite and discriminating user who demands crisp clear sound that comes from the smallest and lightest package in the world, get ready for this headset because it will take your breath away.

This is not an ordinary headset, the BTH-11 is intelligently designed to fit snugly and comfortably in your ear and while not in use, simply place the patented headset into another patented necklace charger (included) that will enable you to talk up to 15 hours. The power bank not only charges the headset while not in use, but also it serves as a storage cradle that is at the same time sophisticatedly designed to look like a jewelry.

1

1. Place headset into power bank. The blue LED on power bank will illuminate and headset starts to charge.
2. While charging, the indicator light shows a steady blue light and turned off when the battery is fully charged.
3. For optimal performance, please charge the battery 5-6 times before usage.

Charging Power Bank

1. Please plug the Nokia adaptor into the charger port.
2. The power bank indicator LED will display a steady green light and turn off after the battery is fully charged.


● Getting Started

Before you use your BTH-11, you must pair it with a device, for example, a Bluetooth mobile phone. The communication range of the mobile phone and the Bluetooth headset is up to 10 m (30 ft) outdoors or up to 5 m (15 ft) indoors with no solid objects in between.

5


● Package

- Bluetooth Headset
- Power Bank
- User manual
- Belt Clip
- Necklace
- 3 rubber ear pieces



● Headset Overview

1. Charging point
2. Call handling button
3. Indicator light
4. Volume up
5. Volume down
6. Speaker
7. Microphone
8. Extendable Microphone boom



● Pairing

1. Enable the Bluetooth function of the mobile phone in accordance to the mobile phone's user manual,
2. With the headset set to off, press and hold the call handling button for up to 10 seconds until the indicator light on the headset flashes blue and red. The headset is then in pairing mode.
3. Following the phone's user manual, enter the headset PIN code: 1234.
4. When pairing is completed, the headset indicator light flashes blue.

Note: You only need to pair the headset to the phone once. If you want to use the headset with a new phone, you need to pair it to the new phone.

Turning on/off Headset

To turn on headset, please press and hold the call handling button until you hear a short low tone. The headset indicator light flashes blue.

6

To turn off headset, please press and hold the call handling button until you hear a short high tone followed by a short low tone. The headset indicator light switched off.

● Answering, Rejecting and Hang-up

You can make and answer calls by using the button on the headset. When there is an in-coming call, press the call handling button once to answer the call. To hang up this call, press the call handling button once again. Please note that if the in-coming call is answered through the mobile phone and NOT through the headset, you will have to continue the call with the mobile phone. This is so, as all the mobile phone functions are still available. Calls could only be answered by either the mobile phone or headset, NOT both. The in-coming call could be rejected by pressing and holding the call handling button for about 2-3 seconds.

● Adjusting the Volume

During talking, you can adjust the volume by the buttons of headset.

- To increase the volume, press "button 4".
- To decrease the volume, press "button 5".

7

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experience radio/TV technician for help.

You are cautioned that changes or modifications not expressly approved by the party responsible for compliance could void your authority to operate the equipment.

● FCC RF Radiation Exposure Statement:

This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

● Silver Nano Ear Plugs

The "Silver Nano" material is applied to X-Sport ear plugs which can kill the bacteria.

Note: It is advised that the volume not to be adjusted to the maximum level for both safety and comfort.

● Using Voice Dialing

Please make sure the phone and the headset are turned on and within range of each other. Press the call handling button about 1-2 seconds. During this time, you might hear the beep tone in the headset. After the beep, voice dial as normal. In order to use voice dialing, you must make sure your mobile phone supports this function.

● Audio Transfer

During a call, you can press and hold the call handling button until a beep tone is heard to transfer the call to mobile phone. If the headset is turned on after a call has been initiated, or an in-coming call answered through the mobile phone, the call could be transferred to the headset by pressing the call handling button once.

● Please note

The warranty will be invalid, if fail to follow the operation manual.

8

Federal Communications Commission (FCC) Statement:

15.21

You are caution 11.01 changers or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

15.1.5 (b)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and if not installed and used in accordance with the instruction may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following methods:

9