



Label information:

<p>51156751-003, FIELD DEVICE ACCESS POINT GEN3, FDAP31</p> <p>Honeywell FIELD DEVICE ACCESS POINT GEN3 Fort Washington, PA 19034, USA ASSEMBLED IN MEXICO Model: FDAP31 Part No.: 51156751-003 Ser. No.: Power: 12 V - 30 VDC, 1.0 W Temp.: -40 TO +70 °C</p> <p>CE 0344 0981 N314</p> <p>Ex Sira 16ATEX2289X II 1G Ex ia IIB T4 Gc IECEX CSA 14.0024X: Ex ia IIB T4 Gc IP66/67</p> <p>SF 16.70068015X Ex ia, Cl I, Div.1 Gp.CD;T4 Cl I, Zn 0, Ex ia IIB; T4 Gc IP66/67</p> <p>CSA/ATEX/IECEX: Installation per Dwg 50165525</p> <p>This device complies with Part 15 of FCC Rules and Regulations.Operation is subject to the following conditions: (1) This device may not cause harmful interference and (2) This Device must accept any interference received, including interference that may cause undesired operation.</p> <p>FCC ID : S5751307990 Contains FCC ID : XPYNINAB1 Ethernet MAC: 00-40-84-xx-xx-xx-xx</p> <p>IC: 573W-51307990 Contains IC: 8595A-NINAB1 Model NINA-B1 BLE MAC: 00-xx-yy-11-22</p>	<p>51156751-002, FIELD DEVICE ACCESS POINT GEN3, FDAP32</p> <p>Honeywell FIELD DEVICE ACCESS POINT GEN3 Fort Washington, PA 19034, USA ASSEMBLED IN MEXICO Model: FDAP32 Part No.: 51156751-002 Ser. No.: Power: 12 V - 30 VDC, 2.2 W POE 48V - 60 VDC, 2.3 W Temp.: -40 TO +70 °C</p> <p>CE 0344 0981 N314</p> <p>Ex Sira 15ATEX4120X: II 3G Ex eC [ic] IIC T4 Gc IECEX SIR 15.0048X: Ex eC [ic] IIC T4 Gc IP66/67</p> <p>SF 16.70068015X Cl I, Div. 2 Gp. ABCD; T4 Cl I, Zn 2, Ex eC [ic] IIC; T4 Gc IP66/67</p> <p>CSA/ATEX/IECEX: Installation per Dwg 50165525</p> <p>This device complies with Part 15 of FCC Rules and Regulations.Operation is subject to the following conditions: (1) This device may not cause harmful interference and (2) This Device must accept any interference received, including interference that may cause undesired operation.</p> <p>FCC ID : S5751307990 Contains FCC ID : XPYNINAB1 Ethernet MAC: 00-40-84-xx-xx-xx-xx</p> <p>IC: 573W-51307990 Contains IC: 8595A-NINAB1 Model NINA-B1 BLE MAC: 00-xx-yy-11-22</p>
<p>51156751-001, FIELD DEVICE ACCESS POINT GEN3 PLUS,FDAP3P</p> <p>Honeywell FIELD DEVICE ACCESS POINT GEN3 PLUS Fort Washington, PA 19034, USA ASSEMBLED IN MEXICO Model: FDAP3P Part No.: 51156751-001 Ser. No.: Power: POE 48V - 60 VDC, 2.3 W Temp.: -40 TO +70 °C</p> <p>CE 0344 0981 N314</p> <p>Ex Sira 15ATEX4120X: II 3G Ex eC [ic] IIC T4 Gc IECEX SIR 15.0048X: Ex eC [ic] IIC T4 Gc IP66/67</p> <p>SF 16.70068015X Cl I, Div. 2 Gp. ABCD; T4 Cl I, Zn 2, Ex eC [ic] IIC; T4 Gc IP66/67</p> <p>CSA/ATEX/IECEX: Installation per Dwg 50165525</p> <p>This device complies with Part 15 of FCC Rules and Regulations.Operation is subject to the following conditions: (1) This device may not cause harmful interference and (2) This Device must accept any interference received, including interference that may cause undesired operation.</p> <p>FCC ID : S5751307990 Contains FCC ID : XPYNINAB1 Ethernet MAC: 00-40-84-xx-xx-xx-xx</p> <p>IC: 573W-51307990 Contains IC: 8595A-NINAB1 Model NINA-B1 BLE MAC: 00-xx-yy-11-22</p>	