

VR300W Reverse Camera System

User Manual

Package Content

1. Reverse Camera
2. TFT LCD Monitor
3. Monitor Mounting Stand
4. Monitor Power Cable with 12V DC Adaptor
5. Wire Connector With In-line Fuse
6. Grommet

Installation

CAMERA INSTALLATION

- (1) Remove the screws of the rear license plate.
- (2) Thread the screws through the holes on the camera's mounting bracket.
- (3) Then put the screws through the holes on the license plate that aligns with the holes on the vehicle.
- (4) Tighten the screws.
- (5) Route the camera's power cable through vehicle's body to a location where the reversing light circuit is. Some vehicle may have a hole for passing the wire though. If not, you can use an existing opening or drill a hole on the vehicle's body.
- (6) If you have drilled a hole, pass the power cable through the grommet into the vehicle. The grommet is used to prevent sharp edge of the hole from cutting the power cable, or prevent water from coming in.



- (7) Locate the reverse light circuit. You can ask a professional for help if necessary.
- (8) Connect one end of the wire with in-line fuse holder to the red wire of the power cable.



- (9) Attach the in-line fuse wire connector to the reverse light's positive, and attach the white wire of the power cable to the negative.

TFT MONITOR INSTALLATION

- (1) In the cab, choose a location to mount the monitor. Make sure the driver's vision is not obstructed. Place the monitor stand in the location that you have chosen and mount the monitor on the stand.
- (2) Insert the 12V DC adaptor into the cigarette lighter socket and connect the other end to the

DC-IN jack of the monitor.

- (3) Press on the ON/OFF power switch on the monitor to see images.

MONITOR BUTTONS



FCC NOTICE

1. This device complies with Part 15 of the FCC Rules.
Operation is subject to the following two conditions:
 - (1) This device may not cause harmful interference, and
 - (2) This device must accept any interference received, including interference that may cause undesired operation.
2. Changes or modifications not expressly approved by Shenzhen Yifang Digital Technologies Co., Ltd. responsible for compliance could void the user's authority to operate the equipment.