

# BTH-310 Bluetooth stereo headset

## User Manual

Thanks for choosing BTH-310 Bluetooth Stereo Headset. Please read this user manual before using.

### Contents

Introduction.....	
Specification .....	
Precaution and Warning.....	
Legal Notice.....	
Wear Headset.....	
Use Headset.....	
Charge headset.....	
Power On/Off.....	
Pairing Device.....	
Answer a Call.....	
Switch to mobile phone call	
End a Call.....	
Reject a Call.....	
Make a Voice Dial call.....	
Last Number Redial.....	
Listening to Music	
Pair With More Devices...	
Troubleshooting.....	
Warranty .....	

## Introduction

BTH-310 Bluetooth Stereo Headset is an elegant Bluetooth headset that combines entertainment & communication all-in-one.

Enjoy HI-FI stereo sound, voice clarity, and comfort-all without wires!

BTH-310 Bluetooth stereo headset has slim shape, with clip and hang for option.

It switches freely between your phone call and audio music. So you'll never miss a call while listening wirelessly to your favorite music or movies. It has up to 5 hours talk and audio listening time. Enjoy wireless stereo sound from ipod, laptop, PC, DVD and MP3.

Specifications :

Core chip:CSR BC03MM [external](#)

Bluetooth specification:V1.2,Class 2

Bluetooth protocol:HSP,HFP,A2DP,AVRCP

Frequency Range:2402 -2480\_MHZ

Working Distance:10m

Key: Main function key, Volume+/Volume-, Play / Pause, Previous / Next

Main function: Receive a call, Reject a call, End a call, Voice dial, Last number redial, Cancel a call, Player remote control.

Dimension:55x28x9.6 ( mm )

Weight:18g

Talking/playing time:5H

Standby time:150H

Power:Built in rechargeable Li-polymer battery DC 3.7V

Charging time:2-3H

Charging voltage:DC 5V

Support mobile phone:Nokia, ,Motorola, LG, SonyEricson etc.

## Precaution and warning

- \* Turn off the headset before putting into pocket to avoid connection through which you do not want.
- \* Don't place headset into liquid or in a moist place.
- \* Don't clean headset with caustic liquids.
- \* Keep headset away from high temperature and fire to avoid explosion.
- \* Don't try disassembly of headset. In case of any abnormality, send it to appointed service center for support.
- \* If you don't use the headset for long periods, be sure to store it in a dry place, free from extreme temperatures and dust.

## Legal Notice

This product is in line with requirements as per BQB、CE、FCC、ROHS, but it dose not mean that it is in line with any national or regional standard. Please refer to local rules and regulations.

## Wear Headset



## Use Headset

Belowing using ways may be different when you you pair different devices.


Charge headset

- \* You need to charge its built-in battery fully before first time use.
- \* In charging, Red Indicator light keeps on for 2-3 hours. When Red Indicator Light is off, it means charging completed and available for use.
- \*When the Red indicator light flashes with sound of beep, it means the battery needs to be recharged.
- \*While charging a battery over extended periods of time, indicator light will not light up until minutes later.
- \*Do not attempt to charge the headset with anything other than the charger provided.

#### **Power On/Off**

- \* Please confirm the battery is fully charged before turning your headset on.
- \* Press and hold  or 3 seconds, heard one beep and the blue light will flash 3 times, the headset is turned on.
- \* In power-on state, press and hold  for 5 seconds, heard one beep and the red light will light 7 seconds, the headset is turned off.

#### **Pair device**

- 1.Place the headset and the phone where they are easily viewable and no more than 10meter apart.
- 2.Press and hold  tton of Bluetooth headset about 5 seconds when the power is off, then heard 2 short beep the LED will blink red and blue alternative, which indicates the headset in pairing mode.

3.Please activate Bluetooth function of your devices (such as Bluetooth mobile phone).

4.Please select the name of "BTH-310" and conform.

5.Please input "0000" when the phone ask for pin code, heard one beep and the blue LED flash, it means pair successfully. Please try it again by the same way if pair failed.


Note: After first successful pairing, the headset will search the last pairing device automatically when you turn it on, no need pair again.

#### **Answer a Call**


Tap (Volume+/Volume-, Previous / Next) button to for answering.

#### **Switch to mobile phone call**

Press and hold  tton in the talking mode, sound will be transferred to phone.

Press again  ound will be transferred to headset.


#### **End a Call**

Tap  ton for ending the call.



#### **Reject a call**

Press and hold  utton for rejecting a call in the talking mode.

#### **Make a Voice Dial call**


Press and hold  button for 2 seconds for voice dial call.


### **Last Number Redial**


Press and hold  [or](#)  for 2 second for last number redial.


### **Listening to music**

When you listen to music from Bluetooth mobile phone, ipod, laptop, PC, DVD and MP3 etc. :

 Select next music

 Select previous music

 y/pause

 stop

### **Pair With More Devices**

To pair with more devices, please refer to Repeat Pairing Device Operation.

### **Troubleshooting**

- \* No power-on: The reason may be the low battery. Please charge headset and then restart.
- \* No light-up of charging indicator light: The reason may be the dead battery. Connect secure with power source and charge for another more 10 minutes.
- \* No connection: Check if the headset is in pairing state (Blue indicator keeps lighting), check if mobile phone is searching for audio device. If connection still fails, please turn off the mobile phone and restart for pairing.

### **Warranty**

In case of any faults, please do not disassemble the Bluetooth headset by yourself, but send it to the appointed service center.

Thanks for purchasing BTH-310. May the joy from it.

## **Warning:**

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance will void the user's authority to operate the equipment. Any change to the equipment will void FCC grant.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The equipment complies with FCC radiation exposure limit set forth for uncontrolled Environment