



## 1. Before you use this device, please make sure that you

- 1.1 Fully charge the device at least 3 hours before you use it the first time. Afterward it takes approximate 2 hours to fully recharge power. (Please refer to 3.1 showed below for details.)
- 1.2 To pair the speakers with a Bluetooth mobile handset or other Bluetooth devices before you making calls. The Bluetooth audio connection between the speakers and your phone can be established by setting up a paired link. (Please refer to 3.2 showed below for details.)

## 2. Introduction

### 2.1 Features

- a. Multipoint Technology – Dual connecting capability, easily press one button to seamlessly switch between two Bluetooth mobile phones or mobile phone and VoIP.
- b. Voice announcing for Incoming Callers' number.
- c. Stereo streaming your favorite MP3 tracks stored on your cellphones wirelessly to the speakers.
- d. Auto Swap between music operations and calls handling as soon as calls have been made.
- e. Abnormal disconnection notifications.
- f. Comfortable ergonomic formation can be clipped or pendent.
- g. Super lightweight and ultra small as only 10g, cutting edge design easy to carry and storage.
- h. 3.5mm audio jack allows users to use own earphones.

connecting with a Bluetooth AV Transmitter;  $\textcircled{b}$  button will act as "mute" function.

- 3.6 Activate or close the Caller's ID announcement feature
  - a. This Bluetooth Stereo Headset supports Caller's ID announcement feature, press and hold the  $\textcircled{b}$  button more than 10 seconds during power off status, users can switch between announcement or no announcement features.

- 3.7 Multipoint Technology : This Bluetooth Stereo Headset supports Multipoint Technology, please refer to the 5.2 Function Matrix for the operation guide.

3.8 Pin code: "1234"


## 4. Indications: Amber(A), Blue(B)

Pairing	(B) Blink rapidly
During Communication	(B) Rapidly blink 3 times per second
Playing Music	(B) Rapidly blink 2 times per second
Connected and Standby	(B) Blink tardily once per second
Standby without Connected	(B) Blink rapidly once every 2 second
Low Battery	(A) continuing blinking, the lower the faster
Charging	(A) light on

## 2.2 Product Specification

Bluetooth Specification	Bluetooth v1.2 Class2
Bluetooth Profiles	HSP / HFP / A2DP / AVRCP
Frequency Band	2.4GHz~2.4835GHz ISM Band
Working Distance	10 meters
Standby Time	120 hours
Playing Time	4~7 hours
Battery	3.7V Li-Polymer rechargeable battery
Weight	10g
Packing Contents	1. Bluetooth Stereo Pendant 2. 100-240V DC adapter 3. 3.5mm earpiece 4. One User manual

## 2.3 Product Outlook



## 5. Operation Button and Symbol Definition

### 5.1 Buttons: $\textcircled{b}$ $\textcircled{a}$ $\textcircled{c}$

- a. Short Click: "+": Clip and release less than 1 second
- b. Long Press: "++": Press and release for 2 seconds
- c. Double Click: "v v": Click twice within 0.5 second
- d. Press and Hold: "+++": Press and hold the key for more than 6 seconds
- e. Ultra Press: "++++": Press and hold the key for more than 10 seconds

### 5.2 Function Matrix

Feature	Buttons	Operation	Conditions
Power On	$\textcircled{b}$	++	Power Off
Pairing	$\textcircled{b}$	+++	Power Off
Power Off	$\textcircled{b}$	+++	Power On
Pick Up	$\textcircled{b}$	+	Incoming Call
Hang Up	$\textcircled{b}$	+	Activate Call
Pick Up Line 2 and put Line 1 on hold	$\textcircled{b}$	VV	Line 1 in Use
Reject Line 2 call	$\textcircled{b}$	++	Line 1 in Use
Swap between phone calls	$\textcircled{a}$ $\textcircled{c}$	++	Line 1 & 2 both in use
Callers' Number Announcement Enabled / Disabled	$\textcircled{b}$	++++	Power Off
**Reject incoming call	$\textcircled{b}$	++	Incoming Call

## 3. Prepare to use the product

### 3.1 Power Supply and Charging

- a. As soon as power jack have been connected, the device charging can be progressed under "ON" or "OFF" circumstance.
- b. The battery must be charged with the appropriate charger, one DC5V adapter has been enclosed in the package.
- c. While charging, the amber indicator will stay on and the amber indicator will be off as soon as it is completed. It takes you 2 hours to re-charge every time. (It takes 3 hours to fully charge power at the very first time)

### 3.2 Power On / Power Off

- a. Power On: Press and hold the  $\textcircled{b}$  button for approximately 2 seconds under power off status until you see the indicators start and flashing three times.
- b. Power Off: Press and hold the  $\textcircled{b}$  button for approximately 6 seconds under standby until you see the Blue and Amber indicators bright at the same time and distinguished.

### 3.3 Pairing and establish a connection

Please make sure you have paired the product with Bluetooth AV sources before you start to use. Kindly following the pairing procedure shows hereunder:

- a. Turn your Bluetooth stereo headphone on by press and hold the  $\textcircled{b}$  button till indication blinks rapidly. At this moment, the product is in the pairing mode.
- b. To activate Bluetooth devices searching from your Bluetooth AV sources by follow their original instruction. Please choose the device name and enter the pass key "1234" to establish a pairing connection.
- c. The speaker supports two audio connections. Please select HEADSET/HANDSFREE profile if you like to connect to the mobile phone. Or A2DP/AVRCP profile for stereo sound effect to your audio sourcing.

Note: If the pairing can not be established within 60 seconds, the blue indicator turns to regular blinking once every 2 second automatically. A re-pairing procedure is needed. Please repeat pairing procedure listed above.

### 3.4 Bluetooth Cellphone Operation

- a. Check your mobile phone's user guide, find out the paragraphs of Bluetooth Connectivity and follow the instruction to complete pairing with the speaker.
- b. If your cellphone support only Hands Free profile, please activate connection from the cellphone. (Please refer to your mobile phone's manual for operation details)
- c. Cellphone will always be the top priority, since an incoming/outgoing has been progressed, it interrupts actively and the ongoing music will be muted. As soon as the call has been hung up, the music rebound afterward.

### 3.5 Audio Streaming via other Bluetooth audio sources

- a. NB / PC (Bluetooth USB dongle)
  - a.1 Play music: Please complete AV pairing and then activate intended audio player interface afterward, the music will be transmitted to the headset automatically.
  - a.2 Conversation: Please complete HSP pairing and then you can start to use the conversation functions, such as Skype.

Note: The Bluetooth USB Dongle should support AVRCP profile to activate "remote control" function.

- b. Bluetooth AV Transmitter: Please make sure the Bluetooth Stereo Headset has been connected with the transmitter (blue indicator will be blinked rapidly 2 times per second). The music will be transmitted from audio player to Bluetooth stereo headset via Bluetooth AV Transmitter automatically.

Note: The device did not support "remote control" function when

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### 6.3 European Union Directives Conformance Statement

We, Global Target enterprise declares that this product: Bluetooth portable speaker with hands free function (CK817) is conformity with the appropriate standards EN300328, EN301489-1, EN301489-17, EN60950. In accordance with the council directive 1999/5/EC. For more information, please visit: <http://www.globaltarget.com.tw>

### 6.4 Bluetooth is a trade mark owned by Bluetooth SIG, Inc.

### 7. Caution

- 1.1 Important information regarding safe and efficient operation. Read this information before using the product. Users are not permitted to make changes or modify the device in any way. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### 7.2 Operation is subject to the following two conditions:

- a. this device may not cause harmful interference, and
- b. this device must accept any interference received, including interference that may cause undesired operation of the device.

### 7.3 FCC RF Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operation instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operation in conjunction with any other antenna or transmitter.

The above functions which are remarked with \*\* can act on only if the cellphone supports HFP.

Note (\*1): The above functionalities may vary depending on the model of mobile handsets. Ex. Some mobile handsets may disconnect after call transfer.

### 6. Certification and Safety Approvals/General Information

- 6.1 The device is CE:FCC and BQB approved.
- 6.2 Federal Communication Commission(FCC) Statement:
  - a. Rule15.21: You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.
  - b. Rule15.105(b): This equipment has been tested and found to comply with limits for a Class B digital device, pursuant to part 15 of the FCC rules.