


	CHARGING THE SPEAKER	PAIRING THE SPEAKER	PAIRING THE
Display button: ick press to PLAY/PAUSE usic in Bluetooth and AUX ode ng press to switch from uetooth, AUX and FM Radio odes	 Connect the small end of the Micro USB charging cable to the Micro USB charging port on the speaker. Connect the large end of the Micro USB cable to your computer's USB port or an AC adapter (not included). The LED indicator light turns RED when charging. When fully charged, the LED indicator light turns off 	 Slide the Power ON/OFF Switch to the ON position. Press and hold the [>II] Button for 3 seconds. The Bluetooth icon will flash to indicate that it is in pairing mode. Keep your Bluetooth speaker and Bluetooth-enabled device within 3 feet of each other during the pairing process. Set your mobile phone or other Bluetooth-enabled device to search for Bluetooth devices. 	On a Blackberry • Go to SETTINGS/OPTIONS > BL • Enable BLUETOOTH
button: ick press to decrease volume annel in FM Radio mode button: ick press to increase volume. ing press to select next FM tion in FM Radio mode. tight ON/OFF o USB charging port FM port er ON/OFF	Micro USB Charging Cable User of the computer Nicro USB Computer Nicro USB Charging Port Computer	<text></text>	On an Android Phone • Go to SETTINGS > BLUETOOTH sure Bluetooth is turned ON)
KER ole to the AUX/FM port on the ry Cable into the headphone rer. ode. Use the controls on your and volume. external media device and are e on your Bluetooth-enabled volume on the speaker by	 SETTING THE TIME 1. Press and hold the [►II] button for 3 seconds and release. The "Hours" field will begin to flash. 2. Quick press the [+] or [-] buttons to adjust the desired hour. 3. Quick press the [►II] button again to switch to the Minutes field. 4. Use the [+] and [-] buttons to adjust the Minutes field. 5. Quick Press the [►II] button to confirm your entry. 	 USING THE FM RADIO Long press the [►II] button for 3 seconds and release. Stop when the FM radio mode is selected. The FM indicator will appear on the LCD display. Connect the 3.5mm Auxiliary Cable-FM Radio Antenna into the AUX/FM antenna port on the back of the speaker. The 3.5mm cable can also be used as an FM radio antenna. Quick press the [►II] button to scan and save broadcasting radio stations. Press and hold the [-] button for 3 seconds to switch to the previous station. Press and hold the [+] button for 3 seconds to switch to the next station. 	I can pair the speaker v (?) I can pair the speaker v (?) I cannot hear any music. 1. Make sure your Bluetooth device 2. Turn up the volume on your Bluet 3. You may have to unpair the speak (?) My Bluetooth device is speaker. 1. Make sure the speaker is turned 2. Keep the speaker and Bluetooth other during the pairing process. 3. Check that YOUR device's Blueto 4. Try repeating the pairing process. 5. Make sure the speaker is charge (?) I cannot get the spea 1. Make sure the speaker is turned 0 2. Press and hold the [>II] Button flash to indicate that it is in pairi 3. Check that the speaker is charge

SPEAKER (cont'd

> BLUETOOTH



TH > MENU > Search for devices (make



OTING (cont

vice supports A2DP profile. luetooth device.

peaker, then re-pair to your device.

ned ON before beginning the pairing process. ooth-enabled device within 3 feet of each ess.

uetooth feature is turned ON.


cess, see "Pairing the Speaker." irged.

ned ON before beginning the pairing process. tton for 3 seconds. The Bluetooth icon will pairing mode. narged.

PAIRING THE SPEAKER (cont'd

On other Cell Phones/Devices

• Review the instruction manual that came with your phone/device.



- 5. When the Bluetooth-enabled device finds the speaker, select "PBT508" from the list of found devices.
- 6. If required, enter the password 0000. Select OK or Yes to pair with your device.
- 7. After a successful pairing, the Bluetooth icon on the speaker's main display will remain RED.





This product as supplied and distributed new by AIT, Inc. ("AIT") to the original consumer purchaser is warranted by AIT against defects in material and workmanship for a period of one year from your date of purchase ("Warranty"). In the unlikely event that this product is defective, or does not perform properly, you may within one year from your original date of purchase return it to the authorized service center for repair or exchange.

TO OBTAIN WARRANTY SERVICE:

- Call the Customer Support number located below, or go to our website portal to receive an SRO number.
 Provide proof of the date of purchase within the package (Dated bill of sale).
 Prepay all shipping costs to the authorized service center, and remember to insure your return.
 Include a return shipping address (no RO. Boxes), a telephone contact number, and the defective unit within the
- package.
 Describe the defect or reason you are returning the product.

Your product will be repaired or replaced, at our option, for the same or similar model of equal value if examination by the service center determines this product is defective. Products received damaged as a result of shipping, will require you to file a claim with the carrier.

The shipping address of the authorized service center is:

AIT. Inc. ATTN: Customer Service (2nd Floor) 14-C 53rd Street Brooklyn, NY 11232

IN NO EVENT WILL AIT. ITS MANUFACTURERS, DISTRIBUTORS OR PLR IP HOLDINGS, LLC BE LIABLE FOR ANY INCIDENTAL, DIRECT, INDIRECT, SPECIAL, PUNITIVE OR CONSEQUENTIAL DAMAGES (SUCH AS, BUT NOT LIMITED TO, DAMAGES FOR LOSS OF PROFITS, BUSINESS, SAVINGS, DATA OR RECORDS) RELATED TO THIS PRODUCT. EXCEPT AS STATED HEREIN, NO OTHER WARRANTIES SHALL APPLY.



