User's Manual




H901A **Bluetooth Headset**

1 What's in the box

The headset contains the following parts:

- 1. Speaker
- 2. Multi-function Button
- 3. Indicator Light
- 4. Microphone
- 5. Volume Up Button
- 6. Volume Down Button
- 7. Charging Socket
- 8. Ear Hook



Package contents list:

- 1 H901A Bluetooth Headset
- 2. Travel Charger
- 3. USB Charging Cable
- 4. User Manual

2 Pair to your Bluetooth phone

Before you use your headset the first time, you must pair the unit with a Bluetooth device e.g. Bluetooth mobile phone. This operation guide based on the Bluetooth phone as the host's device. Please refer to the following step to set up the pairing:



Ensure the



Press and hold the MFB for 4 seconds until you see the Blue and Red LED light flash alternately to enterthe pairing mode.



Following your phone's instruction guide, operate your Bluetooth phone to active Bluetooth function and search the headset.





Your phone will find the headset and show the device name on the screen, select the device name and confirm to pairing.





Enter PIN code as 0000 (4 zeros) and confirm to complete pairing.

NOTE:

- If the pairing is successful, the headset will connect to your phone automatically, you may need to confirm the enquiry.
- While the headset is paired with the phone and connected, the indication light will flash 2 times every 5 seconds. If failed or didn't connect to the phone, the blue indicator light will flash 1 time every 3 seconds.
- Once you paired the headset with one device or more, the Headset will automatically
 connect to the phone you last connected wherever you turn the headset on, but make sure
 your phone's Bluetooth function is active.
- The headset is supports Bluetooth v2.1+EDR specification, the simplified pairing process
 will make paring your devices easily, if your mobile phone supports Bluetooth v2.1+EDR
 specification, you just need turn on both of them, and add new Bluetooth device on your
 phone, the headset and your phone will find each other and connect automatically.
- The headset supports multi-point technology. If you need connect the headset to the 2nd
 Bluetooth phone, please repeat the pairing operation steps above. When finish the pairing,
 turn off the headset and turn on again, the headset will connect to the both 2 phones
 automatically.

3

3 Charging the battery

This headset has an internal, non-removable, rechargeable battery. Do not attempt to remove the battery from the device as you may damage the device. Please refer to the following step to charge the battery:

- 1. Connect the charger to the correct outlet.
- 2. When the charger is connected to headset, the red indicator light will turn on during charging. Charging the battery fully may take up to 2 hours.
- 3. When the battery is fully charged, the red indicator light will turn off. Disconnect the charger from the headset and the wall outlet. The headset is ready to use.

NOTE:

- The fully charged battery has power for up to 3 hours of talk-time or up to 100 hours of standby time. However, the talk and standby times may vary when used with different mobile phones or other compatible Bluetooth devices, usage settings, usage styles, and environments.
- When battery power is low, the headset will remind you by beeps every 20 seconds, and the red indicator light starts to flash.

4 Battery information

Your device is powered by a chargeable battery. The full performance of a new battery's an achieved only after two or three complete charge and discharge cycle. The battery can be charged and discharged hundreds of times, but it will eventually wear out.

Unplug the charger from the electrical plug and the device when not in use. Do not leave a fully charged battery connected to a charger, since overcharging may shorten its life time. If left unused, a fully charged battery will lose its charge over time.

If the headset would be leave unused for a long time, please charge fully and turn off the headset. To prevent over discharge endangering the battery, you are recommended to charge the headset fully each month.

Never use any other charger that is damaged.

5 Turning headset on /off

*Turn on the headset

If the headset is turned off, press and hold MFB for 2 seconds until you hear a melody from low to high, the headset turns on, the Blue indicator light will flash 3 times at the same time.

*Connects to the phone

- 1.If your headset has finished the pairing operation successfully, when the headset is turned on, it will connect to the phone(s) you last connected automatically, but make sure your phone's Bluetooth function is active.
- 2.The headset supports multi-point and connects to 2 phones at the same time. In some operations, you need to distinguish the connection sequence, so we appoint the phone first connected as phone 1, the second one as phone 2.

5

*Turn off the headset


At any working state after the headset turns on, press and hold MFB for 4 seconds, you will hear a melody from high to low, and the Red indicator light will flash 3 times at the same time, the headset turns off.

Note

 For saving the power, while the headset didn't connect to any device over 1 hour, the headset will turn off automatically.

6 Wearing your headset

The headset can be worn on either the Left or Right ear. If you want to carry the headset on the other ear, please refer to the following figures to change the direction of the ear gel:



7 Making a call

* By phone's keypad

At the stand-by state, dial the number on your phone directly to make a call.

* Use Voice-Dialing

At the stand-by state, press the MFB shortly, you will hear a short tone from the headset, and the phone will prompt you say the voice tag like your friend's name. If the voice tag is identified by the phone, the related number will be dial-out later.

Make sure whether your mobile phone supports voice dialing function, and you need to set up voice tags on your mobile phone firs t. If the headset has connected to 2 phones, double press the MFB will start Voice-Dialing of phone 2.

* Last number re-dialing

Press and hold Vol- for 2 seconds, you will hear 2 short tones, the last number you dialed will be re-dial out. If the headset has connected to 2 phones, press and hold Volume Up button for 2 seconds will start last number re-dialing of phone 2.

NOTE

If the headset has connected to 2 phones, when one phone has active a call, the headset
will disconnect to other phone temperately, when you end the call the headset will
re-connect it automatically, please make sure your phone's Bluetooth function would not
be inactive during the calling.

7

8 Ending a call

 $When in the calling, press the MFB shortly \ will \ end \ the call, \ also \ you \ can \ end \ call \ on \ your \ mobile.$

9 Reject an incoming call

 $When you \, receive \, an \, incoming \, call, \, press \, and \, hold \, MFB \, for \, 2 \, seconds \, will \, reject \, the \, incoming \, call.$

10 Answering a call

When you receive an incoming call, press the MFB shortly can pick up the incoming call; also you can pick up the call on your mobile.

11 Transferring a call

When in the calling, press and hold Volume Up button for 2 seconds can transfer the call from headset to phone. Repeat the operation can transfer the call between the phone and headset each other.

12 Call-waiting (Three-Way Calling)

Before using Call-waiting function on your headset, please ensure that your phone supports the Hands-free profile, and you have been provide the service by the net provider.

- * If there is another incoming call while you are in the calling, press MFB shortly can accept the waiting call and end current calling.
- * If there is another incoming call while you are in the calling, press and hold MFB for 2 seconds can accept the waiting call and hold on current calling.

- *While you are in the calling and another call was holding on, press MFB shortly can end current call and resume the holding on calling.
- * While you are in the calling and another call was holding on, press and hold MFB for 2 seconds can shift the current calling to the holding on calling.
- * While you are in the calling and another call was holding on, press Volume Up button shortly can add the holding on call to the current conversation to make a multiparty call.
- * While you are in the calling and another call was holding on, or you are in a multiparty calling, double press MFB can end the calling or remove yourself from the multiparty calling.

13 Volume control & Mute function

While you are in the calling, you can adjust the volume by pressing vol+ and Vol- or you can adjust the volume on your mobile.

14 Mute

While you are in the calling, Press and hold the Vol- for 2 seconds, you will hear a melody from low to high, then the headset's MIC will be muted, and you will hear remindful melody every 10 seconds. Repeat the operation your will hear the melody from high to low, the mute function is cancelled.

15 Warranty

The condition of this warranty and our responsibilities under this warranty are as follows: Warranty is non-transferable and is limited to the original purchaser only.

- * You must be able to prove the date of original purchase of the unit with a dated receipt.
- *The warranty is not applicable if the product has been subject to physical abuse, improper installation, modification or repair by unauthorized third party.
- *The responsibility of supplier's products shall be limited to the repair or replacement of the product at it's sole discretion.
- * Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear such as batteries, decorates and other accessories.
- * Supplier will not take any responsibility if the failure of the unit has resulted from accident, abuse, misuse, or any unauthorized repair, modification or disassemble.
- * Modification and repair of the unit should be done by authorized and qualified service center or returned to the manufacturer
- *This warranty gives you specific legal rights, and you may also have other rights which vary under local laws.

FCC WARNING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.