

User's manual

BH-530

Bluetooth Stereo Headset



Specifications

Bluetooth version	Bluetooth V3.0+EDR SUPPORT: HSP, HFP, A2DP and AVRCP
Buttons	Volume up/down Song last/next MFB pair/pick up call/hang up call/redial
Effective range	10 meters
Working time	Music: Up to 10 hours Talk: Up to 11hours
Standby time	Up to 250 hours
Input	DC: 5V/160mA
Charging time	Approx 3 hours
Microphone	Bulid-in 360° Omin directional
Rechargeable	Micro USB cable

Welcome use Bluetooth stereo headset, BH-530

BH-530 is a Bluetooth stereo headset which supports following Bluetooth profiles:

HSP — Headset Profile

HFP — Hands-free Profile

A2DP— Advanced Audio Distribution Profile

AVRCP— Audio/Video Remote Control Profile

You can enjoy wireless music and hand free talking by using BH-530.

Function:

1) Pairing with any mobile phone with built-in Bluetooth devices (e.g. iPhone, HTC, Samsung) and Tablet PC (such as iPad).

- Answer, end and reject call from the headset
- Redial last number.
- Voice dial.
- Listen to music wirelessly
- Fully remote control buttons on the headset for pause/play/last song/next song/re-dial/voice call.

2) Automatic switching in between conversation and music, you will not miss any incoming call during music listening.

3) Automatic connecting with the last paired device when turn on the headset.

4) Feature of the battery indicator is available on iOS5, 6 on iPhone, iPad. it will show the battery status for the headset without installing any Apps.

5) Multilink technology allows you to connect to two devices at the same time. All you need to do is simply repeat the pairing process for the second device and manually reconnect from the first device.

6) Voice prompt now comes with five status alerts in English. Power on, power off, pairing, pairing completed, incoming call. The voice notice comes directly through the headset and tells what the current status is about.

Note: Even though the paired device and headset support the same Bluetooth profiles, the functions may be different due to the specification difference of the paired devices.

I - Before using

1) Overview



- 1.extension panel can fit different size user.
- 2.> key :next song
- 3.< key :last song
- 4.LED Indicator for different states
- 5.Multifunction button (MFB):Switch on/off the headset, answer, stop call, voice dial, redial last number, pause and play
- 6/7.+ key: volume up / – key: volume down

2) Charging the headset

- First time charging : first time charger battery ,please be sure the battery has been charged fully before use.
- Next time: When you hear warning tones of “DU DU DU” out and at the same time the red light blinks two times. It means battery is almost run out ,you need to charge it.

A. Charging the battery with Micro USB cable

- Step1: Insert USB charging cable into USB port which have support 5V power (such as AC/DC USB adapter or PC USB port)
- Step2: Connect charging cable to the charging port of headset.

- When the red light is on, the headset is in charging.
- When the blue light is on, the headset is fully charged.
- It takes about almost 3 hours to charge the headset fully.

Note: when you plug the charger cable please turn off the BH-530.

II - How to use

1) Switching on / off headset

Function	Operation	LED indicator	Voice prompt
Switch on	Press the MFB button for 3 seconds, and release it till the blue LED is on	Blue LED blink 3 times.	Power On
Switch off	Press the MFB button for 5 seconds, and release it till the red LED is on	Red LED blink 3 times	Power Off

2) Pairing the headset with Bluetooth devices

A. How to enter pairing mode

Function	Operation	LED indicator	Voice prompt
Enter pairing mode	Make sure the headset is off. Press and hold MFB button for 6 seconds, and release it till the red and blue LEDs blink alternately	Red and blue LEDs blink alternately.	Pairing

B. Pairing the headset with Bluetooth mobile phone

Please make sure your mobile phone has Bluetooth function that can be used.

Notes: Specific pairing procedures may vary with different mobile phone. Please refer to your mobile phone manual for further information. Steps as follows:

- Please keep the headset and mobile phone in the range of 1 meter when pairing.
- Make the headset enter into pairing mode (LED is red and blue blinking)

- Start the Bluetooth function of mobile phone and search for new Bluetooth devices.

After searched, select "BH-530" in the Bluetooth device list.

- According to indication, enter password or PIN No: "0000", and press the key of "Yes" or "confirmed". (it depends on the Bluetooth device setting)
- After successful pairing, select "BH-530" in the Bluetooth device list, and press "connect".
- After connect successfully, the blue LED of the headset will keep blinking.

Notes:

- If the pairing is not successful, please switch off headset firstly, and then re-pair again.
- After pairing is successful, paired devices will remember each other. Unless pairing information is deleted because of new pairing, no need to pair when use next time. If you want to pair the headset with other devices, please pair it with the new device according to steps 1~6 mentioned above.
- Multilink technology allows simultaneous connection to two different devices, just simply repeat the pairing process on both devices.
- Although WIN7 is a superior operating system with most drivers already built-in, in some cases this does not cover the various hardware configurations built into the device (e.g. PC, Note book, Net book etc) from the manufacturer. In this case, please visit the manufacturer's web site for the latest Bluetooth drivers for your onboard Bluetooth device.

3) Re-connecting to a Bluetooth device

- **Automatic connecting**

Every time the headset is switched on, it will connect to last connected device automatically, of course the source device Bluetooth must be on "on" states

- **Manual connecting to last connected HFP device**

When the headset is in standby mode and doesn't connect to any HFP devices, short press **MFB** button once, it will connect to last connected source device automatically.

Notes:

- Before connecting to a Bluetooth device, please turn on the Bluetooth device's Bluetooth function.

- On some Bluetooth devices, take some Nokia mobile phones for example, you have to allow automatic connecting in the mobile phone's settings. Please refer to your mobile phone's manual for further information.

4) Making calls with the headset

Function	Status of headset	Operation
Voice dial	Standby mode	Press and hold MFB button for 1 second, release it till hearing indication sound ,then speak the call you want to.
Redial last number	Standby mode	Short press MFB twice quickly
Volume up	Conversation mode	Short press + key
Volume down	Conversation mode	Short press - key
Answer calling	Ringing	Short press MFB
Reject calling	Ringing	Press and hold MFB button for 1 second, and release until you hear indication sound

- Not all the mobile phones support all the functions listed above. Please refer to the instruction of your mobile phone.
- Some functions and indication tones may vary with different mobile phones.
- When the volume is adjusted to max or min, you will hear a indication tone.
- For some mobile phones, when you press the key of accepting on the phone, the conversation will be sent to the mobile phone. At this time, you can switch the call to headset by using the conversation switch button or through operating on the mobile phone. Please refer to the instruction of your mobile phone for further information.

5) Playing music

When the headset connects with the mobile phone or Bluetooth transmitter , you can enjoy music through headset wirelessly.

Function	Status of headset	Operation
Pause	Playing music	Short press MFB
Play	Pausing	Short press MFB
Next song	Playing music	Short press > key
Last song	Playing music	Short press < key
Volume up	Playing music	Short press + key
Volume down	Playing music	Short press - key

Notes:

- For some of mobile phones, when they are playing music, the music will transmit to the speaker of mobile phone, you have to choose “transmit the sound through Bluetooth” in the “setting” of music play interface, and then choose “BH-530” in the device list, the music will be transmitted to the headset. Please refer to the instruction of your mobile phone for further information.
- When the volume of headset is adjusted to max. or min, you will hear a indication DU DU tone.
- Remote control the function of last song/next song/pause, it needs your mobile phone or Bluetooth transmitter supports AVRCP. Please refer to the instruction of your mobile phone or Bluetooth transmitter for further information.

6) LED

1) Battery Charging mode

LED indicator	Status of the headset
Red LED is on	Charging
Blue LED is on	Finish charging

2) Operation mode

LED Indicator	Status of the headset
Red and blue LEDs blink alternately	Pairing mode
Blue LED quickly blinks twice every 1 seconds.	Not connected to a device
Blue and Red LED quickly blinks three times every 2 seconds	Set up HFP and A2DP connection
Red LED blinks twice every 20 seconds	Low power

8) Low power Indication tone

“DU” tones every 20 seconds

- **Care and maintenance**

Please read the following suggestions carefully, that will help you to fulfill any warranty obligations and to enjoy this product for many years.

- Keep dry and don't put it in the dump place, in case of effecting the interior circuit of product.
- Don't put the product under the sunlight or place hot areas. High temperature will short the life of electronic device, destroy the battery, or distort certain plastic.
- Don't expose the product in the cold areas. It may damage the internal circuit board.
- Don't try to take apart the product. It may damage the product if you are not professional.
- Don't fall off on the floor or knock the hard substance. It may damage interior circuit.
- Don't use intensify chemical or detergent to clean the product.
- Don't scrap the surface with sharp things. In case the product doesn't function properly, send it to the store you bought it. The staff will help you to solve the problem.

FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation