

CANT-0036 Dual-Band Omni Outdoor Signal Antenna

The CANT-0036 dual-band outdoor signal antenna is a high gain antenna supporting both cellular and PCS frequency bands. The CANT-0036 is an Omni directional antenna and will transmit and receive signals to all surrounding network towers. The CANT-0036 has a f female connection that is compatible with the RG-6 cabling provided by the Zboost product.

For best performance, the antenna should be mounted on the highest point available on the roof. Avoid mounting the antenna within 2 feet of wires or metal objects such as gutters.



CANT-0036 Specifications

Frequency	824-894 MHz	1850-1990 MHz
Gain	3 dBi	5 dBi
Beam width	360 degree	360 degree
VSWR	<= 1.5 : 1	
Connector	Type f female	
Impedance	75 Ohm	
Supported transfer protocols	GSM, CDMA, GPRS, EDGE, EV-DO, HSPA+	
Dimensions	1" by 16"	
Weight	5 oz	