

**APP USER GUIDE**

**24/7 HELP** For 24/7 customer support, visit [feit.com/help](http://feit.com/help)

**System Requirements**  
Minimum: iOS 9.3, Android™ 4.4 KitKat® or higher  
- Dedicated 2.4GHz Wi-Fi Network -

Your screen images may differ from this user guide.

**BEFORE USING THIS USER GUIDE SEE INCLUDED INSTALLATION GUIDE FOR PROPER PRODUCT INSTALLATION.**

NOTE: Only works with 2.4GHz Wi-Fi networks.

Go to your Wi-Fi settings and connect your phone to your 2.4GHz Wi-Fi network.

### Set Up Device

- Download the **Feit Electric** app.
- Launch the **Feit Electric** app. Enter an email address to register, then tap **Continue**. A verification code will be sent to your email.
- Create a password then tap **Done**.

### Permissions & Location Access

4 **Permissions & Location Access**  
Allow notifications (highly recommended).

5 Allow the **Feit Electric** app to access your location to help connect your smart plug.

6 **Enable Bluetooth** on your smart device to facilitate simple pairing.

### Simple Pairing Mode

- Make sure the smart plug is blinking, then tap **Add Device** or the plus icon (+) on the upper right corner.
- The Smart Plugs name will appear in a small window for simple pairing enabled devices. Tap **Go to add**.
- Select one smart plug from the list. Tap the plus icon (+).

NOTE: If the smart plug is not blinking, then press and hold the button for 5 seconds. LED indicator blinking rapidly means plug is in pairing mode.

### Alternative Set-up Method EZ Mode

- Tap the plus icon (+) in the upper right corner.
- Tap **Plugs**, then select **Smart Plug**.
- Tap upper right corner and make sure you have **EZ Mode** selected. Follow steps 4-6 from **Simple Pairing Mode** to complete setup.

NOTE: Use EZ Mode to set-up multiple smart products at the same time or if there are issues with Simple Pairing.

### Alternative Set-up Method AP Mode

- Tap the plus icon (+) in the upper right corner.
- Tap **Plugs**, then select **Smart Plug**.
- Choose **AP Mode**. Make sure your smart plug is in AP pairing mode (smart plug should flash one time every three seconds). Tap **Confirm** then tap **Next** to go on to the next step.
- Enter the name of your 2.4GHz Wi-Fi network, enter your password and tap **Next** to begin connecting.

NOTE: AP Mode is an alternate method to connect your device if Simple Pairing Mode and EZ Mode are not successful.

NOTE: Your Wi-Fi network name and password are case sensitive.

- After confirming that you are on a 2.4GHz Wi-Fi network, enter your password then tap **Confirm**.

- The status window will appear and show progress toward set-up.
- To rename the smart plug, tap the **Pen** icon, enter the new name and tap **Done**. The smart plug is now ready to be controlled with the **Feit Electric** app.

NOTE: If 'Failed to Add' appears on the screen. Confirm. Then restart the pairing process by unplugging then re-plugging in the smart plug and repeating steps 1 - 4.

NOTE: Constant power to the smart plug(s) is required at all times.

### Features

- Individual Smart Plug On/Off**  
Tap the Smart Plug icon to turn the Smart Plug On/Off.
- Individual Smart Plug Operation**  
Press and hold the Smart Plug icon for two seconds to enter operation.

### Schedule

- Tap on **Schedule**.
- Tap **Add Schedule**.
- Choose a Start Time (On) and End Time (Off). To repeat on certain days of the week, tap **Repeat** otherwise the schedule will only occur once.
- Tap on the day(s) of the week you would like the schedule to repeat, then tap back "←" then **Save**.

### Timers

- Select **Timer**. Set the time then select **Confirm**.

### Settings

- Power State:** Plug will return to its previous state in case of a power outage.  
**LED Indicator Light:** Manage the LED indicator light.  
**Lock Mode:** Press the switch four consecutive times to unlock.

### Groups

- Tap the **Groups** icon at the bottom of the app home screen.
- Tap on **Create Group**.
- Tap on **Smart Plug**.
- Select the smart plugs that you want to group.
- Tap the group name and enter the name of the group.
- Once the group is named and the smart plugs are selected, tap **Save** in the upper right corner.
- Manage Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Manage Group**.
- Once selected, tap **Edit** in the upper right hand corner.
- Rename the group or remove a smart plug from the group. Once complete, tap **Save** in the upper right corner.
- Delete Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Delete Group**.

NOTE: To create groups you will need at least two Smart Plugs. You can only group a smart plug with other smart plugs.

- Tap **Go connect**. In your smart device's Wi-Fi settings, choose the **SmartLife-XXXX** network.

- In your smart device's Wi-Fi settings, choose the **SmartLife-XXXX** network. After you have connected to **SmartLife**, return to the **Feit Electric** app.

NOTE: After connecting the smart plug, your smart device will automatically rejoin your original 2.4GHz network.

- Your device should begin connecting using **AP Mode**.
- If you see this screen your device was added successfully.

### Groups

- Tap on **Create Group**.
- Tap on **Smart Plug**.
- Select the smart plugs that you want to group.
- Tap the group name and enter the name of the group.
- Once the group is named and the smart plugs are selected, tap **Save** in the upper right corner.
- Manage Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Manage Group**.
- Once selected, tap **Edit** in the upper right hand corner.
- Rename the group or remove a smart plug from the group. Once complete, tap **Save** in the upper right corner.
- Delete Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Delete Group**.

NOTE: Smart plugs with different functionalities can be grouped. However, the app will only be able to control the Smart Plugs' intended capabilities.

### Groups

- Tap the **Groups** icon at the bottom of the app home screen.
- Tap on **Create Group**.
- Tap on **Smart Plug**.
- Select the smart plugs that you want to group.
- Tap the group name and enter the name of the group.
- Once the group is named and the smart plugs are selected, tap **Save** in the upper right corner.
- Manage Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Manage Group**.
- Once selected, tap **Edit** in the upper right hand corner.
- Rename the group or remove a smart plug from the group. Once complete, tap **Save** in the upper right corner.
- Delete Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Delete Group**.

### Groups

- Tap the **Groups** icon at the bottom of the app home screen.
- Tap on **Create Group**.
- Tap on **Smart Plug**.
- Select the smart plugs that you want to group.
- Tap the group name and enter the name of the group.
- Once the group is named and the smart plugs are selected, tap **Save** in the upper right corner.
- Manage Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Manage Group**.
- Once selected, tap **Edit** in the upper right hand corner.
- Rename the group or remove a smart plug from the group. Once complete, tap **Save** in the upper right corner.
- Delete Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Delete Group**.

### Groups

- Tap the **Groups** icon at the bottom of the app home screen.
- Tap on **Create Group**.
- Tap on **Smart Plug**.
- Select the smart plugs that you want to group.
- Tap the group name and enter the name of the group.
- Once the group is named and the smart plugs are selected, tap **Save** in the upper right corner.
- Manage Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Manage Group**.
- Once selected, tap **Edit** in the upper right hand corner.
- Rename the group or remove a smart plug from the group. Once complete, tap **Save** in the upper right corner.
- Delete Groups  
Tap the **Groups** icon.
- Tap the context menu in the upper right corner (⋮).
- Tap **Delete Group**.