


GBH702

Bluetooth headset quickstart guide



BEFORE YOU BEGIN

Before using this product, please take a moment to familiarize yourself with your new GBH702 headset.



1. Multi-Function Button
2. Volume Up/Down Button
3. Indicator Light
4. Charging Interface
5. Microphone
6. Adjustable Ear Loop
7. Receiver


PACKAGE CONTENTS

1. GBH702 headset unit
2. AC Power Adapter
3. USB Charging cable (Optional)
4. User guide

CHARGE


The headset has a built-in battery. You can charge the headset by using the AC power adaptor or USB charging cable through the computer. Before using the headset, you must first charge it. Light is steady red when battery is charging.

1. Charging with AC power adapter



- (1) Verify the headset is powered off.
- (2) Plug the charger into the end of the headset, the indicator light turns red when the battery is charging. When the headset is fully charged (about 2 hours), the indicator light turns off.
- (3) Disconnect the charger

2. Charging with the computer (USB charging cable is an optional accessory)



Please refer to **1. Charging with AC power adapter** for the charging process.

PAIR

This headset comes with EASYPAIR feature so pairing with your Bluetooth phone is even easier. Follow the instructions below to pair your phone and headset for the first time.

EASYPAIR

1. Prepare headset-Make the headset enter pairing mode
Begin with headset turned off. Turn headset on (press Multi-Function button for 3-5 seconds until the light flashes blue) and it will automatically go into pairing mode, flashing red and blue.

2. Prepare Phone-Turn on Bluetooth
Scroll to the Bluetooth menu in your phone and search for active devices. (Refer to the phone's user manual for details) And when the search completes, a list of devices is displayed. (The screen examples here are from a Nokia 6230)



3. Pairing
Select GBH702 from the list. When prompted for a passkey, enter the default passkey (0000). When successfully paired, the red/blue LED on the headset changes to flash blue. It is now powered on and ready to use.

Note:
Normally you only need to pair the headset and handset once. If headset has been previously paired with another device, follow pairing instructions below.

PAIR Cont'd

If headset has been previously paired with another device, please follow these instructions for pairing a second time.




Begin with headset turned off

1. Press and hold Multi-Function button more than 5 seconds until the headset status indicator begins to flash blue then red. The headset is now in pairing mode for the next 120 seconds.
2. While the headset is flashing, use the phone menu to search for Bluetooth devices and select "GBH702". You can refer to EasyPair for the details of this step.
3. When prompted for a passkey, enter 0000. Headset will flash blue when paired successfully.

Note:

1. The headset can pair to multiple Bluetooth devices, but will only connect to one device at a time. Then headset will automatically connect to the last device to which it was connected.
2. If the headset is disconnected from the Bluetooth device, you can re-connect it by briefly pressing Multi-Function button.

ADJUSTING FIT



1. Lift ear loop.

Swivel ear loop to the right or left for right or left ear wearing.




3. Place ear loop behind ear.

4. Pivot headset to place speaker into ear.

5. Position speaker and align microphone with mouth.

USING YOUR HEADSET

TURNING HEADSET ON AND OFF



To turn your headset on, press Multi-Function button for 3-5 seconds. The indicator light is steady blue for 1 second, and then flashes blue once every 5 seconds. To turn your headset off, press and hold Multi-Function button more than 5 seconds, indicator light is steady red for 1 second and then turn off.

ANSWERING/ENDING/MAKING CALLS




For best performance, position your phone on the same side of your body as the headset.

To answer or end a call, briefly press the Multi-Function button. To make a call, enter number on your phone, press send, and the call is automatically transferred to headset; no need to press Multi-Function button.

USING YOUR HEADSET

ADJUSTING THE VOLUME



Briefly press up or down on the volume button for incremental volume steps. You can also press and hold volume Up/Down button to adjust the volume continuously. You will hear two tones (high tone followed by low tone) at the volume limit.

DISABLE/ENABLE LED STANDBY AND ON-LINE INDICATION

With the headset is connected, press and hold Volume Down button more than 5 seconds until you hear a high tone, and then LED will only light for low battery, Pairing, etc., but not for standby or in-use modes. Press and hold Volume Up button more than 5 seconds until you hear a high tone, and then LED is enabled again.

ADDITIONAL FEATURES

Redialing Last Number

To activate last number redial, double press the Multi-Function button. You will hear a high tone after each double key press.

Using Voice Dialing

With the headset on, press the Multi-Function button for 3-5 seconds to activate the voice dialing.

Note:

To use voice activated dialing, the voice dialing feature must be enabled on your phone. See your Bluetooth phone manual for instructions.

Rejecting a Call

When a call is incoming, press and hold the Multi-Function button until your phone stops ringing.

Switching a Call from Phone to Headset

To switch an active call from your phone to your headset, press the Multi-Function button for 3-5 seconds.

Switching a Call from Headset to Phone

To switch an active call from your headset to your phone, press and hold the Multi-Function button until the call is available in the handset.

INDICATOR LIGHTS

With the Charger Plugged In

Headset Status	Headset Indicator
Charging	Steady Red
Charging complete	Off

With No Charger Plugged In

Headset Status	Headset Indicator
Powering on	Steady Blue for 1 second
Powering off	Steady Red for 1 second and goes off
Pairing mode	Blue/Red flashes
Standby mode	Blue flashes, Repeat (0.2 second on 5 seconds off)
Ringing	Purple flashes. Briefly press Multi-Function button to answer the call. Press Multi-Function for 3-5 seconds to reject the call
Ongoing call	Blue flashes, Repeat (0.5 second of 2 seconds off)
Missed call	Purple flashes. Single press the Multi-Function button to cancel
Low battery	Red flashes

TROUBLESHOOTING

1. My headset can not discover my phone.

Make sure your phone has the Bluetooth Voice Gateway function built in.

Make sure the Bluetooth feature of your phone has turned on and you have records with the accurate pairing steps.

2. My headset can not work well with my phone.

Make sure the headset has turned on. Press the Multi-Function button for 3-5 seconds until you hear a tone or see the indicator light steady blue for 1 second to turn the headset on.

Make sure your headset is not out of the working range. Move the headset closer to the phone or Bluetooth device.

Make sure your headset battery is not drained. Charge your battery using the AC power adapter supplied.

The listening volume is too low. Press the Volume Up to increase the sound heard in the headset.

PRODUCT SPECIFICATION

Talk Time	6 hours
Standby Time	170 hours
Charge Time	2 hours
Working Range	Bluetooth standard 33 feet (10 meters)
Bluetooth Version	Bluetooth 2.0+EDR
Supported Bluetooth profile	Headset Hands-free
Weight	13.5 g
Dimension	56.4 * 20 * 21.1 mm (length * width * height)
Storage and Usage Temperature	-4 °F-122 °F (-20 °C-50 °C)

FCC RF Radiation Exposure Statement

Federal Communications Commission (FCC) Statement

15.21

You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

FCC RF Radiation Exposure Statement

15.105 (b)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC RF Radiation Exposure Statement

Operation is subject to the following two conditions:

- (1) this device may not cause interference and
- (2) this device must accept any interference, including interference that may cause undesired operation of the device.

FCC RF Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

SUPPORT

If you need further help, please contact us:

GoerTek Electronics
Global Location:
• Qingdao • Taiwan • USA • Hong Kong • Shenzhen
http://www.goertek.com
e-mail: service@goertek.com
Customer Service Hotline: 86-532-88999318

The copyright and brand name are owned by the register. All information in this manual is subject to change without prior notice.
GoerTek has the authority to explain the above information.
For more information, please visit GoerTek Website:
http://www.goertek.com